



Service Bulletin

No. : MZ10-059

Date: October 13, 2010

Model: NA7004

Subject: Correction of the Firmware via DPMS (D&M Product Management Server).

Countermeasure is applicable only upon claim from the customer.

Symptom: 1) Add a new feature that "Update Notification function" which will Display a notification message on the menu screen when the latest firmware is released.
2) Countermeasure for failure.
2)-1 "This is a function for only U model". When push ENTER button after chose "I am new to Pandora" after select the function of "ONLINE MUSIC" to "Pandora" during "Read only mode" of Pandora, a message that "Activation has not been completed" will be displayed on the monitor.
2)-2 The unit does not send response via RS-232C when operate the unit by button of main unit or RC unit in "Internet Radio", "Music Server", "USB", and "iPod" function.

Solution: We corrected the firmware so that no malfunction occurs.

Updating the firmware (Refer to the Instruction Manual.)

- 1) Turn the Power Supply of the unit off.
- 2) Connect the Ethernet terminal of the unit to the Network line by Ethernet straight cable. (Don't use Ethernet cross cable.)
- 3) The connection of the network recommends the Ethernet cable for certain update.
- 4) Turn the Power Supply of the unit on.
- 5) The unit sets the Internet. It wishes waiting for about two minutes until customer's router ends the setting.

CONFIDENTIALITY NOTICE:

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.

Caution: The update doesn't succeed when the customers set cannot hook up to the Internet correctly. In this case, please confirm the internet environment of the customer house. If the Internet radio can be received correctly or not can be used to determine whether the Internet is properly connected. There are some problems under the internet environment when the Internet radio can not be received.

- 6) Press "MENU" button on the front panel and indicates the GUI menu.
- 7) Press "CURSOR" button.
- 8) The GUI indicates, "OTHER" > "Firmware Update".

Caution: The update interrupts when it is not possible to connect it with the Internet correctly. In this case, please do from 1) again.

- 9) Select the "Start" on GUI.
- 10) Press the "ENTER" button.
- 11) The firmware will start updating.

Caution: when the firmware update starts correctly, the GUI and the audio signal, etc. stops and everything, becomes the update operation.

- 12) During the updating, the progress of update is indicated on the GUI as follows.

[Updating]

xx min yy

System (<- Device name is indicated)

Time necessary for update: approximately 15 min.

Caution: The update time might change depending on the situation of the DPMS server and the speed of the Internet environment of the customer house.

- 13) After upgrading, the unit restarts automatically.

CONFIDENTIALITY NOTICE:

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.

Troubleshooting: If the display reads as shown below, check the settings and network environment, then update again. The problem is not in the Internet connection if the Internet radio can be able to be received correctly

Indication of FL Display	Reason of failure	Countermeasure
Download failed	The update is imperfect or fails.	Please turn off the power supply of the unit, turn on again, and update it while confirming the operating procedure again.
Updating failed	The update is imperfect or fails.	Please turn off the power supply of the unit, turn on again, and update it while confirming the operating procedure again.
Login failed	The connection fails in the Internet.	Please confirm whether the unit is correctly connected with the Internet. Please remove PC, connect the set, and confirm it when PC operates correctly.
Server is busy	Server is busy.	Please execute the update work after a while again.
Connection failed	The connection fails in the Internet.	Please confirm whether the unit is correctly connected with the Internet. When PC operates correctly, remove the Ethernet cable from PC, and connect the Ethernet cable to the unit. If the unit still does not work properly, please confirm the environment of internet.

Cautions during the updating operation:

- 1) Do not turn off the power until updating is completed.
- 2) Even with a broadband connection to the Internet, approximately 20 minutes is required for the updating procedure to be completed.
- 3) Once updating starts, normal operations on this unit cannot be performed until updating is completed.

CONFIDENTIALITY NOTICE:

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.

- 4) Furthermore, updating the firmware may reset the backup data for the parameters, etc. set for this unit.
- 5) If the update fails, remove and re-insert the power cord. "Update retry" appears on the display and update restarts from the point at which update failed. If the error continues despite this, check the network environment.

Confirming the firmware's number after upgraded:

After completion of the updating operation, the new version number can be confirmed by starting up the unit according to the following procedure.

Plug AC cord into power outlet while holding both "CURSOR UP" button and "B" button on the front panel simultaneously. Push "MENU" Button then the version of the firmware is indicated, then chose the device by "CURSOR UP" "CURSOR DOWN" button.

Caution: "Ethernet SBL" and "Ethernet IMG" are takes approximately 1min to indicate the version from turn on the unit.

NA7004

	Name	Version
1	System	A1.30
2	System FBL	A0.20
3	Display	00.30
4	Ethernet SBL	B201002171914
5	Ethernet IMG	I201009270136

Serial Number Range:

Please apply the above modification to the production models in the following serial numbers.

*****000001 ~ *****32*****

CONFIDENTIALITY NOTICE:

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.