

Service Manual

Pioneer

ORDER NO.
RRV2505

STEREO DVD CASSETTE DECK RECEIVER

XV-VS800 XV-VS600

THIS MANUAL IS APPLICABLE TO THE FOLLOWING MODEL(S) AND TYPE(S).

Type	Model		Power Requirement	Region No.	The voltage can be converted by the following method.
	XV-VS800	XV-VS600			
DBDXJ	○	○	AC110-127V/220-230V/240V	3	With the voltage selector
DDXJRA	○	—	AC110-127V/220-230V/240V	1	With the voltage selector
DDXJ/RB	○	○	AC110-127V/220-230V/240V	2	With the voltage selector
DDXJ/AR	○	—	AC110-127V/220-230V/240V	4	With the voltage selector
DLXJ/NC	○	○	AC110-120V/220-230V/240V	3	With the voltage selector

● This service manual should be used together with the following manual(s):

Model No.	Order No.	Remarks
XR-A9800D/KUCXJ	RRV2329	

CONTENTS

1. SAFETY INFORMATION	2
2. CONTRAST OF MISCELLANEOUS PARTS	3
3. SCHEMATIC DIAGRAM	12
4. PCB CONNECTION DIAGRAM	22

PIONEER CORPORATION 4-1, Meguro 1-chome, Meguro-ku, Tokyo 153-8654, Japan
PIONEER ELECTRONICS SERVICE, INC. P.O. Box 1760, Long Beach, CA 90801-1760, U.S.A.
PIONEER EUROPE NV Haven 1087, Keetberglaan 1, 9120 Melsele, Belgium
PIONEER ELECTRONICS ASIACENTRE PTE. LTD. 253 Alexandra Road, #04-01, Singapore 159936
©PIONEER CORPORATION 2001

T – ZZK JULY 2001 Printed in Japan

1. SAFETY INFORMATION

This service manual is intended for qualified service technicians ; it is not meant for the casual do-it-yourselfer. Qualified technicians have the necessary test equipment and tools, and have been trained to properly and safely repair complex products such as those covered by this manual.

Improperly performed repairs can adversely affect the safety and reliability of the product and may void the warranty. If you are not qualified to perform the repair of this product properly and safely, you should not risk trying to do so and refer the repair to a qualified service technician.

LABEL CHECK

WARNING !

THE AEL (ACCESSIBLE EMISSION LEVEL) OF THE LASER POWER OUTPUT IS LESS THAN CLASS 1 BUT THE LASER COMPONENT IS CAPABLE OF EMITTING RADIATION EXCEEDING THE LIMIT FOR CLASS 1.

A SPECIALLY INSTRUCTED PERSON SHOULD DO SERVICING OPERATION OF THE APPARATUS.



LASER DIODE CHARACTERISTICS

FOR DVD : MAXIMUM OUTPUT POWER : 5 mW


WAVELENGTH : 655 nm

FOR CD : MAXIMUM OUTPUT POWER : 5mW

WAVELENGTH : 785 nm



Printed on the Rear Panel
(DLXJ/NC Type only)



Additional Laser Caution

1. Inside detection switch (S201 on the SMEB assy) and loading-status detection switch (S9503 on the MOTOR assy) are detected by the microprocessor (IC11 in the DVDM assy).
• To permit the laser diode to oscillate, it is required to set the inside detection switch for the inside position (S201 : ON) and to set the loading-status detection switch for the clamp position (the center terminal of S9503 is shorted to +5V). The 655 nm laser diode for DVD oscillation will continue if pin 19 of IC1 is shorted to +5V (fault condition) in the DVDM assy. The 785 nm laser diode for CD oscillates if pin 20 of IC1 is shorted to +5V in the DVDM assy. In the test mode * , the laser diode oscillates when microprocessor detects a PLAY signal, or when the PLAY key is pressed (S5931 ON in the DISPLAY assy), with the above requirements satisfied.
2. When the cover is open, close viewing through the objective lens with the naked eye will cause exposure to the laser beam.

* : Refer to page 82 on the service manual RRV2329.

2. CONTRAST OF MISCELLANEOUS PARTS

NOTES: ● Parts marked by "NSP" are generally unavailable because they are not in our Master Spare Parts List.

● The $\triangle$ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.

● Screws adjacent to ∇ mark on product are used for disassembly.

● Reference Nos. indicate the pages and Nos. in the service manual for the base model.

● When ordering resistors, first convert resistance values into code form as shown in the following examples.

Ex.1 When there are 2 effective digits (any digit apart from 0), such as 560 ohm and 47k ohm (tolerance is shown by J=5%, and K=10%).

560 $\rightarrow$ 56 $\times 10^1 \rightarrow$ 561 RD1/4PU561J

47k $\rightarrow$ 47 $\times 10^3 \rightarrow$ 473 RD1/4PU473J

0.5 $\rightarrow$ R50 RN2H[R]50K

1 $\rightarrow$ 1R0 RS1P[R]1R0K

Ex.2 When there are 3 effective digits (such as in high precision metal film resistors).

5.62k $\rightarrow$ 562 $\times 10^1 \rightarrow$ 5621 RN1/4PC5621F

■ CONTRAST TABLE for XV-VS800

XV-VS800/DBDXJ, DDXJRA, DDXJ/RB, DDXJ/AR, DLXJ/NC and XR-A9800D/KUCXJ are constructed the same except for the following :

Ref. No.	Mark	Symbol and Description	Part No.						Remarks
			XR-A9800D /KUCXJ	XV-VS800 /DBDXJ	XV-VS800 /DDXJRA	XV-VS800 /DDXJ/RB	XV-VS800 /DDXJ/AR	XV-VS800 /DLXJ/NC	
P5- 1		PCB ASSEMBLIES MAIN ASSY └ AF ASSY	XWM3174 XWZ3330	XWM3172 XWZ3322	XWM3172 XWZ3322	XWM3172 XWZ3322	XWM3172 XWZ3322	XWM3172 XWZ3322	
P5- 4 P7- 1		COMPLEX ASSY └ PRIMARY ASSY └ DISPLAY ASSY	XWM3178 XWZ3332 XWZ3331	AWM7618 XWZ3326 AWU7801	AWM7618 XWZ3326 AWU7801	AWM7618 XWZ3326 AWU7801	AWM7618 XWZ3326 AWU7801	AWM7618 XWZ3326 AWU7801	
P3- 1 P3- 5 P3- 9 P3-10 P3-11	⚠	PACKING SECTION Power Cord Remote Control Unit Front Pad Rear Pad Packing Case	ADG7022 XZN3109 XHA3020 XHA3021 XHD3144	ADG1158 XZN3110 XHA3030 XHA3031 XHD3280	ADG1158 XZN3110 XHA3030 XHA3031 XHD3280	ADG1154 XZN3110 XHA3030 XHA3031 XHD3280	ADG1158 XZN3110 XHA3030 XHA3031 XHD3291	ADG1154 XZN3110 XHA3030 XHA3031 XHD3281	
P3-12 P3-14	NSP	Warranty Card Operating Instructions (English/French) Operating Instructions (English/Chinese)	ARY7045 XRE3036	Not used Not used	Not used Not used	Not used Not used	Not used Not used	Not used Not used	
		Operating Instructions (English)	Not used	Not used	XRB3010	XRB3010	Not used	Not used	
		Operating Instructions (English/Spanish)	Not used	Not used	Not used	Not used	XRE3053	Not used	
	⚠	Power Cord	Not used	Not used	Not used	Not used	XDG3009	Not used	
	⚠	Power-cord Plug Conversion Adapter	Not used	XKM3002	Not used	Not used	XKM3002	Not used	Accessories
		Caution Sheet	XRH3004	Not used	Not used	Not used	XRH3002	Not used	
		Region Label	Not used	Not used	VRW1708	VRW1701	Not used	Not used	For Packing Case
		Caution Sheet AR	Not used	Not used	Not used	Not used	XRH3002	Not used	Accessories
P5-12 P5-12	⚠ ⚠	EXTERIOR SECTION Power Transformer (T1) (AC120V) Power Transformer (T1) (AC110-127V/220-230V/240V)	XTS3042 Not used	Not used XTS3055	Not used XTS3055	Not used XTS3055	Not used XTS3055	Not used XTS3055	
P5-13 P5-13	⚠ ⚠	Fuse (FU1 : 6.3A) Fuse (FU1 : T5A)	REK1085 Not used	Not used AEK1061	Not used AEK1061	Not used AEK1061	Not used AEK1061	Not used AEK1061	
P5-25 P5-38		Rear Panel Tray Cap Tray Panel DVD	XNC3065 XAK3157 Not used	XNC3131 XAK3236 XAK3251	XNC3131 XAK3236 XAK3251	XNC3131 XAK3236 XAK3251	XNC3131 XAK3236 XAK3251	XNC3132 XAK3236 XAK3251	For Tray Cap
P5-41 P5-42	NSP NSP	Fuse Card Getter	AAX2374 XAX3175	Not used XAX3271	Not used XAX3271	Not used XAX3271	Not used XAX3271	Not used XAX3271	
P5-43		65 Label	ARW7050	Not used	Not used	Not used	Not used	Not used	
	⚠	Fuse (FU2, FU3 : T3.15A)	Not used	AEK1059	AEK1059	AEK1059	AEK1059	AEK1059	*1
	NSP	Name Label	Not used	Not used	XAL3101	XAL3101	XAL3101	Not used	*2
	NSP	Region Label	Not used	Not used	XAX3183	XAX3184	XAX3185	Not used	For Rear Panel
		Caution Label	Not used	XRW3003	XRW3003	XRW3003	XRW3003	XRW3003	*3

XV-VS800, XV-VS600

Ref. No.	Mark	Symbol and Description	Part No.						Remarks
			XR-A9800D /KUCXJ	XV-VS800 /DBDXJ	XV-VS800 /DDXJRA	XV-VS800 /DDXJ/RB	XV-VS800 /DDXJ/AR	XV-VS800 /DLXJ/NC	
	NSP	SISIR Label Rear Sheet	Not used AED7037	Not used Not used	Not used Not used	Not used Not used	Not used Not used	XAX3280 Not used	For Rear Panel
		FRONT PANEL SECTION							
P7-8		GND Plate C	XNG3047	Not used	Not used	Not used	Not used	Not used	
P7-8		GND Plate A	Not used	XNG3030	XNG3030	XNG3030	XNG3030	XNG3030	
P7-18		Volume Knob	XAA3013	XAA3022	XAA3022	XAA3022	XAA3022	XAA3022	
P7-21		FUNC Button L	XAD3061	XAD3118	XAD3118	XAD3118	XAD3118	XAD3118	No.8
		FUNC Cap L	Not used	XAK3247	XAK3247	XAK3247	XAK3247	XAK3247	No.7
P7-22		FUNC Button R	XAD3051	XAD3112	XAD3112	XAD3112	XAD3112	XAD3112	No.10
		FUNC Cap R	Not used	XAK3248	XAK3248	XAK3248	XAK3248	XAK3248	No.9
P7-23		FUNC Frame L	XAD3052	Not used	Not used	Not used	Not used	Not used	
P7-24		FUNC Frame R	XAD3053	Not used	Not used	Not used	Not used	Not used	
P7-25		DVD ENT Button	XAD3056	XAD3110	XAD3110	XAD3110	XAD3110	XAD3110	No.12
P7-26		Display Panel	XAK3135	XAK3259	XAK3259	XAK3259	XAK3259	XAK3259	
P7-27		EQ Panel	XAK3150	Not used	Not used	Not used	Not used	Not used	
		SC Panel	Not used	XAK3268	XAK3268	XAK3268	XAK3268	XAK3268	No.26
		SC Panel Assy	Not used	XXG3090	XXG3090	XXG3090	XXG3090	XXG3090	No.13
P7-28		JOG Lens	XAK3152	XAK3243	XAK3243	XAK3243	XAK3243	XAK3243	No.23
P7-29		V Lens	XAK3153	XAK3237	XAK3237	XAK3237	XAK3237	XAK3237	
P7-33		FL Cover	XAK3164	XAK3239	XAK3239	XAK3239	XAK3239	XAK3239	
P7-34		Cover Sheet L	XAK3184	Not used	Not used	Not used	Not used	Not used	
P7-35		Cover Sheet R	XAK3185	Not used	Not used	Not used	Not used	Not used	
		LED Barrier	Not used	XEC3022	XEC3022	XEC3022	XEC3022	XEC3022	No.24
P7-36		Power Button	XAD3044	XAD3102	XAD3102	XAD3102	XAD3102	XAD3102	No.17
P7-37		CD Button	XAD3045	XAD3104	XAD3104	XAD3104	XAD3104	XAD3104	No.19
P7-38		SC Button	XAD3060	Not used	Not used	Not used	Not used	Not used	
		SC Button L	Not used	XAD3105	XAD3105	XAD3105	XAD3105	XAD3105	No.29
		SC Cap L	Not used	XAK3241	XAK3241	XAK3241	XAK3241	XAK3241	No.27
		SC Button R	Not used	XAD3106	XAD3106	XAD3106	XAD3106	XAD3106	No.30
		SC Cap R	Not used	XAK3267	XAK3267	XAK3267	XAK3267	XAK3267	No.28
		ASES Button	Not used	XAD3114	XAD3114	XAD3114	XAD3114	XAD3114	No.20
		Timer Button	Not used	XAD3115	XAD3115	XAD3115	XAD3115	XAD3115	No.21
P7-39		SC Button L	XAD3047	Not used	Not used	Not used	Not used	Not used	
		Audio Button	Not used	XAD3107	XAD3107	XAD3107	XAD3107	XAD3107	No.14
P7-40		SC Button R	XAD3049	Not used	Not used	Not used	Not used	Not used	
		Visual Button	Not used	XAD3108	XAD3108	XAD3108	XAD3108	XAD3108	No.15
P7-41		DOLBY Button	XAD3054	XAD3121	XAD3121	XAD3121	XAD3121	XAD3121	No.11
P7-42		Sub Panel	XAK3203	XAK3271	XAK3271	XAK3271	XAK3271	XAK3271	No.6
P7-43		Standby Lens	XAK3151	XAK3240	XAK3240	XAK3240	XAK3240	XAK3240	No.18
P7-44		Deck Lens L	XAK3159	XAK3249	XAK3249	XAK3249	XAK3249	XAK3249	No.3
P7-45		Deck Lens R	XAK3160	XAK3250	XAK3250	XAK3250	XAK3250	XAK3250	No.5
P7-46		JOG Conductor	XAK3165	XAK3244	XAK3244	XAK3244	XAK3244	XAK3244	No.22
P7-47		Deck Door_L	XAN3022	XAN3037	XAN3037	XAN3037	XAN3037	XAN3037	No.2
P7-48		Deck Door_R	XAN3026	XAN3038	XAN3038	XAN3038	XAN3038	XAN3038	No.4
P7-49		Front Panel	XMB3027	XMB3058	XMB3058	XMB3058	XMB3058	XMB3058	No.1
P7-50		DV Button L	XAD3057	Not used	Not used	Not used	Not used	Not used	
P7-51		DV Button R	XAD3059	Not used	Not used	Not used	Not used	Not used	
P7-52	NSP	Front Panel ASSY	XXG3066	XXG3086	XXG3086	XXG3086	XXG3086	XXG3086	
		O/C Button	Not used	XAD3103	XAD3103	XAD3103	XAD3103	XAD3103	No.16
		Spacer	XEB3012	Not used	Not used	Not used	Not used	Not used	
		Spacer	XEB3013	Not used	Not used	Not used	Not used	Not used	
		Cushion Spacer	XEB3015	Not used	Not used	Not used	Not used	Not used	
		Cushion Spacer	XEB3016	Not used	Not used	Not used	Not used	Not used	
		Cushion Spacer	XEB3017	Not used	Not used	Not used	Not used	Not used	
		Spacer	XEC3014	Not used	Not used	Not used	Not used	Not used	
		Spacer	XEC3019	Not used	Not used	Not used	Not used	Not used	

Notes : For PCB ASSEMBLIES, Refer to “CONTRAST OF PCB ASSEMBLIES” and “3. SCHEMATIC DIAGRAM”.

The numbers in the remarks column correspond to the numbers on the “ FRONT PANEL ASSY ”.

*1 Refer to “3. SCHEMATIC DIAGRAM”. *2 Stick Name Label on the Rear Panel. *3 Refer to “LABEL CHECK”.

■ CONTRAST TABLE for XV-VS600

XV-VS600/DBDXJ, DDXJ/RB, DLXJ/NC and XR-A9800D/KUCXJ are constructed the same except for the following :

Ref. No.	Mark	Symbol and Description	Part No.				Remarks
			XR-A9800D /KUCXJ	XV-VS600 /DBDXJ	XV-VS600 /DDXJ/RB	XV-VS600 /DLXJ/NC	
		PCB ASSEMBLIES					
P5- 1		MAIN ASSY	XWM3174	AWM7605	AWM7605	AWM7605	
P5- 2		└ AF ASSY	XWZ3330	AWU7789	AWU7789	AWU7789	
		└ SECONDARY ASSY	XWZ3323	XWZ3317	XWZ3317	XWZ3317	
P5- 3		COMPLEX ASSY	XWM3178	AWM7617	AWM7617	AWM7617	
P5- 4		└ REAR AMP ASSY	XWZ3325	XWZ3319	XWZ3319	XWZ3319	
P7- 1		└ PRIMARY ASSY	XWZ3332	XWZ3320	XWZ3320	XWZ3320	
		└ DISPLAY ASSY	XWZ3331	AWU7800	AWU7800	AWU7800	
		PACKING SECTION					
P3- 1	⚠	Power Cord	ADG7022	ADG1158	ADG1158	ADG1154	
P3- 5		Remote Control Unit	XZN3109	XZN3108	XZN3108	XZN3108	
P3- 9		Front Pad	XHA3020	XHA3030	XHA3030	XHA3030	
P3-10		Rear Pad	XHA3021	XHA3031	XHA3031	XHA3031	
P3-11		Packing Case	XHD3144	XHD3277	XHD3277	XHD3278	
P3-12	NSP	Warranty Card	ARY7045	Not used	Not used	Not used	
P3-14		Operating Instructions (English/French)	XRE3036	Not used	Not used	Not used	
		Operating Instructions (English/Chinese)	Not used	XRE3052	Not used	XRE3052	
		Operating Instructions (English)	Not used	Not used	XR3010	Not used	
	⚠	Power-cord Plug Conversion Adapter	Not used	XKM3002	Not used	Not used	
		Region Label	Not used	Not used	VRW1701	Not used	For Packing Case
		Caution Sheet	XR3004	Not used	Not used	Not used	Accessories
		EXTERIOR SECTION					
P5-12	⚠	Power Transformer (T1) (AC120V)	XTS3042	Not used	Not used	Not used	
P5-12	⚠	Power Transformer (T1) (AC110-127V/220-230V/240V)	Not used	XTS3039	XTS3039	XTS3039	
P5-13	⚠	Fuse (FU1 : 6.3A)	REK1085	Not used	Not used	Not used	
P5-13	⚠	Fuse (FU1 : T5A)	Not used	AEK1061	AEK1061	AEK1061	
P5-15		Power Bracket	XNG3033	Not used	Not used	Not used	
P5-25		Rear Panel	XNC3065	XNC3128	XNC3128	XNC3129	
P5-26		SEC Holder	XMR3013	XMR3014	XMR3014	XMR3014	
P5-38		Tray Cap	XAK3157	XAK3236	XAK3236	XAK3236	
		Tray Panel DVD	Not used	XAK3251	XAK3251	XAK3251	
P5-41	NSP	Fuse Card	AAX2374	Not used	Not used	Not used	
P5-42	NSP	Getter	XAX3175	XAX3269	XAX3269	XAX3269	
P5-43		65 Label	ARW7050	Not used	Not used	Not used	
P5-44	NSP	\$M Mecha. DVD (5ch)	XXA3019	Not used	Not used	Not used	
P5-44	NSP	\$M Mecha. DVD (2ch)	Not used	XXA3018	XXA3018	XXA3018	
	⚠	Fuse (FU2, FU3 : T3.15A)	Not used	AEK1059	AEK1059	AEK1059	*1
	NSP	Name Label	Not used	Not used	XAL3099	Not used	*2
	NSP	Region Label	Not used	Not used	XAX3184	Not used	For Rear Panel
		Caution Label	Not used	XRW3003	XRW3003	XRW3003	*3
	NSP	SISIR Label	Not used	Not used	Not used	XAX3279	For Rear Panel
		Rear Sheet	AED7037	Not used	Not used	Not used	
		FRONT PANEL SECTION					
P7-8		GND Plate C	XNG3047	Not used	Not used	Not used	
P7-8		GND Plate A	Not used	XNG3030	XNG3030	XNG3030	
P7-18		Volume Knob	XAA3013	XAA3022	XAA3022	XAA3022	
P7-21		FUNC Button L	XAD3061	XAD3118	XAD3118	XAD3118	No.8
		FUNC Cap L	Not used	XAK3247	XAK3247	XAK3247	No.7
P7-22		FUNC Button R	XAD3051	XAD3112	XAD3112	XAD3112	No.10
		FUNC Cap R	Not used	XAK3248	XAK3248	XAK3248	No.9
P7-23		FUNC Frame L	XAD3052	Not used	Not used	Not used	
P7-24		FUNC Frame R	XAD3053	Not used	Not used	Not used	
P7-25		DVD ENT Button	XAD3056	XAD3110	XAD3110		No.12
P7-26		Display Panel	XAK3135	XAK3238	XAK3238	XAK3238	
P7-27		EQ Panel	XAK3150	Not used	Not used	Not used	
		SC Panel	Not used	XAK3268	XAK3268	XAK3268	No.26
		SC Panel Assy	Not used	XXG3090	XXG3090	XXG3090	No.13
P7-28		JOG Lens	XAK3152	XAK3243	XAK3243	XAK3243	No.23

XV-VS800, XV-VS600

Ref. No.	Mark	Symbol and Description	Part No.				Remarks
			XR-A9800D /KUCXJ	XV-VS600 /DBDXJ	XV-VS600 /DDXJ/RB	XV-VS600 /DLXJ/NC	
P7-29	NSP	V Lens	XAK3153	XAK3237	XAK3237	XAK3237	No.24
P7-33		FL Cover	XAK3164	XAK3239	XAK3239	XAK3239	
P7-34		Cover Sheet L	XAK3184	Not used	Not used	Not used	
P7-35		Cover Sheet R	XAK3185	Not used	Not used	Not used	
		LED Barrier	Not used	XEC3022	XEC3022	XEC3022	
P7-36		Power Button	XAD3044	XAD3102	XAD3102	XAD3102	No.17
P7-37		CD Button	XAD3045	XAD3104	XAD3104	XAD3104	No.19
P7-38		SC Button	XAD3060	Not used	Not used	Not used	No.29
		SC Button L	Not used	XAD3105	XAD3105	XAD3105	
		SC Cap L	Not used	XAK3241	XAK3241	XAK3241	No.27
		SC Button R	Not used	XAD3106	XAD3106	XAD3106	No.30
		SC Cap R	Not used	XAK3267	XAK3267	XAK3267	No.28
		ASES Button	Not used	XAD3114	XAD3114	XAD3114	No.20
		Timer Button	Not used	XAD3115	XAD3115	XAD3115	No.21
P7-39		SC Button L	XAD3047	Not used	Not used	Not used	No.14
		Audio Button	Not used	XAD3107	XAD3107	XAD3107	
P7-40		SC Button R	XAD3049	Not used	Not used	Not used	
		Visual Button	Not used	XAD3108	XAD3108	XAD3108	No.15
P7-41		DOLBY Button	XAD3054	XAD3121	XAD3121	XAD3121	No.11
P7-42		Sub Panel	XAK3203	XAK3246	XAK3246	XAK3246	No.6
P7-43		Standby Lens	XAK3151	XAK3240	XAK3240	XAK3240	No.18
P7-44		Deck Lens L	XAK3159	XAK3249	XAK3249	XAK3249	No.3
P7-45		Deck Lens R	XAK3160	XAK3250	XAK3250	XAK3250	No.5
P7-46		JOG Conductor	XAK3165	XAK3244	XAK3244	XAK3244	No.22
P7-47		Deck Door_L	XAN3022	XAN3037	XAN3037	XAN3037	No.2
P7-48		Deck Door_R	XAN3026	XAN3038	XAN3038	XAN3038	No.4
P7-49		Front Panel	XMB3027	XMB3058	XMB3058	XMB3058	No.1
P7-50		DV Button L	XAD3057	Not used	Not used	Not used	No.16
P7-51		DV Button R	XAD3059	Not used	Not used	Not used	
P7-52		Front Panel ASSY	XXG3066	XXG3080	XXG3080	XXG3080	
		O/C Button	Not used	XAD3103	XAD3103	XAD3103	
		Spacer	XEB3012	Not used	Not used	Not used	
		Spacer	XEB3013	Not used	Not used	Not used	
		Cushion Spacer	XEB3015	Not used	Not used	Not used	
		Cushion Spacer	XEB3016	Not used	Not used	Not used	
		Cushion Spacer	XEB3017	Not used	Not used	Not used	
		Spacer	XEC3014	Not used	Not used	Not used	
		Spacer	XEC3019	Not used	Not used	Not used	

Notes : For PCB ASSEMBLIES, Refer to “CONTRAST OF PCB ASSEMBLIES” and “3. SCHEMATIC DIAGRAM”.

The numbers in the remarks column correspond to the numbers on the “ FRONT PANEL ASSY ”.

*1 Refer to “3. SCHEMATIC DIAGRAM”. *2 Stick Name Label on the Rear Panel. *3 Refer to “LABEL CHECK”.


■ CONTRAST OF \$M MECHA. DVD

XXA3018 and XXA3019 are constructed the same except for the following :

Ref. No.	Mark	Symbol and Description	Part No.		Remarks
			XXA3019 (XR-A9800D)	XXA3018 (XV-VS600)	
P5-10		CONNECT ASSY (6CH)	XWX3023	Not used	
P5-10		CONNECT ASSY (2CH)	Not used	XWX3019	
P5-14		25P Flexible Cable	XDD3046	Not used	
P5-14		15P Flexible Cable	Not used	XDD3049	
P5-18		30P Flexible Cable	XDD3044	Not used	
P5-18		16P Flexible Cable	Not used	XDD3043	
P5-21		7P Flexible Cable/30V	XDD3053	ADD7197	
P5-23		DVD Base	XNG3034	ANG7262	
P5-24		DVD Shield	XNK3006	ANK7066	
P5-55		21P Flexible Cable	XDD3052	Not used	
P5-55		7P Flexible Cable	Not used	XDD3045	

Notes : For PCB ASSEMBLIES, Refer to “PCB PARTS LIST”, “3. SCHEMATIC DIAGRAM” and “4. PCB CONNECTION DIAGRAM”.

FRONT PANEL ASSY



(1) FRONT PANEL ASSY PARTS LIST

Mark	No.	Description	Part No.	Mark	No.	Description	Part No.
	1	Front Panel	XMB3058		16	O/C Button	XAD3103
	2	Deck Door_L	XAN3037		17	Power Button	XAD3102
	3	Deck Lens L	XAK3249		18	Standby Lens	XAK3240
	4	Deck Door_R	XAN3038		19	CD Button	XAD3104
	5	Deck Lens R	XAK3250		20	ASES Button	XAD3114
	6	Sub Panel	See Contrast table (2)		21	Timer Button	XAD3115
	7	FUNC Cap L	XAK3247		22	JOG Conductor	XAK3244
	8	FUNC Button L	XAD3118		23	JOG Lens	XAK3243
	9	FUNC Cap R	XAK3248		24	LED Barrier	XEC3022
	10	FUNC Button R	XAD3112		25	Screw	BPZ30P100FZK
	11	DOLBY Button	XAD3121		26	SC Panel	XAK3268
	12	CD ENT Button	XAD3110		27	SC Cap L	XAK3241
	13	SC Panel Assy	XXG3090		28	SC Cap R	XAK3267
	14	Audio Button	XAD3107		29	SC Button L	XAD3105
	15	Visual Button	XAD3108		30	SC Button R	XAD3106

(2) CONTRAST TABLE

XV-VS600 and XV-VS800 are constructed the same except for the following :

Mark	No.	Symbol and Description	Part No.		Remarks
			XV-VS800	XV-VS600	
	6	Sub Panel	XAK3271	XAK3246	

■ CONTRAST OF PCB ASSEMBLIES

IF AF ASSY

XWZ3322, AWU7789 and XWZ3330 are constructed the same except for the following :

Mark	Symbol and Description	Part No.			Remarks
		XWZ3330	XWZ3322	AWU7789	
△	IC3301	STK407-070B	STK407-070B	STK407-090B	
△	IC3305, IC3306 (5A)	AEK7019	AEK7019	Not used	
△	IC3305, IC3306 (7A)	Not used	Not used	AEK7021	
	IC3835	Not used	M65847AFP	M65847AFP	
△	Q3351	IRFI9Z34G	IRFI9Z34G	IRF9540A	
△	Q3352	IRFIZ34G	IRFIZ34G	IRF540A	
	Q3803	Not used	2SD1858X	2SD1858X	
	D3002	1SS133	1SS133	Not used	
	D3803	Not used	MTZJ5.6B	MTZJ5.6B	
	F2201, F2202	RTF1209	XTF3002	XTF3002	
	L3065 CHIP BEAD	VTL1081	VTL1081	Not used	
	L3065	Not used	Not used	LCTB4R7K1608	
	C3011, C3012	Not used	Not used	CEAT100M50	
	C3042, C3991	CKSRYB103K50	CKSRYB103K50	Not used	
	C3045, C3046, C3091	CEAT100M50	CEAT100M50	CEAT101M16	
	C3623, C3624	CKSRYB471K50	CKSRYB471K50	Not used	
	C3625	CEAT330M16	CEAT330M16	Not used	
	C3815	Not used	CEAT100M50	CEAT100M50	
	C3816, C3819	Not used	CEAT470M16	CEAT470M16	
	C3817	Not used	CKSRYB473K16	CKSRYB473K16	
	C3818	Not used	CCSRCH101J50	CCSRCH101J50	
	C3828–C3830	Not used	CKSRYB683K16	CKSRYB683K16	
	C3831	Not used	CKSRYB102K50	CKSRYB102K50	
	C3832	Not used	CKSRYB122K50	CKSRYB122K50	
	C3833–C3836	Not used	CKSRYB103K50	CKSRYB103K50	
	C3837	Not used	CCSRCH471J50	CCSRCH471J50	
	C3838	Not used	CKSRYB472K50	CKSRYB472K50	
	C3839, C3840	Not used	CKSRYB224K10	CKSRYB224K10	
	C3842, C3843	Not used	CEAT2R2M50	CEAT2R2M50	
	C3858	CEAT100M50	Not used	Not used	
	C3890	Not used	CKSRYB822K50	CKSRYB822K50	
	R3010	RS1/16S822J	RS1/16S822J	RS1/16S472J	
	R3026	RD1/4PU822J	RD1/4PU822J	RD1/4PU472J	
	R3619, R3620	RD1/4LMF100J	RD1/4LMF100J	RD1/2LMF100J	
	R3627	RS1/16S471J	RS1/16S471J	Not used	
	R3831	Not used	RD1/4PU102J	RD1/4PU102J	
	R3832–R3834	Not used	RS1/16S102J	RS1/16S102J	
	R3835, R3839	Not used	RS1/16S682J	RS1/16S682J	
	R3836, R3837	Not used	RS1/16S472J	RS1/16S472J	
	R3838, R3846	Not used	RS1/16S153J	RS1/16S153J	
	R3840–R3842, R3844, R3845	Not used	RS1/16S103J	RS1/16S103J	
	R3843	Not used	RS1/16S562J	RS1/16S562J	
	R3855	Not used	RS1/16S680J	RS1/16S680J	
	CN3601 4P SPEAKER TERMINAL	AKE7018	XKE3004	AKE7018	
	CN3603 9P JUMPER CONNECTOR	KPE9	KPE9	Not used	
	CN5104 30P FFC CONNECTOR	HLEM30R-1	HLEM30R-1	Not used	
	CN5104 16P FFC CONNECTOR	Not used	Not used	HLEM16R-1	
	JA3441 2P PIN JACK	Not used	Not used	VKB1060	
	JA3991 HEADPHONE JACK	XKN3009	XKN3009	AKN-056	
	SCREW	Not used	Not used	BBZ30P140FMC	
	MICA SHEET	Not used	Not used	XEE3003	
	FET BRACKET	Not used	Not used	XNG3016	

REAR AMP ASSY

XWZ3319 and XWZ3325 are constructed the same except for the following :

Mark	Symbol and Description	Part No.		Remarks
		XWZ3325	XWZ3319	
△	IC3401	STK402-230	Not used	
	Q3401-Q3404	2SD2114K	Not used	
	Q3405, Q3410	DTA124EK	Not used	
	Q3406-Q3409, Q3411-Q3413, Q3415	2SC2412K	Not used	
	Q3414, Q3471, Q3472	2SA1037K	Not used	
	D3425, D3426, D3471, D3472	1SS355	Not used	
	D3403-D3406, D3408, D3427, D3428	1SS133	Not used	
	D3409	MTZJ12C	Not used	
	D3429	MTZJ4.7B	Not used	
	L3401-L3403 AF CHOKE COIL	ATH-133	Not used	
	L3404 CHIP BEAD	VTL1081	Not used	
	RY3401, RY3402	ASR7017	Not used	
	C3401-C3403	CEANP2R2M50	Not used	
	C3404-C3406	CKSRYB222K50	Not used	
	C3407-C3409	CCSRCH221J50	Not used	
	C3410-C3412	CEANP100M35	Not used	
	C3413-C3415	CCSRCJ3R0C50	Not used	
	C3416, C3417, C3431	CEAT101M50	Not used	
	C3419	CEATR47M50	Not used	
	C3420	CEAT101M10	Not used	
	C3421	CEAT100M50	Not used	
	C3422, C3471, C3472	CCSRCH100D50	Not used	
	C3423, C3424, C3429	CKSRYB103K50	Not used	
	C3425-C3428	CKSRYF104Z25	Not used	
	C3432	CEAT221M16	Not used	
	R3401-R3404	RS1/16S332J	Not used	
	R3405-R3408	RS1/16S102J	Not used	
	R3409-R3411	RS1/10S273J	Not used	
	R3412	RS1/10S104J	Not used	
	R3413-R3415	RS1/16S563J	Not used	
	R3416-R3418	RS1/10S561J	Not used	
	R3419-R3421	RD1/4PU563J	Not used	
	R3422	RS1/10S223J	Not used	
	R3424	RS1/16S102J	Not used	
	R3425-R3428	RS1/10S823J	Not used	
	R3429, R3430, R3432	RS1/10S153J	Not used	
	R3433	RS1/16S273J	Not used	
	R3434, R3475, R3476	RS1/10S392J	Not used	
	R3435	RS1/16S104J	Not used	
	R3436-R3437, R3439, R3440	RS1/16S223J	Not used	
	R3438	RS1/16S103J	Not used	
	R3441	RS1/16S224J	Not used	
	R3442-R3444	RD1/4LMF100J	Not used	
	R3445-R3447	RS1/16S100J	Not used	
	R3448	RS3LMF102J	Not used	
	R3449	RD1/4PU681J	Not used	
	R3471-R3473	RS1LMFR22J	Not used	
	R3477-R3478	RD1/4MUF101J	Not used	
	R3474	RS1/16S0R0J	Not used	
	CN3401 1P PIN JACK	AKB7042	Not used	
	CN3404 FFC CONNECTOR 25P	HLEM25R-1	Not used	
	CN3404 FFC CONNECTOR 15P	Not used	HLEM15R-1	
	J3401 JUMPER WIRE	D15A09-100-2651	Not used	
	JA3403 AUDIO 3P PIN JACK	XKB3007	Not used	
	J3409 JUMPER WIRE	DB018NT0	Not used	
	9P CABLE HOLDER	51063-0905	51063-1105	
	11P CABLE HOLDER	51063-1105	Not used	

MF DISPLAY ASSY

AWU7801, AWU7800 and XWZ3331 are constructed the same except for the following :

Mark	Symbol and Description	Part No.			Remarks
		XWZ3331	AWU7801	AWU7800	
	IC3931 IC5601 Q5822-Q5824, Q5827 D3931 D5592	Not used HEF4794BT Not used Not used 1SS133	M65855FP HEF4794BT Not used MTZJ5.1B Not used	M65855FP Not used DTC143EK MTZJ5.1B Not used	
	D5593 D5595 D5601-D5608, D5622 D5610, D5611, D5615, D5616, D5904 D5612, D5614	1SS133 1SS181 SLP3118C51H SLP3118C51H SLP6118C51H	1SS133 1SS181 SLR-343MC(NPQ) SLR-343MC(NPQ) SLR-343DC(NPQ)	Not used Not used SLR-343MC(NPQ) SLR-343MC(NPQ) SLR-343DC(NPQ)	
	D5617 D5618 D5619, D5620, D5903 D5621 D5902	SLP6118C51H SLP3118C51H SLP9118C51H SLP6118C51H SLP7118C51H	Not used Not used SLR-343VC(NPQ) SLR-343MC(NPQ) SLR-343PC(KLM)	Not used Not used SLR-343VC(NPQ) SLR-343MC(NPQ) SLR-343PC(KLM)	
	S5911-S5913, S5915-S5940 L3921, L3922 CHIP BEAD L3931 C3931, C3934, C3940 C3932	XSG3001 VTL1081 Not used Not used Not used	ASG1051 VTL1081 LCTB100K2125 CKSRYB103K50 CEJAR47M50	ASG1051 Not used LCTB100K2125 CKSRYB103K50 CEJAR47M50	
	C3933 C3935 C3937 C3938 C3939	Not used Not used Not used Not used Not used	CEJQ220M10 CKSRYB473K16 CEJA4R7M50 CKSRYB472K50 CKSRYB123K50	CEJQ220M10 CKSRYB473K16 CEJA4R7M50 CKSRYB472K50 CKSRYB123K50	
	C3942 C3943 C5601 C5603, C5604 R3931	Not used Not used CCSRCH101J50 CCSRCH100D50 Not used	CKSRYF104Z25 CEJQ101M10 CCSRCH101J50 CCSRCH100D50 RS1/16S472J	CKSRYF104Z25 CEJQ101M10 Not used Not used RS1/16S472J	
	R3932, R3937, R3938 R3933 R3934 R3935 R3936	Not used Not used Not used Not used Not used	RS1/16S123J RS1/16S153J RS1/16S124J RS1/16S822J RS1/16S103J	RS1/16S123J RS1/16S153J RS1/16S124J RS1/16S822J RS1/16S103J	
	R3939 R3940 R5590, R5984, R5985, R5987, R5990 R5591 R5610	RS1/16S0R0J Not used RS1/16S473J RS1/16S152J Not used	Not used RD1/4PU121J RS1/16S473J RS1/16S152J Not used	Not used RD1/4PU121J Not used Not used RS1/16S0R0J	
	R5619 R5620, R5621, R5626 R5986, R5988, R5989 R9901, R9902 VR3931 (10kΩ-B)	RS1/16S221J RS1/16S102J RS1/16S103J Not used Not used	RS1/16S221J RS1/16S102J RS1/16S103J RS1/16S101J XCS3002	Not used Not used Not used RS1/16S101J XCS3002	
	CN5502 FFC CONNECTOR 21P CN5502 FFC CONNECTOR 7P	52492-2120 Not used	52492-2120 Not used	Not used 52492-0720	

JF SECONDARY ASSY

XWZ3317 and XWZ3323 are constructed the same except for the following :

Mark	Symbol and Description	Part No.		Remarks
		XWZ3323	XWZ3317	
△	C33, C34 (4700μF/80V)	ACH7071	Not used	
△	C33, C34 (4700μF/71V)	Not used	XCH3001	

LF PRIMARY ASSY

XWZ3326, XWZ3320 and XWZ3332 are constructed the same except for the following :

Mark	Symbol and Description	Part No.			Remarks
		XWZ3332	XWZ3326	XWZ3320	
△	S1 VOLTAGE SELECTOR	Not used	XKX3001	XKX3001	
△	R1 (2.2MΩ/ 1/2W)	RCN1080	Not used	Not used	
△	AN1 1P AC INLET	XKP3042	XKP3041	XKP3041	
△	CN2 4P VH CONNECTOR	Not used	B4P7-VH	B4P7-VH	
	H3-H6 FUSE CLIP	Not used	AKR7001	AKR7001	

Mark No. Description Part No.

● PCB PARTS LIST for XV-VS600

GF CONNECT ASSY (2CH)

SEMICONDUCTORS

IC8202	LA7137M
IC8203	NJM78L08A
IC8301	PCM1716E
IC8201	TA7302P
Q8203, Q8204	2PB709A
Q8205, Q8206	2SD2114K
Q8302	DTA124EK
Q8201	DTC114YK
Q8301	DTC124EK
Q8202	PDTA124EK
D8304, D8305	1SS355

COILS AND FILTERS

L8201	LCTA470J2520
L8241-L8245 CHIP BEADS	VTL1081
L8103 CHIP BEADS	VTL1095
L8205 CHIP SOLID INDUCTOR	VTL1145

CAPACITORS

C8104	CCSRCH101J50
C8105, C8106, C8109, C8110, C8316	CCSRCH221J50
C8201	CCSRCH390J50
C8111	CEAT102M10
C8311, C8312	CEJA100M16

Mark No. Description Part No.

C8209, C8210, C8217, C8226, C8227	CEJA101M10
C8235	CEJA101M10
C8212, C8223	CEJA331M6R3
C8302, C8305, C8306, C8309	CEJA470M10
C8317	CEJQ470M10
C8301, C8315	CGCYX104K25
C8101, C8232, C8233, C8304	CKSRYB103K50
C8202-C8206, C8208, C8211	CKSRYB104K16
C8213, C8214, C8216, C8221, C8222	CKSRYB104K16
C8228, C8236, C8237, C8308	CKSRYB104K16
C8313, C8314	CKSRYB681K50

RESISTORS


All Resistors	RS1/16S□□□J
---------------	-------------

OTHERS

CN8202	4P MINI DIN SOCKET	AKP7008
JA8203	OPTICAL LINK OUT	GP1F32T
CN8105	FFC CONNECTOR 15P	HLEM15S-1
CN8103	FFC CONNECTOR 16P	HLEM16S-1
CN8104	FFC CONNECTOR 7P	HLEM7S-1
JA8201	1P PIN JACK	VKB1063
CN8106	7P FFC CONNECTOR	VKN1183
CN8102	27P FFC CONNECTOR	VKN1203
CN8107	7P FFC CONNECTOR	VKN1211
CN8101	32P FFC CONNECTOR	VKN1263
KN8301	EARTH METAL FITTING	VNF1084
S8201	SLIDE SWITCH	VSH1020

GF CONNECT ASSY (2 CH)
(XWX3019)

 : AUDIO SIGNAL ROUTE
 (D)  : DVD AUDIO SIGNAL ROUTE
 (V)  : V SIGNAL ROUTE
 (Y)  : Y SIGNAL ROUTE
 (C)  : C SIGNAL ROUTE



3.2 AF (2/3) ASSY


A

B

C

D

- (TA) : TUNER AUDIO SIGNAL ROUTE
- (OUT) : REC OUT SIGNAL ROUTE
- ↗ : AUDIO SIGNAL ROUTE
- (F) : AUDIO (FRONT) SIGNAL ROUTE
- (PB) : DECK PB SIGNAL ROUTE
- (REC) : DECK REC SIGNAL ROUTE
- (K) : KARAOKE SIGNAL ROUTE
- (MIC) : MIC SIGNAL ROUTE




NOTES


ALL CAPACITORS ARE IN μ F
UNLESS OTHERWISE SPECIFIED

LA : CFTLA
M : CQMB
(OTHER : CKCYF)
CH : CCSQCH
SL : CCSQSL
YF : CKSQYF
(OTHER : CKSQYB)
AF : CEAL
HAO : CEHAO
(OTHER : CEAS***M#orCEAT***M#)

ALL RESISTORS ARE IN Ω
1/4W
1/10W (CHIP)
1/4WPU
ALL INDUCTORS ARE IN μ H
LAU
LCTB

D





CAUTION : FOR CONTINUED PROTECTION AGAINST RISK OF FIRE. REPLACE ONLY WITH
SAME TYPE NO. 4911.25 MFD, BY LITTELFUSE INC. FOR IC3302 (AEK7010).

CAUTION : FOR CONTINUED PROTECTION AGAINST RISK OF FIRE. REPLACE ONLY WITH SAME TYPE NO. 491005 MFD, BY LITTELFUSE INC. FOR IC15, IC3305 AND IC3306 (AEK7019).

CAUTION : FOR CONTINUED PROTECTION AGAINST RISK OF FIRE. REPLACE ONLY WITH SAME TYPE NO. 491.630 MFD, BY LITTELFUSE INC. FOR IC17 (AEK7006).

CAUTION : FOR CONTINUED PROTECTION AGAINST RISK OF FIRE. REPLACE ONLY WITH SAME TYPE NO. 491004 MFD, BY LITTELFUSE INC. FOR IC16 (AEK7018).

CAUTION : FOR CONTINUED PROTECTION AGAINST RISK OF FIRE. REPLACE ONLY WITH SAME TYPE NO. 491010 MFD, BY LITTELFUSE INC. FOR IC11 AND IC12 (AEK7022).

CAUTION : FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE NO. 491010F MFD, BY LITTELFUSE INC. FOR IC13 AND IC14 (AEK7068).

3.4 PRIMARY ASSY

NOTES

ALL CAPACITORS ARE IN μF
UNLESS OTHERWISE SPECIFIED

$\perp$ TL : CFTLA
 $\top$ M : CQMB
 (OTHER : CKCYF)

ALL RESISTORS ARE IN Ω

1/4WPU




ALL INDUCTORS ARE IN μH


 LAU

NO MARK DIODE

1SS133

POWER TRANSFORMER
XV-VS800 : XTS3055
XV-VS600 : XTS3039





• NOTE FOR FUSE REPLACEMENT

CAUTION -FOR CONTINUED PROTECTION AGAINST RISK OF FIRE.
REPLACE WITH SAME TYPE AND RATINGS ONLY.


3.5 DISPLAY and BLUE LED ASSYS

A

B


C

D



8

D



D

