

AV AMPLIFIER

# DSP-A592

## SERVICE MANUAL

### IMPORTANT NOTICE

This manual has been provided for the use of authorized YAMAHA Retailers and their service personnel. It has been assumed that basic service procedures inherent to the industry, and more specifically YAMAHA Products, are already known and understood by the users, and have therefore not been restated.

**WARNING:** Failure to follow appropriate service and safety procedures when servicing this product may result in personal injury, destruction of expensive components and failure of the product to perform as specified. For these reasons, we advise all YAMAHA product owners that all service required should be performed by an authorized YAMAHA Retailer or the appointed service representative.

**IMPORTANT:** The presentation or sale of this manual to any individual or firm does not constitute authorization, certification or recognition of any applicable technical capabilities, or establish a principle-agent relationship of any form.

The data provided is believed to be accurate and applicable to the unit(s) indicated on the cover. The research, engineering, and service departments of YAMAHA are continually striving to improve YAMAHA products. Modifications are, therefore, inevitable and specifications are subject to change without notice or obligation to retrofit. Should any discrepancy appear to exist, please contact the distributor's Service Division.

**WARNING:** Static discharges can destroy expensive components. Discharge any static electricity your body may have accumulated by grounding yourself to the ground buss in the unit (heavy gauge black wires connect to this buss).

**IMPORTANT:** Turn the unit OFF during disassembly and parts replacement. Recheck all work before you apply power to the unit.

### ■ CONTENTS

|                                           |     |                                  |       |
|-------------------------------------------|-----|----------------------------------|-------|
| TO SERVICE PERSONNEL .....                | 1   | ADJUSTMENTS .....                | 8     |
| FRONT PANEL .....                         | 1   | IC DATA .....                    | 9~12  |
| REAR PANELS .....                         | 2   | PIN CONNECTION DIAGRAM .....     | 13    |
| SPECIFICATIONS .....                      | 3   | PRINTED CIRCUIT BOARD .....      | 14~23 |
| INTERNAL VIEW .....                       | 4   | BLOCK DIAGRAM .....              | 24~25 |
| DISASSEMBLY PROCEDURES .....              | 4   | SCHEMATIC DIAGRAM .....          | 26~30 |
| SELF CHECK MODE .....                     | 5~7 | PARTS LIST .....                 | 31~41 |
| PROTECTION OPERATION CHECK FUNCTION ..... | 7   | REMOTE CONTROL TRANSMITTER ..... | 42    |

100580

**YAMAHA**  
YAMAHA CORPORATION  
P.O.Box1, Hamamatsu, Japan


1.65K-72.177 Printed in Japan '97.5

DSP-A592



## ■ TO SERVICE PERSONNEL

### Critical Components Information.

Components having special characteristics are marked and must be replaced with parts having specifications equal to those originally installed.




## ■ FRONT PANEL



### WARNING

Do not change the **IMPEDANCE SELECTOR** switch setting while the power to this unit is on, otherwise this unit may be damaged.





## SPECIFICATIONS

### Minimum RMS Output Power Per Channel

|                                  |     |
|----------------------------------|-----|
| MAIN (20Hz—20kHz, 0.04% THD, 8Ω) | 70W |
| CENTER (1kHz, 0.07% THD, 8Ω)     | 70W |
| REAR (1kHz, 0.3% THD, 8Ω)        | 35W |

### Maximum Power (R model)

|                                   |      |
|-----------------------------------|------|
| MAIN & CENTER (1kHz, 10% THD, 8Ω) | 110W |
| REAR (1kHz, 10% THD, 8Ω)          | 50W  |

### Dynamic Power Per Channel

|                                            |                    |
|--------------------------------------------|--------------------|
| (by IHF Dynamic Headroom Measuring Method) |                    |
| MAIN (8Ω/6Ω/4Ω/2Ω)                         | 95W/120W/150W/170W |

### DIN Standard Output Power Per Channel (G model)

|                           |      |
|---------------------------|------|
| MAIN (1kHz, 0.7% THD, 4Ω) | 110W |
|---------------------------|------|

### IEC Power (G model)

|                           |     |
|---------------------------|-----|
| MAIN (1kHz, 0.1% THD, 8Ω) | 85W |
|---------------------------|-----|

### Power Band Width

|                          |            |
|--------------------------|------------|
| MAIN (0.09% THD, 30W/8Ω) | 10Hz—50kHz |
|--------------------------|------------|

### Damping Factor

|                       |    |
|-----------------------|----|
| MAIN (20Hz—20kHz, 8Ω) | 80 |
|-----------------------|----|

### Input Sensitivity/Impedance

|                     |            |
|---------------------|------------|
| PHONO (MM)          | 2.5mV/47kΩ |
| CD, etc             | 150mV/47kΩ |
| 6 ch DISCRETE INPUT | 150mV/50kΩ |

### Maximum Input Signal (1kHz)

|                       |       |
|-----------------------|-------|
| PHONO (MM), 0.04% THD | 110mV |
| CD, etc, 0.5% THD     | 2.2V  |

### Output Level/Impedance (Effect off)

|                       |             |
|-----------------------|-------------|
| REC OUT               | 150mV/2.5kΩ |
| PRE OUT (MAIN/CENTER) | 2.2V/1.2kΩ  |
| PRE OUT (REAR)        | 1.6V/1.2kΩ  |
| SUB WOOFER            | 6.0V/1.5kΩ  |

### Headphone Jack Rated Output/Impedance

|               |           |
|---------------|-----------|
| 0.04% THD, 8Ω | 0.5V/390Ω |
|---------------|-----------|

### Frequency Response (20Hz—20kHz)

|          |         |
|----------|---------|
| CD, etc. | 0±0.5dB |
|----------|---------|

### RIAA Equalization Deviation(20Hz—20kHz)

|            |         |
|------------|---------|
| PHONO (MM) | 0±0.5dB |
|------------|---------|

### Total Harmonic Distortion

|                                       |        |
|---------------------------------------|--------|
| PHONO (MM) to REC OUT (20Hz—20kHz) 1V | 0.02%  |
| CD, etc. to MAIN SP out               |        |
| 20Hz—20kHz, 30W/8Ω (Effect off)       | 0.025% |

### Signal-to-Noise Ratio (IHF-A-Network)

|                           |      |
|---------------------------|------|
| PHONO (MM), Input Shorted |      |
| R models                  | 85dB |
| B, G models               | 82dB |
| CD, etc, Input Shorted    | 98dB |

### Residual Noise (IHF-A-Network)

|                  |       |
|------------------|-------|
| MAIN L, R SP out | 140μV |
|------------------|-------|

### Channel Separation (Vol -30dB, Effect off)

|                                          |           |
|------------------------------------------|-----------|
| PHONO (MM), Input Shorted, 1kHz/10kHz    | 60dB/50dB |
| CD, etc, Input 5.1kΩ Shorted, 1kHz/10kHz | 60dB/45dB |

### Tone Control Characteristics

|        |                    |               |
|--------|--------------------|---------------|
| Bass   | Boost/Cut          | ±10dB (50Hz)  |
|        | Turnover frequency | 350Hz         |
| Treble | Boost/Cut          | ±10dB (20kHz) |
|        | Turnover frequency | 3.5kHz        |

### BASS EXTENTION

+6dB (50Hz)

### Gain Tracking Error (0dB to -60dB)

3dB

### Video

|                                |   |                 |
|--------------------------------|---|-----------------|
| Video Signal Type              |   | NTSC/PAL        |
| R model                        |   | PAL             |
| B, G models                    |   | 1Vp-p/75Ω       |
| Video Signal Level             |   | 1Vp-p/75Ω       |
| S-Video Signal Level           | Y | 0.286Vp-p/75Ω   |
|                                | C |                 |
| Maximum Input Level            |   | 1.5Vp-p         |
| S/N                            |   | 50dB            |
| Monitor Out Frequency Response |   | 5Hz—10MHz, -3dB |

### Power Supply

|             |                            |
|-------------|----------------------------|
| B, G models | AC230V 50Hz                |
| R model     | AC110/120/220/240V 60/50Hz |

### Power Consumption

270W

### AC Outlets

|                              |                 |
|------------------------------|-----------------|
| 3 Switched Outlets (R model) | 100W max. total |
| 2 Switched Outlets (G model) | 100W max. total |
| 1 Switched Outlet (B model)  | 100W max.       |

### Dimensions (W x H x D)

435 x 151 x 379.5mm  
(17-1/8" x 5-15/16" x 14-15/16")

### Weight

11.0kg (24 lbs. 4 oz)

\*Specifications are subject to change without notice.


**B** ..... British model

**G** ..... European model

**R** ..... General model


Manufactured under license from Dolby Laboratories Licensing Corporation. "Dolby", "Pro Logic", and the double-D symbol  are trademarks of Dolby Laboratories Licensing Corporation.

## DIMENSIONS



Unit : mm (inch)

## ■ INTERNAL VIEW



- ① P. C. B. INPUT (4)
- ② P. C. B. INPUT (3)
- ③ P. C. B. AMP (3)
- ④ P. C. B. OPERATION (4)
- ⑤ P. C. B. INPUT (2)
- ⑥ P. C. B. AMP (4)
- ⑦ P. C. B. AMP (2)
- ⑧ P. C. B. AMP (1)
- ⑨ P. C. B. OPERATION (3)
- ⑩ P. C. B. INPUT (1)
- ⑪ P. C. B. OPERATION (2)

## ■ DISASSEMBLY PROCEDURES (Remove parts in disassembly order as numbered.)

### 1. Removal of Top Cover

- a. Remove 4 screws ( ① ) and 4 screws ( ② ) in Fig. 1.

### 2. Removal of Bottom Cover

- a. Remove 6 screws ( ③ ) in Fig. 1.

### 3. Removal of Front Panel

- a. Remove 4 knobs.
- b. Remove 6 screws ( ④ ) in Fig. 1.




Fig. 1

## ■ SELF CHECK MODE (SELF)

This machine has the SELF CHECK MODE (SELF) for facilitating inspection and measurement.

### HOW TO START & CANCEL

Turn the POWER switch ON while pressing the DVD/LD and CONCERT HALL keys simultaneously, and then the unit enters the SELF CHECK MODE (SELF). FL displays "SELF 1" first.

(The INPUT CD and SW levels are 0dB.)

If the sound field program key of the main unit is pressed, the mode is set to the CHECK mode of that number. It is possible to select the INPUT even during the self check (except for SELF 8).

\* Switching between 2CH and 6CH is possible when SELF1 is selected.

To cancel the SELF CHECK MODE, turn the POWER switch OFF or press the CONCERT HALL key. (The unit enters the normal mode.)

### CONTENTS OF SELF CHECK MODE

| No. | Menu                       | Select Key                                    |
|-----|----------------------------|-----------------------------------------------|
| 1   | RAM THROUGH A              | <input checked="" type="checkbox"/> PRO LOGIC |
| 2   | RAM THROUGH B              | ENHANCED                                      |
| 3   | RAM THROUGH C              | CONCERT VIDEO                                 |
| 4   | EFFECT OFF/DISCO/FL ALL ON | MONO MOVIE                                    |
| 5   | MANUAL TEST                | STADIUM                                       |
| 6   | DOLBY PRO LOGIC            | DISCO                                         |
| 7   | MAKER PRESET               | ROCK CONCERT                                  |
| 8   | EXIT                       | CONCERT HALL                                  |

### HOW TO USE SELF CHECK MODE


In order to confirm characteristics (specifications) listed in the table below, use SELF NO. 1, 3 and 4. (For specifications, refer to page 3.)

| No. | Items                                                                                                                                                                                                                                               |
|-----|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1   | <ul style="list-style-type: none"> <li>Output Level/Impedance</li> <li>Frequency Response</li> <li>Total Harmonic Distortion (Rec Out &amp; MAIN)</li> <li>S/N</li> </ul>                                                                           |
| 3   | <ul style="list-style-type: none"> <li>Minimum RMS Output Power Per Channel (Center &amp; Rear)</li> <li>Total Harmonic Distortion (Rear)</li> </ul>                                                                                                |
| 4   | <ul style="list-style-type: none"> <li>Minimum RMS Output Power Per Channel (MAIN)</li> <li>Input Sensitivity/Impedance</li> <li>Headphone Jack Rated Output/Impedance</li> <li>Channel Separation</li> <li>Tone Control Characteristics</li> </ul> |

### DETAILS OF SELF CONTENT

#### SELF 1 RAM THROUGH A


- MAIN L/R is output through the bypass.
- CENTER is output with the steering OFF and by  $(L+R)/2$ . (WIDE mode)
- RL/RR passes through the PS-RAM and is output through the DSP.
- The electronic volume is 0dB for CENTER and -2dB for REAR.
- FL displays "SELF 1"



|          |                     |
|----------|---------------------|
| CD INPUT | : 1kHz, -20dB       |
| VOLUME   | : MAX               |
| PRE OUT  | : MAIN +4.1dB±1dB   |
|          | : REAR +1.0dB±1dB   |
|          | : CENTER +4.9dB±1dB |

## SELF 2 RAM THROUGH B


- L/R and RL/RR pass through the PS-RAM and are output through the DSP.
- CENTER is output with the steering OFF and by  $(L+R)/2$ . (WIDE mode)
- The electronic volume (for CENTER/REAR) is -10dB.
- FL displays "SELF 2"



CD INPUT : 1kHz, -20dB  
 VOLUME : MAX  
 PRE OUT : MAIN +3.5dB±1dB  
           : REAR -6.7dB±1dB  
           : CENTER -∞dB

## SELF 3 RAM THROUGH C

- L/R is output with the steering OFF.
- CENTER is output with the steering OFF and by  $(L+R)/2$ . (WIDE mode)
- RL/RR passes through the PS-RAM and is output through the DSP.
- The electronic volume is +10dB for CENTER and +9dB for REAR.
- FL displays "SELF 3"



CD INPUT : 1kHz, -35dB  
 VOLUME : MAX  
 PRE OUT : MAIN -10.4dB±1dB  
           : REAR -2.8dB±1dB  
           : CENTER -∞dB

## SELF 4 EFFECT OFF/DISCO/FL ALL ON

- Every time the MONO MOVIE key is pressed, the menu changes.
- 1: EFFECT OFF
  - 2: DISCO (electronic volume is 0dB.)
  - 3: FL displays all ON

## SELF 5 MANUAL TEST

- Every time STADIUM key is pressed, the TEST TONE shifts in the order of  $L \rightarrow C \rightarrow R \rightarrow S$  and is output. (The CENTER mode is WIDE)
- The electronic volume (for CENTER/REAR) is 0dB.

## SELF 6 DOLBY PRO LOGIC

- The auto input balance which is ON in the normal mode is turned OFF.
- CENTER MODE is changed by pressing the DISCO key or the CENTER MODE key.
- The electronic volume (for CENTER/REAR) is 0dB.
- The FL displays "SELF 6" and the center mode.

CD INPUT : 1kHz, -35dB  
 VOLUME : MAX  
 PRE OUT : MAIN -30.7dB±1dB  
           : REAR -∞dB  
           : CENTER -8.2dB±1dB

## SELF 7 MAKER PRESET

- Every time the ROCK CONCERT key is pressed, the mode changes between the KEEP DATA and PRESET modes. Turning OFF the power in the "PRESET" mode will restore the FACTORY PRESET mode.

### • Factory Preset

#### 1) SURROUND section

DELAY TIME : ☐ PRO LOGIC 20ms  
                   ENHANCED 20ms  
                   CONCERT VIDEO 28ms  
                   MONO MOVIE 20ms  
                   STADIUM 45ms  
                   DISCO 14ms  
                   ROCK CONCERT 17ms  
                   CONCERT HALL 30ms

CENTER MODE : NORMAL  
 VOLUME LEVEL : CENTER 0dB  
                   REAR 0dB  
                   SW 0dB

#### 2) SELECTOR section

INPUT : CD  
 VIDEO (BGV) : DVD/LD

## PROTECTION OPERATION CHECK FUNCTION

1. Turn the POWER switch ON while pressing the TUNER and CONCERT HALL keys simultaneously, and the protection operation mode and the microprocessor AD input value are displayed for 3 seconds.

Example : PRT-PS [AD value]  
 PRT-DC [AD value]  
 PRT-I

[PRT-PS] indicates detection of an abnormal voltage of the power supply.

[PRT-DC] indicates detection of an abnormal DC value from the amplifier.

[PRT-I] indicates detection of an abnormal overcurrent from the amplifier.

[PRT-NON] indicates no detection.

When the CONCERT HALL key is pressed during the above display, the input data are retained till they are cleared.  
 ("PRT-NON" appears on display when the data are cleared.)

2. Turn the POWER switch ON while pressing the TUNER and the ROCK CONCERT keys simultaneously, and the input value for detection of an abnormal power supply voltage and the input value for detection of an abnormal amplifier DC will be displayed.

Example : P - [AD value] D - [AD value]

[P- ] indicates detection of an abnormal power supply voltage.

[DC- ] indicates detection of an abnormal amplifier DC.

| Type of protection                            | Normal (AD value) | Abnormal (AD value) |
|-----------------------------------------------|-------------------|---------------------|
| Detection of an abnormal power supply voltage | 37 - 74           | 0 - 36 & 75 - 255   |
| Detection of an abnormal amplifier DC         | 3 - 35            | 0 - 2 & 36 - 255    |

Press any key, and the display will be canceled.

## SELF 8 EXIT

- "MODEL/DESTINATION" is displayed first. When the CONCERT HALL key is pressed again, the unit will exit the SELF CHECK mode and enters the NORMAL mode.




## ■ ADJUSTMENTS

### ● Confirmation of Idling Current




- 1) No signal applied.
- 2) Non-loaded condition.
- 3) Aging is not necessary.

| Item   | Test Point | Rating (DC) | Note                                                                                                                                                                                           |
|--------|------------|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| MAIN L | CB529      | 0.1mV~3mV   | If the measured voltage exceeds 3.1mV, cut the lead wires of R557(L ch), R565(R ch), R572(C ch), R731(RL ch) and R738(RR ch) and then check again if each measured value satisfies the rating. |
| MAIN R | CB530      |             |                                                                                                                                                                                                |
| CENTER | CB531      |             |                                                                                                                                                                                                |
| REAR L | R745       |             |                                                                                                                                                                                                |
| REAR R | R748       |             |                                                                                                                                                                                                |




#### Note)

- If R557(L ch), R565(R ch), R572(C ch), R731(RL ch) or R738(RR ch) have already been cut off and idling current does not flow, reconnect R557(820Ω), R565(820Ω), R572(820Ω), R731(1kΩ) or R738(1kΩ).
- Q514, Q516, Q518, Q708 and Q713 are transistors for temperature correction. Apply silicone grease to the contact surface with the heat sink.



# ■ IC DATA

IC601 : M38172M4-192FP  
8 bit  $\mu$ -COM



| Pin No. | Port | I/O | Function                                                              |
|---------|------|-----|-----------------------------------------------------------------------|
| 1       | P73  | I   | KEY AD IN 1 (A-D)                                                     |
| 2       | P72  | I   | METER IN (Not used) (A-D)                                             |
| 3       | P71  | I   | PROTECTION 1 DETECT ( PS ) (A-D)                                      |
| 4       | P70  | I   | PROTECTION 2 DETECT ( DC ) (A-D)                                      |
| 5       | P57  | I   | PROTECTION 3 DETECT ( I )                                             |
| 6       | P56  | O   | SCLK 2                                                                |
| 7       | P55  | O   | SOUT 2                                                                |
| 8       | P54  | I   | DO IN for tuner                                                       |
| 9       | P53  | O   | Full mute out [L : ON]                                                |
| 10      | P52  | I   | SCLK IN RDS                                                           |
| 11      | P51  | I/O | V2 market / RES OUT RDS                                               |
| 12      | P50  | I/O | V1 market / SDATA IN RDS                                              |
| 13      | P65  | I   | RDS SELECT IN [H : RDS]                                               |
| 14      | P64  | I   | DSP-A SELECT IN [H : DSPA]                                            |
| 15      | P63  | I   | 492 SELECT IN [H : 492]                                               |
| 16      | P62  | I   | V392 SELECT IN [H : V392]                                             |
| 17      | P61  | O   | Speaker relay out (Center & Rear) [EFFECT ON or 6ch or TEST mode : H] |
| 18      | P60  | O   | OPEN                                                                  |
| 19      | P47  | O   | CETUN for tuner                                                       |
| 20      | P46  | O   | TMUTE for tuner [L : ON]                                              |
| 21      | P45  | I/O | Standby = Pull up [L : LED ON]                                        |

## Protection 1 (3 pin)

Detection of an abnormal power supply voltage. Normal when AD value (37 - 74)/256. Detection starts 2 seconds after the power is turned ON.  
50ms wait time before detection

## Protection 2 (4 pin)

Detection of an abnormal amplifier DC. Normal when AD value (3 - 35)/256. Detection starts 2 seconds after the power is turned ON.


## Protection 3 (5 pin)

Detection of an abnormal amplifier overcurrent. Abnormality detected at H. Detection starts after the power is turned ON.

| Pin No. | Port  | I/O | Function                          |
|---------|-------|-----|-----------------------------------|
| 22      | P44   | I   | /ST for tuner [L : STEREO]        |
| 23      | P43   | I   | Power switch in [H : ON]          |
| 24      | P42   | I   | Power down detect [L : DOWN]      |
| 25      | P41   | I   | REMOTE CONTROL IN (INT1)          |
| 26      | P40   | I   | START IN RDS (INT0)               |
| 27      | RES   |     | RESET                             |
| 28      | XCIN  |     | GND                               |
| 29      | XCOUT |     | OPEN                              |
| 30      | XIN   |     | 6.3 MHz IN (CLOCK)                |
| 31      | XOUT  |     | 6.3 MHz OUT (CLOCK)               |
| 32      | VSS   |     | GND                               |
| 33      | P27   | O   | VIDEO SELECTOR A (VSEL1)          |
| 34      | P26   | O   | VIDEO SELECTOR B (VSEL2)          |
| 35      | P25   | O   | NOT VCR SELECT [H : VCR]          |
| 36      | P24   | O   | CE VR                             |
| 37      | P23   | O   | CE SEL                            |
| 38      | P22   | O   | CE DSP                            |
| 39      | P21   | O   | VOL UP OUT                        |
| 40      | P20   | O   | VOL DOWN OUT                      |
| 41      | P17   | O   | DSP SERIAL SELECT [H : DSP]       |
| 42      | P16   | O   | POWER RELAY OUT [H : ON]          |
| 43      | P15   | O   | SPEAKER RELAY OUT (MAIN) [H : ON] |
| 44      | P14   | O   | FL DIGIT 1 [H : ON]               |
| 45      | P13   | O   | FL DIGIT 2 [H : ON]               |
| 46      | P12   | O   | FL DIGIT 3 [H : ON]               |
| 47      | P11   | O   | FL DIGIT 4 [H : ON]               |
| 48      | P10   | O   | FL DIGIT 5 [H : ON]               |
| 49      | P07   | O   | FL DIGIT 6 [H : ON]               |
| 50      | P06   | O   | FL DIGIT 7 [H : ON]               |
| 51      | P05   | O   | FL DIGIT 8 [H : ON]               |
| 52      | P04   | O   | FL DIGIT 9 [H : ON]               |
| 53      | P03   | O   | FL DIGIT 10 [H : ON]              |
| 54      | P02   | O   | FL DIGIT 11 [H : ON]              |
| 55      | P01   | O   | FL DIGIT 12 [H : ON]              |
| 56      | P00   | O   | FL DIGIT 13 [H : ON]              |
| 57      | P37   | O   | FL SEGMENT 16 [H : ON]            |
| 58      | P36   | O   | FL SEGMENT 15 [H : ON]            |
| 59      | P35   | O   | FL SEGMENT 14 [H : ON]            |
| 60      | P34   | O   | FL SEGMENT 13 [H : ON]            |
| 61      | P33   | O   | FL SEGMENT 12 [H : ON]            |
| 62      | P32   | O   | FL SEGMENT 11 [H : ON]            |
| 63      | P31   | O   | FL SEGMENT 10 [H : ON]            |
| 64      | P30   | O   | FL SEGMENT 9 [H : ON]             |
| 65      | P87   | O   | FL SEGMENT 8 [H : ON]             |
| 66      | P86   | O   | FL SEGMENT 6 [H : ON]             |
| 67      | P85   | O   | FL SEGMENT 5 [H : ON]             |
| 68      | P84   | O   | FL SEGMENT 4 [H : ON]             |
| 69      | P83   | O   | FL SEGMENT 3 [H : ON]             |
| 70      | P82   | O   | FL SEGMENT 2 [H : ON]             |
| 71      | P81   | O   | FL SEGMENT 1 [H : ON]             |
| 72      | P80   | O   | FL SEGMENT 0 [H : ON]             |
| 73      | VCC   |     | +5V                               |
| 74      | VEE   |     | -21V                              |
| 75      | AVSS  |     | GND                               |
| 76      | VREF  |     | A-D REFERENCE VOLTAGE IN (+5V)    |
| 77      | P77   | I   | KEY AD IN 5 (A-D)                 |
| 78      | P76   | I   | KEY AD IN 4 (A-D)                 |
| 79      | P75   | I   | KEY AD IN 3 (A-D)                 |
| 80      | P74   | I   | KEY AD IN 2 (A-D)                 |

IC17 : YSS203B

Digital Dolby Pro Logic Decoder with Auto Input Balance



| No. | Name  | I/O | Function                                                 |
|-----|-------|-----|----------------------------------------------------------|
| 1   | CD    | Its | Serial data of parameter data input                      |
| 2   | TSBWD | Ic  | LSI test terminal Normally connected to DVDD terminal    |
| 3   | TI/O  | Ic  | LSI test terminal Normally connected to DVDD terminal    |
| 4   | AVDD  | A—  | +5V power supply (D/A, A/D section)                      |
| 5   | RL    | AO  | RL channel D/A output                                    |
| 6   | FL    | AO  | FL channel D/A output                                    |
| 7   | CHL   | A—  | LINS input Sample/hold Capacitor external terminal       |
| 8   | LINS  | AI  | L channel A/D input                                      |
| 9   | RINS  | AI  | R channel A/D input                                      |
| 10  | CHR   | A—  | RINS input Sample/hold Capacitor external terminal       |
| 11  | FR    | AO  | FR channel D/A output                                    |
| 12  | RR    | AO  | RR channel D/A output                                    |
| 13  | CV    | AO  | A/D, multiplying DAC center voltage                      |
| 14  | AGND  | A—  | Ground (D/A, A/D section)                                |
| 15  | AGND  | A—  | Ground (Multiplying DAC section)                         |
| 16  | VREF  | AI  | Multiplying DAC reference voltage input                  |
| 17  | LINM  | AI  | L channel Multiplying DAC input                          |
| 18  | RINM  | AI  | R channel Multiplying DAC input                          |
| 19  | VOLM  | AO  | L channel operation amplifier, connected to (–) terminal |
| 20  | VOLP  | AO  | L channel operation amplifier, connected to (+) terminal |

| No. | Name  | I/O             | Function                                                             |
|-----|-------|-----------------|----------------------------------------------------------------------|
| 21  | VOCM  | AO              | C channel operation amplifier, connected to (–) terminal             |
| 22  | VOCP  | AO              | C channel operation amplifier, connected to (+) terminal             |
| 23  | VORM  | AO              | R channel operation amplifier, connected to (–) terminal             |
| 24  | VORP  | AO              | R channel operation amplifier, connected to (+) terminal             |
| 25  | AVDD  | A—              | +5V power supply (multiplying DAC section)                           |
| 26  | DVDD  | —               | +5V power supply (digital section)                                   |
| 27  | D7    | I/Ot            | External delay RAM data terminal                                     |
| 28  | D6    | I/Ot            | External delay RAM data terminal                                     |
| 29  | D5    | I/Ot            | External delay RAM data terminal                                     |
| 30  | D4    | I/Ot            | External delay RAM data terminal                                     |
| 31  | D3    | I/Ot            | External delay RAM data terminal                                     |
| 32  | D2    | I/Ot            | External delay RAM data terminal                                     |
| 33  | D1    | I/Ot            | External delay RAM data terminal                                     |
| 34  | D0    | I/Ot            | External delay RAM data terminal                                     |
| 35  | A0    | O               | External data RAM address terminal                                   |
| 36  | A1    | O               | External data RAM address terminal                                   |
| 37  | A2    | O               | External data RAM address terminal                                   |
| 38  | A3    | O               | External data RAM address terminal                                   |
| 39  | A4    | O               | External data RAM address terminal                                   |
| 40  | DGND  | —               | Ground (digital section)                                             |
| 41  | DGND  | —               | Ground (digital section)                                             |
| 42  | A5    | O               | External data RAM address terminal                                   |
| 43  | A6    | O               | External data RAM address terminal                                   |
| 44  | A7    | O               | External data RAM address terminal                                   |
| 45  | A12   | O               | External data RAM address terminal                                   |
| 46  | A14   | O               | External data RAM address terminal                                   |
| 47  | /WE   | O               | External delay RAM write enable terminal                             |
| 48  | A13   | O               | External delay RAM address terminal                                  |
| 49  | A8    | O               | External delay RAM address terminal                                  |
| 50  | A9    | O               | External delay RAM address terminal                                  |
| 51  | A11   | O               | External delay RAM address terminal                                  |
| 52  | /OE   | O               | External delay RAM output enable terminal                            |
| 53  | A10   | O               | External delay RAM address terminal                                  |
| 54  | /CE   | O               | External delay RAM chip enable terminal                              |
| 55  | XO    | O               | Crystal oscillator connecting terminal                               |
| 56  | XI    | I               | Crystal oscillator connecting terminal                               |
| 57  | SYNCI | It              | Test terminal for system synchronization, normally connected to DVDD |
| 58  | DVDD  | —               | +5V power supply (digital section)                                   |
| 59  | SYNCO | O               | Test terminal for system synchronization, normally unconnected       |
| 60  | /IC   | Ics             | Initial clear terminal (Power ON resetting is necessary)             |
| 61  | LRS   | O               | External automatic input balance terminal, normally unconnected      |
| 62  | /CSS  | O               | External automatic input balance terminal, normally unconnected      |
| 63  | BCK   | I <sub>ts</sub> | Bit clock for parameter data input                                   |
| 64  | WCK   | I <sub>ts</sub> | Word clock for parameter data input                                  |

**Note :** Letters used in the above I/O column represent as follows.

I : Input terminal    O : Output terminal    t : TTL level  
c : CMOS level    s : Schmidt input    A : Analog terminal

## PIN CONNECTION DIAGRAM

### ICs

|                        |                                |                                    |                           |                      |                   |                    |
|------------------------|--------------------------------|------------------------------------|---------------------------|----------------------|-------------------|--------------------|
| <b>AN78N05</b><br>     | <b>NJM79M12FA</b><br>          | <b>NJM4558L<br/>NJM4558L-D</b><br> | <b>LA7956</b><br>         | <b>μPC4570HA</b><br> | <b>LB1641</b><br> | <b>TC9299P</b><br> |
| <b>LH5P832D-10</b><br> | <b>LC78213<br/>LC78211</b><br> | <b>YSS203B</b><br>                 | <b>M38172M4-192FP</b><br> |                      |                   |                    |

### Diodes

|                               |                                                                                                                  |
|-------------------------------|------------------------------------------------------------------------------------------------------------------|
| <b>1SS133<br/>1SS270A</b><br> | <b>HZS5C2TD<br/>HZS5B2TD<br/>HZS6B2TD<br/>HZS6C2TD<br/>HZS6A2TD<br/>HZS12B2TD<br/>HZS12C2TD<br/>HZS242TD</b><br> |
| <b>D5SB20</b><br>             |                                                                                                                  |
| <b>S1NB20</b><br>             |                                                                                                                  |
| <b>S4VB20</b><br>             |                                                                                                                  |

### Transistors


|                                                                                                                                        |                                                                                                                               |
|----------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------|
| <b>2SA933S (Q, R)<br/>2SA1740S (R, S)<br/>2SD1915F (S, T)<br/>DTA114ES<br/>DTC144ES</b><br>                                            | <b>2SA1708 (S, T)<br/>2SC4488 (S, T)</b><br>                                                                                  |
| <b>2SA893A (D, E)<br/>2SA970 (GR, BL)<br/>2SA1015 (Y)<br/>2SA2878 (R, S)</b><br>                                                       | <b>2SC535 (A, B, C)<br/>2SC1815 (Y)<br/>2SC1890A (D, E)<br/>2SC2061 (P, Q, R)<br/>2SC2229 (O, Y)<br/>2SC2240 (GR, BL)</b><br> |
| <b>2SA1492Z (O, P, Y)<br/>2SC3856Z (O, P, Y)<br/>2SA1693 (O, P, Y)<br/>2SC4466 (O, P, Y)<br/>2SA1962 (R, O)<br/>2SC5242 (R, O)</b><br> | <b>2SA1358 (O, Y)<br/>2SC3421 (O, Y)</b><br>                                                                                  |
|                                                                                                                                        | <b>2SD856 (P, Q)<br/>2SD2396 (J, K)</b><br>                                                                                   |

# PRINTED CIRCUIT BOARD (Foil side) / シート図 (パターン側)

Point ① (Pin55 of IC17)

V : 2V/div H : 50 nsec/div

DC range 1 : 1 probe



P. C. B. INPUT (1)


TO : OPERATION (2)

TO : OPERATION (2)

FROM : OPERATION (1)  
FROM : OPERATION (5)

METER/EXT  
R/CLK  
CETUN  
MUTE  
R/RES  
SDT  
CE1  
VSEL1  
/VCR  
VOLU

SEL DSP  
R/START  
DO  
/ST  
R/DATA  
SCK  
CEDSP  
CEVR  
VSEL2  
VOLD



PHONO

CD

TUNER

PB

TAPE  
(MD)

REC

DVD/LD


TV/DBS

IN

VCR

OUT


P. C. B. INPUT (2)






PRINTED CIRCUIT BOARD (Foil side) / シート図 (パターン側)


P. C. B. INPUT (3)




P. C. B. OPERATION (2)




P. C. B. OPERATION (4)



P. C. B. INPUT (4)




P. C. B. OPERATION (3)







■ PRINTED CIRCUIT BOARD (Foil side) / シート図 (パターン側)



P. C. B. OPERATION (5)




Point ② (Pin31 of IC601)  
V : 2V/div H : 0.1  $\mu$ sec/div  
DC range 1 : 1 probe



Point ③

CH1 : Anode of D613 V : 2V/div (CH1)  
CH2 : Pin27 of IC601 V : 2V/div (CH2)  
H : 0.5 sec/div DC range 1 : 1 probe  
(This waveform is not available by pushing the power switch ON and OFF.)




With the POWER ON, disconnect the A/C power cord. Reconnect the A/C power cord and the above waveforms will start.


Disconnect the power cord from the AC outlet.

PRINTED CIRCUIT BOARD (Foil side) / シート図 (パターン側)


P. C. B. AMP (3)




P. C. B. AMP (1)




P. C. B. AMP (4)



P. C. B. AMP (5)



P. C. B. AMP (6)




VOLTAGE SELECTOR


|      |         |
|------|---------|
| 240V | 1-2/5-6 |
| 220V | 2-3/6-7 |
| 110V | 3-4/7-8 |
| 120V | 4-5/8-1 |

■ PRINTED CIRCUIT BOARD (Foil side) / シート図 (パターン側)

P. C. B. AMP (2)




P. C. B. AMP (7)




Note) Mounting of C546, 547, 550, 551 shown as below.  
(B, G models only)

MAIN SPEAKERS



## BLOCK DIAGRAM / ブロックダイアグラム



# SCHEMATIC DIAGRAM (INPUT) / 総回路図

| REMARKS | PARTS NAME                       | REMARKS |
|---------|----------------------------------|---------|
| NO MARK | ELECTROLYTIC CAPACITOR           | 11      |
| ○       | TANTALUM CAPACITOR               |         |
| ●       | CERAMIC CAPACITOR                |         |
| △       | CERAMIC TUBULAR CAPACITOR        |         |
| ○       | POLYESTER FILM CAPACITOR         |         |
| ○       | POLYSTYRENE FILM CAPACITOR       |         |
| ○       | MICA CAPACITOR                   |         |
| ○       | POLYPROPYLENE FILM CAPACITOR     |         |
| ●       | SEMICONDUCTIVE CERAMIC CAPACITOR |         |


| REMARKS | PARTS NAME                      | REMARKS |
|---------|---------------------------------|---------|
| NO MARK | CARBON FILM RESISTOR (P=5)      |         |
| □       | CARBON FILM RESISTOR (P=10)     |         |
| △       | METAL OXIDE FILM RESISTOR       |         |
| △       | METAL FILM RESISTOR             |         |
| △       | METAL PLATE RESISTOR            |         |
| △       | FIRE PROOF CARBON FILM RESISTOR |         |
| △       | CEMENT MOLDED RESISTOR          |         |
| △       | SEMI VARIABLE RESISTOR          |         |
| ■       | CHIP RESISTOR                   |         |

Interchangeable Parts at Manufacture-Stage


| Mark | Reference Parts Number | Parts Name                                         |
|------|------------------------|----------------------------------------------------|
| K1   | 1C8-30                 | TC4013BP<br>UPC4053BC                              |
| K2   | 07-251-706             | HS104<br>155133<br>155176                          |
| K3   | D1-2                   | H259C2TD<br>MT245-1B                               |
| K4   | D13-14                 | H259C2TD<br>MT245-1B                               |
| K5   | IC18                   | HM65056GLSP-10<br>TC51832ASPL-10                   |
| K6   | Q253-723               | 2501740S (R/S)<br>2503031E (P/S)<br>2503311A (G/S) |
| K7   | FJH-2.4                | RJ-1075-04-0351A<br>YK21-3049                      |
| K8   | PJ6                    | RJ-1075-04-351A<br>HSP-252V2-07                    |
| K9   | PJ7                    | RJ-1085-04-0352A<br>YK21-3111                      |
| K10  | IC15                   | LC78213<br>LC7823N                                 |

| MODEL No.     | J                             | R                     | B                             | G                             |
|---------------|-------------------------------|-----------------------|-------------------------------|-------------------------------|
| 1 Circuit NO. |                               |                       |                               |                               |
| 1 0725        | X                             | CR3901J/K1<br>VH51080 | X                             | X                             |
| 2 J713        | O                             | X                     | O                             | O                             |
| 3 C745        | X                             | 1000P<br>F261310      | X                             | X                             |
| 4 0708        | X                             | H251252<br>VH51960    | X                             | X                             |
| 5 R784-785    | X                             | 5.6K<br>VH75555       | X                             | X                             |
| 6 C746        | X                             | 47/63<br>UJ57747      | X                             | X                             |
| 7             |                               |                       |                               |                               |
| 8 T701        | X                             | X542<br>X5597         | X1331<br>X1341                | X0480<br>X0584                |
| 9 TC703       | YV11890                       | YV11890               | VH54330                       | VH54340                       |
| 10 J714       | O                             | O                     | O                             | O                             |
| 11 CB714-715  | X                             | X                     | X                             | X                             |
| 12 F703       |                               |                       |                               | 72-5AL250V<br>K800308         |
| 13 F702       | 7A125V<br>V9K950              | 7A125V<br>V9K950      | X                             | X                             |
| 14 CB712-713  | VP20650                       | VP20650               | X                             | X                             |
| 15 C744       | X                             | X                     | O-1                           | O-1                           |
| 16 X707       | X                             | X                     | MH20225                       | MH20225                       |
| 17 CB716-718  | X                             | X                     | VP20650                       | VP20650                       |
| 18 F704       |                               |                       | TS-15AL250V                   | TS-15AL250V                   |
| 19 RY703      | VJ34580<br>VJ34580<br>VH23080 | VY72530               | VJ34580<br>VJ34580<br>VH23080 | VJ34580<br>VJ34580<br>VH23080 |
| 20 C2-4       | X                             | X                     | 100P                          | 100P                          |
| 21 R1-4       | 47                            | 47                    | X                             | X                             |


IC2 : LC78211  
Analog Function Switch




±LB & ±LB1  
POWER SUPPLY





SUB POWER SUPPLY



IC16 : LC78213  
Analog Function Switch




IC18 : LH5P  
256K Pseudo







3  
4  
5  
6  
7  
8



\* All voltage are measured with a 10MΩ/V DC el  
\* Components having special characteristics are  
replaced with parts having specifications equal to  
\* Schematic diagram is subject to change without





- \* All voltage are measured with a 10M $\Omega$ /V DC electric volt meter.
- \* Components having special characteristics are marked  $\Delta$  and must be replaced with parts having specifications equal to those originally installed.
- \* Schematic diagram is subject to change without notice.

- 電圧は、内部抵抗10M $\Omega$ の電圧計で測定したものです。
- $\Delta$ 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
- 本回路図は標準回路図です。改良のため予告なく変更することがございます。



## SCHEMATIC DIAGRAM (OPERATION) / 総回路図

● V601 : 13-BT-1

## RESISTOR

| REMARKS | PARTS NAME                      |
|---------|---------------------------------|
| NO MARK | CARBON FILM RESISTOR (P=5)      |
| □       | CARBON FILM RESISTOR (P=10)     |
| △       | METAL OXIDE FILM RESISTOR       |
| ⊠       | METAL FILM RESISTOR             |
| ⊡       | METAL PLATE RESISTOR            |
| ■       | FIRE PROOF CARBON FILM RESISTOR |
| □       | CEMENT MOLDED RESISTOR          |
| ⊙       | SEMI VARIABLE RESISTOR          |
| ■       | CHIP RESISTOR                   |

## CAPACITOR

| REMARKS | PARTS NAME                       |   |
|---------|----------------------------------|---|
| NO MARK | ELECTROLYTIC CAPACITOR           | # |
| ⊗       | TANTALUM CAPACITOR               |   |
| NO MARK | CERAMIC CAPACITOR                |   |
| ⊙       | CERAMIC TUBULAR CAPACITOR        |   |
| ⊙       | POLYESTER FILM CAPACITOR         |   |
| ○       | POLYSTYRENE FILM CAPACITOR       |   |
| ⊙       | MICA CAPACITOR                   |   |
| ⊙       | POLYPROPYLENE FILM CAPACITOR     |   |
| ⊙       | SEMICONDUCTIVE CERAMIC CAPACITOR |   |


## NOTICE (model)

(J)..... JAPANESE  
(U)..... U. S. A  
(C)..... CANADIAN  
(R)..... GENERAL  
(A)..... AUSTRALIAN  
(B)..... BRITISH  
(G)..... EUROPEAN  
(T)..... CHINA  
(L)..... SINGAPORE

|    |      | J | R                                         | B.G                                       |
|----|------|---|-------------------------------------------|-------------------------------------------|
| S1 | J501 | 0 | X                                         | X                                         |
| S2 | R510 | X | 100K                                      | 100K                                      |
| S3 | R570 | X | 10K                                       | 10K                                       |
| S4 | Q604 | X | A933S(Q/R)<br>A1115(E/F)<br>A1309A(Q/R/S) | A933S(Q/R)<br>A1115(E/F)<br>A1309A(Q/R/S) |
| S5 | R545 | X | 470                                       | 470                                       |
| S6 | D510 | X | SLR-325VC                                 | SLR-325VC                                 |
| S7 |      |   |                                           |                                           |
| S8 |      |   |                                           |                                           |
| S9 |      |   |                                           |                                           |

## Interchangeable Parts at Manufacture-Stage

| Mark | Reference Parts Number | Parts Name                                       |
|------|------------------------|--------------------------------------------------|
| 41   | Q501                   | 2SC1740S(R/S)<br>2SC2603(E/F)<br>2SC3311A(Q/R/S) |
| 42   | D603-607-611-613-615   | HSS104<br>1SS133<br>1SS176                       |




## ● PIN CONNECTION

|            |     |
|------------|-----|
| Pin No.    | 55  |
| Connection | F2  |
| Pin No.    | 36  |
| Connection | P16 |
| Pin No.    | 17  |
| Connection | P13 |

Note 1) F1, F2 ..... Fila  
2) NP ..... No

## ● GRID ASSIGNMEN



## ● ANODE CONNEC


|     | 136    |
|-----|--------|
| P1  | a      |
| P2  | b, c   |
| P3  | d      |
| P4  | e, f   |
| P5  | g      |
| P6  | j, p   |
| P7  | m      |
| P8  | PRESET |
| P9  | STEREO |
| P10 | B1     |
| P11 | B2     |
| P12 | B3     |
| P13 | B4     |
| P14 | B5     |
| P15 | S1     |
| P16 | SLEEP  |

(R)..... GENERAL  
(A)..... AUSTRALIAN  
(B)..... BRITISH  
(G)..... EUROPEAN  
(T)..... CHINA  
(L)..... SINGAPORE

|    |      | J | R                                         | B-G                                       |
|----|------|---|-------------------------------------------|-------------------------------------------|
| s1 | J601 | 0 | X                                         | X                                         |
| s2 | R610 | X | 100K                                      | 100K                                      |
| s3 | R570 | X | 10K                                       | 10K                                       |
| s4 | Q504 | X | A933S(a/r)<br>A111S(E/F)<br>A1309A(G/R/S) | A933S(a/r)<br>A111S(E/F)<br>A1309A(G/R/S) |
| s5 | R645 | X | 470                                       | 470                                       |
| s6 | D610 | X | SLR-325VC                                 | SLR-325VC                                 |
| s7 |      |   |                                           |                                           |
| s8 |      |   |                                           |                                           |
| s9 |      |   |                                           |                                           |

Interchangeable Parts at Manufacture-Stage


| Mark | Reference Parts Number | Parts Name                                         |
|------|------------------------|----------------------------------------------------|
| k1   | Q501                   | 2SC1740S(a/r/s)<br>2SC2603(E/F)<br>2SC3311A(G/R/S) |
| k2   | D603-607, 611-613-615  | HSS104<br>ISS133<br>ISS176                         |



# ANODE CONNEC

|     | 13G    |
|-----|--------|
| P1  | a      |
| P2  | b, c   |
| P3  | d      |
| P4  | e, f   |
| P5  | g      |
| P6  | j, p   |
| P7  | m      |
| P8  | PRESET |
| P9  | STEREO |
| P10 | B1     |
| P11 | B2     |
| P12 | B3     |
| P13 | B4     |
| P14 | B5     |
| P15 | S1     |
| P16 | SLEEP  |

Point ② (Pin31 of IC601)  
V : 2V/div H : 0.1 μs  
DC range 1 : 1 probe





\* All voltage are measured with a 10MΩ/V DC elec  
\* Components having special characteristics are  
replaced with parts having specifications equal to  
\* Schematic diagram is subject to change without









# SCHEMATIC DIAGRAM (OPERATION) / 総回路図



IC251: LC78213  
Analog Function Switch



3


4

5

6


7

8



\* All voltage are measured with a 10M $\Omega$ /V DC electric volt  
 \* Components having special characteristics are marked  
 replaced with parts having specifications equal to those o  
 \* Schematic diagram is subject to change without notice.





| REMARKS | PARTS NAME                       |    |
|---------|----------------------------------|----|
| NO MARK | ELECTROLYTIC CAPACITOR           | #  |
| ⊗       | TANTALUM CAPACITOR               |    |
| NO MARK | CERAMIC CAPACITOR                | 11 |
| ⊙       | CERAMIC TUBULAR CAPACITOR        |    |
| ⊖       | POLYESTER FILM CAPACITOR         |    |
| ○       | POLYSTYRENE FILM CAPACITOR       |    |
| ⊕       | MICA CAPACITOR                   |    |
| ⊖       | POLYPROPYLENE FILM CAPACITOR     |    |
| ●       | SEMICONDUCTIVE CERAMIC CAPACITOR |    |


| REMARKS | PARTS NAME                      |
|---------|---------------------------------|
| NO MARK | CARBON FILM RESISTOR (P=5)      |
| ⊗       | CARBON FILM RESISTOR (P=10)     |
| △       | METAL OXIDE FILM RESISTOR       |
| ⊖       | METAL FILM RESISTOR             |
| ⊕       | METAL PLATE RESISTOR            |
| ⊖       | FIRE PROOF CARBON FILM RESISTOR |
| ⊖       | CEMENT MOLDED RESISTOR          |
| ⊖       | SEMI VARIABLE RESISTOR          |
| ⊖       | CHIP RESISTOR                   |

Interchangeable Parts at Manufacture-Stage

| Mark | Reference Parts Number | Parts Name                     |
|------|------------------------|--------------------------------|
| 45   | IC251                  | LC78213<br>LC7823N             |
| 46   | PJ5                    | HSP-253V-06<br>RJ-1085-01-0300 |
| 47   | PJ251                  | YKC21-3822<br>RJ-1074-25-0353A |


| MODEL No. | IC                  | RES | RES | B.G         |
|-----------|---------------------|-----|-----|-------------|
| 31        | IC251               |     |     |             |
| 32        | R915, 916           | 1   |     | 1.8K        |
| 33        | R925, 926           | 1   |     | 2.2K        |
| 34        | R914, 917, 925, 930 | ×   |     | 10K         |
| 35        | Q901-904            | ×   |     | D1915FIS/T1 |
| 36        | C609-613            | ×   |     | 100P        |

IC26, 27 : TC9299P  
Electric Controlled Volume





IC28 : LB1641  
Motor Driver

Other ICs  
● IC601: M38177ECHFP → See page E-9/J-7




IC22, 23, 901 : μPC4570HA  
Dual OP-Amp






IC251 : LC78213  
Analog Function Switch




OPERATION(3)



| IC No. | IC Name | IC No.      | IC Name          |
|--------|---------|-------------|------------------|
| 45     | IC251   | LC78213     | LC78213          |
| 46     | PJ5     | HSP-253V-06 | RJ-1086-01-0300  |
| 47     | PJ251   | YKC21-3B22  | RJ-1074-25-0353A |


| MODEL No.             | RX-V592/ADSML |  |             |
|-----------------------|---------------|--|-------------|
| s Circuit No.         | JR            |  | B-6         |
| 31                    |               |  |             |
| 32 RS15-916           | 1             |  | 1.8K        |
| 33 RS25-926           | 1             |  | 2.2K        |
| 34 RS14-917, 929, 930 | X             |  | 10K         |
| 35 0901-904           | X             |  | D1915FIS/TI |
| 36 C609-613           | X             |  | 100P        |

IC26, 27 : TC9299P  
Electric Controlled Volume




IC28 : LB1641  
Motor Driver

Other ICs  
● IC601: M36177ECHFP → See page E-8/J-7




# CH DISCRETE SELECTOR



## CENTER

## LEVEL CONTROL



- \* All voltage are measured with a 10MΩ/V DC electric volt meter.
- \* Components having special characteristics are marked  $\Delta$  and must be replaced with parts having specifications equal to those originally installed.
- \* Schematic diagram is subject to change without notice.

- 電圧は、内部抵抗10MΩの電圧計で測定したものです。
- $\Delta$ 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
- 本回路図は標準回路図です。改良のため予告なく変更することがございます。



SCHEMATIC DIAGRAM (AMP) / 総回路図


| REMARKS | PARTS NAME                      |
|---------|---------------------------------|
| NO MARK | CARBON FILM RESISTOR [P=5]      |
| □       | CARBON FILM RESISTOR [P=10]     |
| △       | METAL OXIDE FILM RESISTOR       |
| ▲       | METAL FILM RESISTOR             |
| ⊠       | METAL PLATE RESISTOR            |
| ■       | FIRE PROOF CARBON FILM RESISTOR |
| □       | CEMENT MOLDED RESISTOR          |
| ⊗       | SEMI VARIABLE RESISTOR          |
| ■       | CHIP RESISTOR                   |

| REMARKS | PARTS NAME                       |
|---------|----------------------------------|
| NO MARK | ELECTROLYTIC CAPACITOR           |
| ⊗       | TANTALUM CAPACITOR               |
| NO MARK | CERAMIC CAPACITOR                |
| ⊙       | CERAMIC TUBULAR CAPACITOR        |
| ⊖       | POLYESTER FILM CAPACITOR         |
| ○       | POLYSTYRENE FILM CAPACITOR       |
| ①       | MICA CAPACITOR                   |
| ⊖       | POLYPROPYLENE FILM CAPACITOR     |
| ●       | SEMICONDUCTIVE CERAMIC CAPACITOR |

NOTICE (model)  
 (J)..... JAPANESE  
 (U)..... U.S.A  
 (C)..... CANADIAN  
 (R)..... GENERAL  
 (A)..... AUSTRALIAN  
 (B)..... BRITISH  
 (S)..... EUROPEAN  
 (T)..... CHINA  
 (L)..... SINGAPORE

P-E30/J28  
 6-G  
 TO AMP (1)


P-E27/J25  
 5-G  
 TO OPE (1)





NOTICE (mode1)  
 (J)..... JAPANESE  
 (U)..... U. S. A  
 (C)..... CANADIAN  
 (R)..... GENERAL  
 (A)..... AUSTRALIAN  
 (B)..... BRITISH  
 (G)..... EUROPEAN  
 (T)..... CHINA  
 (L)..... SINGAPORE

P-E27/J25  
 5-G  
 TO OPE (1)



|     |                        | U-C     | R       | A               | B-G             | L               |
|-----|------------------------|---------|---------|-----------------|-----------------|-----------------|
| s47 | R501, R502             | X       | X       | X               | 4.7K            | X               |
| s48 | R503                   | X       | X       | X               | 15K             | X               |
| s49 | C502                   | X       | X       | X               | 1/50            | X               |
| s10 | SW502                  | X       | X       | X               | VS80250         | X               |
| s5  | C545, 554              | X       | X       | 0.01<br>UA95410 | 0.01<br>UA95410 | 0.01<br>UA95410 |
| s6  | C550, 551              | X       | X       | 0.01<br>V171670 | 0.01<br>V171670 | 0.01<br>V171670 |
| s54 | C546, C547, C548, C549 | X       | X       | 0.022           | 0.022           | 0.022           |
| s9  | TE501                  | YV00310 | YV00310 | VU00310         | VU01970         | VU01970         |
| s55 | C500, 510              | 33P     | 33P     | 220P            | 220P            | 220P            |
| s56 | C512                   | 33P     | 33P     | 100P            | 100P            | 100P            |

Interchangeable Parts at Manufacture-Stage

| Mark | Reference Parts Number           | Parts Name                                      |
|------|----------------------------------|-------------------------------------------------|
| k1   | Q521                             | 2SA933S(I/R)<br>2SA1115(E/F)<br>2SA1309A(I/R/S) |
| k2   | Q520                             | 2SC2061(P/Q/R)<br>2SD438(E/F)                   |
| k3   | Q502, 504, 505,<br>701, 702, 724 | 2SD1915F(I/S/T)<br>2SC2678(A/B)                 |












```
NOTICE (model)
(J)..... JAPANESE
(U)..... U. S. A
(C)..... CANADIAN
(R)..... GENERAL
(A)..... AUSTRALIAN
(B)..... BRITISH
(G)..... EUROPEAN
(T)..... CHINA
(L)..... SINGAPORE
```



|     |                | U. C     | R            | A        | B. G   | L      |
|-----|----------------|----------|--------------|----------|--------|--------|
| s17 | SW702          | X        | YABE160      | X        | X      | X      |
| s18 | F705           | X        | T3. 15AL25GV | X        | X      | X      |
| s19 | CB719- CB720   | X        | VP20650      | X        | X      | X      |
| s20 | C739           | X        | X            | 0. 1     | 0. 1   | 0. 1   |
| s21 | C749- 750      | X        | X            | 0. 01    | 0. 01  | 0. 01  |
| s22 | C736- 740- 741 | X        | X            | 0. 022   | 0. 022 | 0. 022 |
| s23 | R783           | X        | X            | 2. 2     | 2. 2   | 2. 2   |
| s24 | W709           | X        | MH01240      | X        | X      | X      |
| s25 | W710           | X        | MH04240      | X        | X      | X      |
| s26 | W708           | X        | MH03240      | X        | X      | X      |
| s27 | W713           | X        | MH06240      | X        | X      | X      |
| s28 | W714           | X        | MH02240      | X        | X      | X      |
| s29 | W715           | X        | MH09240      | X        | X      | X      |
| s30 | C748           | 0. 47/50 | 0. 47/50     | 0. 47/50 | 1/50   | 1/50   |



|     |                | U-C     | R           | A       | B-G   | L     |
|-----|----------------|---------|-------------|---------|-------|-------|
| s17 | SW702          | X       | YA96180     | X       | X     | X     |
| s18 | F705           | X       | T3.15AL250V | X       | X     | X     |
| s19 | CB719, CB720   | X       | VP20650     | X       | X     | X     |
| s20 | C739           | X       | X           | 0.1     | 0.1   | 0.1   |
| s21 | C749, 750      | X       | X           | 0.01    | 0.01  | 0.01  |
| s22 | C738, 740, 741 | X       | X           | 0.022   | 0.022 | 0.022 |
| s23 | R763           | X       | X           | 2.2     | 2.2   | 2.2   |
| s24 | W709           | X       | MH01240     | X       | X     | X     |
| s25 | W710           | X       | MH04240     | X       | X     | X     |
| s26 | W708           | X       | MH03240     | X       | X     | X     |
| s27 | W713           | X       | MH05240     | X       | X     | X     |
| s28 | W714           | X       | MH02240     | X       | X     | X     |
| s29 | W715           | X       | MH09240     | X       | X     | X     |
| s30 | C748           | 0.47/50 | 0.47/50     | 0.47/50 | 1/50  | 1/50  |



| SW702<br>VOLTAGE SELECTOR |         |
|---------------------------|---------|
| 240V                      | 1-2/5-6 |
| 220V                      | 2-3/6-7 |
| 110V                      | 3-4/7-8 |
| 120V                      | 4-5/8-1 |

- \* All voltage are measured with a 10MΩ/V DC electric volt meter.
- \* Components having special characteristics are marked  $\Delta$  and must be replaced with parts having specifications equal to those originally installed.
- \* Schematic diagram is subject to change without notice.

- 電圧は、内部抵抗10MΩの電圧計で測定したものです。
- $\Delta$ 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
- 本回路図は標準回路図です。改良のため予告なく変更することがございます。



# PARTS LIST

## ■ ELECTRICAL PARTS

### ■ WARNING

Components having special characteristics are marked  $\Delta$  and must be replaced with parts having specifications equal to those originally installed.

- Carbon resistors (1/6W or 1/4W) are not included in the ELECTRICAL PARTS List. For the part Nos. of the carbon resistors, refer to the last page.

### ABBREVIATIONS IN THIS LIST ARE AS FOLLOWS :

|            |                                |            |                                |
|------------|--------------------------------|------------|--------------------------------|
| C.A.EL.CHP | : CHIP ALUMI. ELECTROLYTIC CAP | L.EMIT     | : LIGHT EMITTING MODULE        |
| C.CE       | : CERAMIC CAP                  | LED.DSPLY  | : LED DISPLAY                  |
| C.CE.ARRAY | : CERAMIC CAP ARRAY            | LED.INFRD  | : LED, INFRARED                |
| C.CE.CHP   | : CHIP CERAMIC CAP             | MODUL.RF   | : MODULATOR, RF                |
| C.CE.ML    | : MULTILAYER CERAMIC CAP       | PHOT.CPL   | : PHOTO COUPLER                |
| C.CE.M.CHP | : CHIP MULTILAYER CERAMIC CAP  | PHOT.INTR  | : PHOTO INTERRUPTER            |
| C.CE.SAFTY | : RECOGNIZED CERAMIC CAP       | PHOT.RFLCT | : PHOTO REFLECTOR              |
| C.CE.TUBLR | : CERAMIC TUBULAR CAP          | PIN.TEST   | : PIN, TEST POINT              |
| C.CE.SMI   | : SEMI CONDUCTIVE CERAMIC CAP  | PLST.RIVET | : PLASTIC RIVET                |
| C.EL       | : ELECTROLYTIC CAP             | R.ARRAY    | : RESISTOR ARRAY               |
| C.MICA     | : MICA CAP                     | R.CAR      | : CARBON RESISTOR              |
| C.ML.FLM   | : MULTILAYER FILM CAP          | R.CAR.CHP  | : CHIP RESISTOR                |
| C.MP       | : METALLIZED PAPER CAP         | R.CAR.FP   | : FLAME PROOF CARBON RESISTOR  |
| C.MYLAR    | : MYLAR FILM CAP               | R.FUS      | : FUSABLE RESISTOR             |
| C.MYLAR.ML | : MULTILAYER MYLAR FILM CAP    | R.MTL.CHP  | : CHIP METAL FILM RESISTOR     |
| C.PAPER    | : PAPER CAPACITOR              | R.MTL.FLM  | : METAL FILM RESISTOR          |
| C.PLS      | : POLYSTYRENE FILM CAP         | R.MTL.OXD  | : METAL OXIDE FILM RESISTOR    |
| C.POL      | : POLYESTER FILM CAP           | R.MTL.PLAT | : METAL PLATE RESISTOR         |
| C.POLY     | : POLYETHYLENE FILM CAP        | RSNR.CE    | : CERAMIC RESONATOR            |
| C.PP       | : POLYPROPYLENE FILM CAP       | RSNR.CRYS  | : CRYSTAL RESONATOR            |
| C.TNTL     | : TANTALUM CAP                 | R.TW.CEM   | : TWIN CEMENT FIXED RESISTOR   |
| C.TNTL.CHP | : CHIP TANTALUM CAP            | R.WW       | : WIRE WOUND RESISTOR          |
| C.TRIM     | : TRIMMER CAP                  | SCR.BND.HD | : BIND HEAD B-TITE SCREW       |
| CN         | : CONNECTOR                    | SCR.BW.HD  | : BW HEAD TAPPING SCREW        |
| CN.BS.PIN  | : CONNECTOR, BASE PIN          | SCR.CUP    | : CUP TITE SCREW               |
| CN.CANNON  | : CONNECTOR, CANNON            | SCR.TERM   | : SCREW TERMINAL               |
| CN.DIN     | : CONNECTOR, DIN               | SCR.TR     | : SCREW, TRANSISTOR            |
| CN.FLAT    | : CONNECTOR, FLAT CABLE        | SUPRT.PCB  | : SUPPORT, P.C.B.              |
| CN.POST    | : CONNECTOR, BASE POST         | SURG.PRTCT | : SURGE PROTECTOR              |
| COIL.MX.AM | : COIL, AM MIX                 | SW.TACT    | : TACT SWITCH                  |
| COIL.AT.FM | : COIL, FM ANTENNA             | SW.LEAF    | : LEAF SWITCH                  |
| COIL.DT.FM | : COIL, FM DETECT              | SW.LEVER   | : LEVER SWITCH                 |
| COIL.MX.FM | : COIL, FM MIX                 | SW.MICRO   | : MICRO SWITCH                 |
| COIL.OUTPT | : OUTPUT COIL                  | SW.PUSH    | : PUSH SWITCH                  |
| DIOD.ARRAY | : DIODE ARRAY                  | SW.RT.ENC  | : ROTARY ENCODER               |
| DIODE.BRG  | : DIODE BRIDGE                 | SW.RT.MTR  | : ROTARY SWITCH WITH MOTOR     |
| DIODE.CHP  | : CHIP DIODE                   | SW.RT      | : ROTARY SWITCH                |
| DIODE.VAR  | : VARACTOR DIODE               | SW.SLIDE   | : SLIDE SWITCH                 |
| DIOD.Z.CHP | : CHIP ZENER DIODE             | TERM.SP    | : SPEAKER TERMINAL             |
| DIODE.ZENR | : ZENER DIODE                  | TERM.WRAP  | : WRAPPING TERMINAL            |
| DSCR.CE    | : CERAMIC DISCRIMINATOR        | THRMST.CHP | : CHIP THERMISTOR              |
| FER.BEAD   | : FERRITE BEADS                | TR.CHP     | : CHIP TRANSISTOR              |
| FER.CORE   | : FERRITE CORE                 | TR.DGT     | : DIGITAL TRANSISTOR           |
| FET.CHP    | : CHIP FET                     | TR.DGT.CHP | : CHIP DIGITAL TRANSISTOR      |
| FL.DSPLY   | : FLUORESCENT DISPLAY          | TRANS      | : TRANSFORMER                  |
| FLTR.CE    | : CERAMIC FILTER               | TRANS.PULS | : PULSE TRANSFORMER            |
| FLTR.COMB  | : COMB FILTER MODULE           | TRANS.PWR  | : POWER TRANSFORMER ASS'y      |
| FLTR.LC.RF | : LC FILTER, EMI               | TUNER.AM   | : TUNER PACK, AM               |
| GND.MTL    | : GROUND PLATE                 | TUNER.FM   | : TUNER PACK, FM               |
| GND.TERM   | : GROUND TERMINAL              | TUNER.PK   | : FRONT-END TUNER PACK         |
| HOLDER.FUS | : FUSE HOLDER                  | VR         | : ROTARY POTENTIOMETER         |
| IC.PRTCT   | : IC PROTECTOR                 | VR.MTR     | : POTENTIOMETER WITH MOTOR     |
| JUMPER.CN  | : JUMPER CONNECTOR             | VR.SW      | : POTENTIOMETER WITH ROTARY SW |
| JUMPER.TST | : JUMPER, TEST POINT           | VR.SLIDE   | : SLIDE POTENTIOMETER          |
| L.DTCT     | : LIGHT DETECTING MODULE       | VR.TRIM    | : TRIMMER POTENTIOMETER        |

**Note)** Those parts marked with “#” are not included in the P.C.B. ass'y.

## P.C.B. OPERATION

| Schm Ref.  | PART NO. | Description            |
|------------|----------|------------------------|
| * VV575400 | P. C. B. | OPERATION (R)          |
| * VV575500 | P. C. B. | OPERATION (BG)         |
| CB6        | Vi878500 | CN. BS. PIN 7P         |
| CB7        | VK025100 | CN. BS. PIN 7P         |
| CB8        | Vi878600 | CN. BS. PIN 8P         |
| CB9        | Vi878300 | CN. BS. PIN 5P         |
| CB10       | VK025200 | CN. BS. PIN 8P         |
| CB251      | Vi878900 | CN. BS. PIN 11P        |
| CB252      | Vi878900 | CN. BS. PIN 11P        |
| CB602      | VU282000 | CN 20P                 |
| CB603      | Vi878900 | CN. BS. PIN 11P        |
| CB901      | VK025200 | CN. BS. PIN 8P         |
| CB902      | VK025300 | CN. BS. PIN 9P         |
| C103       | VH053100 | C. CE. TUBLR 0.1uF 50V |
| C104       | VF466800 | C. CE. TUBLR 100pF 50V |
| C105       | VH053100 | C. CE. TUBLR 0.1uF 50V |
| C106       | VF466800 | C. CE. TUBLR 100pF 50V |
| C127       | VJ839000 | C. EL 0.47uF 50V       |
| C128       | VJ839000 | C. EL 0.47uF 50V       |
| C129       | VJ839200 | C. EL 2.2uF 50V        |
| C130       | VJ839200 | C. EL 2.2uF 50V        |
| C131       | VJ839200 | C. EL 2.2uF 50V        |
| C134       | UA652100 | C. MYLAR 100pF 50V     |
| C135       | UA652100 | C. MYLAR 100pF 50V     |
| C138       | UM417100 | C. EL 10uF 50V         |
| C139       | FG211100 | C. CE 10pF 50V         |
| C140       | VJ837200 | C. EL 47uF 16V         |
| C141       | VG278400 | C. CE. TUBLR 220pF 50V |
| C142       | FG212100 | C. CE 100pF 50V        |
| C143       | VG278400 | C. CE. TUBLR 220pF 50V |
| C144       | UM417100 | C. EL 10uF 50V         |
| C145       | VJ837200 | C. EL 47uF 16V         |
| C147       | UM417100 | C. EL 10uF 50V         |
| C148       | FG211100 | C. CE 10pF 50V         |
| C149       | VJ837200 | C. EL 47uF 16V         |
| C150       | VJ837200 | C. EL 47uF 16V         |
| C152       | FG211100 | C. CE 10pF 50V         |
| C153       | VJ837200 | C. EL 47uF 16V         |
| C154       | UM417100 | C. EL 10uF 50V         |
| C168       | VG722100 | C. EL 1uF 50V          |
| C169       | VH053100 | C. CE. TUBLR 0.1uF 50V |
| C189       | UJ638470 | C. EL 470uF 16V        |
| C257       | VH053100 | C. CE. TUBLR 0.1uF 50V |
| C258       | VG278400 | C. CE. TUBLR 220pF 50V |
| C259       | VG278400 | C. CE. TUBLR 220pF 50V |
| C260       | VG278400 | C. CE. TUBLR 220pF 50V |
| C261       | VG278400 | C. CE. TUBLR 220pF 50V |
| C262       | VG278400 | C. CE. TUBLR 220pF 50V |
| C263       | VG278400 | C. CE. TUBLR 220pF 50V |
| C264       | VJ839200 | C. EL 2.2uF 50V        |
| C601       | VJ839000 | C. EL 0.47uF 50V       |
| C602       | VH053100 | C. CE. TUBLR 0.1uF 50V |
| C603       | VJ839200 | C. EL 2.2uF 50V        |

\* New Parts

| Schm Ref. | PART NO. | Description                |
|-----------|----------|----------------------------|
| C604      | VF637900 | C. EL 1000uF 10V           |
| C605      | VU545000 | C. EL 47000uF 5.5V         |
| C606      | VH053100 | C. CE. TUBLR 0.1uF 50V     |
| C607      | VH053100 | C. CE. TUBLR 0.1uF 50V     |
| C609      | VF466800 | C. CE. TUBLR 100pF 50V(BG) |
| C610      | VF466800 | C. CE. TUBLR 100pF 50V(BG) |
| C611      | VF466800 | C. CE. TUBLR 100pF 50V(BG) |
| C612      | VF466800 | C. CE. TUBLR 100pF 50V(BG) |
| C613      | VF466800 | C. CE. TUBLR 100pF 50V(BG) |
| C901      | VJ839100 | C. EL 1uF 50V              |
| C902      | UM215100 | C. EL 0.1uF 50V            |
| C903      | VJ839000 | C. EL 0.47uF 50V           |
| C904      | VG287800 | C. EL 330uF 16V            |
| C905      | VG287800 | C. EL 330uF 16V            |
| C906      | UM215100 | C. EL 0.1uF 50V            |
| C907      | VJ839000 | C. EL 0.47uF 50V           |
| C908      | VJ839100 | C. EL 1uF 50V              |
| C909      | UM407220 | C. EL 22uF 16V             |
| C910      | FG211470 | C. CE 47pF 50V             |
| C911      | VJ839200 | C. EL 2.2uF 50V            |
| C912      | VJ839200 | C. EL 2.2uF 50V            |
| C913      | FG211470 | C. CE 47pF 50V             |
| C914      | UM407220 | C. EL 22uF 16V             |
| C915      | UA655120 | C. MYLAR 0.12uF 50V        |
| C916      | UA654330 | C. MYLAR 0.033uF 50V       |
| C917      | UA654330 | C. MYLAR 0.033uF 50V       |
| C918      | UA655120 | C. MYLAR 0.12uF 50V        |
| D14       | VM974200 | DIODE. ZENR HZS5C2TD 5.0V  |
| D601      | VM974100 | DIODE. ZENR HZS5B2TD 5.0V  |
| D602      | VM974100 | DIODE. ZENR HZS5B2TD 5.0V  |
| D603      | VD631600 | DIODE 1SS133, 176, HSS104  |
| D604      | VD631600 | DIODE 1SS133, 176, HSS104  |
| D605      | VD631600 | DIODE 1SS133, 176, HSS104  |
| D606      | VD631600 | DIODE 1SS133, 176, HSS104  |
| D607      | VD631600 | DIODE 1SS133, 176, HSS104  |
| D610      | VS132300 | LED(re) SLR-325VCT31       |
| D611      | VD631600 | DIODE 1SS133, 176, HSS104  |
| D612      | VM974300 | DIODE. ZENR HZS6A2TD 6.0V  |
| D613      | VD631600 | DIODE 1SS133, 176, HSS104  |
| D614      | VD631600 | DIODE 1SS133, 176, HSS104  |
| D615      | VD631600 | DIODE 1SS133, 176, HSS104  |
| G601      | VR463400 | TERM. GND D3.5 TP00385     |
| IC22      | XB247301 | IC uPC4570HA               |
| IC23      | XB247301 | IC uPC4570HA               |
| IC26      | XR040A00 | IC TC9299P                 |
| IC27      | XR040A00 | IC TC9299P                 |
| IC28      | XF494A00 | IC LB1641                  |
| IC251     | XP896A00 | IC LC78213                 |
| IC601     | XS983A00 | IC M38172M4-192FP CPU      |
| IC901     | XB247301 | IC uPC4570HA               |
| JK1       | VU245200 | CN. DIN 1P                 |
| * PJ5     | VV325100 | JACK. PIN 3P               |
| * PJ251   | VV577800 | JACK. PIN 6P               |

\* New Parts

## P.C.B. OPERATION &amp; INPUT

| Schm Ref. | PART NO. | Description                  |
|-----------|----------|------------------------------|
| Q601      | iC174020 | TR 2SC1740S R, S             |
| Q602      | VG722000 | TR. DGT DTC144ES             |
| Q603      | VD678500 | TR. DGT DTA114ES             |
| Q604      | iA093320 | TR 2SA933S Q, R              |
| Q901      | VK432900 | TR 2SD1915F S, T (BG)        |
| Q902      | VK432900 | TR 2SD1915F S, T (BG)        |
| Q903      | VK432900 | TR 2SD1915F S, T (BG)        |
| Q904      | VK432900 | TR 2SD1915F S, T (BG)        |
| R217      | HV453470 | R. CAR. FP 4.7 $\Omega$ 1/4W |
| R218      | HV453470 | R. CAR. FP 4.7 $\Omega$ 1/4W |
| R219      | HV454100 | R. CAR. FP 10 $\Omega$ 1/4W  |
| R221      | HV454100 | R. CAR. FP 10 $\Omega$ 1/4W  |
| R931      | HL315100 | R. MIL. OXD 100 $\Omega$ 1W  |
| R932      | HL315100 | R. MIL. OXD 100 $\Omega$ 1W  |
| SW601     | VG392900 | SW. TACT SKHVAA              |
| SW602     | VG392900 | SW. TACT SKHVAA              |
| SW603     | VG392900 | SW. TACT SKHVAA              |
| SW606     | VG392900 | SW. TACT SKHVAA              |
| SW607     | VG392900 | SW. TACT SKHVAA              |
| SW608     | VG392900 | SW. TACT SKHVAA              |
| SW609     | VG392900 | SW. TACT SKHVAA              |
| SW612     | VG392900 | SW. TACT SKHVAA              |
| SW613     | VG392900 | SW. TACT SKHVAA              |
| SW614     | VG392900 | SW. TACT SKHVAA              |
| SW615     | VG392900 | SW. TACT SKHVAA              |
| SW620     | VG392900 | SW. TACT SKHVAA              |
| SW621     | VG392900 | SW. TACT SKHVAA              |
| SW624     | VG392900 | SW. TACT SKHVAA              |
| SW625     | VG392900 | SW. TACT SKHVAA              |
| SW626     | VG392900 | SW. TACT SKHVAA              |
| SW627     | VG392900 | SW. TACT SKHVAA              |
| SW632     | VG392900 | SW. TACT SKHVAA              |
| SW633     | VG392900 | SW. TACT SKHVAA              |
| SW634     | VG392900 | SW. TACT SKHVAA              |
| SW637     | VG392900 | SW. TACT SKHVAA              |
| SW638     | VG392900 | SW. TACT SKHVAA              |
| SW639     | VG392900 | SW. TACT SKHVAA              |
| * SW901   | VV887300 | SW. PUSH SPUN19              |
| U601      | VU591000 | L. DTCT GP1U271X             |
| * V601    | VV485500 | FL. DSPLY 13-BT-149GK        |
| * VR1     | VV135100 | VR. MTR A100K $\Omega$       |
| VR901     | VP741800 | VR B20K $\Omega$             |
| VR902     | VP741900 | VR G25K $\Omega$             |
| VR903     | VP742000 | VR MN100K $\Omega$           |
| XL601     | VR891500 | RSNR. CE 6.30MHz             |
|           | VJ828000 | PIN IMSA-6024-03E            |
|           | BB071360 | SCR. TERM 8.3x13             |
|           | VRO11400 | SHEET. FL                    |
| *         | VV499900 | SPACER FL-T7.5               |

\* New Parts

| Schm Ref.  | PART NO. | Description               |
|------------|----------|---------------------------|
| * VV819500 | P. C. B. | INPUT (R)                 |
| * VV953100 | P. C. B. | INPUT (B)                 |
| * VV953200 | P. C. B. | INPUT (G)                 |
| CB1        | Vi878700 | CN. BS. PIN 9P            |
| CB2        | VK025100 | CN. BS. PIN 7P            |
| CB3        | Vi878500 | CN. BS. PIN 7P            |
| CB4        | Vi878600 | CN. BS. PIN 8P            |
| CB5        | VQ047500 | CN. BS. PIN 20P           |
| CB11       | Vi878700 | CN. BS. PIN 9P            |
| CB705      | Vi878400 | CN. BS. PIN 6P            |
| CB706      | VK024700 | CN. BS. PIN 3P            |
| CB712      | VP206500 | HOLDER. FUS EYF-52BC (R)  |
| CB713      | VP206500 | HOLDER. FUS EYF-52BC (R)  |
| CB714      | VP206500 | HOLDER. FUS EYF-52BC (G)  |
| CB715      | VP206500 | HOLDER. FUS EYF-52BC (G)  |
| CB716      | VP206500 | HOLDER. FUS EYF-52BC (BG) |
| CB717      | VG879900 | CN. BS. PIN 2P            |
| CB718      | VP206500 | HOLDER. FUS EYF-52BC (BG) |
| C2         | UA652100 | C. MYLAR 100pF 50V (BG)   |
| C3         | UA652220 | C. MYLAR 220pF 50V        |
| C4         | UA652100 | C. MYLAR 100pF 50V (BG)   |
| C5         | UA652220 | C. MYLAR 220pF 50V        |
| C7         | VK533900 | C. PP 100pF 200V          |
| C8         | VK533900 | C. PP 100pF 200V          |
| C9         | VF466800 | C. CE. TUBLR 100pF 50V    |
| C10        | VF466800 | C. CE. TUBLR 100pF 50V    |
| C11        | VF466800 | C. CE. TUBLR 100pF 50V    |
| C12        | VF466800 | C. CE. TUBLR 100pF 50V    |
| C13        | VF466800 | C. CE. TUBLR 100pF 50V    |
| C14        | VF466800 | C. CE. TUBLR 100pF 50V    |
| C15        | FG211470 | C. CE 47pF 50V            |
| C16        | FG211470 | C. CE 47pF 50V            |
| C17        | VF466800 | C. CE. TUBLR 100pF 50V    |
| C18        | VF466800 | C. CE. TUBLR 100pF 50V    |
| C21        | VF466800 | C. CE. TUBLR 100pF 50V    |
| C22        | VF466800 | C. CE. TUBLR 100pF 50V    |
| C23        | FG211470 | C. CE 47pF 50V            |
| C24        | FG211470 | C. CE 47pF 50V            |
| C25        | VJ839200 | C. EL 2.2uF 50V           |
| C26        | VE117600 | C. EL 220uF 10V           |
| C27        | VJ837200 | C. EL 47uF 16V            |
| C28        | UA653910 | C. MYLAR 9100pF 50V       |
| C29        | UA654330 | C. MYLAR 0.033uF 50V      |
| C30        | UA653910 | C. MYLAR 9100pF 50V       |
| C31        | UA654330 | C. MYLAR 0.033uF 50V      |
| C32        | VJ837200 | C. EL 47uF 16V            |
| C33        | VE117600 | C. EL 220uF 10V           |
| C34        | VJ839200 | C. EL 2.2uF 50V           |
| C35        | UM417100 | C. EL 10uF 50V            |
| C36        | UA652100 | C. MYLAR 100pF 50V        |
| C37        | UM417100 | C. EL 10uF 50V            |
| C38        | UM417100 | C. EL 10uF 50V            |
| C39        | UA652100 | C. MYLAR 100pF 50V        |

\* New Parts

## P.C.B. INPUT

| Schm Ref. | PART NO. | Description             |
|-----------|----------|-------------------------|
| C41       | VJ839100 | C. EL 1uF 50V           |
| C42       | UA652100 | C. MYLAR 100pF 50V      |
| C43       | UA652100 | C. MYLAR 100pF 50V      |
| C44       | UA652100 | C. MYLAR 100pF 50V      |
| C45       | UA652100 | C. MYLAR 100pF 50V      |
| C46       | VJ839100 | C. EL 1uF 50V           |
| C47       | UA652100 | C. MYLAR 100pF 50V      |
| C48       | UA655150 | C. MYLAR 0.15uF 50V     |
| C49       | VJ839100 | C. EL 1uF 50V           |
| C50       | VJ839100 | C. EL 1uF 50V           |
| C51       | UM417100 | C. EL 10uF 50V          |
| C52       | VF466800 | C. CE. TUBLR 100pF 50V  |
| C53       | VG279600 | C. CE. TUBLR 3300pF 16V |
| C54       | UM417100 | C. EL 10uF 50V          |
| C55       | UM417100 | C. EL 10uF 50V          |
| C56       | UM417100 | C. EL 10uF 50V          |
| C57       | VG279600 | C. CE. TUBLR 3300pF 16V |
| C58       | VF466800 | C. CE. TUBLR 100pF 50V  |
| C59       | UA653680 | C. MYLAR 6800pF 50V     |
| C60       | VG287800 | C. EL 330uF 16V         |
| C61       | VJ837200 | C. EL 47uF 16V          |
| C62       | VJ839100 | C. EL 1uF 50V           |
| C63       | UA652220 | C. MYLAR 220pF 50V      |
| C64       | UA652220 | C. MYLAR 220pF 50V      |
| C65       | VJ839100 | C. EL 1uF 50V           |
| C66       | VG287800 | C. EL 330uF 16V         |
| C67       | UA653680 | C. MYLAR 6800pF 50V     |
| C68       | UA653470 | C. MYLAR 4700pF 50V     |
| C69       | UA653120 | C. MYLAR 1200pF 50V     |
| C70       | UA654180 | C. MYLAR 0.018uF 50V    |
| C71       | FG612390 | C. CE 390pF 50V         |
| C73       | FG612390 | C. CE 390pF 50V         |
| C75       | UA653120 | C. MYLAR 1200pF 50V     |
| C76       | UA654180 | C. MYLAR 0.018uF 50V    |
| C77       | UA653470 | C. MYLAR 4700pF 50V     |
| C78       | UM407220 | C. EL 22uF 16V          |
| C79       | UM407220 | C. EL 22uF 16V          |
| C80       | UM407220 | C. EL 22uF 16V          |
| C81       | UM407220 | C. EL 22uF 16V          |
| C82       | UA652330 | C. MYLAR 330pF 50V      |
| C83       | UM407220 | C. EL 22uF 16V          |
| C84       | UM407220 | C. EL 22uF 16V          |
| C85       | UA652330 | C. MYLAR 330pF 50V      |
| C86       | UA652330 | C. MYLAR 330pF 50V      |
| C87       | UM407220 | C. EL 22uF 16V          |
| C88       | UM407220 | C. EL 22uF 16V          |
| C89       | VJ839100 | C. EL 1uF 50V           |
| C90       | VG277000 | C. CE. TUBLR 33pF 50V   |
| C91       | VG278400 | C. CE. TUBLR 220pF 50V  |
| C92       | VG279500 | C. CE. TUBLR 2700pF 16V |
| C93       | VG278400 | C. CE. TUBLR 220pF 50V  |
| C94       | VG279500 | C. CE. TUBLR 2700pF 16V |
| C95       | VG277000 | C. CE. TUBLR 33pF 50V   |

\* New Parts

| Schm Ref. | PART NO. | Description             |
|-----------|----------|-------------------------|
| C96       | VJ839100 | C. EL 1uF 50V           |
| C97       | VG277000 | C. CE. TUBLR 33pF 50V   |
| C98       | UA653270 | C. MYLAR 2700pF 50V     |
| C99       | VF466600 | C. CE. TUBLR 10pF 50V   |
| C100      | VF466600 | C. CE. TUBLR 10pF 50V   |
| C101      | UA653270 | C. MYLAR 2700pF 50V     |
| C102      | VG277000 | C. CE. TUBLR 33pF 50V   |
| C108      | UM407220 | C. EL 22uF 16V          |
| C109      | UM407220 | C. EL 22uF 16V          |
| C111      | VG279600 | C. CE. TUBLR 3300pF 16V |
| C112      | VG279600 | C. CE. TUBLR 3300pF 16V |
| C113      | VH053100 | C. CE. TUBLR 0.1uF 50V  |
| C114      | VH053100 | C. CE. TUBLR 0.1uF 50V  |
| C115      | UJ638330 | C. EL 330uF 16V         |
| C116      | VH053100 | C. CE. TUBLR 0.1uF 50V  |
| C117      | VH053100 | C. CE. TUBLR 0.1uF 50V  |
| C118      | VJ837200 | C. EL 47uF 16V          |
| C119      | VJ837200 | C. EL 47uF 16V          |
| C120      | VJ837200 | C. EL 47uF 16V          |
| C121      | VF964800 | C. EL 100uF 16V         |
| C122      | VE117600 | C. EL 220uF 10V         |
| C124      | VH053100 | C. CE. TUBLR 0.1uF 50V  |
| C125      | VJ837200 | C. EL 47uF 16V          |
| C155      | VF466800 | C. CE. TUBLR 100pF 50V  |
| C156      | VF466800 | C. CE. TUBLR 100pF 50V  |
| C157      | VJ836900 | C. EL 10uF 16V          |
| C158      | VJ836900 | C. EL 10uF 16V          |
| C159      | VJ836900 | C. EL 10uF 16V          |
| C160      | VF637900 | C. EL 1000uF 10V        |
| C161      | VF466800 | C. CE. TUBLR 100pF 50V  |
| C164      | VF637900 | C. EL 1000uF 10V        |
| C165      | VF466800 | C. CE. TUBLR 100pF 50V  |
| C171      | VJ836900 | C. EL 10uF 16V          |
| C172      | VJ837200 | C. EL 47uF 16V          |
| C173      | VF637900 | C. EL 1000uF 10V        |
| C174      | VG276600 | C. CE. TUBLR 22pF 50V   |
| C175      | VJ837200 | C. EL 47uF 16V          |
| C176      | VF637900 | C. EL 1000uF 10V        |
| C177      | VF466800 | C. CE. TUBLR 100pF 50V  |
| C178      | VF466800 | C. CE. TUBLR 100pF 50V  |
| C179      | VJ836900 | C. EL 10uF 16V          |
| C180      | VJ837200 | C. EL 47uF 16V          |
| C181      | UM397330 | C. EL 33uF 16V          |
| C182      | VG276600 | C. CE. TUBLR 22pF 50V   |
| C183      | VJ837200 | C. EL 47uF 16V          |
| C184      | UM397330 | C. EL 33uF 16V          |
| C185      | VH053100 | C. CE. TUBLR 0.1uF 50V  |
| C186      | VJ837200 | C. EL 47uF 16V          |
| C187      | UJ638330 | C. EL 330uF 16V         |
| C190      | VH053100 | C. CE. TUBLR 0.1uF 50V  |
| C729      | VY841300 | C. EL 3300uF 50V        |
| C730      | VY841300 | C. EL 3300uF 50V        |
| C731      | VH053100 | C. CE. TUBLR 0.1uF 50V  |

\* New Parts

## P.C.B. INPUT &amp; AMP

| Schm Ref. | PART NO. | Description                   |
|-----------|----------|-------------------------------|
| C732      | UJ648470 | C. EL 470uF 25V               |
| C733      | VH053100 | C. CE. TUBLR 0.1uF 50V        |
| C734      | VH053100 | C. CE. TUBLR 0.1uF 50V        |
| C742      | VS745400 | C. POL. MTL 0.1uF 100V        |
| C743      | VS745400 | C. POL. MTL 0.1uF 100V        |
| C744      | UA655100 | C. MYLAR 0.1uF 50V (BG)       |
| C745      | FG213100 | C. CE 1000pF 50V (R)          |
| C746      | Ui377470 | C. EL 47uF 63V (R)            |
| C747      | Vi716700 | C. MYLAR 0.01uF 50V           |
| C751      | UA654100 | C. MYLAR 0.01uF 50V           |
| △ C752    | VS741700 | C. CE. SAFTY 0.01uF 275V      |
| C760      | UJ649220 | C. EL 2200uF 25V              |
| C761      | VF606700 | C. EL 1000uF 25V              |
| C762      | VS745400 | C. POL. MTL 0.1uF 100V        |
| D7        | VD631600 | DIODE 1SS133, 176, HSS104     |
| D251      | VD631600 | DIODE 1SS133, 176, HSS104     |
| △ D702    | VR253700 | DIODE. BRG SINB20 1.0A 200V   |
| △ D705    | iH001090 | DIODE. BRG S4VB20 2.6A 200V   |
| △ D706    | VD631600 | DIODE 1SS133, 176, HSS104     |
| △ D707    | VR253700 | DIODE. BRG SINB20 1.0A 200V   |
| △ D708    | VM975600 | DIODE. ZENR HZS12B2TD 12V (R) |
| △ F702    | VP909900 | FUSE T7.0A 125V (R)           |
| △ F703    | KB002980 | FUSE T2.5A 250V (G)           |
| △ F704    | KB000760 | FUSE T3.15A 250V (BG)         |
| IC1       | XB247301 | IC uPC4570HA                  |
| IC2       | XP894A00 | IC LC78211                    |
| IC3       | XB247301 | IC uPC4570HA                  |
| IC4       | XB247301 | IC uPC4570HA                  |
| IC7       | XB247301 | IC uPC4570HA                  |
| IC8       | XB247301 | IC uPC4570HA                  |
| IC9       | XB247301 | IC uPC4570HA                  |
| IC10      | XB247301 | IC uPC4570HA                  |
| IC11      | XB247301 | IC uPC4570HA                  |
| IC12      | XB247301 | IC uPC4570HA                  |
| IC13      | XQ212A00 | IC NJM4558LD                  |
| IC14      | XB247301 | IC uPC4570HA                  |
| IC15      | XM922A00 | IC NJM4558L                   |
| IC16      | XP896A00 | IC LC78213                    |
| IC17      | Xi022B00 | IC YSS203B-F                  |
| * IC18    | XS881A00 | IC LH5P832D-10 PSRAM          |
| IC19      | XA507A00 | IC AN78N05                    |
| IC29      | XH436A00 | IC LA7956                     |
| IC31      | XH436A00 | IC LA7956                     |
| IC32      | XH436A00 | IC LA7956                     |
| JK2       | VN938100 | CN. DIN 3P S                  |
| PJ1       | VV306900 | JACK. PIN 4P                  |
| PJ2       | VV306900 | JACK. PIN 4P                  |
| PJ3       | VT974600 | JACK. PIN 6P                  |
| PJ4       | VV306900 | JACK. PIN 4P                  |
| * PJ6     | VV325000 | JACK. PIN 2P                  |
| * PJ7     | VV852500 | JACK. PIN 3P                  |
| Q3        | iA101521 | TR 2SA1015 Y                  |
| Q4        | iC1815C0 | TR 2SC1815 Y                  |

\* New Parts

| Schm Ref. | PART NO. | Description                   |
|-----------|----------|-------------------------------|
| Q5        | iA101521 | TR 2SA1015 Y                  |
| Q6        | iC1815C0 | TR 2SC1815 Y                  |
| Q7        | iC1815C0 | TR 2SC1815 Y                  |
| Q252      | iC1815C0 | TR 2SC1815 Y                  |
| Q253      | iC174020 | TR 2SC1740S R, S              |
| Q723      | iC174020 | TR 2SC1740S R, S              |
| Q725      | VR510800 | TR 2SD2396 J, K (R)           |
| R35       | HV453220 | R. CAR. FP 2.2Ω 1/4W          |
| R50       | HV453220 | R. CAR. FP 2.2Ω 1/4W          |
| R136      | HV453220 | R. CAR. FP 2.2Ω 1/4W          |
| R149      | HV453220 | R. CAR. FP 2.2Ω 1/4W          |
| R150      | HV453220 | R. CAR. FP 2.2Ω 1/4W          |
| R151      | HL314470 | R. MTL. OXD 47Ω 1W            |
| R152      | HV453220 | R. CAR. FP 2.2Ω 1/4W          |
| R242      | HV453220 | R. CAR. FP 2.2Ω 1/4W          |
| R784      | HV456560 | R. CAR. FP 5.6KΩ 1/4W (R)     |
| R785      | HV456560 | R. CAR. FP 5.6KΩ 1/4W (R)     |
| △ RY703   | VU349800 | RELAY DC SDT-SS112DM (BG)     |
| △ RY703   | VY735300 | RELAY DC G5P-1 (R)            |
| △ T701    | XQ486B00 | TRANS. PWR (BG)               |
| △ T701    | XT331A00 | TRANS. PWR (R)                |
| △ TE703   | VU543300 | OUTLET. AC 1P (B)             |
| △ TE703   | VU543400 | OUTLET. AC 2P (G)             |
| △ * TE703 | VV118800 | OUTLET. AC 3P (R)             |
| XL1       | VK175200 | RSNR. CE 11.28MHz             |
|           | VJ828000 | PIN IMSA-6024-03E             |
|           | VR506800 | HEAT. SINK PUH16-25 (R)       |
|           | VR264300 | PLATE. GND                    |
|           | ED330066 | SCR. BND. HD 3x6 FCRM3-BL (R) |
| * * *     | VV577200 | P. C. B. AMP (R)              |
| * * *     | VV577400 | P. C. B. AMP (BG)             |
| CB501     | Vi878700 | CN. BS. PIN 9P                |
| CB502     | VK025500 | CN. BS. PIN 11P               |
| CB520     | Vi878200 | CN. BS. PIN 4P                |
| CB521     | VQ584800 | CN. BS. PIN 6P                |
| CB522     | VQ584800 | CN. BS. PIN 6P                |
| CB523     | VQ585000 | CN. BS. PIN 8P                |
| CB524     | VQ585000 | CN. BS. PIN 8P                |
| CB525     | Vi879000 | CN. BS. PIN 12P               |
| CB526     | Vi878100 | CN. BS. PIN 3P                |
| CB529     | LA002110 | TERM. WRAP 2P                 |
| CB530     | LA002110 | TERM. WRAP 2P                 |
| CB531     | LA002110 | TERM. WRAP 2P                 |
| CB532     | LA002320 | TERM. WRAP 3P                 |
| CB701     | VK024900 | CN. BS. PIN 5P                |
| CB702     | VK025600 | CN. BS. PIN 12P               |
| CB703     | VF728300 | CN 6P                         |
| CB704     | VK024800 | CN. BS. PIN 4P                |
| CB719     | VP206500 | HOLDER. FUS EYF-52BC (R)      |
| CB720     | VP206500 | HOLDER. FUS EYF-52BC (R)      |

\* New Parts

## P.C.B. AMP

| Schm Ref. | PART NO. | Description               |
|-----------|----------|---------------------------|
| CB721     | Vi878800 | CN. BS. PIN 10P           |
| CB722     | Vi878800 | CN. BS. PIN 10P           |
| CB725     | VP206500 | HOLDER, FUS EYF-52BC      |
| C501      | UM416470 | C. EL 4.7uF 50V           |
| C502      | VJ839100 | C. EL 1uF 50V (BG)        |
| C503      | UM417100 | C. EL 10uF 50V            |
| C504      | UM417100 | C. EL 10uF 50V            |
| C505      | VF760000 | C. EL 100uF 10V           |
| C506      | VK399200 | C. MYLAR. ML 0.39uF 50V   |
| C507      | UM416470 | C. EL 4.7uF 50V           |
| C508      | FG212220 | C. CE 220pF 50V (BG)      |
| C508      | FG251330 | C. CE 33pF 50V (R)        |
| C509      | UA652100 | C. MYLAR 100pF 50V        |
| C510      | FG212220 | C. CE 220pF 50V (BG)      |
| C510      | FG251330 | C. CE 33pF 50V (R)        |
| C511      | UA652100 | C. MYLAR 100pF 50V        |
| C512      | FG212100 | C. CE 100pF 50V (BG)      |
| C512      | FG251330 | C. CE 33pF 50V (R)        |
| C513      | UM417100 | C. EL 10uF 50V            |
| C514      | UA652100 | C. MYLAR 100pF 50V        |
| C515      | UM417100 | C. EL 10uF 50V            |
| C516      | VK399200 | C. MYLAR. ML 0.39uF 50V   |
| C517      | VQ245400 | C. PP 33pF 200V           |
| C518      | VJ837200 | C. EL 47uF 16V            |
| C519      | UA653100 | C. MYLAR 1000pF 50V       |
| C520      | VQ245400 | C. PP 33pF 200V           |
| C521      | VJ837200 | C. EL 47uF 16V            |
| C522      | UA653100 | C. MYLAR 1000pF 50V       |
| C523      | VQ245400 | C. PP 33pF 200V           |
| C524      | VJ837200 | C. EL 47uF 16V            |
| C525      | UA653100 | C. MYLAR 1000pF 50V       |
| C526      | VR325000 | C. MYLAR 100pF 100V       |
| C527      | UJ667470 | C. EL 47uF 50V            |
| C528      | UJ667470 | C. EL 47uF 50V            |
| C529      | VR325000 | C. MYLAR 100pF 100V       |
| C530      | VK347900 | C. EL 470uF 63V           |
| C531      | VR325000 | C. MYLAR 100pF 100V       |
| C532      | UJ667470 | C. EL 47uF 50V            |
| C533      | UJ667470 | C. EL 47uF 50V            |
| C534      | VR325000 | C. MYLAR 100pF 100V       |
| C535      | VR325000 | C. MYLAR 100pF 100V       |
| C536      | UJ667470 | C. EL 47uF 50V            |
| C537      | UJ667470 | C. EL 47uF 50V            |
| C538      | VR325000 | C. MYLAR 100pF 100V       |
| C539      | VJ836900 | C. EL 10uF 16V            |
| C540      | VJ839200 | C. EL 2.2uF 50V           |
| C541      | VJ839100 | C. EL 1uF 50V             |
| C542      | UA654680 | C. MYLAR 0.068uF 50V      |
| C543      | UA654680 | C. MYLAR 0.068uF 50V      |
| C544      | UA654680 | C. MYLAR 0.068uF 50V      |
| C545      | UA654100 | C. MYLAR 0.01uF 50V (BG)  |
| C546      | UA654220 | C. MYLAR 0.022uF 50V (BG) |
| C547      | UA654220 | C. MYLAR 0.022uF 50V (BG) |

\* New Parts

| Schm Ref. | PART NO. | Description                 |
|-----------|----------|-----------------------------|
| C548      | UA654220 | C. MYLAR 0.022uF 50V (BG)   |
| C549      | UA654220 | C. MYLAR 0.022uF 50V (BG)   |
| C550      | Vi716700 | C. MYLAR 0.01uF 50V (BG)    |
| C551      | Vi716700 | C. MYLAR 0.01uF 50V (BG)    |
| * C552    | VV887100 | C. EL 12000uF 63V           |
| * C553    | VV887100 | C. EL 12000uF 63V           |
| C554      | UA654100 | C. MYLAR 0.01uF 50V (BG)    |
| C555      | UA654100 | C. MYLAR 0.01uF 50V         |
| C556      | VS745400 | C. POL. MTL 0.1uF 100V      |
| C557      | VS745400 | C. POL. MTL 0.1uF 100V      |
| C558      | VH053100 | C. CE. TUBLR 0.1uF 50V      |
| C559      | UJ167330 | C. EL 33uF 50V              |
| C701      | UM416470 | C. EL 4.7uF 50V             |
| C702      | UM416470 | C. EL 4.7uF 50V             |
| C703      | UA652100 | C. MYLAR 100pF 50V          |
| C704      | UA652470 | C. MYLAR 470pF 50V          |
| C705      | VJ837200 | C. EL 47uF 16V              |
| C706      | UA652470 | C. MYLAR 470pF 50V          |
| C707      | UA652100 | C. MYLAR 100pF 50V          |
| C708      | VR516400 | C. CE 15p 500V              |
| C709      | VJ837200 | C. EL 47uF 16V              |
| C710      | UA653100 | C. MYLAR 1000pF 50V         |
| C711      | VG722100 | C. EL 1uF 50V               |
| C712      | UA653100 | C. MYLAR 1000pF 50V         |
| C713      | VJ837200 | C. EL 47uF 16V              |
| C714      | VR516400 | C. CE 15p 500V              |
| C715      | VR325000 | C. MYLAR 100pF 100V         |
| C716      | UJ667470 | C. EL 47uF 50V              |
| C717      | UJ667470 | C. EL 47uF 50V              |
| C718      | VR325000 | C. MYLAR 100pF 100V         |
| C719      | UJ668100 | C. EL 100uF 50V             |
| C720      | VR325000 | C. MYLAR 100pF 100V         |
| C721      | UJ667470 | C. EL 47uF 50V              |
| C722      | UJ667470 | C. EL 47uF 50V              |
| C723      | VR325000 | C. MYLAR 100pF 100V         |
| C724      | UA654220 | C. MYLAR 0.022uF 50V        |
| C725      | UA654220 | C. MYLAR 0.022uF 50V        |
| C726      | VJ837200 | C. EL 47uF 16V              |
| C727      | UJ667470 | C. EL 47uF 50V              |
| C728      | VJ837200 | C. EL 47uF 16V              |
| C729      | UJ668100 | C. EL 100uF 50V             |
| C731      | VJ839000 | C. EL 0.47uF 50V            |
| C733      | VF466900 | C. CE. TUBLR 470pF 50V      |
| C734      | VF466900 | C. CE. TUBLR 470pF 50V      |
| C735      | VF466900 | C. CE. TUBLR 470pF 50V      |
| C736      | VF466900 | C. CE. TUBLR 470pF 50V      |
| C737      | VF466900 | C. CE. TUBLR 470pF 50V      |
| C738      | UA654220 | C. MYLAR 0.022uF 50V (BG)   |
| C739      | VH053100 | C. CE. TUBLR 0.1uF 50V (BG) |
| C740      | UA654220 | C. MYLAR 0.022uF 50V (BG)   |
| C741      | UA654220 | C. MYLAR 0.022uF 50V (BG)   |
| C748      | VJ839000 | C. EL 0.47uF 50V (R)        |
| C748      | VJ839100 | C. EL 1uF 50V (BG)          |

\* New Parts

## P.C.B. AMP

| Schm Ref. | PART NO. | Description                    |
|-----------|----------|--------------------------------|
| C749      | UA654100 | C. MYLAR 0.01uF 50V (BG)       |
| C750      | UA654100 | C. MYLAR 0.01uF 50V (BG)       |
| C765      | UJ667470 | C. EL 47uF 50V                 |
| C766      | UJ667470 | C. EL 47uF 50V                 |
| D501      | VM976300 | DIODE. ZENR HZS242TD 24V       |
| D502      | VM976300 | DIODE. ZENR HZS242TD 24V       |
| D503      | VM974500 | DIODE. ZENR HZS6C2TD 6.0V      |
| D504      | VD631600 | DIODE 1SS133, 176, HSS104      |
| D505      | VM974400 | DIODE. ZENR HZS6B2TD 6.0V      |
| D506      | VN008700 | DIODE 1SS270A                  |
| D507      | VN008700 | DIODE 1SS270A                  |
| D508      | VN008700 | DIODE 1SS270A                  |
| D509      | VD631600 | DIODE 1SS133, 176, HSS104      |
| D510      | VN011400 | DIODE. BRG D5SB20 5A 200V      |
| D511      | VD631600 | DIODE 1SS133, 176, HSS104      |
| D512      | VD631600 | DIODE 1SS133, 176, HSS104      |
| D513      | VM975700 | DIODE. ZENR HZS12C2TD 12V      |
| D701      | VM975700 | DIODE. ZENR HZS12C2TD 12V      |
| D703      | VM976300 | DIODE. ZENR HZS242TD 24V       |
| D704      | VM976300 | DIODE. ZENR HZS242TD 24V       |
| D705      | VN008700 | DIODE 1SS270A                  |
| D706      | VN008700 | DIODE 1SS270A                  |
| D707      | VM975700 | DIODE. ZENR HZS12C2TD 12V      |
| F705      | KB000760 | FUSE T3.15A 250V(R)            |
| IC701     | XD343A00 | IC NJM79M12FA                  |
| JK501     | VY687200 | JACK. PHONE JY-6317-02-030 NUT |
| L501      | VR906600 | COIL 0.95uH                    |
| L502      | VR906600 | COIL 0.95uH                    |
| L701      | VP575600 | COIL 1.5uH                     |
| L702      | VP575600 | COIL 1.5uH                     |
| L703      | VP575600 | COIL 1.5uH                     |
| PJ701     | VR245000 | JACK. PIN 6P                   |
| Q502      | VK432900 | TR 2SD1915F S,T                |
| Q504      | VK432900 | TR 2SD1915F S,T                |
| Q505      | VK432900 | TR 2SD1915F S,T                |
| Q506      | IA101521 | TR 2SA1015 Y                   |
| Q507      | VP883000 | TR 2SA893A D,E                 |
| Q508      | VP883000 | TR 2SA893A D,E                 |
| Q509      | VP883000 | TR 2SA893A D,E                 |
| Q510      | IC224030 | TR 2SC2240 GR,BL               |
| Q511      | VP883000 | TR 2SA893A D,E                 |
| Q512      | VP883000 | TR 2SA893A D,E                 |
| Q513      | VP883000 | TR 2SA893A D,E                 |
| Q514      | IC174020 | TR 2SC1740S R,S                |
| Q515      | VR325600 | TR 2SC2229 O,Y                 |
| Q516      | IC174020 | TR 2SC1740S R,S                |
| Q517      | VR325600 | TR 2SC2229 O,Y                 |
| Q518      | IC174020 | TR 2SC1740S R,S                |
| Q519      | VR325600 | TR 2SC2229 O,Y                 |
| Q520      | IC206110 | TR 2SC2061 P,Q,R               |
| Q521      | IA093320 | TR 2SA933S Q,R                 |
| Q522A     | IX603580 | TR 2SA1358                     |
| Q522C     | IX603590 | TR 2SC3421                     |

\*New Parts

| Schm Ref. | PART NO. | Description           |
|-----------|----------|-----------------------|
| Q523A     | IX606460 | TR 2SA1492 O,P,Y      |
| Q523C     | IX606470 | TR 2SC3856 O,P,Y      |
| Q526A     | IX603580 | TR 2SA1358            |
| Q526C     | IX603590 | TR 2SC3421            |
| Q527A     | IX606460 | TR 2SA1492 O,P,Y      |
| Q527C     | IX606470 | TR 2SC3856 O,P,Y      |
| Q530A     | IX603580 | TR 2SA1358            |
| Q530C     | IX603590 | TR 2SC3421            |
| Q531A     | IX606460 | TR 2SA1492 O,P,Y      |
| Q531C     | IX606470 | TR 2SC3856 O,P,Y      |
| Q534      | IA097000 | TR 2SA970 GR,BL       |
| Q535      | VP883100 | TR 2SC1890A D,E       |
| Q536      | VP883100 | TR 2SC1890A D,E       |
| Q537      | VP883100 | TR 2SC1890A D,E       |
| Q538      | IC174020 | TR 2SC1740S R,S       |
| Q539      | IC174020 | TR 2SC1740S R,S       |
| Q701      | VK432900 | TR 2SD1915F S,T       |
| Q702      | VK432900 | TR 2SD1915F S,T       |
| Q703      | VP883000 | TR 2SA893A D,E        |
| Q704      | VP883000 | TR 2SA893A D,E        |
| Q705      | VP883000 | TR 2SA893A D,E        |
| Q706      | VP883000 | TR 2SA893A D,E        |
| Q707      | VP872700 | TR 2SC4488 S,T        |
| Q708      | IC174020 | TR 2SC1740S R,S       |
| Q709      | VP872600 | TR 2SA1708 S,T        |
| Q710      | VR325600 | TR 2SC2229 O,Y        |
| Q711      | VR325600 | TR 2SC2229 O,Y        |
| Q712      | VP872600 | TR 2SA1708 S,T        |
| Q713      | IC174020 | TR 2SC1740S R,S       |
| Q714      | VP872700 | TR 2SC4488 S,T        |
| Q715A     | IX633320 | TR 2SA1693 O,P,Y      |
| Q715C     | IX633330 | TR 2SC4466 O,P,Y      |
| Q717A     | IX633320 | TR 2SA1693 O,P,Y      |
| Q717C     | IX633330 | TR 2SC4466 O,P,Y      |
| Q719      | VP883100 | TR 2SC1890A D,E       |
| Q720      | VP883100 | TR 2SC1890A D,E       |
| Q721      | IE000020 | FET 2SK30ATM GR       |
| Q724      | VK432900 | TR 2SD1915F S,T       |
| Q725      | IC174020 | TR 2SC1740S R,S       |
| Q726      | IC224030 | TR 2SC2240 GR,BL      |
| Q727      | VV855300 | TR 2SD856 Q,P         |
| Q728      | IC174020 | TR 2SC1740S R,S       |
| R508      | HV456560 | R. CAR. FP 5.6KΩ 1/4W |
| R517      | HV456100 | R. CAR. FP 1KΩ 1/4W   |
| R531      | HL315560 | R. MIL. OXD 560Ω 1W   |
| R553      | HL316560 | R. MIL. OXD 5.6KΩ 1W  |
| R554      | HL316560 | R. MIL. OXD 5.6KΩ 1W  |
| R555      | HV456270 | R. CAR. FP 2.7KΩ 1/4W |
| R557      | HV455820 | R. CAR. FP 820Ω 1/4W  |
| R558      | VK189000 | R. FUS 1KΩ 1/4W       |
| R559      | HV454470 | R. CAR. FP 47Ω 1/4W   |
| R560      | HL314100 | R. MIL. OXD 10Ω 1W    |
| R561      | HL316560 | R. MIL. OXD 5.6KΩ 1W  |

\*New Parts

## P.C.B. AMP

| Schm Ref. | PART NO. | Description                |
|-----------|----------|----------------------------|
| R562      | HL316560 | R. MIL. OXD 5.6KΩ 1W       |
| R563      | HV456270 | R. CAR. FP 2.7KΩ 1/4W      |
| R565      | HV455820 | R. CAR. FP 820Ω 1/4W       |
| R566      | VK189000 | R. FUS 1KΩ 1/4W            |
| R567      | HV454470 | R. CAR. FP 47Ω 1/4W        |
| R568      | HL316560 | R. MIL. OXD 5.6KΩ 1W       |
| R569      | HL316560 | R. MIL. OXD 5.6KΩ 1W       |
| R570      | HV456270 | R. CAR. FP 2.7KΩ 1/4W      |
| R572      | HV455820 | R. CAR. FP 820Ω 1/4W       |
| R573      | VK189000 | R. FUS 1KΩ 1/4W            |
| R574      | HV454470 | R. CAR. FP 47Ω 1/4W        |
| R580      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R581      | VK188400 | R. FUS 330Ω 1/4W           |
| R583      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R584      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R585      | VK188400 | R. FUS 330Ω 1/4W           |
| R587      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R588      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R589      | VK188400 | R. FUS 330Ω 1/4W           |
| R590      | HZ003780 | R. MIL. PLAT 0.22Ω+0.22 5W |
| R591      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R598      | HL314100 | R. MIL. OXD 10Ω 1W         |
| R603      | HL314100 | R. MIL. OXD 10Ω 1W         |
| R609      | HL314100 | R. MIL. OXD 10Ω 1W         |
| R611      | HV454100 | R. CAR. FP 10Ω 1/4W        |
| R613      | HV454100 | R. CAR. FP 10Ω 1/4W        |
| R614      | VP944500 | R. MIL. OXD 390Ω 1W        |
| R615      | VP944500 | R. MIL. OXD 390Ω 1W        |
| R628      | VY689500 | R. WW 0.22Ω 3W             |
| R629      | VY689500 | R. WW 0.22Ω 3W             |
| R630      | VY689500 | R. WW 0.22Ω 3W             |
| R631      | VY689500 | R. WW 0.22Ω 3W             |
| R728      | HV456270 | R. CAR. FP 2.7KΩ 1/4W      |
| R729      | VK188400 | R. FUS 330Ω 1/4W           |
| R731      | HV456100 | R. CAR. FP 1KΩ 1/4W        |
| R732      | VK189000 | R. FUS 1KΩ 1/4W            |
| R733      | HV454470 | R. CAR. FP 47Ω 1/4W        |
| R734      | HL314470 | R. MIL. OXD 47Ω 1W         |
| R735      | HV454470 | R. CAR. FP 47Ω 1/4W        |
| R736      | VK189000 | R. FUS 1KΩ 1/4W            |
| R738      | HV456100 | R. CAR. FP 1KΩ 1/4W        |
| R739      | VK188400 | R. FUS 330Ω 1/4W           |
| R740      | HV456270 | R. CAR. FP 2.7KΩ 1/4W      |
| R744      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R745      | VU981700 | R. MIL. PLAT 0.22Ω+0.22 3W |
| R746      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R747      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R748      | VU981700 | R. MIL. PLAT 0.22Ω+0.22 3W |
| R749      | HV453470 | R. CAR. FP 4.7Ω 1/4W       |
| R754      | HL314100 | R. MIL. OXD 10Ω 1W         |
| R755      | HL314100 | R. MIL. OXD 10Ω 1W         |
| R759      | HV454100 | R. CAR. FP 10Ω 1/4W        |
| R760      | HV454100 | R. CAR. FP 10Ω 1/4W        |


\*New Parts

| Schm Ref. | PART NO. | Description                |
|-----------|----------|----------------------------|
| R763      | HV454100 | R. CAR. FP 10Ω 1/4W        |
| R764      | HV453220 | R. CAR. FP 2.2Ω 1/4W       |
| R765      | HL315560 | R. MIL. OXD 560Ω 1W        |
| R766      | HL315560 | R. MIL. OXD 560Ω 1W        |
| R800      | HL313220 | R. MIL. FLM 2.2Ω 1W        |
| RY501     | VK438300 | RELAY DH24D2-OT/M2         |
| RY701     | VK438300 | RELAY DH24D2-OT/M2         |
| RY702     | VU566700 | RELAY DG24D2-OS/M          |
| * SW501   | VV523900 | SW. PUSH PBS-YM-001        |
| SW502     | VS602600 | SW. SLIDE SS070-P022 A(BG) |
| * SW701   | VV523800 | SW. SLIDE SL13B-022-BMC1   |
| * SW702   | VA961800 | VOLT. SELCT ESE-37247-F(R) |
| TE501     | VU819700 | TERM. SP 8P(BG)            |
| * TE501   | VV003100 | TERM. SP 8P(R)             |
| TE701     | VS578600 | TERM. SP 8P                |
|           | VJ828000 | PIN IMSA-6024-03E          |
|           | BB071360 | SCR. TERM 8.3x13           |
|           | VS606000 | HEAT. SINK DPS35-45        |
|           | EP630280 | SCR. BND. HD 3x10 FCRM3-BL |
|           | VY987200 | DAMPER HEATSINK RX-V692ML  |

\*New Parts



# EXPLODED VIEW



# MECHANICAL PARTS

| Ref. No. | PART NO. | Description             | Remarks           | Markets           |
|----------|----------|-------------------------|-------------------|-------------------|
| * 1- 1   | VV142600 | FRONT PANEL             | BL                |                   |
| * 1- 1   | VV142700 | FRONT PANEL             | TI                |                   |
| * 1- 4   | VV123700 | ESCUTCHEON, 3/8         | BL                |                   |
| * 1- 4   | VV123800 | ESCUTCHEON, 3/8         | TI                |                   |
| * 2- 1   | VV575400 | P.C.B. ASS'Y            |                   | (R)               |
| * 2- 1   | VV575500 | P.C.B. ASS'Y            |                   | (BG)              |
| * 2- 8   | MF120400 | FLEXIBLE FLAT CABLE C&C |                   |                   |
| * 2-11   | VV140700 | SUB CHASSIS             |                   |                   |
| * 2-12   | VV136900 | BUTTON CASE             | BL                |                   |
| * 2-12   | VV137000 | BUTTON CASE             | TI                |                   |
| * 2-15   | VV309400 | SUB PANEL CASE          | BL                |                   |
| * 2-15   | VV309500 | SUB PANEL CASE          | TI                |                   |
| * 2-17   | VV149500 | ESCUTCHEON, VOL         | BL                |                   |
| * 2-17   | VV149600 | ESCUTCHEON, VOL         | TI                |                   |
| * 2-18   | VV149800 | ESCUTCHEON, PJ          | BL                |                   |
| * 2-18   | VV149900 | ESCUTCHEON, PJ          | TI                |                   |
| * 2-19   | VU629200 | DAMPER, LED             |                   |                   |
| 2-23     | ED330066 | BIND HEAD SCREW         | 3x6 FCRM3-BL      |                   |
| 2-24     | VT669300 | PW HEAD B-TITE SCREW    | 3x8-8 MFC2        |                   |
| 2-25     | EP630220 | BIND HEAD P-TITE SCREW  | 3x8 ZMC2-BL       |                   |
| 2-30     | VS699700 | DAMPER                  | 2x12x12 SIDE      |                   |
| * 3-1-1  | VV143000 | HEAT SINK ASS'Y         |                   |                   |
| * 3-1-3  | VV901800 | RADIATION SHEET         |                   |                   |
| * 3-1-4  | VV849300 | RADIATION SHEET         | BFG-20ADH-3 19X24 |                   |
| 3-1-5    | IX606460 | TRANSISTOR              | 2SA1492 O,P,Y     | Q523A, 527A, 531A |
| 3-1-6    | IX606470 | TRANSISTOR              | 2SC3856 O,P,Y     | Q523C, 527C, 531C |
| 3-1-7    | VK173200 | SCREW, TRANSISTOR       | 3x15 SP FCM3      |                   |
| * 3-1-8  | VV518700 | SUPPORT, HEAT SINK      | L                 |                   |
| 3-1-9    | Ei330086 | BIND HEAD B-TITE SCREW  | 3x8 FCRM3-BL      |                   |
| * 3-2    | VV577200 | P.C.B. ASS'Y            | AMP               | (R)               |
| * 3-2    | VV577400 | P.C.B. ASS'Y            | AMP               | (BG)              |
| 3-11     | VQ368500 | PUSH RIVET              | P3545-B           |                   |
| 3-15     | VV491300 | SUPPORT, PCB            |                   |                   |
| 3-16     | VV901900 | SUPPORT, TR             |                   |                   |
| 3-20     | VK173200 | SCREW, TRANSISTOR       | 3x15 SP FCM3      |                   |
| 3-21     | Ei330086 | BIND HEAD B-TITE SCREW  | 3x8 FCRM3-BL      |                   |
| * 9      | VV575100 | P.C.B. ASS'Y            | INPUT             | (G)               |
| * 9      | VV819500 | P.C.B. ASS'Y            | INPUT             | (R)               |
| * 9      | VV953100 | P.C.B. ASS'Y            | INPUT             | (B)               |
| * 9      | VV953200 | P.C.B. ASS'Y            | INPUT             | (G)               |
| * 11     | XS865A00 | POWER TRANSFORMER       |                   | (R)               |
| * 11     | XS867A00 | POWER TRANSFORMER       |                   | (BG)              |
| * 12     | VL238100 | POWER CORD ASS'Y        |                   | (R)               |
| * 12     | VN363700 | POWER CORD ASS'Y        |                   | (G)               |
| * 12     | VV437300 | POWER CORD ASS'Y        |                   | (B)               |
| 15       | VU590000 | BINDING TIE             | CBTD001B          |                   |
| * 101    | VV121300 | TOP COVER               | BL                |                   |
| * 101    | VV121500 | TOP COVER               | TI                |                   |
| * 102    | VS001400 | CHASSIS                 |                   |                   |
| * 103    | VV148000 | REAR PANEL              |                   | (R)               |
| * 103    | VV148100 | REAR PANEL              |                   | (B)               |
| * 103    | VV148200 | REAR PANEL              |                   | (G)               |
| * 104    | VS025000 | LEG                     | D60xH21           |                   |

\* New Parts





| Ref.<br>No. | PART NO. | Description                  | Remarks         | Markets |
|-------------|----------|------------------------------|-----------------|---------|
| * 105       | VV123100 | FRAME, TRANS                 |                 |         |
| 106         | VR264400 | SPACER                       | H8              |         |
| * 107       | VV268800 | KNOB                         | D40             | BL      |
| * 107       | VV268900 | KNOB                         | D40             | TI      |
| * 108       | VV311000 | KNOB                         | D14             | BL      |
| 108         | VV311400 | KNOB                         | D14             | TI      |
| * 109       | VV123500 | BUTTON, 3/8                  |                 | BL      |
| * 109       | VV123600 | BUTTON, 3/8                  |                 | TI      |
| 111         | VN158600 | CORD STOPPER                 | No. 2104        |         |
| * 113       | VV139600 | SHEET, WINDOW                |                 | (R)     |
| * 113       | VV139800 | SHEET, WINDOW                |                 | (BG)    |
| * 115       | VV124300 | PLATE SIDE L                 | 130             | BL      |
| * 115       | VV124400 | PLATE SIDE L                 | 130             | TI      |
| * 116       | VV124500 | PLATE SIDE R                 | 130             | BL      |
| * 116       | VV124600 | PLATE SIDE R                 | 130             | TI      |
| 120         | VQ368600 | PUSH RIVET                   | P3555-B         |         |
| 121         | VN413300 | BIND HEAD BONDING B-T. SCREW | 3x8 MFZN2-BL    |         |
| 122         | Ei330086 | BIND HEAD B-TITE SCREW       | 3x8 FCRM3-BL    |         |
| 123         | ED330066 | BIND HEAD SCREW              | 3x6 FCRM3-BL    |         |
| 124         | VT669400 | PW HEAD B-TITE SCREW         | 3x15-8 MFC2     |         |
| 125         | EK365090 | PW HEAD S-TITE SCREW         | 4x8-10 FCRM3-BL |         |
| 126         | EK365090 | PW HEAD S-TITE SCREW         | 4x8-10 FCRM3-BL |         |
| 127         | AA627310 | GROUND TERMINAL              |                 |         |
| 128         | Ei030086 | BIND HEAD B-TITE SCREW       | 3x8 ZMC2-Y      |         |
| 129         | VT669300 | PW HEAD B-TITE SCREW         | 3x8-8 MFC2      |         |
| 130         | VK002600 | HEXAGONAL CAP NUT            | 4mm             |         |
| 131         | VS758000 | DAMPER, T5                   |                 |         |
| 132         | VS936800 | DAMPER                       | 3x5x10          |         |
| 133         | VU984400 | RING                         | D14             |         |
| 134         | VY731300 | DAMPER                       | TRANS           | (G)     |
| 135         | VQ366100 | DAMPER, PCB                  |                 |         |
| 136         | VY989400 | DAMPER                       | SIDE            |         |
| 160         | VY731200 | BONDING HEAD TAPPING SCREW   | 3x10 MFNI33     |         |
| 161         | VZ047200 | DAMPER                       | TOP             |         |
| 171         | VV050400 | SPACER                       |                 |         |
| ACCESSORIES |          |                              |                 |         |
| * 200       | VV486400 | REMOTE CONTROL TRANSMITTER   | SBGH20020A RAV4 |         |
| 200-1       | CX679050 | LID                          | 74x34BLALPS     |         |
|             |          | BATTERY, MANGANESE           | SUM-3, AA, R06  |         |

\* New Parts

DSP-A592

# REMOTE CONTROL TRANSMITTER



## ■ SCHEMATIC DIAGRAM



| Key No. | FUNCTION               | CUSTOM (BIN) | DATA (HEX) |
|---------|------------------------|--------------|------------|
| 1       | EFFECT ON/OFF          | 7A           | 56         |
| 2       | PROGRAM <1             | 7A           | 59         |
| 3       | PROGRAM <2             | 7A           | 58         |
| 4       | PROLOGIC               | 7A           | 88         |
| 5       | ENHANCED               | 7A           | 89         |
| 7       | V-AUX                  | 7A           | 65         |
| 9       | VCR                    | 7A           | 0F         |
| 10      | TV/DBS                 | 7A           | 54         |
| 11      | DVD/LD                 | 7A           | 17         |
| 12      | DIR A                  | 7A           | 07         |
| 13      | DIR B                  | 7A           | 40         |
| 14      | REC/PAUSE              | 7A           | 04         |
| 15      | PLAY (TAPE)            | 7A           | 00         |
| 17      | <<< (TAPE)             | 7A           | 01         |
| 18      | >>> (TAPE)             | 7A           | 02         |
| 19      | □ (TAPE)               | 7A           | 03         |
| 20      | DECK A/B               | 7A           | 06         |
| 21      | TAPE                   | 7A           | 18         |
| 22      | PRESET -               | 7A           | 11         |
| 23      | PRESET +               | 7A           | 10         |
| 24      | A/B/C/D/E              | 7A           | 12         |
| 25      | TUNER                  | 7A           | 16         |
| 26      | <<< (CD)               | 7A           | 0D         |
| 27      | >>> (CD)               | 7A           | 0C         |
| 28      | DISC                   | 7A           | 4F         |
| 29      | PLAY (CD)              | 7A           | 08         |
| 30      | CD                     | 7A           | 15         |
| 31      | <<< (CD)               | 7A           | 0B         |
| 32      | >>> (CD)               | 7A           | 0A         |
| 33      | □ (CD)                 | 7A           | 09         |
| 35      | PHONO                  | 7A           | 14         |
| 36      | SLEEP                  | 7A           | 57         |
| 37      | POWER                  | 7A           | 1F         |
| 38      | VOLUME -               | 7A           | 1B         |
| 39      | VOLUME +               | 7A           | 1A         |
| 41      | TIME/LEVEL -           | 7A           | 53         |
| 42      | TIME/LEVEL +           | 7A           | 52         |
| 43      | DELAY/CENTER/REAR/SWFR | 7A           | 86         |
| 44      | TEST                   | 7A           | 85         |
| 50      | 2CH/6CH                | 7A           | 87         |

# Parts List for Carbon Resistors

| Value          | 1/4W Type Part No. | 1/6W Type Part No. | Value          | 1/4W Type Part No. | 1/6W Type Part No. |
|----------------|--------------------|--------------------|----------------|--------------------|--------------------|
| 1.0 $\Omega$   | HJ35 3100          | HF85 3100          | 10 k $\Omega$  | HF45 7100          | HF45 7100          |
| 1.8 $\Omega$   | HJ35 3180          | *                  | 11 k $\Omega$  | HF45 7110          | HF45 7110          |
| 2.2 $\Omega$   | HJ35 3220          | HF85 3220          | 12 k $\Omega$  | HJ35 7120          | HF85 7120          |
| 3.3 $\Omega$   | HJ35 3330          | HF85 3330          | 13 k $\Omega$  | HF45 7130          | HF45 7130          |
| 4.7 $\Omega$   | HJ35 3470          | HF85 3470          | 15 k $\Omega$  | HF45 7150          | HF45 7150          |
| 5.6 $\Omega$   | HJ35 3560          | HF85 3560          | 18 k $\Omega$  | HF45 7180          | HF45 7180          |
| 10 $\Omega$    | HF45 4100          | HF45 4100          | 22 k $\Omega$  | HF45 7220          | HF45 7220          |
| 15 $\Omega$    | HJ35 4150          | HF85 4150          | 24 k $\Omega$  | HF45 7240          | HF45 7240          |
| 22 $\Omega$    | HF45 4220          | HF45 4220          | 27 k $\Omega$  | HJ35 7270          | HF85 7270          |
| 27 $\Omega$    | HJ35 4270          | HF85 4270          | 30 k $\Omega$  | HF45 7300          | HF45 7300          |
| 33 $\Omega$    | HF45 4330          | HF45 4330          | 33 k $\Omega$  | HF45 7330          | HF45 7330          |
| 39 $\Omega$    | HJ35 4470          | HF85 4390          | 36 k $\Omega$  | HF45 7360          | HF45 7360          |
| 47 $\Omega$    | HF45 4470          | HF45 4470          | 39 k $\Omega$  | HF45 7390          | HF45 7390          |
| 56 $\Omega$    | HF45 4560          | HF45 4560          | 47 k $\Omega$  | HF45 7470          | HF45 7470          |
| 68 $\Omega$    | HF45 4680          | HF45 4680          | 51 k $\Omega$  | HF45 7510          | HF45 7510          |
| 75 $\Omega$    | HF45 4750          | HF45 4750          | 56 k $\Omega$  | HF45 7560          | HF45 7560          |
| 82 $\Omega$    | HF45 4820          | HF45 4820          | 62 k $\Omega$  | HF45 7620          | HF45 7620          |
| 91 $\Omega$    | HF45 4910          | HF45 4910          | 68 k $\Omega$  | HF45 7680          | HF45 7680          |
| 100 $\Omega$   | HF45 5100          | HF45 5100          | 82 k $\Omega$  | HF45 7820          | HF45 7820          |
| 110 $\Omega$   | HJ35 5110          | HF85 5110          | 91 k $\Omega$  | HF45 7910          | HF45 7910          |
| 120 $\Omega$   | HF45 5120          | HF45 5120          | 100 k $\Omega$ | HF45 8100          | HF45 8100          |
| 150 $\Omega$   | HF45 5150          | HF45 5150          | 110 k $\Omega$ | HF45 8110          | HF45 8110          |
| 160 $\Omega$   | HJ35 5160          | *                  | 120 k $\Omega$ | HF45 8120          | HF45 8120          |
| 180 $\Omega$   | HF45 5180          | HF45 5180          | 150 k $\Omega$ | HF45 8150          | HF45 8150          |
| 200 $\Omega$   | HF45 5200          | HF45 5200          | 180 k $\Omega$ | HF45 8180          | HF45 8180          |
| 220 $\Omega$   | HF45 5220          | HF45 5220          | 220 k $\Omega$ | HJ35 8220          | HF85 8220          |
| 270 $\Omega$   | HF45 5270          | HF45 5270          | 270 k $\Omega$ | HF45 8270          | HF45 8270          |
| 330 $\Omega$   | HF45 5330          | HF45 5330          | 300 k $\Omega$ | HF45 8300          | HF45 8300          |
| 390 $\Omega$   | HF45 5390          | HF45 5390          | 330 k $\Omega$ | HF45 8330          | HF45 8330          |
| 430 $\Omega$   | HF45 5430          | HF45 5430          | 390 k $\Omega$ | HJ35 8390          | HF85 8390          |
| 470 $\Omega$   | HF45 5470          | HF45 5470          | 470 k $\Omega$ | HF45 8470          | HF45 8470          |
| 510 $\Omega$   | HF45 5510          | HF45 5510          | 560 k $\Omega$ | HJ35 8560          | HF85 8560          |
| 560 $\Omega$   | HF45 5560          | HF45 5560          | 680 k $\Omega$ | HJ35 8680          | HF85 8680          |
| 680 $\Omega$   | HF45 5680          | HF45 5680          | 820 k $\Omega$ | HJ35 8820          | HF85 8820          |
| 820 $\Omega$   | HF45 5820          | HF45 5820          | 1.0 M $\Omega$ | HF45 9100          | HF45 9100          |
| 910 $\Omega$   | HF45 5910          | HF45 5910          | 1.2 M $\Omega$ | HJ35 9120          | *                  |
| 1.0 k $\Omega$ | HF45 6100          | HF45 6100          | 1.5 M $\Omega$ | HJ35 9150          | HF85 9150          |
| 1.2 k $\Omega$ | HF45 6120          | HF45 6120          | 1.8 M $\Omega$ | HJ35 9180          | HF85 9180          |
| 1.5 k $\Omega$ | HF45 6150          | HF45 6150          | 2.2 M $\Omega$ | HJ35 9220          | HF85 9220          |
| 1.8 k $\Omega$ | HF45 6180          | HF45 6180          | 3.3 M $\Omega$ | HJ35 9330          | HF85 9330          |
| 2.0 k $\Omega$ | HJ35 6200          | HF85 6200          | 3.9 M $\Omega$ | HJ35 9390          | *                  |
| 2.2 k $\Omega$ | HF45 6220          | HF45 6220          | 4.7 M $\Omega$ | HJ35 9470          | HF85 9470          |
| 2.4 k $\Omega$ | HJ35 6240          | HF85 6240          |                |                    |                    |
| 2.7 k $\Omega$ | HF45 6270          | HF45 6270          |                |                    |                    |
| 3.0 k $\Omega$ | HF45 6300          | HF45 6300          |                |                    |                    |
| 3.3 k $\Omega$ | HF45 6330          | HF45 6330          |                |                    |                    |
| 3.6 k $\Omega$ | HJ35 6360          | HF85 6360          |                |                    |                    |
| 3.9 k $\Omega$ | HF45 6390          | HF45 6390          |                |                    |                    |
| 4.7 k $\Omega$ | HF45 6470          | HF45 6470          |                |                    |                    |
| 5.1 k $\Omega$ | HF45 6510          | HF45 6510          |                |                    |                    |
| 5.6 k $\Omega$ | HF45 6560          | HF45 6560          |                |                    |                    |
| 6.8 k $\Omega$ | HF45 6680          | HF45 6680          |                |                    |                    |
| 8.2 k $\Omega$ | HF45 6820          | HF45 6820          |                |                    |                    |
| 9.1 k $\Omega$ | HF45 6910          | HF45 6910          |                |                    |                    |



# DSP-A592

---

## YAMAHA

---