

AV RECEIVER RX-V1200/RX-V1200RDS/ HTR-5490/RX-V2200 SERVICE MANUAL

RX-V1200/RX-V1200RDS/
HTR-5490/RX-V2200

IMPORTANT NOTICE

This manual has been provided for the use of authorized YAMAHA Retailers and their service personnel. It has been assumed that basic service procedures inherent to the industry, and more specifically YAMAHA Products, are already known and understood by the users, and have therefore not been restated.

WARNING: Failure to follow appropriate service and safety procedures when servicing this product may result in personal injury, destruction of expensive components, and failure of the product to perform as specified. For these reasons, we advise all YAMAHA product owners that any service required should be performed by an authorized YAMAHA Retailer or the appointed service representative.

IMPORTANT: The presentation or sale of this manual to any individual or firm does not constitute authorization, certification or recognition of any applicable technical capabilities, or establish a principle-agent relationship of any form.

The data provided is believed to be accurate and applicable to the unit(s) indicated on the cover. The research, engineering, and service departments of YAMAHA are continually striving to improve YAMAHA products. Modifications are, therefore, inevitable and specifications are subject to change without notice or obligation to retrofit. Should any discrepancy appear to exist, please contact the distributor's Service Division.

WARNING: Static discharges can destroy expensive components. Discharge any static electricity your body may have accumulated by grounding yourself to the ground buss in the unit (heavy gauge black wires connect to this buss).

IMPORTANT: Turn the unit OFF during disassembly and part replacement. Recheck all work before you apply power to the unit.

■ CONTENTS

TO SERVICE PERSONNEL	1	AMP ADJUSTMENT	36
IMPEDANCE SELECTOR	1	DISPLAY DATA	37~38
FRONT PANELS	2~3	IC DATA	39~45
REAR PANELS	3~7	BLOCK DIAGRAM	46~49
REMOTE CONTROL TRANSMITTER	8	PRINTED CIRCUIT BOARD	50~89
SPECIFICATIONS	9~10	PIN CONNECTION DIAGRAM	90~91
INTERNAL VIEW	11	SCHEMATIC DIAGRAM	92~99
DISASSEMBLY PROCEDURES	12~14	PARTS LIST	100~126
SELF DIAGNOSIS FUNCTION (DIAG)	15~36	REMOTE CONTROL TRANSMITTER	127~130



このサービスマニュアルは、エコマーク認定の再生紙を使用しています。
This Service Manual uses recycled paper.



■ TO SERVICE PERSONNEL

1. Critical Components Information

Components having special characteristics are marked  and must be replaced with parts having specifications equal to those originally installed.

2. Leakage Current Measurement (For 120V Models Only)

When service has been completed, it is imperative to verify that all exposed conductive surfaces are properly insulated from supply circuits.

- Meter impedance should be equivalent to 1500 ohm shunted by 0.15μF.
- Leakage current must not exceed 0.5mA.
- Be sure to test for leakage with the AC plug in both polarities.



“CAUTION”


“F201, F202: FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE 8A, 125V FUSE.”

CAUTION

F201, F202: REPLACE WITH SAME TYPE 8A, 125V FUSE.

ATTENTION

F201, F202: UTILISER UN FUSIBLE DE RECHANGE DE MEME TYPE DE 8A, 125V.



WARNING: CHEMICAL CONTENT NOTICE!


The solder used in the production of this product contains LEAD. In addition, other electrical/electronic and/or plastic (where applicable) components may also contain traces of chemicals found by the California Health and Welfare Agency (and possibly other entities) to cause cancer and/or birth defects or other reproductive harm.

DO NOT PLACE SOLDER, ELECTRICAL/ELECTRONIC OR PLASTIC COMPONENTS IN YOUR MOUTH FOR ANY REASON WHATSOEVER!

Avoid prolonged, unprotected contact between solder and your skin! When soldering, do not inhale solder fumes or expose eyes to solder/flux vapor!

If you come in contact with solder or components located inside the enclosure of this product, wash your hands before handling food.

■ IMPEDANCE SELECTOR




IMPEDANCE SELECTOR

WARNING:

Do not change the IMPEDANCE SELECTOR switch setting while the power to this unit is on, otherwise this unit may be damaged.


• DIMENSIONS




Unit : mm (inch)

FRONT PANELS


RX-V1200 (U, C, A, R, T, K models)



RX-V1200RDS (B, G models)




HTR-5490 (U, C, A, T models)




RX-V1200/RX-V1200RDS/
HTR-5490/RX-V2200RX-V1200/RX-V1200RDS/
HTR-5490/RX-V2200RX-V1200/RX-V1200RDS/
HTR-5490/RX-V2200RX-V1200/RX-V1200RDS/
HTR-5490/RX-V2200

RX-V1200 (A model)




RX-V1200 (R, T, K models)

AC OUTLETS: R, T models only



R model

RX-V1200RDS (B model)



DIGITAL OUTPUT
OPTICAL

AUDIO
DIGITAL OUT
DIGITAL IN
CO-R
CO-L
DVD
P-VIDEO
S-VIDEO
VIDEO
MONITOR OUT

COMPONENT VIDEO
DVD
D-TV/LED
MONITOR OUT

TUNER
AM ANT
FM ANT
78.0V 100W
P.A. ANT

OUTPUT
MAIN
REAR
CENTER
SUB WOOFER

IMPEDANCE SELECTOR
SWITCH BEFORE POWER ON

AC OUTLETS
SWITCHED
100W MAX. TOTAL

YAMAHA CORPORATION
MODEL NO. RX-V1500RDS
530 VOLTS
380 WATTS
50 Hz
MADE IN MALAYSIA

MANUFACTURED UNDER LICENSE FROM EXHIBIT LABORATORIES, "EXHIBIT," "PRO LOGIC," AND THE SCORBLE-CO SYMBOL, ITS ARE TRADEMARKS OF EXHIBIT LABORATORIES.

DIGITAL OUTPUT
OPTICAL
① TAPE
② CD-R
③ CD-R
④ CD-R
⑤ DVD
⑥ DVD
⑦ CD-R
⑧ DVD
⑨ DVD
⑩ DVD
⑪ DVD
⑫ DVD
⑬ DVD
⑭ DVD
⑮ DVD
⑯ DVD
⑰ DVD
⑱ DVD
⑲ DVD
⑳ DVD
㉑ DVD
㉒ DVD
㉓ DVD
㉔ DVD
㉕ DVD
㉖ DVD
㉗ DVD
㉘ DVD
㉙ DVD
㉚ DVD
㉛ DVD
㉜ DVD
㉝ DVD
㉞ DVD
㉟ DVD
㊱ DVD
㊲ DVD
㊳ DVD
㊴ DVD
㊵ DVD
㊶ DVD
㊷ DVD
㊸ DVD
㊹ DVD
㊺ DVD
㊻ DVD
㊼ DVD
㊽ DVD
㊾ DVD
㊿ DVD

AUDIO
① TAPE
② CD-R
③ CD-R
④ CD-R
⑤ DVD
⑥ DVD
⑦ CD-R
⑧ DVD
⑨ DVD
⑩ DVD
⑪ DVD
⑫ DVD
⑬ DVD
⑭ DVD
⑮ DVD
⑯ DVD
⑰ DVD
⑱ DVD
⑲ DVD
⑳ DVD
㉑ DVD
㉒ DVD
㉓ DVD
㉔ DVD
㉕ DVD
㉖ DVD
㉗ DVD
㉘ DVD
㉙ DVD
㉚ DVD
㉛ DVD
㉜ DVD
㉝ DVD
㉞ DVD
㉟ DVD
㊱ DVD
㊲ DVD
㊳ DVD
㊴ DVD
㊵ DVD
㊶ DVD
㊷ DVD
㊸ DVD
㊹ DVD
㊺ DVD
㊻ DVD
㊼ DVD
㊽ DVD
㊾ DVD
㊿ DVD

VIDEO
① TAPE
② CD-R
③ CD-R
④ CD-R
⑤ DVD
⑥ DVD
⑦ CD-R
⑧ DVD
⑨ DVD
⑩ DVD
⑪ DVD
⑫ DVD
⑬ DVD
⑭ DVD
⑮ DVD
⑯ DVD
⑰ DVD
⑱ DVD
⑲ DVD
⑳ DVD
㉑ DVD
㉒ DVD
㉓ DVD
㉔ DVD
㉕ DVD
㉖ DVD
㉗ DVD
㉘ DVD
㉙ DVD
㉚ DVD
㉛ DVD
㉜ DVD
㉝ DVD
㉞ DVD
㉟ DVD
㊱ DVD
㊲ DVD
㊳ DVD
㊴ DVD
㊵ DVD
㊶ DVD
㊷ DVD
㊸ DVD
㊹ DVD
㊺ DVD
㊻ DVD
㊼ DVD
㊽ DVD
㊾ DVD
㊿ DVD

COMPONENT VIDEO
DVD
D-TV/LED
MONITOR OUT
TUNER
AM ANT
GRD
75 Ω LINEAL
FM ANT

CAUTION
RISK OF ELECTRIC SHOCK
DO NOT OPEN

ATTENTION
RISQUE DE CHOC ELECTRIQUE
NE PAS OUVRI

AC OUTLETS
SWITCHED
80W MAX. TOTAL

YAMAHA
MODEL NO. KTR-5490
120 VOLTS 60 Hz ~ 260 WATTS
MADE IN MALAYSIA
V7R1680 U-1

MANUFACTURED UNDER LICENSE FROM DOLBY LABORATORIES, "DOLBY" "DOLBY LOGIC" AND THE DOLBY-D SYMBOL ARE TRADEMARKS OF DOLBY LABORATORIES.

DIGITAL OUTPUT
OPTICAL

1 NEW TAPE
2 CD-R
3 CD-R
4 CD-R
5 DVD
6 DLT
7 PHONE
8 CD
9 MAIN
10 SURROUND
11 CENTER
12 SUBWOOFER

AUDIO
1 NEW TAPE
2 CD-R
3 CD-R
4 CD-R
5 DVD
6 DLT
7 PHONE
8 CD
9 MAIN
10 SURROUND
11 CENTER
12 SUBWOOFER

VIDEO
1 DVD
2 P-V
3 S-V
4 VCR 1
5 VCR 2
6 VCR 3
7 VCR 4
8 VCR 5
9 VCR 6
10 VCR 7
11 VCR 8
12 VCR 9

COMPONENT VIDEO
DVD
P-V
D-TV
MONITOR OUT
TUNER
AM ANT
FM ANT
75 Ω UNBAL.
PA ANT

MAIN
1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762

[illegible]

The diagram illustrates the rear panel of the Yamaha RX-V2200 receiver, organized into several functional sections:

- DIGITAL INPUT/OUTPUT:** Includes a DIGITAL INPUT (OPTICAL) and a DIGITAL OUTPUT (OPTICAL).
- AUDIO:** Features inputs for MC/TAPE, CD-R, CD-I, CD, and PHONO. It also includes a MAIN output and a SUBWOOFER output.
- VIDEO:** Includes inputs for S VIDEO and VIDEO, and outputs for S VIDEO and VIDEO.
- COMPONENT VIDEO:** Features inputs for Pb/Cb, Pr/Cr, and Y, and a MONITOR OUT.
- CONTROL:** Includes a TUNER, REMOTE, and a CONTROL OUT.
- OUTPUTS:** Includes MAIN, REAR, SUBWOOFER, and CENTER outputs.
- IMPEDANCE SELECTOR:** A switch for selecting the output impedance.
- AC INLET:** A standard AC power inlet.
- AC OUTLETS:** Two outlets for external speakers, labeled MAIN A and B, and REAR A and B.
- SAFETY WARNINGS:** Includes a CAUTION about the risk of electric shock and a WARNING about the risk of fire or electric shock.
- YAMAHA LOGO AND MODEL INFORMATION:** The Yamaha logo is prominently displayed, along with the model number RX-V2200 and the text "MADE IN MALAYSIA".

DIGITAL OUTPUT
SPEAK. ① ② ③
MD/TAPE ④
CD-R ⑤
DVI ⑥
DVI ⑦
DVI ⑧
DVI ⑨
DVI ⑩
DVI ⑪
DVI ⑫
DVI ⑬
DVI ⑭
DVI ⑮
DVI ⑯
DVI ⑰
DVI ⑱
DVI ⑲
DVI ⑳
DVI ㉑
DVI ㉒
DVI ㉓
DVI ㉔
DVI ㉕
DVI ㉖
DVI ㉗
DVI ㉘
DVI ㉙
DVI ㉚
DVI ㉛
DVI ㉜
DVI ㉝
DVI ㉞
DVI ㉟
DVI ㊱
DVI ㊲
DVI ㊳
DVI ㊴
DVI ㊵
DVI ㊶
DVI ㊷
DVI ㊸
DVI ㊹
DVI ㊺
DVI ㊻
DVI ㊼
DVI ㊽
DVI ㊾
DVI ㊿

AUDIO
S VIDEO ① ② ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿

VIDEO
S VIDEO ① ② ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿

COMPONENT VIDEO
Pb/Cb ① ② ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿

TUNER
MAIN ① ② ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿

REMOTE
MAIN ① ② ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿

CONTROL
MAIN ① ② ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿

IMPEDANCE SELECTOR
MAIN ① ② ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿

AD OUTLET
MAIN ① ② ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿

CAUTION
MAIN ① ② ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿


YAMAHA
MODEL NO. RX-V2800
840 VOLTS 410 WATTS
50Hz
YAMAHA CORPORATION
MADE IN MALAYSIA

MANUFACTURED UNDER LICENSE FROM DENON THEATER SYSTEMS, INC. IN THE U.S.A. AND MALAYSIA.
ALABAMA, ALASKA, ARIZONA, ARKANSAS, CALIFORNIA, COLORADO, CONNECTICUT, DELAWARE, FLORIDA, GEORGIA, HAWAII, ILLINOIS, INDIANA, IOWA, KANSAS, KENTUCKY, LOUISIANA, MAINE, MARYLAND, MASSACHUSETTS, MICHIGAN, MINNESOTA, MISSISSIPPI, MISSOURI, MONTANA, NEBRASKA, NEVADA, NEW HAMPSHIRE, NEW JERSEY, NEW MEXICO, NEW YORK, NORTH CAROLINA, NORTH DAKOTA, OHIO, OKLAHOMA, OREGON, PENNSYLVANIA, RHODE ISLAND, SOUTH CAROLINA, SOUTH DAKOTA, TENNESSEE, TEXAS, UTAH, VERMONT, VIRGINIA, WASHINGTON, WISCONSIN, WYOMING.


[illegible]

REMOTE CONTROL TRANSMITTER



RX-V1200/HTR-5490
(U, C, A, R, T, K models)



RX-V1200RDS
(B, G models)



RX-V2200



SPECIFICATIONS

Audio Section

Minimum RMS Output Power (Power Amp. Section)

RX-V1200/RX-V1200RDS/HTR-5490 (20 Hz to 20 kHz, 0.04% THD, 8 ohms)	
MAIN L/R	80W + 80W
CENTER	80W
REAR L/R/C	80W + 80W + 80W
(1 kHz, 0.04% THD, 8 ohms)	
MAIN L/R	
[U, C models]	95W + 95W
[A, B, G, R, T, K models]	90W + 90W
CENTER	
[U, C models]	95W
[A, B, G, R, T, K models]	90W
REAR L/R/C	
[U, C models]	95W + 95W + 95W
[A, B, G, R, T, K models]	90W + 90W + 90W

RX-V2200 (20 Hz to 20 kHz, 0.04% THD, 8 ohms)	
MAIN L/R	100W + 100W
CENTER	100W
REAR L/R/C	100W + 100W + 100W
(1 kHz, 0.04% THD, 8 ohms)	
MAIN L/R	
CENTER	115W + 115W
REAR L/R/C	115W
REAR L/R/C	115W + 115W + 115W

Maximum Power (EIAJ)

RX-V1200/HTR-5490 [R, T, K models] (1 kHz, 10% THD, 8 ohms)	
MAIN L/R	125W + 125W
CENTER	125W
REAR L/R/C	125W + 125W + 125W
RX-V2200 [R, T models] (1 kHz, 10% THD, 8 ohms)	
MAIN L/R	155W + 155W
CENTER	155W
REAR L/R/C	155W + 155W + 155W

Dynamic Power Per Channel (IHF)

RX-V1200/RX-V1200RDS/HTR-5490 MAIN L/R (8/6/4/2 ohms)	
105/130/170/200 W	
RX-V2200 MAIN L/R (8/6/4/2 ohms)	
130/160/200/245 W	

DIN Standard Output Power Per Channel

RX-V1200RDS [G model] (1 kHz, 0.7% THD, 4 ohms)	
MAIN L/R	135W + 135W
CENTER	135W
REAR L/R/C	135W + 135W + 135W

Dynamic Headroom

RX-V1200/HTR-5490 (8 ohms)	
[U model]	1.2 dB
[C model]	1.1 dB
RX-V2200 (8 ohms)	
[U, C models]	1.1 dB

IEC Power

RX-V1200RDS [G model] MAIN L/R (1 kHz, 0.04% THD, 8 ohms)	
90W + 90W	

Damping Factor

MAIN L/R (20 Hz to 20 kHz, SPEAKER-A, 8 ohms) ...	80 or more
---	------------

Input Sensitivity / Input Impedance

PHONO (MM)	2.5 mV / 47 k-ohms
CD, etc.	150 mV / 47 k-ohms
EXT. DECODER	
MAIN L/R	150 mV / 47 k-ohms
CENTER, SURROUND L/R, SUBWOOFER ...	150 mV / 40 k-ohms

Maximum Input Signal Level

PHONO (MM) (1 kHz, 0.1% THD)	100 mV
CD, etc. (1 kHz, 0.5% THD, EFFECT ON)	2.2 V

Output Level / Output Impedance

REC OUT	150 mV / 0.9 k-ohms
PRE OUT	2.57 V / 1.2 k-ohms
SUB WOOFER [MAIN SP: Small]	4.0 V/1.2 k-ohms

Headphone Jack Rated Output / Impedance

1 kHz, 40 mV, 8 ohms	0.15 V / 100 ohms
----------------------------	-------------------

Frequency Response

CD, etc. to MAIN (10 Hz to 100 kHz)	0/-3 dB
Power Amp. section (5 Hz to 100 kHz)	0/-3 dB

RIAA Equalization Deviation

PHONO (MM) (20 Hz to 20 kHz)	0±0.5 dB
------------------------------------	----------

Total Harmonic Distortion

(20 Hz to 20 kHz)	
PHONO (MM) to REC OUT (1V)	0.02% or less
CD, etc. (EFFECT OFF) to MAIN SP OUT (50W / 8 ohms) ..	0.04% or less

Signal to Noise Ratio (IHF-A network)

(Input shorted)	
PHONO (MM) to REC OUT (5 mV)	
[U, C, R, T, K models]	86 dB or more
[A, B, G models]	81 dB or more
CD, etc. (EFFECT OFF) to MAIN SP OUT	
250 mV	100 dB or more

Residual Noise (IHF-A network)

MAIN L/R SP OUT	150 μV or less
-----------------------	----------------

Channel Separation

(Vol -30 dB, EFFECT OFF)	
PHONO (Input shorted, 1 kHz/10 kHz)	60 dB or more/55 dB or more
CD, etc. (Input 5.1 k-ohms shorted, 1 kHz/10 kHz) ...	60 dB or more/45 dB or more

Tone Control Characteristics

Bass: Boost/Cut	±10 dB (50 Hz)
Turnover Frequency	350 Hz
Treble: Boost/Cut	±10 dB (20 kHz)
Turnover Frequency	3.5 kHz

Filter Characteristics

MAIN, Rear SP Small (H.P.F.)	90 Hz, 12 dB/oct.
SUBWOOFER (L.P.F.)	90 Hz, 18 dB/oct.

Bass Extension

60 Hz	6 dB
-------------	------

Video Section

S-Video Signal Type

[U, C models]	NTSC
[R, T, K models]	NTSC or PAL
[A, B, G models]	PAL

Video Signal Level

.....	1 Vp-p / 75 ohms
-------	------------------

S-Video Signal Level

Y	1 Vp-p / 75 ohms
C	0.286 Vp-p / 75 ohms

Component Signal Level

Y	1 Vp-p / 75 ohms
Cb/Cr	0.7 Vp-p / 75 ohms

Maximum Input Level

.....	1.5 Vp-p
-------	----------

Signal to Noise Ratio

.....	50 dB or more
-------	---------------

Monitor Out Frequency Response

S-Video Signal Level	5 Hz to 10 MHz, -3 dB
Component Signal Level	DC to 60 MHz, -3 dB

FM Section

Tuning Range

[U, C models]	87.5 to 107.9 MHz
[A, B, G models]	87.50 to 108.00 MHz
[R, T, K models]	87.5 to 108.0 / 87.50 to 108.00 MHz

50 dB Quieting Sensitivity (IHF)

(100% Mod)	
Mono	2.0 μV (17.3 dBf)
Stereo	25 μV (39.2 dBf)

Usable Sensitivity (IHF)

Mono	1.0 μV (11.2 dBf)
------------	-------------------

Selectivity

at 400 kHz	70 dB
------------------	-------

Signal to Noise Ratio (IHF)

Mono / Stereo	76 dB / 70 dB
---------------------	---------------

Harmonic Distortion

(1 kHz)	
Mono/Stereo	0.2 / 0.3 %

Stereo Separation

1 kHz	45 dB
-------------	-------

Frequency Response

20 Hz to 15 kHz	+0.5 / -2 dB
-----------------------	--------------

Antenna Input

.....	75 ohms unbalanced
-------	--------------------

AM Section

Tuning Range

[U, C models]	530 to 1,710 kHz
[A, B, G models]	531 to 1,611 kHz
[R, T, K models]	530 to 1,710 / 531 to 1,611 kHz

Usable Sensitivity

.....	300 μV/m
-------	----------

Antenna

.....	Loop Antenna
-------	--------------

General

Power Supply

[U, C models]	AC 120 V, 60 Hz
[A model]	AC 240 V, 50 Hz
[B, G models]	AC 230 V, 50 Hz
[R model]	AC 110/120/220/240 V, 50/60 Hz
[T model]	AC 220 V, 50 Hz
[K model]	AC 110/220 V, 60 Hz

Power Consumption

RX-V1200/RX-V1200RDS/HTR-5490	
[U model]	260 W
[C model]	270 W / 370 VA
[A, B, G, R, T, K models]	360 W
RX-V2200	
[U model]	390 W
[C model]	400 W / 500 VA
[A, R, T models]	410 W

Standby Power Consumption (reference data)

[U, C, A, B, G models]	1.2 W
------------------------------	-------

[R, T models] AC 220V, 50Hz 1.5 W
 [K model] AC 220V, 60Hz 1.5 W
Maximum Power Consumption
RX-V1200/RX-V2200 [R model]
 5ch Drive, 10% THD 585 W

AC Outlets

2 switched outlets
 [U, C models] 80W max., total
 [G model] RX-V1200RDS only 100W max., total
 [R, T models] 50W max., total
 1 switched outlet
 [A, B models] B: RX-V1200RDS only 100W max.

Dimensions (W x H x D)

435 x 171 x 431.5 mm (17-1/8" x 6-3/4" x 17")

Weight

15.0 kg (33 lbs. 1 oz.)

Finish

RX-V1200 Gold color (R, T, K) models
 Black color (U, C, R, A) models
 RX-V1200RDS Gold color (G) model
 Black color (B, G) models
 Titan color (B, G) models
 HTR-5490 Gold color (T) model
 Black color (U, C, A) models
 RX-V2200 Gold color (R, T) models
 Black color (U, C, R, A) models

Accessories

Remote control transmitter, Manganese batteries, Indoor FM antenna, AM loop antenna, Antenna adaptor [B model], Power cord ass'y [V1200/V2200 U, C models]

* Specifications are subject to change without notice due to product improvements.

U **U.S.A. model** **C** **Canadian model**
A **Australian model** **B** **British model**
G **European model** **R** **General model**
T **Chinese model** **K** **Korean model**



Manufactured under license from Dolby Laboratories.
 "Dolby", "Pro Logic" and the double-D symbol are trademarks of Dolby Laboratories.



"DTS" and "DTS Digital Surround" are registered trademarks of Digital Theater Systems, Inc.

• Set Menu Table

No.	SET MENU	PRESET VALUE	SETTING RANGES
1.	SPEAKER SET		
1A	CENTER SPEAKER	LARGE	LARGE, SMALL, NONE
1B	MAIN SPEAKER	LARGE	LARGE, SMALL
1C	REAR L/R SPEAKER	LARGE	LARGE, SMALL, NONE
1D	REAR CENTER SPEAKER	LARGE	LARGE, SMALL, NONE
1E	LFE/BASS OUT	BOTH	SUBWOOFER, MAIN, BOTH
1F	MAIN LEVEL	NORMAL	NORMAL, -10dB
2.	LOW FREQ. TEST	TEST TONE : OFF OUTPUT : MAIN L/R FREQ. : 88Hz	OFF, ON MAIN L/R, L, C, R, RS, RC, LS, SWFR 35Hz/ ... /88Hz/ ... /WIDE
3.	L/R BALANCE	CENTER	L, ... , CENTER, ... , R (40 steps)
4.	HP TONE CONTROL	HP BASS : 0dB HP TREBLE : 0dB	-6dB — +3dB (1dB step) -6dB — +3dB (1dB step)
5.	CENTER GRAPHIC EQ.	100Hz : 0dB 300Hz : 0dB 1kHz : 0dB 3kHz : 0dB 10kHz : 0dB	-6dB — +6dB (1dB step) -6dB — +6dB (1dB step) -6dB — +6dB (1dB step) -6dB — +6dB (1dB step) -6dB — +6dB (1dB step)
6.	INPUT RENAME	DVD (Currently selected input)	
7.	I/O ASSIGNING		
7A	COMPONENT VIDEO INPUT 1	[A] : DVD	DVD, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, V-AUX
	COMPONENT VIDEO INPUT 2	[B] : D-TV/LD	DVD, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, V-AUX
7B	OPTICAL OUT 1	(1) : MD/TAPE	DVD, MD/TAPE, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, V-AUX, PHONO, CD, CD-R
	OPTICAL OUT 2	(2) : CD-R	DVD, MD/TAPE, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, V-AUX, PHONO, CD, CD-R
7C	OPTICAL IN 1	(3) : CD	CD, CD-R, MD/TAPE, DVD, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, PHONO
	OPTICAL IN 2	(4) : CD-R	CD, CD-R, MD/TAPE, DVD, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, PHONO
	OPTICAL IN 3	(5) : DVD	CD, CD-R, MD/TAPE, DVD, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, PHONO
	OPTICAL IN 4	(6) : D-TV/LD	CD, CD-R, MD/TAPE, DVD, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, PHONO
7D	COAXIAL IN 1	(7) : CD	CD, CD-R, MD/TAPE, DVD, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, V-AUX, PHONO
	COAXIAL IN 2	(8) : CBL/SAT	CD, CD-R, MD/TAPE, DVD, D-TV/LD, CABLE, SAT, VCR1, VCR2/DVR, V-AUX, PHONO
8.	INPUT MODE	AUTO	AUTO/LAST
9.	PARAMETER INITIALIZE	PARAMETER INITIALIZE	The number key of the remote controller is pushed and initialized.
10.	LFE LEVEL	SPEAKER : 0dB HEADPHONE : 0dB	-2dB — 0dB (1dB step) -2dB — 0dB (1dB step)
11.	DYNAMIC RANGE	SP DYNAMIC RANGE : MAX HP DYNAMIC RANGE : MAX	MAX, STD, MIN MAX, STD, MIN
12.	SPEAKER DELAY TIME	CENTER : 0ms REAR CENTER : 3ms	0ms — 5ms (1ms step) 0ms — 30ms (1ms step)
13.	DISPLAY SET	BLUE BACK : AUTO OSD SHIFT : 0 DIMMER : 0	AUTO/OFF -5 — +5 (1 step) -4 — 0 (1 step)
14.	MEMORY GUARD	OFF	ON/OFF
15.	DUAL MONO	MAIN	MAIN, SUB, ALL


• The variable range of the parameter (Min/Max/Step)

Parameter name	Pro Logic	Pro Logic II Movie	Pro Logic II Music	Neo:6	2ch	DD/dts/AAC	6.1/ES	Unit
(P.) INIT. DLY	-	-	-	-	1/99/1	1/99/1	1/99/1	ms
(P.) ROOM SIZE	-	-	-	-	0.1/2.0/0.1	0.1/2.0/0.1	0.1/2.0/0.1	-
(P.) LIVENESS	-	-	-	-	0/10/1	0/10/1	0/10/1	-
S. DELAY	10/25/1	10/25/1	0/15/1	0/30/1	0/49/1	0/49/1	0/49/1	ms
S. INIT. DLY	-	-	-	-	-	1/49/1	1/49/1	ms
S. ROOM. SIZE	-	-	-	-	0.1/2.0/0.1	0.1/2.0/0.1	0.1/2.0/0.1	-
S. LIVENESS	-	-	-	-	0/10/1	0/10/1	0/10/1	-
RC. INT.DLY	-	-	-	-	-	-	1/49/1	ms
RC. ROOM, SIZE	-	-	-	-	-	-	0.1/2.0/0.1	-
RC. LIVENESS	-	-	-	-	-	-	0/10/1	-
REV. TIME	-	-	-	-	1.0/5.0/0.1	1.0/5.0/0.1	1.0/5.0/0.1	s
REV. DELAY	-	-	-	-	0/250/1	0/250/1	0/250/1	ms
REV. LEVEL	-	-	-	-	0/100/1	0/100/1	0/100/1	%
Panorama	-	OFF	OFF/ON	-	-	-	-	-
Dimension	-	0 (STD)	-3/+3/1	-	-	-	-	-
C Width	-	0	0/7/1	-	-	-	-	-

6ch Stereo Parameter		Unit
CT. LEVEL	0/100/1	%
RL. LEVEL	0/100/1	%
RC. LEVEL	0/100/1	%
RR. LEVEL	0/100/1	%

■ INTERNAL VIEW

- ① POWER (1) P.C.B.
- ② POWER (7) P.C.B.
- ③ MAIN (6) P.C.B.
- ④ MAIN (4) P.C.B.
- ⑤ MAIN (5) P.C.B.
- ⑥ POWER (10) P.C.B.
- ⑦ TUNER
- ⑧ VIDEO (4) P.C.B.
- ⑨ VIDEO (2) P.C.B.
- ⑩ VIDEO (1) P.C.B.
- ⑪ VIDEO (6) P.C.B.
- ⑫ VIDEO (8) P.C.B.
- ⑬ VIDEO (7) P.C.B.
- ⑭ VIDEO (5) P.C.B.
- ⑮ DSP P.C.B.
- ⑯ FUNCTION P.C.B.
- ⑰ POWER (4) P.C.B.
- ⑱ MAIN (1) P.C.B.
- ⑲ OPERATION (5) P.C.B.
- ⑳ OPERATION (4) P.C.B.
- ㉑ MAIN (2) P.C.B.
- ㉒ OPERATION (2) P.C.B.
- ㉓ POWER (8) P.C.B.
- ㉔ OPERATION (6) P.C.B.
(RX-V2200 only)
- ㉕ OPERATION (1) P.C.B.
- ㉖ OPERATION (3) P.C.B.
- ㉗ POWER (3) P.C.B.
- ㉘ OPERATION (7) P.C.B.
- ㉙ POWER (5) P.C.B.
- ㉚ POWER (2) P.C.B.
- ㉛ MAIN (7) P.C.B.
- ㉜ MAIN (3) P.C.B.



■ DISASSEMBLY PROCEDURES

(Remove parts in the order as numbered.)
Disconnect the power cord from the AC outlet.

1. Removal of Top Cover

- Remove 2 screws (①), 4 screws (②) and 5 screws (③). (Fig. 1)
- Slide the Top Cover rearward to remove it. (Fig. 1)

2. Removal of Front Panel

- Remove the BASS and TREBLE knobs (④). (Fig. 1)
- Remove 9 screws (⑤) and then remove the Front Panel forward. (Fig. 1)

3. Removal of Sub Chassis

- Remove 4 push rivets (⑥) and then remove the Side Plates. (Fig. 2)
- Remove 2 screws (⑦) and 2 screws (⑧), and then remove the Sub Chassis forward. (Fig. 2)

4. Removal of DSP P.C.B.

- Remove 2 screws (⑨) and then remove the Supports. (Fig. 2)
- Remove 4 screws (⑩) and then remove the Brackets. (Fig. 2)
- Remove 1 screw (⑪). (Fig. 2)
- Remove 9 screw (⑫). (Fig. 3)
- Remove the DSP P.C.B. upward. (Fig. 2)

5. Removal of VIDEO (5) P.C.B.

- Remove 2 screws (⑬). (Fig. 2)
- Remove the VIDEO (5) P.C.B. which is connected directly to the lower P.C.B. with connectors. (Fig. 2)




Fig. 1




Fig. 2




Fig. 3

6. Removal of VIDEO (1), VIDEO (2), VIDEO (4) and VIDEO (8) P.C.B.s and Tuner

- Remove 17 screws (14). (Fig. 3)
- Remove VIDEO (1), VIDEO (2), VIDEO (4) and VIDEO (8) P.C.B.s and the Tuner. (Fig. 4)

When checking the P.C.B.:

- Put the rubber sheet and a cloth over the equipment. Then place the P.C.B. upside down on the cloth and check it. (Fig. 4)
- Connect VIDEO (5) and FUNCTION P.C.B.s by using the extension cable (AAX30610) for the P.C.B. check. (Fig. 6)
- Reconnect all cables (connectors) that have been disconnected.
- The P.C.B. removed from the rear panel does not work because its grounding is loose. Be sure to connect the ground of each P.C.B. to the chassis or GND with a jumper wire or the like.




Fig. 4

7. Removal of VIDEO (6), VIDEO (7), and FUNCTION P.C.B.s

- Remove CB212, CB975, CB510, CB509, CB505 and CB503. (Fig. 5)
- Remove 9 screws (15). (Fig. 3)
- Remove VIDEO (6), VIDEO (7), and FUNCTION P.C.B.s. (Fig. 6)

When checking the P.C.B.:

- Put a cloth beside the equipment. Then place the P.C.B. on the cloth and check it. (Fig. 4)
- Connect VIDEO (5) and FUNCTION P.C.B.s by using the extension cable (AAX30610) for the P.C.B. check. (Fig. 6)
- Reconnect all cables that have been disconnected.
- The P.C.B. removed from the rear panel does not work because its grounding is open. Be sure to connect the ground of each P.C.B. to the chassis or GND with a jumper wire or the like.




Fig. 5






Fig. 6

8. Removal of Duct/Fan Section (If applicable)

- a. Remove 2 screws (16) and 2 screws (17). (Fig. 7)
- b. Remove the duct/fan together with the frame by lifting them up.

**Fig. 7****9. Removal of MAIN (1), MAIN (2), POWER (4) and POWER (8) P.C.B.'s.**

- a. Remove 2 screws (18), 3 screws (19) and 1 screw (20). (Fig. 8)
- b. Remove MAIN (1), MAIN (2), POWER (4) and POWER (8) P.C.B.s. (Fig. 8)

**Fig. 8**

■ SELF DIAGNOSIS FUNCTION (DIAG)


There are 18 DIAG menu items, each of which has sub-menu items. Listed in the table below are menu items and sub-menu items. (Some diagnostic functions do not apply to all models or to all markets.)

No	DIAG menu	sub-menu
1	YSS938 1. ANALOG BYPASS	1. ANALOG BYPASS 2. YSS 0dB 3. YSS FULL BIT
2	YSS-CS 2. YSS-CS 0dB	1. YSS-CS 0dB 2. YSS-CS FULL BIT
3	CS-YSS 3. CS-YSS 0dB	1. CS-YSS 0dB 2. CS-YSS FULL BIT
4	CS49329 4. CS 0dB	1. CS49329 0dB 2. CS49329 FULL BIT
5	HP ROUTE 5. HP 0dB	1. HP 0dB 2. HP FULL BIT
6	RAM THROUGH 6. RAM 0dB	1. RAM 0dB 2. MAIN ATT
7	DOLBY PRO LOGIC 7. PRO LOGIC I	1. PRO LOGIC I 2. PRO LOGIC II 3. NEO: 6
8	SPEAKER SET 8. MAIN: SML 0dB	1. MAIN: SMALL 0dB 2. MAIN: LARGE -10dB 3. CENTER: NONE 4. LFE/BASS: MAIN 5. FRONT MIX: 5ch 6. REAR C: MUTE 7. REAR L/R: MUTE
9	EFFECT OFF/ DISPLAY CHECK 9. VFD CHECK	1. VFD CHECK (Initial display) 2. VFD DISP OFF (All segments OFF) 3. VFD DISP ALL (All segments ON 100%) 4. VFD DIMMER (All segments ON 50%) 5. CHECKED PATTERN (ON in lattice)
10	MANUAL TEST 10 TEST ALL	1. TEST ALL 2. TEST MAIN L 3. TEST CENTER 4. TEST MAIN R 5. TEST REAR R 6. TEST REAR CENTER 7. TEST REAR L 8. TEST LFE
11	RS-232C 11 TxRxData:XX	1. TX DATA 2. HARD FLOW
12	FACTORY PRESET 12 PRESET INHI	1. PRESET INHIBIT (memory initialization inhibited) 2. PRESET RESERVED (memory initialized)
13	AD DATA CHECK /FAN TEST DC:007 PS:025	1. DC/PS (protection) 2. THM/FAN OUT 3. REC-OUT 4. IMP SW/POWER LIMIT 5. K0/K1 (panel key) 6. FAN DRIVE TEST: HIGH (Fan test only applies to models with a fan.) 7. FAN DRIVE TEST: MID (Fan test only applies to models with a fan.) 8. FAN DRIVE TEST: LOW (Fan test only applies to models with a fan.)

No	DIAG menu	sub-menu
14	IF STATUS IS1:440308C000	1. IS 1
		2. IS 2
		3. IS 3
		4. CS 1
		5. CS 2
		6. CS 3
		7. CS 4
		8. CS 5
		9. BY1
		10. BY2
		11. BY3
		12. BY4
		13. BC1
		14. BC2
		15. BC3
		16. BC4
		17. BC5
		18. YS1
		19. YS2
		20. YS3
		21. CS
		22. MTT
15	DSP RAM CHECK YSS Bus:NoEr	1. YSS938 BUS CHECK
		2. PLD/SRAM BUS CHECK
16	CS DL CODE RDV:X	1. ROM DATA VERSION
		2. TOC AREA 0
		3. TOC AREA 1
		4. TOC AREA 2
		5. TOC AREA 3
		6. TOC AREA 4
		7. TOC AREA 5
		8. SUM CHECK AREA 0
		9. SUM CHECK AREA 1
		10. SUM CHECK AREA 2
		11. SUM CHECK AREA 3
		12. SUM CHECK AREA 4
		13. SUM CHECK AREA 5
17	SOFT SW 17.SW :PCB	1. SW MODE
		2. MODEL SETTING
		3. TUNER DESTINATION
		4. TUNER EXIST
		5. RDS EXIST
		6. ZONE 2 EXIST
		7. VIDEO FORMAT
18	ROM VERSION/CHECK SUM/ PORT VER. XXXXXXXX	1. VERSION
		2. SUM ALL/PROGRAM
		3. SUM 232C/MAKER
		4. PORT
		5. AAC PORT

• Starting DIAG

Press the “STANDBY/ON” key while pressing those two keys indicated in the figure on the right.



• Starting DIAG in the protection cancel mode

If the protection function works and causes hindrance to trouble diagnosis, cancel the protection function as described below, and it will be possible to enter the DIAG mode. (The protection functions other than the excess current detect function will be cancelled.)

Press the “STANDBY/ON” key while pressing those two keys indicated in the figure on the right. At this time, keep pressing those two keys for 3 seconds or longer.

In this mode, the “SLEEP” segment of the FL display of the main unit flashes to indicate that the mode is DIAG mode with the protection functions cancelled.

CAUTION!

Using this product with the protection function disabled may cause damage to itself. Use special care for this point when using this mode.

• Canceling DIAG

[1] Before canceling DIAG, execute setting for PRESET of DIAG menu No.12 (Memory initialization inhibited or Memory initialized).

* In order to keep the user memory stored, be sure to select PRESET INHI (Memory initialization inhibited).

[2] Turn off the power by pressing the “STANDBY/ON” key of the main unit or the “STANDBY” key of the remote controller.

• Display provided when DIAG started


When the monitor is connected, DIAGNOSTIC MENU appears on its screen as shown in the figure. (It remains on display until DIAG is cancelled.)

DIAGNOSTIC MENU


1.DSP THR	10.MAN LTEST
2.YSS-CS	11.RS232C
3.CS-YSS	12.PRESET
4.CS49329	13.AD/FAN
5.HP ROUTE	14.STATUS
6.RAM THR	15.DSP RAM
7.PRO LOGIC	16.CS DL COD
8.SP SET	17.SOFT SW
9.VFD CHECK	18.VER/SUM/P

The FL display of the main unit displays the protection function history data and the version (1 alphabet) and the DIAG menu (sub-menu (ANALOG BYPASS) of DIAG menu No.1 YSS938) a few seconds later.

When there is no history of protection function:



When there is a history of protection function:



Cause: An excessive current flowed through the power amplifier.

Supplementary information: As current of the power transistor is detected, the abnormal channel can be identified by checking the current detect transistor.

Turning on the power without correcting the abnormality will cause the protection function to work immediately and the power supply will instantly be shut off.

When there is a history of protection function due to abnormal voltage in the power supply section

PS PRT:000 F

Voltage display in %

Version
(1 alphabet)

Cause: The voltage in the power supply section is abnormal.

Supplementary information: The abnormal voltage is displayed in % based on 5V as 100%.

Turning on the power without correcting the abnormality will cause the protection function to work 1 second later and the power supply will be shut off.

When there is a history of protection function due to abnormal DC output

DC PRT:000 F

Voltage display in %

Version
(1 alphabet)

Cause: DC output of the power amplifier is abnormal.

Supplementary information: The abnormal voltage is displayed in % based on 5V as 100%.

Turning on the power without correcting the abnormality will cause the protection function to work 3 seconds later and the power supply will be shut off.

When there is a history of protection function due to excessive heat sink temperature

TMP PRT:000 F

Voltage display in %

Version
(1 alphabet)

Cause: The temperature of the heat sink is excessive.

Supplementary information: The abnormal voltage is displayed in % based on 5V as 500%.

Turning on the power without correcting the abnormality will cause the protection function to work 1 second later and the power supply will be shut off.

* Additional causes of protection can be due to loose connections, associated components, CPU, etc.

* For the protection voltage value, refer to DIAG menu No.10 described later.

• History of protection function

When the protection function has worked, its history is stored in memory with a backup. Even if no abnormality is noted while servicing the unit, an abnormality which has occurred previously can be defined as long as the backup data has been stored.

The history of the protection function is cleared when DIAG is cancelled by selecting PRESET RESERVED (Memory initialized) of DIAG menu No.10 or when the backup data is erased.

• Display during menu operation

During the DIAG operation, the menu list described in the section of the startup screen appears on the superimposed screen and the function at work is indicated on the FL indicator. The contents displayed during the function operation are described in the later section on details of functions.

• Operation procedure of DIAG menu and SUB-MENU

There are 18 MENU items, each of which has some SUB-MENU items.

DIAG menu selection



Main unit: Select the menu using ▷ (Forward) and ◁ (Reverse) keys of PRESET/TUNING located in the sealing panel.

Remote control unit: Select the menu using ∨ (Forward) and ∧ (Reverse) keys.

SUB-MENU selection

Main unit: Select the sub-menu using ▷ (Forward) and ◁ (Reverse) keys of PROGRAM located in the sealing panel.

Remote control unit: Select the sub-menu using > (Forward) and < (Reverse) keys.



• Functions in DIAG mode

In addition to the DIAG menu items, functions as listed below are available.

- Input selection, 6CH input
- Center/Rear/Rear Center/Sub-woofer level adjustment
- Muting
- Speaker relay A/B
- Power on/off
- Master volume

- * Functions related to the tuner and the set menu are not available.
- * It is possible to confirm Menu No.14 IF STATUS while keeping the signal process (operation status) of each DIAG menu by using the input mode key of the main unit.

• Initial settings used to start DIAG

The following initial settings are used when starting DIAG.

When DIAG is canceled, these settings are restored to those before starting DIAG.

- Master volume: -40dB
- Input: DVD (6CH INPUT OFF)
- Effect level: 0dB
- Audio mute: OFF
- Speaker relay A/B: ON
- Speaker setting: LARGE / BASS OUT = BOTH
- DIAG menu: YSS938 (1. ANALOG BYPASS)

• Details of DIAG menu

With full-bit output specified in some modes, it is possible to execute 0dBFS output without head margin in each channel.

1. YSS938

This function is for YSS938 only. Main DSP of YSS938 is selected for MAIN L/R output.

Using the sub-menu, it is possible to select the analog bypass, 0dB output level or full-bit output.

ANALOG BYPASS

1. ANALOG BYPASS


- The signal is output through the signal path as shown below.
- The signal for L/R is output as it is without passing through the DSP section.

Reference data (PRE OUT)

INPUT: DVD ANALOG

SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV



YSS 0dB

1. YSS 0dB

- The signal is output including the head margin.
Head margin:
Main L/R: 0dBFS, Center: -6dBFS, Rear Center: -3dBFS, FL/FR: -6dBFS,
RL/RR: -12dBFS, SWFR: Add L/R signal at -20dBFS.

Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV

YSS FULL BIT


1. YSS FULL BIT

- The signal is output in digital full bit without including the head margin.


Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	+0.5 dBV	-3.0 dBV	-2.5 dBV	+6.5 dBV

DSP THROUGH ~
YSS (Analog)



DSP THROUGH ~
YSS (DD/dts (ES off))



2. YSS-CS

8 channels are made usable by CS49329. The signal enters YSS938 through the Sub DSP passage and then undergoes through-output.

CS49329 is selected for the Main L/R output. Using the sub-menu, it is possible to select full bit output at 0dB output level.

YSS-CS 0dB

2.YSS-CS 0dB

- The signal is output including the head margin.

Head margin:

Main L/R: -18dBFS, Center: -6dBFS, Rear Center: -3dBFS, FL/FR: -6dBFS,
RL/RR: -18dBFS, SWFR: Add L/R signal at -20dBFS.

Reference data (PRE OUT)

INPUT: DVD ANALOG

SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV

YSS-CS FULL BIT

2.YSS-CS F BIT

- The signal is output in digital full bit without including the head margin.


Reference data (PRE OUT)

INPUT: DVD ANALOG


SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	+0.5 dBV	-3.0 dBV	-2.5 dBV	+6.5 dBV

DSP THROUGH ~
YSS-CS (Analog)



DSP THROUGH ~
YSS-CS (DD/dts (ES off))



3. CS-YSS

8 channels are made usable by CS49329. The signal enters YSS938 through the Sub DSP passage and then undergoes through-output.

YSS938 Main DSP is selected for the Main L/R output. Using the sub-menu, it is possible to select full bit output at 0dB output level.

CS-YSS 0dB

3. CS-YSS 0dB

- The signal is output including the head margin.
Head margin:
Main L/R: -18dBFS, Center: -6dBFS, Rear Center: -3dBFS, FL/FR: -6dBFS, RL/RR: -18dBFS, SWFR: Add L/R signal at -20dBFS.

Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV

CS-YSS FULL BIT


3. CS-YSS F BIT

- The signal is output in digital full bit without including the head margin.


Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	+0.5 dBV	-3.0 dBV	-2.5 dBV	+6.5 dBV

DSP THROUGH ~
CS-YSS (Analog)
(Use of CS-YSS is not available
due to restriction of the passage.)



DSP THROUGH ~
CS-YSS (AAC/dts (ES off))



4. CS49329

8 channels are made usable by CS49329. The signal enters YSS938 through the Sub DSP passage and then undergoes through-output.

CS49329 is selected for the Main L/R output. Using the sub-menu, it is possible to select full bit output at 0dB output level.

* As a 3dB margin of CS is always effective for RC when decoding dts ES, even when the output in full bit is specified, the RC output remains up to 0dBFS when 0dBFS is input to LS/RS.

CS49329 0dB

4. CS 0dB

- The signal is output including the head margin.

Head margin:

Main L/R: -18dBFS, Center: -6dBFS, Rear Center: -3dBFS, FL/FR: -6dBFS,
RL/RR: -18dBFS, SWFR: Add L/R signal at -20dBFS.

Reference data (PRE OUT)

INPUT: DVD ANALOG

SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV

CS49329 FULL BIT

4. CS FULL BIT

- The signal is output in digital full bit without including the head margin.

Reference data (PRE OUT)

INPUT: DVD ANALOG


SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	+0.5 dBV	-3.0 dBV	-2.5 dBV	+6.5 dBV

DSP THROUGH ~


CS (Analog)

(Use of CS only is not available
due to restriction of the passage.)




DSP THROUGH ~

CS (PCM)



DSP THROUGH ~
CS (AAC/dts (ES auto))



5. HP ROUTE

This function is for YSS938 only. Sub DSP SDOB3 of YSS938 is selected for MAIN L/R output. Using the sub-menu, it is possible to select the full-bit output at 0dB output level.

HP 0dB

5. HP 0dB

- The signal is output including the head margin.
Head margin:
Main L/R: -18dBFS, Center: -6dBFS, Rear Center: -3dBFS, FL/FR: -6dBFS, RL/RR: -18dBFS, SWFR: Add L/R signal at -20dBFS.

Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	- ∞	- ∞	- ∞	- ∞

HP FULL BIT


5. HP FULL BIT

- The signal is output in digital full bit without including the head margin.

Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -20 dB	+2.5 dBV	- ∞	- ∞	- ∞	- ∞

DSP THROUGH ~
HP ROUTE (Auto)



6. RAM THROUGH

This function is for YSS938 only. Main L/R signal is output through Main DSP of YSS938.
CT/RC, RL/RR and FL/FR signals are output through Sub DSP - DRAM.
Using the sub-menu, it is possible to select the full-bit output at 0dB output level.

RAM 0dB

6. RAM 0dB

Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-5.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV

MAIN ATT


6. MAIN ATT

- MAIN -9dB

Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Both ch, -20 dBV, volume -10 dB	-14.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV

RAM THROUGH ~
(Auto)



7. DOLBY PRO LOGIC [YSS938]

PRO LOGIC I

7. PRO LOGIC I

Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Each ch, -20 dBV, volume -10 dB	-5.5 dBV	- ∞	- ∞	- ∞	- ∞
Both ch, -20 dBV, volume -10 dB	- ∞	-2.5 dBV	- ∞	- ∞	- ∞
Both ch, -20 dBV (reverse phase), volume -10 dB	- ∞	- ∞	- ∞	- ∞	-5.5 dBV

PRO LOGIC II

7. PRO LOGIC II

Reference data (PRE OUT)
INPUT: DVD ANALOG
SWFR: 50Hz, Others: 1kHz

Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Each ch, -20 dBV, volume -10 dB	-5.5 dBV	- ∞	- ∞	- ∞	- ∞
Both ch, -20 dBV, volume -10 dB	- ∞	-2.5 dBV	- ∞	- ∞	- ∞
Both ch, -20 dBV (reverse phase), volume -10 dB	- ∞	- ∞	- ∞	- ∞	-5.5 dBV

The L/C/R/RL/RR signals undergo the Pro-Logic processing and C/RL/RR signals are output through Sub DSP-DRAM. Main DSP is selected for MAIN L/R output.


Using the sub-menu, it is possible to select PRO LOGIC I, II (Movie). The Auto Input Balance function is always off.

When dts/AAC input is used, the signal is decoded by CS49329 and the L/R signal undergoes the Pro-Logic processing.

When the Dolby Digital Multi input is used, the function is the same as in the Dolby Digital Normal mode.

The LFE signal is not output when decoding in the PRO LOGIC I, II mode.

Dolby Pro Logic (Auto)



Neo:6

7. Neo:6

Reference data (PRE OUT)

INPUT: DVD ANALOG

SWFR: 50Hz, Others: 1kHz


Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
Each ch, -20 dBV, volume -10 dB	-5.5 dBV	- ∞	- ∞	- ∞	- ∞
Both ch, -20 dBV, volume -10 dB	- ∞	-2.5 dBV	- ∞	- ∞	- ∞
Both ch, -20 dBV (reverse phase), volume -10 dB	- ∞	- ∞	- ∞	- ∞	-5.5 dBV

L/C/R/RL/RC/RR signals are NEO:6 processed by CS49329 and C/RL/RC/RR signals are output through Sub DSP-DRAM. CS49329 is selected for the MAIN L/R output. The NEO:6 mode is fixed to Cinema 6ch.

When DD/dts input is used, the signal is decoded by YSS-938 and then L/R signal is NEO:6 processed by CS49329.

When AAC input is used, the signal is muted. When NEO:6 decoding is used, the LFE signal is not output.


NEO:6 (Auto)



8. SPEAKERS SET

The input signal is automatically identified in the order of dts → DOLBY DIGITAL → AAC → PCM → Analog.

There are seven sub-menu items as follows. The signals output from the DSP block are the same as 1. YSS938: YSS 0dB.



The analog switch settings for each sub-menu are as shown in the table below.

	Sub-menu	CENTER SP	REAR SP	MAIN SP	MAIN LEVEL	LFE/BASS
1	MAIN: SMALL 0dB	LARGE	LARGE	SMALL	0dB	SWFR
2	MAIN: LARGE -10dB	LARGE	LARGE	LARGE	-10dB	BOTH
3	CENTER: NONE	NONE	LARGE	LARGE	0dB	BOTH
4	LFE/BASS: MAIN	SMALL	SMALL	LARGE	0dB	MAIN
5	FRONT MIX: 5CH	LARGE	LARGE	LARGE	0dB	BOTH
6	REAR CENTER: MUTE	LARGE	LARGE	LARGE	0dB	BOTH
7	REAR L/R: MUTE	LARGE	LARGE	LARGE	0dB	BOTH

LARGE: This mode is used with a speaker with high bass reproduction performance (a large unit). Full bandwidth signals are output.

SMALL: This mode is used with a speaker with low bass reproduction performance (a small unit). The signals of 90Hz or less are mixed into the channel specified by LFE/BASS.

NONE: This mode is used with no center speaker. The center content is reduced by 3dB and distributed to MAIN L/R.

Reference data (PRE OUT)

INPUT: DVD ANALOG (Both ch)

VOLUME: -10 dB


	Sub-menu	Condition	MAIN L/R	CENTER	REAR C	SWFR	RL/RR
1	MAIN: SMALL 0dB	1kHz/90Hz, -20 dBV	-5.5/-8.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV
2	MAIN: LARGE -10dB	1kHz, -20 dBV	-15.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV
3	CENTER: NONE	1kHz, -20 dBV	-9.0 dBV	- ∞	-5.5 dBV	-2.5 dBV	-5.5 dBV
4	LFE/BASS: MAIN	50Hz, -20 dBV	-4.0 dBV	-8.5 dBV (90Hz)	-5.5 dBV	- ∞	-8.5 dBV (90Hz)
5	FRONT MIX: 5CH	1kHz, -20 dBV	-11.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	-5.5 dBV
6	REAR CENTER: MUTE	1kHz, -20 dBV	-5.5 dBV	-5.5 dBV	- ∞	-2.5 dBV	-5.5 dBV
7	REAR L/R: MUTE	1kHz, -20 dBV	-5.5 dBV	-5.5 dBV	-5.5 dBV	-2.5 dBV	- ∞

9. DISPLAY CHECK

This program is used to check the FL display section. The display condition varies as shown below according to the sub-menu operation. The signals are processed using EFFECT OFF (The L/R signal is output using ANALOG MAIN BYPASS.)

The video signal internal/external synchronization switching is controlled by the microprocessor. When the initial message is displayed and all the FL segments light up, it is switched to the internal synchronization but other than that it is forced to the external synchronization setting.

Also, except for the initial display, 128 pictographs for checking the OSD driver are used for the video signal output display.




Segment conditions of the FL driver and the FL tube are checked by turning ON and OFF all segments. Next, the operation of the FL driver is checked by using the dimmer control. Then a short between segments next to each other is checked by turning ON and OFF all segments alternately (in lattice). (In the above example, the segments in the second row from the top are shorted.)

10. MANUAL TEST

The noise generator with a built-in DSP outputs the test noise through the channels specified by the sub-menu.

The noise frequency for LFE is 35 to 250 Hz. Other than that, the center frequency is 800Hz.



11. RS-232C

This menu is unused.

12. FACTORY PRESET

This menu is used to reserve and inhibit initialization of the back-up RAM. The signals are processed using EFFECT OFF. (The L/R signal is output using ANALOG MAIN BYPASS.)

12 PRESET INHI



12 PRESET RSRV

PRESET INHIBIT (Initialization inhibited)

RAM initialization is not executed. Select this sub-menu to protect the values set by the user.

PRESET RESERVED (Initialization reserved)

Initialization of the back-up RAM is reserved. (Actually, initialization is executed the next time that the power is turned on.) Select this sub-menu to reset to the original factory settings or to reset the RAM.

CAUTION: Before setting to the PRESET RESERVED, write down the existing preset memory content of the Tuner in a table as shown below. (This is because setting to the PRESET RESERVED will cause the user memory content to be erased.)

Preset group	P1	P2	P3	P4	P5	P6	P7	P8
A								
B								
C								
D								
E								

• PRESET STATIONS

STATION		FM FACTORY PRESET DATA (MHz)	
PAGE	NO.	U, C	R, T, K, A, B, G
A/C/E	1	87.5	87.5
	2	90.1	90.1
	3	95.1	95.1
	4	98.1	98.1
	5	107.9	108.0
	6	88.1	88.1
	7	106.1	106.1
	8	107.9	108.0

STATION		AM FACTORY PRESET DATA (kHz)	
PAGE	NO.	U, C, R, T, K	A, B, G
B/D	1	630	630
	2	1080	1080
	3	1440	1440
	4	530	531
	5	1710	1611
	6	900	900
	7	1350	1350
	8	1400	1404

13. AD DATA CHECK/FAN TEST

This menu is used to display the A/D conversion value of the main CPU which detects panel keys of the main unit and protection functions in % using the sub-menu. (Reference voltage 5V as 100%) During signal processing, the condition before execution is maintained.

When K0/K1 menu is selected, keys become non-operable due to detection of the values of all keys. However, it is possible to advance to the next sub-menu by turning the VOLUME of the main unit. When using this function, note that turning the VOLUME more than 1 click would cause the volume value to change.

* The figures in the diagram are given as reference only.

DC/PS (protection detection)

DC:007 PS:025

DC: DC detect protection value (Normal value: 1 to 13)

PS: Power supply voltage protection value (Normal value: 21 to 31)

* If DC or PS is out of the normal value range, the protection function works to turn off the power.

THM/FAN OUT (temperature detection/fan drive level)

THM:086 Fan_/_

THM: 500% display of the voltage based on the temperature detected value. Reference voltage : 5V

(Normal value: U, C models 51 to 169

Others models 41 to 151)

Fan: Current fan drive level on the left and the past fan drive history on the right.

REC-OUT (Select position)

REC-OUT:186

This applies to the model equipped with the REC OUT selector.

[Table 1]

Display	REC OUT Select
0+2	CD-R
15+2	CBL/SAT
30+2	PHONO
44+2	V-AUX
60+2	MD/TAPE
76+2	D-TV/LD
92+2	PHONO
122+2	TUNER
137+2	VCR1
153+2	CD
170+2	VCR2/DVR
186+2	SOURCE
202+2	DVD

IMP SW/POWER LIMIT (Impedance/power limiter detection)

IMP:8 PL:009

IMP: 8 or 4 ohm impedance switch setting

PL: Power limiter detection value

K0/K1 (Panel key of main unit) [Remote control code: -]

K0:100 K1:100

A/D of the key fails to function properly when the standard value is deviated by $\pm 4\%$. In this case, check the constant of partial pressure resistor, solder condition, etc. Refer to table 2.

[Table 2]

Display	K0	K1
00+2	PRESET/TUNING ▷	—
10+2	◁ PRESET/TUNING	INPUT ▷
20+2	PRESET/TUNING	◁ INPUT
30+2	FM/AM	INPUT MODE
40+2	MEMORY	SPEAKERS A
50+2	TUNING MODE	SPEAKERS B
60+2	RDS MODE	EFFECT
70+2	RDS EON	PROGRAM ▷
80+2	PTY MODE	◁ PROGRAM
90+2	PTY START	A/B/C/D/E
100	KEY OFF	KEY OFF

FAN DRIVE TEST (For models so equipped)

FAN TEST:HIGH

HIGH

FAN DRIVE TEST (For models so equipped)

FAN TEST:MID

MID

FAN DRIVE TEST (For models so equipped)

FAN TEST:LOW


LOW

14. IF STATUS (Input function status)

Using the sub-menu, the status data is displayed one after another in the hexadecimal notation.
During signal processing, the status before execution of this menu is maintained.

* Numeric values in the figure example are for reference.

IS1-3 (Internal status) • Indicates the status information of the microprocessor.



<1st byte> Digital input/output setting value

Upper 4 bits: REC OUT selected/lower 4 bits: INPUT selected

Numeric value	Selection	Numeric value	Selection
0	NONE	4	OPT D (DVD)
1	OPT A (V-AUX)	6	OPT F (D-TV/LD)
2	OPT B (CD)	8	COAX A (CD)
3	OPT C (CD-R)	9	COAX B (CBL/SAT)

<2nd byte> Fs information of reproduction signal

Display	00	01	02	03	04	05	06	0A	0B	0C	0D
Fs (kHz)	Analog	32	44.1	48	64	88.2	96	Unknown NRM	Unknown DBL	Unknown QUAD	Not defined

<3rd byte> Audio code mode information of reproduction signal

Display	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D
Audio Code	MULTI MONO	1+1	1/0	2/0	3/0	2/1	3/1	2/2	3/2	2/3	3/3	OVER 6.1	MULTI PCE	Unknown

<4th byte> Format information of reproduction signal

*1: Analog processing used for digital reproduction is not possible
because of a commercial bit or 4-ch audio reason.

Display	Signal format
00	Analog (Unlock)
01	Incorrect digital (*1)
10	PCM Audio
20	Digital Data
21	IEC1937 Data
22	None PCM
23	Unknown
50	dtS
51	Red dtS
54	dtS-ES MATRIX
58	dtS-ES DISCRETE
5C	dtS-ES (Both flag)
60	AAC
C0	Dolby Digital
C1	D.D. Karaoke
C4	D.D.6.1 (D.D.EX)

<5th byte> Signal processing status information

*2: With digital signals other than 32kHz, 44.1kHz and 48kHz,
through processing method is used for reproducible signals.

bit7	MUTE request	bit3	—
bit6	Red dtS flashing	bit2	Through & bypass (*2)
bit5	6.1ch. field being processed	bit1	—
bit4	FULL MUTE (ON: 1)	bit0	dtS analog mute

CS1-5: Indicates channel status information of the input signal (IEC60958).

CS1:0299000200 - - - - - CS5:00000000

BY1-4: Indicates information of the bit stream included in the DOLBY DIGITAL signal.

BY1:1E40E1301B - - - - - BY4:01FFFFFF

BC1-4: Indicates information of the bit stream included in the dts signal.

BC1:000070FFFF - - - - - BC5:C4

YS1-3: Indicates device status information of YSS938 (IC514). * The numeric value in the figure is an example for reference.

YS1:FED2004F97

YS2:0101418000

YS3:1A41803D

Byte No.	Function
1	YSS MUTE Reg
2	YSS MODE Reg
3	YSS IPORT BIT 7-0
4	YSS IPORT BIT 14-8
5	YSS OPORT

Byte No.	Function
1	IEC 1937 Preamble Pc
2	Data Stream Reg
3	Status Reg
4	YSS ZERO Reg
5	MIREG

Byte No.	Function
1	DIR Status
2	DIR fs
3	DIR fs count
4	YSS ZEROBF

CS: CS49329 Unsolicited Messages (AUTODETECT_RESPONSE)

CS :000001

MTT: Mute Trigger

MTT:0020000007

Byte No.	Function
1	Mute condition
2	Factor of the last mute
3	Error count of YSS938-FSCNT
4	Mute count by YSS938-FSCNT
5	Error factor of down load of CS49329

15. DSP RAM CHECK

This menu is used to self-diagnose whether or not the bus connection for the YSS938 and the external RAM is made properly.

During signal processing, the status before execution of this menu is maintained.

The address bus and the data bus are checked and the connection condition is displayed.

When no error is detected, "NoEr" appears on display.

YSS938 Bus Check

YSS Bus:NoEr

Display	Description
WAIT	Bus is being checked.
NoEr	No error detected.
DATA	Data bus shorted or open.
RSCS	/RAS or /CAS shorted, or open.
ADDR	Address bus shorted or open.

PLD/SRAM BUS CHECK

CS Bus: NoEr

Display	Description
WAIT	Bus is being checked.
NoEr	No error detected.
DATA	Data bus shorted or open. (XX: 00-07)
ADDR	Address bus shorted or open. (XX: 00-0E)

16. CS DL CODE

This menu is used to display the data version, TOC information and sum calculated value of the flash ROM for CS49329.

ROM DATA VERSION: Displays the data version of the Flash ROM for CS49329.

RDV:X

TOC AREA 0-5: Displays the TOC information.

TA0:0502629A

TA5:FFFFFFFF

SUM CHECK AREA 0-5: Displays the sum calculated value.

SA0:984E984E

SA5:FFFFFFFF

17. SOFT SW

This menu is used to switch the function settings on P.C.B. through the software so as to activate the product.

The protection function follows the P.C.B. settings. When connected to AC or in the maker preset state, the unit is initialized to the P.C. B. setting. Display of each function after initialization varies depending on settings on P.C.B. The operation mode can be changed by selecting the sub-menu and then using the EFFECT key. With SOF selected for the SW mode, the settings become effective.

SW MODE: PCB or SOFT can be selected.

17. SW :PCB

MODEL SETTING: V1200, V2200, V3200 or AX3200 can be selected.

17. MODEL:V1200

TUNER DESTINATION: J, UC, ATKG or R can be selected.

17. DEST :UC

TUNER EXIST: NOT or EXIST can be selected.

17. TUNER:EXIST

RDS EXIST: NOT or EXIST can be selected.

17. RDS :NOT

ZONE 2 EXIST: NOT or EXIST can be selected.


17. ZONE2:NOT

VIDEO FORMAT: NTSC or PAL can be selected.

17. VIDEO:NTSC

18. MICROPROCESSOR INFORMATION

The version, checksum and the port specified by the microprocessor are displayed. The signal is processed using EFFECT OFF. The checksum is obtained by adding the data at every 16 bits for each program area and expressing the result as a 4-figure hexadecimal data.




*2 (Tuner mode)

Tuner mode 0	Tuner mode 1	Tuner frequency
0	0	AM: 531-1611kHz/9kHz FM: 76.0-90.0MHz/100kHz
0	1	AM: 531-1611kHz/9kHz FM: 87.5-108.0MHz/50kHz
1	0	AM: 530-1710kHz/10kHz FM: 87.5-107.9MHz/200kHz
1	1	R destination, Port6: LOW AM: 530-1710kHz/10kHz FM: 87.5-108.0MHz/100kHz HIGH AM: 531-1611kHz/9kHz FM: 87.5-108.0MHz/50kHz

AMP ADJUSTMENT


Confirmation of Idling Current of Main (1) P. C. B.

- Right after power is turned on, confirm that the voltage across the terminals of R64 (Main Lch), R65 (Main Rch), R61 (Center), R59 (Rear Lch), R60 (Rear Rch), R126 (Rear Cch) are between 0.1mV and 10.0mV.
- If it exceeds 10.0mV, open (cutoff) R39 (Main Lch), R40 (Main Rch), R37 (Center), R34 (Rear Lch), R35 (Rear Rch), R117 (Rear Cch) and reconfirm the voltage.
- Confirm that the voltage is 0.20mV ~ 15.0mV after 60 minutes.



■ DISPLAY DATA

● V901 : 16-BT-91GK (V7683200)






● PIN CONNECTION

Pin No.	65	64	63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33
Connection	F2	F2	NP	NP	P37	P36	P35	P34	P33	P32	P31	P30	P29	P28	P27	P26	P25	P24	P23	P22	P21	P20	P19	P18	P17	P16	P15	P14	P13	P12	P11	P10	P9

Pin No.	32	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
Connection	P8	P7	P6	P5	P4	P3	P2	P1	NC	NC	NC	NC	16G	15G	14G	13G	12G	11G	10G	9G	8G	7G	6G	5G	4G	3G	2G	1G	NP	NP	F1	F1

Note : 1) F1, F2 Filament 2) NP No pin 3) NC No connection (NC pin should be electrically open on the PC board.)
4) DL Datum Line 5) 1G ~ 16G Grid 6) Field of vision is a minimum of 29° from the lower side.

● GRID ASSIGNMENT




● ANODE CONNECTION

	16G	15G	14G	13G~2G	1G
P1	S2	S2	1-1	1-1	1-1
P2	<u>V-AUX</u>	<u>TUNER</u>	2-1	2-1	2-1
P3	<u>VCR2/DVR</u>	<u>CD</u>	3-1	3-1	3-1
P4	<u>VCR 1</u>	<u>PHONO</u>	4-1	4-1	4-1
P5	<u>CBL/SAT</u>	STEREO	5-1	5-1	5-1
P6	<u>D-TV/LD</u>	TUNED	1-2	1-2	1-2
P7	<u>DVD</u>	MEMORY	2-2	2-2	2-2
P8	<u>MD/TAPE</u>	AUTO	3-2	3-2	3-2
P9	<u>CD-R</u>	PS	4-2	4-2	4-2
P10	DTS	PTY	5-2	5-2	5-2
P11	Neo:6	RT	1-3	1-3	1-3
P12	DOLBY	CT	2-3	2-3	2-3
P13	DIGITAL	EON	3-3	3-3	3-3
P14	PRO LOGIC	PTY HOLD	4-3	4-3	4-3
P15	II	MUTE	5-3	5-3	5-3
P16	MOVIE THEATER	BASS	1-4	1-4	1-4
P17	1	P. DIRECT	2-4	2-4	2-4
P18	2	VOLUME	3-4	3-4	3-4
P19	ENTERTAINMENT	S1	4-4	4-4	4-4
P20	DSP	B1	5-4	5-4	5-4
P21	AAC	B2	1-5	1-5	1-5
P22	6.1/ES	B3	2-5	2-5	2-5
P23	PCM	B4	3-5	3-5	3-5
P24	dt	B5	4-5	4-5	4-5
P25	MATRIX	B6	5-5	5-5	5-5
P26	DISCRETE	B7	1-6	1-6	1-6
P27	DD DIGITAL	B8	2-6	2-6	2-6
P28	DD PRO LOGIC/II	B9	3-6	3-6	3-6
P29	96kHz/24Bit	DUAL	4-6	4-6	4-6
P30	VIRTUAL	LFE	5-6	5-6	5-6
P31	SILENT	L	1-7	1-7	1-7
P32		C	2-7	2-7	2-7
P33	SP	R	3-7	3-7	3-7
P34	A	RL	4-7	4-7	4-7
P35	B	RC	5-7	5-7	5-7
P36	—	RR	dB	—	T1
P37	—	SLEEP	mS	—	—

IC DATA

IC514 : YSS938-F
DSP

YSS938-F



IC514 : YSS938-F

Pin Description



No.	Name	I/O	Function
1	XO	O	Crystal oscillator connecting terminal
2	XI	I	Crystal oscillator connecting terminal (24.576MHz)
3	SEL1	I+	Built-in selector input 1 (AXD)
4	SEL0	I+	Built-in selector input 0 (GND)
5	SELOA	O+	Built-in selector output A (ISEL)
6	SELOB	O+	Built-in selector output B (RSEL)
7	TESTMS	I+	Test terminal (unconnected)
8	TESTXEN	I+	Test terminal (unconnected)
9	IPORT0	I+	General purpose input terminal (CXDTA)
10	IPORT1	I+	General purpose input terminal (CXDTB)
11	IPORT2	I+	General purpose input terminal
12	IPORT3	I+	General purpose input terminal
13	IPORT4	I+	General purpose input terminal
14	DDIN0	Is	DIR: Digital audio interface data input terminal 0 (ISEL)
15	DDIN1	Is	DIR: Digital audio interface data input terminal 1/General purpose input terminal (Pull down)
16	DDIN2	Is	DIR: Digital audio interface data input terminal 2/General purpose input terminal (Pull down)
17	DDIN3	Is	DIR: Digital audio interface data input terminal 3/General purpose input terminal (Pull down)
18	VSS		Ground terminal
19	CPO	A	PLL filter connecting terminal
20	AVDD		+3.3V power terminal (for DIR)
21	DIRPCO	A	DIR: PLL filter connecting terminal
22	DIRPRO	A	DIR: PLL filter connecting terminal
23	AVSS		Ground terminal (for DIR)
24	TESTBRK	I+	Test terminal (unconnected)
25	TESTR1	I+	PLL initialization signal input terminal for DSP (/ICD)
26	TESTR2	I+	Test terminal (unconnected)
27	VDD1		+3.3V power terminal (for terminal section)
28	SDWCKI0	I+	Word clock input terminal for SDIA, SDOA, SDIB, SDOB interface (Unconnected)
29	SDBCKI0	I+	Bit clock input terminal for SDIA, SDOA, SDIB, SDOB interface (Unconnected)
30	/SDBCK0	O	DIRBCK or SDBCKI0 invert clock output terminal (Unconnected)
31	IPORT8	I+	IPINT general purpose input terminal
32	IPORT9	I+	IPINT general purpose input terminal
33	IPORT10	I+	IPINT general purpose input terminal (NONPCM)
34	IPORT11	I+	IPINT general purpose input terminal (NONPCM)
35	SDIA	I	AC-3/DTS bit stream (or PCM) data input terminal to Main DSP (SDIA)
36	SDOA2	O	PCM output terminal from Main DSP (C/LFE output) (Unconnected)
37	SDOA1	O	PCM output terminal from Main DSP (LS/RS output) (Unconnected)
38	SDOA0	O	PCM output terminal from Main DSP (L/R output)
39	SDIB3	I+	PCM input terminal 3 to Sub DSP
40	SDIB2	I+	PCM input terminal 2 to Sub DSP
41	SDIB1	I+	PCM input terminal 1 to Sub DSP
42	SDIB0	I+	PCM input terminal 0 to Sub DSP
43	VSS		Ground terminal
44	VDD2		+2.5V power terminal (for internal circuit)
45	IPORT12	I+	IPINT general purpose input terminal (MUTE)
46	IPORT13	I+	IPINT general purpose input terminal (DIRINT)
47	IPORT14	I+	IPINT general purpose input terminal (Unconnected)
48	DIRSDO	O	AC-3/DTS bit stream (or PCM) data output terminal from DIR
49	DIRWCK	O	DIR: Serial data word clock (fs) output terminal (WCK)
50	DIRBCK	O	DIR: Serial data bit clock (64fs) output terminal (BCK)
51	DIRMCK	O	DIR: Serial data master clock (256fs or 128fs) output terminal (MCK)
52	ERR/BS	O	DIR: Data error detect output/block start output terminal (Unconnected)
53	SYNC/U	O	DIR: Serial data synchronous timing output/user data output terminal (Unconnected)
54	FS128/C	O	DIR: Serial data master clock 128fs output/channel status output terminal (Unconnected)
55	DBL/V	O	DIR: Double rate clock output/validity flag output terminal (DBL)

No.	Name	I/O	Function
56	SDWCKI1	I+	Word clock input terminal for SDIB, SDOB interface (Unconnected)
57	SDBCKI1	I+	Bit clock input terminal for SDIB, SDOB interface (Unconnected)
58	VSS		Ground terminal
59	SDOB3	O	PCM output terminal from Sub DSP
60	SDOB2	O	PCM output terminal from Sub DSP
61	SDOB1	O	PCM output terminal from Sub DSP
62	SDOB0	O	PCM output terminal from Sub DSP
63	VDD1		+3.3V power terminal (for terminal section)
64	ZEROBF3R	O+	SDOB3 Rch zero flag output terminal (ZF3R)
65	ZEROBF3L	O+	SDOB3 Lch zero flag output terminal (ZF3L)
66	ZEROBF2R	O+	SDOB2 Rch zero flag output terminal (ZF2R)
67	ZEROBF2L	O+	SDOB2 Lch zero flag output terminal (ZF2L)
68	OPORT0	O	General purpose output terminal (/RINH1)
69	OPORT1	O	General purpose output terminal (/RINH2)
70	OPORT2	O	General purpose output terminal (/ICCDC)
71	OPORT3	O	General purpose output terminal (DFS)
72	OPORT4	O	General purpose output terminal (ZSEL0)
73	OPORT5	O	General purpose output terminal (ZSEL1)
74	OPORT6	O	General purpose output terminal (/ICCS)
75	OPORT7	O	General purpose output terminal
76	VSS		Ground terminal
77	VDD2		+2.5V power terminal (for internal circuit)
78	RAMD0	I+/O	Sub DSP: External memory data terminal 0
79	RAMD1	I+/O	Sub DSP: External memory data terminal 1
80	RAMD2	I+/O	Sub DSP: External memory data terminal 2
81	RAMD3	I+/O	Sub DSP: External memory data terminal 3
82	ZEROBF1R	O+	SDOB1 Rch zero flag output terminal (ZF1R)
83	ZEROBF1L	O+	SDOB1 Lch zero flag output terminal (ZF1L)
84	ZEROBF0R	O+	SDOB0 Rch zero flag output terminal (ZF0R)
85	ZEROBF0L	O+	SDOB0 Lch zero flag output terminal (ZF0L)
86	RAMD4	I+/O	Sub DSP: External memory data terminal 4
87	RAMD5	I+/O	Sub DSP: External memory data terminal 5
88	RAMD6	I+/O	Sub DSP: External memory data terminal 6
89	RAMD7	I+/O	Sub DSP: External memory data terminal 7
90	VSS		Ground terminal
91	VDD1		+3.3V power terminal (for terminal section)
92	RAMD8	I+/O	Sub DSP: External memory data terminal 8
93	RAMD9	I+/O	Sub DSP: External memory data terminal 9
94	RAMD10	I+/O	Sub DSP: External memory data terminal 10
95	RAMD11	I+/O	Sub DSP: External memory data terminal 11
96	RAMD12	I+/O	Sub DSP: External memory data terminal 12
97	RAMD13	I+/O	Sub DSP: External memory data terminal 13
98	RAMD14	I+/O	Sub DSP: External memory data terminal 14
99	RAMD15	I+/O	Sub DSP: External memory data terminal 15
100	CASN	O	Sub DSP: Column address strobe output terminal for external DRAM
101	RAMWEN	O	Sub DSP: Write enable terminal for external memory
102	RAMOEN	O	Sub DSP: Output enable terminal for external memory
103	RASN	O	Sub DSP: Low address strobe output terminal for external DRAM
104	VSS		Ground terminal
105	VDD1		+3.3V power terminal (for terminal section)
106	RAMA8	O	Sub DSP: External memory address terminal 8
107	RAMA7	O	Sub DSP: External memory address terminal 7
108	RAMA0	O	Sub DSP: External memory address terminal 0
109	RAMA6	O	Sub DSP: External memory address terminal 6
110	RAMA1	O	Sub DSP: External memory address terminal 1

No.	Name	I/O	Function
111	RAMA5	O	Sub DSP: External memory address terminal 5
112	RAMA2	O	Sub DSP: External memory address terminal 2
113	SELI13	I+	Built-in selector input 13 (Unconnected)
114	SELI12	I+	Built-in selector input 12
115	SELI11	I+	Built-in selector input 11 (Unconnected)
116	SELI10	I+	Built-in selector input 10 (Unconnected)
117	SELI9	I+	Built-in selector input 9
118	RAMA4	O	Sub DSP: External memory address terminal 4
119	RAMA3	O	Sub DSP: External memory address terminal 3
120	RAMA9	O	Sub DSP: External memory address terminal 9 (Unconnected)
121	RAMA10	O	Sub DSP: External memory address terminal 10 (Unconnected)
122	RAMA11	O	Sub DSP: External memory address terminal 11 (Unconnected)
123	VSS		Ground terminal
124	VDD2		+2.5V power terminal (for internal circuit)
125	SELI8	I+	Built-in selector input 8 (CXA)
126	SELI7	I+	Built-in selector input 7 (GND)
127	SELI6	I+	Built-in selector input 6 (OPTF)
128	SELI5	I+	Built-in selector input 5 (Unconnected)
129	RAMA12	O	Sub DSP: External memory address terminal 12 (Unconnected)
130	RAMA13	O	Sub DSP: External memory address terminal 13 (Unconnected)
131	RAMA14	O	Sub DSP: External memory address terminal 14 (Unconnected)
132	RAMA15	O	Sub DSP: External memory address terminal 15 (Unconnected)
133	RAMA16	O	Sub DSP: External memory address terminal 16 (Unconnected)
134	RAMA17	O	Sub DSP: External memory address terminal 17 (Unconnected)
135	OVFB/END	O	Sub DSP: Overflow/program end detect terminal (Unconnected)
136	ZEROFLG	O	Main DSP: Zero flag output terminal (Unconnected)
137	VSS		Ground terminal
138	NONPCM	O	Main DSP: Non-PCM data detect terminal
139	DTSDATA	O	Main DSP: DTS data detect terminal (Unconnected)
140	AC3DATA	O	Main DSP: AC3 data detect terminal (Unconnected)
141	MUTE	O	Main DSP: Auto mute detect terminal
142	KARAOKE	O	Main DSP: AC3 KARAOKE data detect terminal (Unconnected)
143	VDD1	+3.3V	power terminal (for terminal section)
144	SURENC	O	Main DSP: AC-3 2/0 mode Dolby surround encode input detect terminal (Unconnected)
145	CRC	O	Main DSP: AC3 CRC error detect terminal (Unconnected)
146	/LOCK	O	DIR: PLL lock detect terminal (Unconnected)
147	DIRINT	O	DIR: Interrupt output terminal
148	/CS	Is	Microprocessor interface chip select input terminal (CSY)
149	SO	Ot	Microprocessor interface data output terminal
150	SI	Is	Microprocessor interface data input terminal (SDM)
151	SCK	Is	Microprocessor interface clock input terminal (SCKY)
152	/IC	Is	Initial clear input terminal (/ICD)
153	IPINT	O+	Interrupt output terminal by IPORT 8-14
154	SELI4	I+	Built-in selector input 4 (OPTD)
155	VSS		Ground terminal
156	SELI3	I+	Built-in selector input 3 (OPTC)
157	SELI2	I+	Built-in selector input 2 (OPTB)
158	TESTXI	I	Test terminal (should be always connected to VSS)
159	TESTXO	O	Test terminal (Unconnected)
160	VDD2	+2.5V	power terminal (for internal circuit)

Is: Schmidt trigger input terminal
I+: Input terminal with pull-up resistor
O: Digital output terminal
Ot: 3-state digital output terminal
A: Analog terminal

IC520 : M30802SGP
16bit μ -COM (Main CPU)




IC520 : M30802SGP

Pin Description

No.	Port No.	Function name	I/O	Detail of function	Power ON	Power OFF	Backup
1	P96	TXDR	SO	232C TX DATA / YDC TX DATA	O	OL	OL
2	P95	RTS	SCK	232C RTS / YDC CLOCK	I/O	OL	OL
3	P94	CTS	I	232C CTS	I	I	OL
4	P93	FAN	DA/O	FAN CONTROL	I	I	OL
5	P92	SDTN	SO	NON AUDIO TX DATA	SO	OL	OL
6	P91	RXRDS	SI	RDS RX DATA / FREQ SW (R VER)	SI	I	OL
7	P90	SCKN	SCK	NON AUDIO SERIAL CLOCK	SCK	OL	OL
8	P146		O		O	OL	OL
9	P145	CEBU	O/I (PU)	BU2092 CE / ZONE2 FUNCTION	I/O	I/OL	OL
10	P144	/FLR	O	FL IC RESET	O	OL	OL
11	P143	CEM0	I/O	FL1 CE / MODEL DETECT 0	I/O	I/OL	OL
12	P142	CEM1	I	MODEL DETECT 1	I	I	OL
13	P141	RDSE	O/I (PU)	RDS CE / RDS FUNCTION	I/O	I/OL	OL
14	P140	CES	O/I (PU)	OSD CE / NTSC / PAL FORMAT	I/O	I/OL	OL
15	BYTE	BYTE	VSS	16 BIT DATA BUS: Vss	Vss	Vss	Vss
16	CNVss	CNVss	VCC		Vcc	Vcc	Vcc
17	P87	BT232C	I (PU)	232C BOOT SIG. / 6CH INPUT KEY	I	I	OL
18	P86	BTYDC	I	YDC BOOT SIGNAL	I	I	OL
19	RESET	RESET	I	RESET	-	-	-
20	XOUT	XOUT	OPEN	CLOCK OUT	-	-	-
21	VSS	VSS	VSS	GROUND	-	-	-
22	XIN	XIN	12MHz	CLOCK IN	-	-	-
23	VCC	VCC	VCC	+5V	-	-	-
24	P85	NMI		Un-use	-	-	-
25	P84	REM1	INT (LoEdge)	REMOTE CONTROL PULSE	I	I	OL
26	P83	PSW	INT (LoEdge)	POWER SW	I	I	OL
27	P82	PDET	INT (LoEdge)	POWER DETECT	I	I	I
28	P81	VSX	Lo Edge	VERTICAL SYNC PULSE	I	I	OL
29	P80	/ICD	O	IC DSP IC	O	OL	OL
30	P77	RXDR	Double Edge	232C RX DATA	I	I	OL
31	P76	DMT	O	DIGITAL FULL MUTE	O	OL	OL
32	P75	INT938	Lo Edge	YSS938 IPINT	I	I	OL
33	P74	DMTR	O	DIGITAL FULL MUTE REAR L/R	O	OL	OL
34	P73	CEP	I/O	PLL IC CE / TUNER STEP 1	I/O	I/OL	OL
35	P72	SCKP	I/O	PLL IC CLOCK / TUNER STEP 0	I/O	I/OL	OL
36	P71	RDTP	ASI	PLL IC RX DATA	I	I	OL
37	P70	SDTP	I/ASO	PLL IC TX DATA (PU) / TUNER	I/O	OL	OL
38	P67	SDM	SO	DSP IC TX DATA	SO	OL	OL
39	VCC	VCC	VCC	+5V			
40	P66	SDD	SI	DSP IC RX DATA	SI	I	OL
41	VSS	VSS	VSS	GND			
42	P65	SCK	SCK	DSP IC CLOCK	SCK	OL	OL
43	P64	/CSY	I/O	YSS938 CE	I/O	OL	OL
44	P63	CTEV	O	EVOL TX DATA	SO	OL	OL
45	P62	CEEV	O	EVOL CE	O	OL	OL
46	P61	CKEV	SCK	EVOL CLOCK	SCK	OL	OL
47	P60	/CSCS	I/O	CS493X CS	I/O	OL	OL
48	P137	/CSPLD	O	DIGITAL EXT. CONTROL IC CE	O	OL	OL
49	P136	VRB	I	VOLUME ROTARY B	I	I	OL
50	P135	VRA	I	VOLUME ROTARY A	I	I	OL
51	P134	PRI	I	I PROTECTION	I	I	I
52	P57						HI
53	P56		OPEN				HI
54	P55		Vcc				HI
55	P54			OPEN			HI
56	P133	/BEC	O	BASS EXTENTION CONTROL	O	OL	OL
57	VSS	VSS	VSS	GND			
58	P132	/Z2MT	O	ZONE 2 MUTE	O	OL	OL
59	VCC	VCC	VCC	+5V			
60	P131	/HPMT	O	HEADPHONE MUTE	O	OL	OL
61	P130	/MATT	O	MAIN -3dB	O	OL	OL
62	P53		OPEN				HI
63	P52			OE			HI
64	P51						HI
65	P50			WE			HI
66	P127	/FMTS	O	FULL MUTE SWL / SWR / SW MONO	O	OL	OL
67	P126	/FMTC	O	FULL MUTE CENTER	O	OL	OL
68	P125	/FMTM	O	FULL MUTE MAIN L / R, RL / RC / RR	O	OL	OL
69	P47			EXT. ROM ADDRESS BUS			KEEP
70	P46		OPEN	EXT. ROM ADDRESS BUS			KEEP
71	P45		OPEN	EXT. ROM ADDRESS BUS			KEEP
72	P44		OPEN	EXT. ROM ADDRESS BUS			KEEP
73	P43		OPEN	EXT. ROM ADDRESS BUS			KEEP
74	VCC	VCC	VCC	+5V			
75	P42		OPEN	EXT. ROM ADDRESS BUS			KEEP

No.	Port No.	Function name	I/O	Detail of function	Power ON	Power OFF	Backup
76	VSS	VSS	VSS	GND			
77	P41	A17		EXT. ROM ADDRESS BUS			KEEP
78	P40	A16		EXT. ROM ADDRESS BUS			KEEP
79	P37	A15		EXT. ROM ADDRESS BUS			KEEP
80	P36	A14		EXT. ROM ADDRESS BUS			KEEP
81	P35	A13		EXT. ROM ADDRESS BUS			KEEP
82	P34	A12		EXT. ROM ADDRESS BUS			KEEP
83	P33	A11		EXT. ROM ADDRESS BUS			KEEP
84	P32	A10		EXT. ROM ADDRESS BUS			KEEP
85	P31	A9		EXT. ROM ADDRESS BUS			KEEP
86	P124	SCKA	SCK	AUDIO IC CLOCK	O	OL	OL
87	P123	SDTA	SO	AUDIO IC TX DATA	O	OL	OL
88	P122	CEL	O	SANYO IC CE	O	OL	OL
89	P121	RIMA	O	POWER LIMITER A	O	OL	OL
90	P120	RIMB	O	POWER LIMITER B	O	OL	OL
91	VCC	VCC	VCC	+5V			
92	P30	A8		EXT. ROM ADDRESS BUS			KEEP
93	VSS	VSS	VSS	GND			
94	P27	A7		EXT. ROM ADDRESS BUS			KEEP
95	P26	A6		EXT. ROM ADDRESS BUS			KEEP
96	P25	A5		EXT. ROM ADDRESS BUS			KEEP
97	P24	A4		EXT. ROM ADDRESS BUS			KEEP
98	P23	A3		EXT. ROM ADDRESS BUS			KEEP
99	P22	A2		EXT. ROM ADDRESS BUS			KEEP
100	P21	A1		EXT. ROM ADDRESS BUS			KEEP
101	P20	A0		EXT. ROM ADDRESS BUS			KEEP
102	P17	D15		EXT. ROM DATA BUS			KEEP
103	P16	D14		EXT. ROM DATA BUS			KEEP
104	P15	D13		EXT. ROM DATA BUS			KEEP
105	P14	D12		EXT. ROM DATA BUS			KEEP
106	P13	D11		EXT. ROM DATA BUS			KEEP
107	P12	D10		EXT. ROM DATA BUS			KEEP
108	P11	D9		EXT. ROM DATA BUS			KEEP
109	P10	D8		EXT. ROM DATA BUS			KEEP
110	P07	D7		EXT. ROM DATA BUS			KEEP
111	P06	D6		EXT. ROM DATA BUS			KEEP
112	P05	D5		EXT. ROM DATA BUS			KEEP
113	P04	D4		EXT. ROM DATA BUS			KEEP
114	P114	/MLV	O	MAIN LEVEL	O	OL	OL
115	P113	PRY	O	POWER RELAY	O	OL	OL
116	P112	SPE	O	SP RELAY EFFECT	O	OL	OL
117	P111	SPB	O	SP RELAY B	O	OL	OL
118	P110	SPA	O	SP RELAY A	O	OL	OL
119	P03	D3		EXT. ROM DATA BUS			KEEP
120	P02	D2		EXT. ROM DATA BUS			KEEP
121	P01	D1		EXT. ROM DATA BUS			KEEP
122	P00	D0		EXT. ROM DATA BUS			KEEP
123	P157	DCTRG	O	DC TRIGGER CONTROL	O	OL	OL
124	P156	CSINT	I(IPU)/O	CS-DSP INT / ABOOT	I/O	OL	OL
125	P155	BSW	I(IPU)	BASS EXT SW	I	I	OL
126	P154	PSW	I(IPU)	PR. DIRECT SW	I	I	OL
127	P153	/HP	I(IPU)	HEADPHONE DETECT	I	I	OL
128	P152	TMT	O	TUNER MUTE	O	OL	OL
129	P151	/TUNED	I(IPU)	TUNING METER	I	I	OL
130	VSS	VSS	VSS	GND			
131	P150	/ST	I(IPU)	TUNER STEREO	I	I	OL
132	VCC	VCC	VCC	+5V			
133	P107	RMV	AD	Un-use (DETECT PL TYPE)	I	I	I
134	P106	REC	AD	REC OUT SELECTOR	I	I	I
135	P105	PREMT	AD	POWER LIMITER DETECT	I	I	I
136	P104	ADKEY1	AD	KEY SW LINE 1	I	I	I
137	P103	ADKEY0	AD	KEY SW LINE 0	I	I	I
138	P102	THM	AD	TEMPERATURE DETECTION	I	I	I
139	P101	PRD	AD	DC PROTECTION	I	I	I
140	AVSS	AVSS	VSS	AD GND	VSS	VSS	VSS
141	P100	PRV	AD	PS PROTECTION	I	I	I
142	VREF	VREF	VCC	AD REFERENCE	VCC	VCC	VCC
143	AVCC	AVCC	VCC	AD V	VCC	VCC	VCC
144	P97	RXDR	SI	232C / YDC RX DATA	I	I	OL

1 ■ BLOCK DIAGRAM (2/2)



PRINTED CIRCUIT BOARD (Foil side)


FUNCTION P. C. B. (Lead Type Device)

Circuit No.	RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200					RX-V2200/DSP-AX2200			
	J	U, C	R, T, K	A	BG	J	U, C	R, T	A
C508, 509, 517, 518, 521, 522, 625, 626	X	X	X	X	X	X	X	X	X
C533	X	X	X	X	X	X	X	X	X
C603, 604	X	X	X	X	X	X	X	X	X
C679, 692	X	X	X	X	X	X	X	X	X
D517, 518	X	X	X	X	X	X	X	X	X
IC504, 505, 508	X	X	X	X	X	X	X	X	X
J503, 504	X	X	X	X	X	X	X	X	X

X: NOT USED
O: USED / APPLICABLE

Semiconductor Location

Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location
D501	B3	D508	C3	D518	C4	IC502	G3	IC513	E4
D503	B3	D509	C3	D519	D4	IC503	H3	IC514	E4
D504	B3	D510	C3	D521	D4	IC504	F3	IC515	E4
D505	B3	D511	C3	D523	E3	IC505	H3	IC516	D3
D506	C3	D512	C3	D525	D3	IC506	H5	IC517	D4
D507	D5	D517	C4	IC501	H4	IC507	H5	IC518	D4
						IC508	F4	IC519	D4
						IC509	F5	IC520	B4
						IC510	E5	IC521	E5
						IC511	F5	IC522	C3
						IC512	A4	IC523	D5
								IC524	D5
								IC525	D5



Semiconductor Location

Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location
Q501	G5	Q513	A5	Q524	B4	Q535	C4
Q502	G5	Q514	B5	Q525	C4	Q536	C4
Q503	G5	Q515	B5	Q526	D4	Q537	A5
Q504	G5	Q516	B5	Q527	B5	Q538	B5
Q505	G5	Q517	B5	Q528	B5	Q539	B5
Q506	G5	Q518	C5	Q529	B5	Q540	B5
Q507	A5	Q519	C5	Q530	B5	Q541	B5
Q508	A4	Q520	B4	Q531	B5	Q542	C5
Q510	D4	Q521	B4	Q532	C5	Q543	C5
Q511	C3	Q522	B4	Q533	A5	Q544	C3
Q512	C3	Q523	B4	Q534	B5		

Circuit No.	RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200					RX-V2200/DSP-AX2200			
	J	U, C	R, T, K	A	BG	J	U, C	R, T	A
Q501, 502, 507, 508, 535, 536	X	X	X	X	X	X	X	X	X
Q544	X	X	X	X	X	X	X	X	X
R552, 553	X	X	X	X	X	X	X	X	X
R573, 574, 577, 578, 601, 623, 665	X	X	X	X	X	X	X	X	X
R810	X	X	X	X	X	X	X	X	X
R819	X	X	X	X	X	X	X	X	X


X: NOT USED
O: USED / APPLICABLE

1

PRINTED CIRCUIT BOARD (Foil side)

2

FUNCTION P. C. B. (Surface Mount Device)



Circuit No.	RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200					RX-V2200/DSP-AX2200				
	J	U, C	R, T, K	A	BG	J	U, C	R, T	A	
C666, 671, 676, 678	X	O	X	O	O	X	O	X	O	
J501, 502	O	O	O	O	O	X	X	X	X	
J503, 504	X	O	X	O	X	X	X	X	X	
R543, 544	X	X	X	X	X	O	O	O	O	
R563, 564	X	X	X	X	X	X	O	O	O	
R565, 566	X	X	X	X	X	O	O	O	O	
R567, 662	X	X	O	X	X	X	X	O	X	
R594, 665, 763, 809	X	O	X	O	X	X	O	O	O	
R671	O	O	O	O	O	X	X	X	X	
R672	O	X	O	X	O	X	X	X	X	
R805	X	X	X	X	X	X	O	O	O	


X: NOT USED
O: USED / APPLICABLE

• Semiconductor Location


Ref. No.	Location
D502	A4
D513	B4
D514	D4
D515	D4
D520	D4
D522	E4
D524	E3
D526	E3
D531	C4
D532	C4
Q509	A4
Q547	G5
Q548	G5

PRINTED CIRCUIT BOARD (Foil side)


OPERATION (1) P. C. B. (Lead Type Device)



OPERATION (3) P. C. B. (Lead Type Device)



OPERATION (2) P. C. B. (Lead Type Device)



Semiconductor Location

Ref. No.	Location
D901	I2
D902	I3
IC901	F3
Q901	F2
Q902	F2
Q905	G2
Q906	G2
Q907	G2
Q908	G2
Q909	G2
Q910	G2

Circuit No.	RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200	RX-V2200/DSP-AX2200
	J, R, T, K U, C, A B, G J U, C, A, R, T	
D902	X O X X O	
R908	X O X X O	
R941~944	X X O X X	
SW941~944	X X O X X	

X: NOT USED
O: USED / APPLICABLE

Ref. No.	Location
D501	G5
D502	G5
D503	G5
D504	G4
D505	G4
D506	G5
D507	G4
D516	G4
D517	F4
D518	F4
D519	D6
D520	D6
D521	D6
D522	D6
D523	D6
D524	D6
D525	D6
D526	D6
D527	D7
D528	D7
D529	D7
D530	D7
D531	B4
D532	B4
D533	C4
D534	B4
D537	D7
D538	D7
IC509	C4
IC518	C5
IC519	C5
IC520	C5
IC521	C6
IC522	C6
IC523	C7
Q501	D6
Q502	D6
Q503	D6
Q504	D6
Q505	D7
Q506	D7
Q507	B4
Q508	B5
Q509	B4
Q510	C6
Q511	C6
Q512	C6
Q513	C6
Q514	C7
Q515	C7
Q516	B5
Q517	B5

E-60/J-54

From VIDEO (5)

COMPONENT VIDEO

R683	X	O	O	O	X
R684	O	X	X	X	X
SW551	X	X	O	X	X
XL581	X	X	X	X	O

X: NOT USED
O: USED / APPLICABLE

From VIDEO (5)

From VIDEO (8)


X: NOT USED
O: USED / APPLICABLE

■ RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200 PRINTED CIRCUIT BOARD (Foil side)


VIDEO (5) P. C. B. (Lead Type Device)

Circuit No.	J	U, C	R, T, K	A	B, G
C581, 591-595, 596-599	X	X	X	X	O
IC581	X	X	X	X	O
L581	X	X	X	X	O
R561, 562, 567, 568, 577, 578, 859	X	O	X	O	X
R583	X	O	O	X	X
R584	O	X	X	O	O
R585	X	X	X	O	O
R586	O	O	X	X	X
R591, 593-598	X	X	X	X	O
R681	X	X	X	O	O
R682	O	O	O	X	X
R683	X	O	O	O	X
R684	O	X	X	X	O
SW551	X	X	O	X	X
XL581	X	X	X	X	O

X: NOT USED
O: USED / APPLICABLE



VIDEO (5) P. C. B. (Surface Mount Device)



• Semiconductor Location




Ref. No.	Location
D581	J5
IC581	D5
Q581	D3
Q582	E6

■ RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200 PRINTED CIRCUIT BOARD (Foil side)


VIDEO (6) P. C. B. (Lead Type Device)

VIDEO (6) P. C. B. (Surface Mount Device)

VIDEO (7) P. C. B. (Lead Type Device)



VIDEO (8) P. C. B. (Lead Type Device)



Circuit No.	J	U.C	R, T, K	A	B, G
C581, 591-595, 596-599	X	X	X	X	O
IC581	X	X	X	X	O
L581	X	X	X	X	O
R561, 562, 567, 568, 577, 578, 859	X	O	X	O	X
R583	X	O	O	X	X
R584	O	X	X	O	O
R585	X	X	O	O	O
R586	O	O	X	X	X
R591, 593-598	X	X	X	X	O
R681	X	X	X	O	O
R682	O	O	O	X	X
R683	X	O	O	O	X
R684	O	X	X	X	O
SW551	X	X	O	X	X
XL581	X	X	X	X	O

X: NOT USED
O: USED / APPLICABLE

■ RX-V2200/DSP-AX2200 PRINTED CIRCUIT BOARD (Foil side)


Circuit No.	J	U, C	R, T	A
IC606	X	O	O	O
J741, 742	O	X	X	X
Q609	O	X	X	X
R674, 683	X	O	O	O
R675, 684	O	X	X	X
R681	X	X	X	O
R682	O	O	O	X

X: NOT USED
O: USED / APPLICABLE


- **Semiconductor Location**

Ref. No.	Location	Ref. No.	Location
D601	G4	IC606	C5
D602	G4	IC607	B4
D603	G5	IC608	G4
D604	G5	IC609	H6
D605	G5	IC610	B6
D606	F5	IC611	B6
D607	G4	Q601	D6
D608	G4	Q602	D6
D609	G4	Q603	B5
D610	G4	Q604	D6
IC601	H4	Q605	B6
IC602	C4	Q606	B5
IC603	D4	Q607	A5
IC604	C5	Q608	B5
IC605	D5	Q609	B5

VIDEO (1) P. C. B.	(Lead Type Device)
---------------------------	--------------------




VIDEO (1) P. C. B.	(Surface Mount Device)
---------------------------	------------------------



- **Semiconductor Location**


VIDEO (4) P. C. B.	(Lead Type Device)
---------------------------	--------------------

X: NOT USED
O: USED / APPLICABLE



From VIDEO (8)

VIDEO (4) P. C. B.	(Surface Mount Device)
---------------------------	------------------------





E-73/J-67

1

■ RX-V2200/DSP-AX2200 PRINTED CIRCUIT BOARD (Foil side)

VIDEO (5) P. C. B. (Lead Type Device)






1 ■ RX-V2200/DSP-AX2200 PRINTED CIRCUIT BOARD (Foil side)


VIDEO (6) P. C. B. (Lead Type Device)

VIDEO (6) P. C. B. (Surface Mount Device)

VIDEO (7) P. C. B. (Lead Type Device)



VIDEO (8) P. C. B. (Lead Type Device)



Circuit No.	J	U.C	R,T	A
C567, 568	X	O	O	O
R561, 562, 577, 578	X	O	O	O
SW551	X	X	O	X


X: NOT USED
O: USED / APPLICABLE

PRINTED CIRCUIT BOARD (Foil side)

MAIN (1) P. C. B. (Lead Type Device)


Semiconductor Location

Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location
D1	H6	D8	H3	D16	B5	Q5	E2	Q12	H3	Q19A	F2	Q25C	B2	Q33	B3
D2	G3	D9	I3	D18	B6	Q6	I5	Q13	E3	Q19C	G2	Q27A	C2	Q34	D3
D3	H3	D10	F3	D22	A4	Q7	B2	Q14	E3	Q21A	H2	Q27C	D2	Q35	A5
D4	I6	D11	B3	Q1	I5	Q8	D2	Q15	B3	Q21C	I2	Q29	B5	Q37	H5
D5	E3	D12	D3	Q2	I6	Q9	G3	Q16	A3	Q23A	E2	Q30	H3	Q40	B5
D6	A4	D13	A4	Q3	G2	Q10	F3	Q17	C3	Q23C	F2	Q31	I5	Q43	B5
D7	C3	D14	A4	Q4	H2	Q11	I3	Q18	C3	Q25A	B2	Q32	F3		



Circuit No.	RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200	RX-V2200/DSP-AX2200
C38, 47, 89, 90	X	X
C57, 61, 64-66, 68	X	X
C75-82	X	X
D18	X	X
Q40, 43	X	X
R122, 123, R127-129, 132, 189	X	X
SW1	X	X
W11-14	X	X

X: NOT USED
O: USED / APPLICABLE






PRINTED CIRCUIT BOARD (Foil side)

MAIN (2) P. C. B. (Lead Type Device)

MAIN (3) P. C. B. (Lead Type Device)

MAIN (4) P. C. B. (Lead Type Device)



Semiconductor Location

Ref. No.	Location
D15	B2
D21	B3
D23	H5
D24	H5
D27	H4
D28	H4
D31	H4
D32	H4
D33	H4
D34	H4
D36	F2
D38	E4
D39	E4
D40	E4
D41	E4
IC1	C2
Q36	C3
Q38	C3
Q39	B2
Q40, 43	
Q41A	C2
Q41C	C3
Q44	B3
Q47	H3

Circuit No.	RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200	RX-V2200/DSP-AX2200
	J U C R T K A B G	J U C R T A
C38, 47, 89, 90	X X	O O O
C57, 61, 64-66, 68	X X	X X O
C75-82,		
D18	X X	O O O O
Q40, 43	X X	O O O O
R122, 123,	X X	O O O O
R127-129, 132, 189		
SW1	X O	X O O
W11-14	X O	X O O

X: NOT USED
O: USED / APPLICABLE

1 ■ PRINTED CIRCUIT BOARD (Foil side)

Circuit No.	RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200							RX-V2200/DSP-AX2200						
	J	U	C	R, T, K	A	B	G	J	U	C	R, T	A		
C242	X	O	O	O	O	O	O	X	O	O	O	O	O	
CB209, 210	X	X	X	O	X	X	X	X	X	X	O	X		
CB216	X	X	X	O	O	O	O	O	O	O	O	O		
D213	X	O	O	O	O	O	O	X	O	O	O	O		
F203	X	X	X	O	X	X	X	X	X	X	O	X		
Q206	X	O	O	O	O	O	O	X	O	O	O	O		
R228, 229	X	O	O	O	O	O	O	X	O	O	O	O		
SW202	X	X	X	O	X	X	X	X	X	X	O	X		
W221-226	X	X	X	O	X	X	X	X	X	X	O	X		
W247, 248	X	O	O	X	X	X	X	O	O	O	X	X		


X: NOT USED
O: USED / APPLICABLE

• Semiconductor Location


Ref. No.	Location
D211	D3
D212	C3
D213	C3
D214	D3
D215	C3
D216	C6
D217	C6
Q205	C3
Q206	C3
Q207	C6
Q208	C6
Q209	C5
Q210	C5
Q211	C4
Q212	C4
Q213	C3
Q214	D6
Q215	C6
Q216	D6
Q217	C6
Q218	D5
Q219	C5
Q220	D5
Q221	C5
Q222	D4
Q223	C4
Q224	D4
Q225	C4

2 POWER (4) P. C. B. (Lead Type Device)

POWER (5) P. C. B. (Lead Type Device)




From Power Transformer




1 ■ PRINTED CIRCUIT BOARD (Foil side)


2 POWER (7) P. C. B. (Lead Type Device)



3 POWER (8) P. C. B. (Lead Type Device)



4 POWER (10) P. C. B. (Lead Type Device)



• Semiconductor Location




























Ref. No.	Location
D851	G4
IC201	D6
IC202	D6
IC203	D5
IC204	D5
IC205	D6
IC206	D7

Circuit No.	RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200							RX-V2200/DSP-AX2200					
	J	U	C	R, T, K	A	B	G	J	U	C	R, T	A	
C852	X	O	O	X	O	X	X	X	O	O	O	O	
D851	X	O	O	X	O	X	X	X	O	O	O	O	
JK851-853	X	O	O	X	O	X	X	X	O	O	O	O	
W221-226	X	X	X	O	X	X	X	X	X	X	O	X	
W247, 248	X	O	O	X	X	X	X	O	O	O	X	X	

X: NOT USED
O: USED / APPLICABLE





PIN CONNECTION DIAGRAM

• ICs






LM61CIZ  3: +Vs 2: Vout 1: GND	NJM7805FA NJM78M05FA NJM78M12FA  3: IN 2: COM 1: OUT	NJM79M05FA NJM79M12FA  3: COM 2: IN 1: OUT	μPC29M33T-E1  3: IN 2: COM 1: OUT	PQ025EZ5MZP  1 5 1 5 1
NJM2068MD NJM2904M OPA2652U TK15420M μPC4570G2  8 1 4	NJM2068LD NJM4556AL  1 8	TC4066BP  14 1 7	TC74HCT00AF TC74HCT08AF TC74HCU04AF  14 1 7	
LA7108M  16 1 8	MM74HC4051N MM74HC4051SJX MM74HC4053N MM74HC4053SJX TC74HC4051AFEL TC74HC4052AF  16 1 8	TC74HC4051AP TC74HC4053AP  16 1 8	BU2092  18 1 9	YAC520-EE2  20 1 10
LC72722  24 1 12	LC74781-9798  24 1 12	AK4393-VF-E2 CY62256LL  28 1 14	LC78211 LC78213  30 1 15	LC78212  30 1 15
LA7109  36 1 18	MSM514260C-60JS  40 1 20	AK4527BVQ  33 23 34 22 44 12 11 1	MBM29F400BC-70  25 24 48 1	
LC75712E  48 33 49 32 64 17 16 1	XC9572XL-10TQ100C  75 51 76 50 100 26 25 1	M30802SGP  108 73 109 72 144 37 36 1	YSS938F  120 81 121 80 160 41 40 1	

RX-V1200/RX-V1200RDS/
HTR-5490/RX-V2200

• Diodes



1SR139 1SS133 1SS270A 1T2 HZS7B2TD	MTZJ4.7C MTZJ9.1A MTZJ11.0B MTZJ12.0A MTZJ12.0C MTZJ15.0B MTZJ20.0A MTZJ24.0C MTZJ33.0B		1SS355 1SS380 MA8051-M MA8056-L MA8056-M MA8062-H RB501V-40 UDZS5.6BTE-17	
D2SBA20	S5VB20			

• Transistors

2SA893A 2SA970 2SA1015 2SB949 2SC535 2SC1815 2SC1890A 2SC2240 2SC2878		2SA933S 2SC1740S 2SD1915F 2SD1991A DTA144ES DTC114ES DTC144ES		2SB941 2SB1565 2SD2396		2SA1492 2SA1695 2SC3856 2SC4468	
2SA1037K 2SC3326 DTA144EKA DTC144EKA		2SA1708 2SA1770 2SC4488 2SC4614		2SK246			


SCHEMATIC DIAGRAM (RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200 FUNCTION)

RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200/RX-V2200/DSP-AX2200




IC	Part No.	U-C	U-T-X	A	B-D	Comments
1	C501-004	X	X	200P/100V	200P/100V	
2	R504-505	47	RC04047	RC04047	RC04047	
3	R502	X	X	100K	100K	
4	R507	X	X	47	RC04047	
5	Q535	X	A170815/1	A170815/1	X	
6	Q536	X	DTC144EKA	DTC144EKA	X	
7	Q517-518	X	Y100070	Y100070	X	
8	Q519	X	Y133002	Y133002	X	
9	R509	X	RC04047	RC04047	X	
10	R510	X	RC04047	RC04047	X	
11	Q509	MAM000-H	MAM000-H	MAM000-H	MAM000-H	
12	Q510	MAM000-H	MAM000-H	MAM000-H	MAM000-H	
13	R505	X	100K	RC04047	RC04047	
14	R506	X	100K	RC04047	RC04047	
15	R503-504	X	0	RC04047	RC04047	
16	R507, R508, R509	X	RC04047	RC04047	X	
17	R507, R508, R509	X	RC04047	RC04047	X	
18	R504	X	RC04047	RC04047	X	
19	R501	X	RC04047	RC04047	X	
20	R502	X	RC04047	RC04047	X	
21	Q507, Q508, Q509	X	C3301A/B/1	C3301A/B/1	X	
22	Q510	X	C3301A/B/1	C3301A/B/1	X	
23	Q511	X	C3301A/B/1	C3301A/B/1	X	
24	Q512	X	C3301A/B/1	C3301A/B/1	X	
25	Q513	X	C3301A/B/1	C3301A/B/1	X	
26	Q514	X	C3301A/B/1	C3301A/B/1	X	
27	Q515	X	C3301A/B/1	C3301A/B/1	X	
28	Q516	X	C3301A/B/1	C3301A/B/1	X	
29	Q517	X	C3301A/B/1	C3301A/B/1	X	
30	Q518	X	C3301A/B/1	C3301A/B/1	X	


IC501: NJM2068MD
IC506, 507: 511, 513-515: μPC4570G2
IC521, IC523-IC525: μPC4570G2
Dual OP-Amp




IC502: LC78212
Analog Function Switch




IC510: LC78213
Analog Function Switch




IC516-519: YAC520-EE2
Stereo Digital Volume Controller




IC503, 509: LC78211
Analog Function Switch



IC512: MBM29F400BC-70
4Mbit Flash Memory



IC522: NJM78M05FA
Voltage Regulator



NOTICE (model)




Model	Reference Price Number	Price
1	511	511
2	512	512
3	513	513
4	514	514
5	515	515

REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
NO MARK	TANTALUM CAPACITOR
NO MARK	CERAMIC TUBULAR CAPACITOR
NO MARK	POLYESTER FILM CAPACITOR
NO MARK	POLYPROPYLENE FILM CAPACITOR
NO MARK	POLYBUTYLENE FILM CAPACITOR
NO MARK	POLYETHYLENE SULFIDE FILM CAPACITOR







REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
NO MARK	CARBON FILM RESISTOR (P=10)
NO MARK	METAL OXIDE FILM RESISTOR
NO MARK	METAL FILM RESISTOR
NO MARK	METAL PLATE RESISTOR
NO MARK	FIRE PROOF CARBON FILM RESISTOR
NO MARK	CEMENT HOLOID RESISTOR
NO MARK	SEMI VARIABLE RESISTOR
NO MARK	CHIP RESISTOR

- All voltages are measured with a 10M Ω DC electric volt meter.
- Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
- Schematic diagram is subject to change without notice.
- 電圧は、内部抵抗10M Ω の電圧計で測定したものです。
- Δ 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
- 本回路図は標準回路図です。改良のため予告なく変更することがございます。

RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200/RX-V2200/DSP-AX2200
■ SCHEMATIC DIAGRAM (RX-V2200/DSP-AX2200 FUNCTION)



IC	Pin	Symbol	Value	Notes
IC501	1	OUT1	1	
IC501	2	-IN	2	
IC501	3	-IN	3	
IC501	4	-Vcc	4	
IC501	5	+IN	5	
IC501	6	OUT2	6	
IC501	7	+Vcc	7	




REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
NO MARK	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
NO MARK	CERAMIC TUBULAR CAPACITOR
NO MARK	POLYESTER FILM CAPACITOR
NO MARK	POLYPROPYLENE FILM CAPACITOR
NO MARK	MICA CAPACITOR
NO MARK	METAL FILM RESISTOR
NO MARK	METAL PLATE RESISTOR
NO MARK	FILM PROOF CARBON FILM RESISTOR
NO MARK	CERAMIC HOLED RESISTOR
NO MARK	SEMI VARIABLE RESISTOR
NO MARK	POLYPHENYLENE SULFIDE FILM CAPACITOR

★ All voltages are measured with a 10M Ω DC electric volt meter.
★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.


● 電圧は、内部抵抗10M Ω の電圧計で測定したものです。
● Δ 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

1	
2	
3	
4	
5	
6	
7	
8	
9	
























- 電圧は、内部抵抗10MΩの電圧計で測定したものです。
- ㊦印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
- 本回路図は標準回路図です。改良のため予告なく変更することがございます。

RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200/RX-V2200/DSP-AX2200



Mark	Reference Parts Number	Parts Name
41	1C702	TC74HC0514PDL MM74HC0515X
42	1C602, 603	TC74HC0514P MM74HC051N
43	1C607	TC74HC053AP MM74HC053N


- 電圧は、内部抵抗10MΩの電圧計で測定したものです。
- △印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
- 本回路図は標準回路図です。改良のため予告なく変更することがございます。



REMARKS		CAPACITOR		NOTICE [mode1]
REMARKS	PARTS NAME	REMARKS	PARTS NAME	
NO MAIN	NO MAIN	NO MAIN	ELECTROLYTIC CAPACITOR	{ } --- JAPAN
① CARBON FILM RESISTOR (PWR)		① TANTALUM CAPACITOR		{ } --- U.S.
② CARBON FILM RESISTOR (IMP10)		② NO MAIN		{ } --- U.S.
③ METAL PASTE FILM RESISTOR		③ CERAMIC TUBULAR CAPACITOR		{ } --- JAPAN
④ METAL FILM RESISTOR		④ CERAMIC DISC CAPACITOR		{ } --- GENERAL
⑤ PASTE RESISTOR		⑤ POLYESTER FILM CAPACITOR		{ } --- JAPAN
⑥ FILM PAPER CARBON FILM RESISTOR		⑥ POLYSTYRENE FILM CAPACITOR		{ } --- BRITISH
⑦ METAL PASTE RESISTOR		⑦ POLYPROPYLENE FILM CAPACITOR		{ } --- JAPAN
⑧ SEMI-CONDUCTIVE RESISTOR		⑧ POLYPROPYLENE FILM CAPACITOR		{ } --- CHINA
⑨ CHIP RESISTOR		⑨ SEMICONDUCTIVE CERAMIC CAPACITOR		{ } --- KOREA

- ★ All voltages are measured with a 10M Ω DC electric voltmeter.
- ★ Components having special characteristics are marked  and must be replaced with parts having specifications equal to those originally installed.
- ★ Schematic diagram is subject to change without notice.

- 電圧印、内部抵抗10M Ω の電圧計で測定したものです。
- 印のある部品は、安全性確保部品をとしています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
- 本回路図は標準回路図です。改良のため予告なく変更することがございます。



Production of the parts marked with "x" has been discontinued starting with November production of 2001.

×マークの付いた部品は、2001年11月生産分より廃止されています。

x: NOT USED
Q: USED / APPLICABLE

SCHEMATIC DIAGRAM (MAIN)

The voltage value before or above parentheses [] is applicable to RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200 and the value in the parentheses is applicable to RX-V2200/DSP-AX2200. Also, the voltage value without parentheses is commonly applicable to all models.

[] 外の電圧値はRX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200の値を表し、
[] 内の電圧値はRX-V2200/DSP-AX2200の値を表します。また、[] が付いていない電圧値は全モデルに共通の値です。

RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200/RX-V2200/DSP-AX2200

REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
⊗	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
⊙	CERAMIC TUBULAR CAPACITOR
⊖	POLYESTER FILM CAPACITOR
○	POLYETHYLENE FILM CAPACITOR
①	MICA CAPACITOR
⊖	POLYPROPYLENE FILM CAPACITOR
⊖	SEMICONDUCTIVE CERAMIC CAPACITOR
⊖	POLYPHENYLENE SULFIDE FILM CAPACITOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
□	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
⊖	METAL FILM RESISTOR
⊖	METAL PLATE RESISTOR
⊖	FIRE PROOF CARBON FILM RESISTOR
⊖	CEMENT MOLDED RESISTOR
⊖	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

NOTICE (model)

(J)..... JAPANESE
(U)..... U. S. A.
(C)..... CANADIAN
(R)..... GENERAL
(A)..... AUSTRALIAN
(B)..... BRITISH
(G)..... EUROPEAN
(T)..... CHINA
(K)..... KOREA


Interchangeable Parts at Manufacture Stage

Mark	Reference Parts Number	Parts Name
41	04B-49	2SC2876 (A/B)
42	RY4-6	2SD1918F (A/B)
43	D1.4.13.14	DH4D2-01M1-SL DH4D2-01M1-SL


	RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200				RX-V2200/DSP-AX2200			
	J	U-C	R.T.K.A	B-G	J	U-C	R.T.A	
45	R132	X	X	10	10	10	10	
46	R123	X	X	4.7K	4.7K	4.7K	4.7K	
47	Q40	X	BR41 (P-Q)	BR41 (P-Q)	BR41 (P-Q)	BR41 (P-Q)	BR41 (P-Q)	
48	R127	X	X	3.3K	3.3K	3.3K	3.3K	
49	R122	X	X	100	100	100	100	
50	C47	X	X	10/25	10/25	10/25	10/25	
51	D18	X	X	MTZJ24C	MTZJ24C	MTZJ24C	MTZJ24C	
52	R128-R129	X	X	6.8K	6.8K	6.8K	6.8K	
53	R189	X	X	1P10	1P10	1P10	1P10	
54	C38-C89	X	X	100/50	100/50	100/50	100/50	
55	Q43	X	X	C1815 (Y)	C1815 (Y)	C1815 (Y)	C1815 (Y)	
56	TE1-TE2	X	X	V591230	V591230	V591230	V591230	
57	C75-C77	X	X	0.015	0.022	X	X	
58	C76-C78	X	X	0.01	X	X	X	
59	C79-C80-C81	X	X	0.01	X	X	X	
60	C86	X	X	4700P	4700P	X	X	
61	C90	X	X	10/50	10/50	10/50	10/50	
62	W11	X	MH39640	MH39640	MH39640	MH39640	MH39640	
63	SW1	X	SL14-22AMSF	SL14-22AMSF	SL14-22AMSF	SL14-22AMSF	SL14-22AMSF	
64	W12	X	MH31640	MH31640	X	MH31640	MH31640	
65	W5-W9	X	MH34630	MH34630	MH42616	MH32620	MH32620	
66	W14	X	MH33630	MH33630	X	MH33630	MH33630	
67	C65	X	X	4700P	0.01	X	X	
68	W13	X	MH31640	MH31640	X	MH36630	MH36630	
69	R10, 15, 21, 26, 31	1/2P 820	1/2P 820	1/2P 820	1/2P 1K	1/2P 1K	1/2P 1K	
70	R34, 35, 37, 38, 40	1/2P 1K	1/2P 1K	1/2P 1K	1/2P 1K	1/2P 1K	1/2P 1K	
71	Q18A, 19C, 21A, 21C, 22A, 23C, 24A, 24C, 25A, 25C, 26A, 26C	A1695C4468	A1695C4468	A1695C4468	A1695C4468	A1695C4468	A1695C4468	

X: NOT USED
O: USED / APPLICABLE


Point ④ Pin 12 of IC581




Point ⑤ Pin 3 of IC610



Point ⑥ Pin 3 of IC610



IC001: LM61CIZ
Temperature Sensor



- ★ All voltages are measured with a 10M Ω DC electric volt meter.
- ★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
- ★ Schematic diagram is subject to change without notice.

- 電圧は、内部抵抗10M Ω の電圧計で測定したものです。
- Δ 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
- 本回路図は標準回路図です。改良のため予告なく変更することがございます。

■ SCHEMATIC DIAGRAM (POWER)



The voltage value before or above parentheses [] is applicable to RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200 and the value in the parentheses is applicable to RX-V2200/DSP-AX2200. Also, the voltage value without parentheses is commonly applicable to all models.

[] 外の電圧値はRX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200の値を表し、
[] 内の電圧値はRX-V2200/DSP-AX2200の値を表します。また、[] が付いていない電圧値は全モデルに共通の値です。

RESISTOR	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
□	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
■	METAL FILM RESISTOR
□	POLYESTER FILM CAPACITOR
○	POLYSTYRENE FILM CAPACITOR
□	FINE PRINT CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
□	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
○	TANTALUM CAPACITOR
□	CERAMIC CAPACITOR
■	CERAMIC TUBULAR CAPACITOR
□	POLYESTER FILM CAPACITOR
○	POLYSTYRENE FILM CAPACITOR
□	MICA CAPACITOR
□	POLYPROPYLENE FILM CAPACITOR
■	SEMICONDUCTIVE CERAMIC CAPACITOR
○	POLYPHENYLENE SULFIDE FILM CAPACITOR

NOTICE (mode1)
(J)..... JAPANESE
(U)..... U.S.A
(C)..... CANADIAN
(P)..... GENERAL
(A)..... AUSTRALIAN
(B)..... BRITISH
(G)..... EUROPEAN
(T)..... CHINA
(K)..... KOREA



		RX-V1200/RX-V1200RDS/HTR-5490/DSP-AX1200										RX-V2200/DSP-AX2200										
		J	U	C	P.T.K	A	B	G	J	U	C	P.T	A	J	U	C	P.T	A	J	U	C	P.T
95	D002	x	x	x	x	173 V59870	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
96	F201	x	BA125V V58230	x	x	x	x	12.5k425V V58230	x	BA125V V58230	x	x	x	x	x	x	x	x	x	x	x	x
97	I201	x2207	x2208	x2208	x2209	x2209	x2209	x2231	x2231	x2227	x2228	x2228	x2229	x2229	x2229	x2229	x2229	x2229	x2229	x2229	x2229	x2229
98	TE001	V54310	V54310	V54310	V54310	V191500	V54330	V54340	V54310	V54310	V54310	V54310	V54310	V54310	V54310	V54310	V54310	V54310	V54310	V54310	V54310	V54310
99	J002	0	x	0	0	0	0	0	0	0	x	0	x	0	x	0	x	0	x	0	x	0
100	CB004-205	x	VP20650	x	x	x	x	x	VP20650	x	VP20650	x	x	x	x	x	x	x	x	x	x	x
101	J001	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
102	Q201-202	x	x	x	x	Q2096 LKX1 V51080	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
103	R202-203	x	x	x	x	100 HF45310	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
104	R001	x	x	x	x	10k HF45310	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
105	Q201	x	x	x	x	100k133 V583165	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
106	C202	x	x	x	x	10/25 J014710	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
107	C203	x	x	x	x	10/100 J014710	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
108	Q203	x	x	x	x	K246 [Y] IE10062	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
109	Q207	x	x	x	x	MTZ118 V543990	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
110	C204	x	x	x	x	10/50 J014710	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
121	F202	BA125V V58230	BA125V V58230	BA125V V58230	BA125V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230	14AL250V V58230
122	R209	x	1/250 2W V57300	1/250 2W V57300	1/250 2W V57300	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
123	C216-218	x	x	x	x	0.01 V17300	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
124	C217	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410	0.01/100 UP56410
125	W223	x	x	x	x	MM02630	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
126	W221	x	x	x	x	MM04630	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
127	W225	x	x	x	x	MM03630	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
128	W222	x	x	x	x	MM09630	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
129	W224	x	x	x	x	MM06630	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
130	W206	x	x	x	x	MM01630	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
131	W202	x	x	x	x	V718230	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
132	CB209-210	x	x	x	x	VP20650	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
133	F203	x	x	x	x	14AL250V V58230	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x	x
134	CB206	V587990	x	x	x	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990	V587990
135	CB217	x	V586120	V586120	x	x	x	x	x	x	V586120	V586120	V586120	x	x	x	x	x	x	x	x	x
136	C242	x	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510	1000/6.3 UB81510
137	C244-246-252	100P	100P	100P	100P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P
138	C248-250-254	100P	100P	100P	100P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P	220P
139	Q213	x	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910	MTZ118 V543910
140	Q215	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940	MTZ118A V543940
141	Q206	x	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310	C189A10/E V58310
142	Q208	x	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710	10k HF45710
143	R209	x	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747	47k HF45747
144	R215-257	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015
145	R263-269	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015	150 HC05015											

PARTS LIST

■ ELECTRICAL PARTS

■ WARNING

Components having special characteristics are marked $\triangle$ and must be replaced with parts having specifications equal to those originally installed.

- Carbon resistors (1/6W or 1/4W) are not included in the ELECTRICAL PARTS List. For the parts No. of the carbon resistors, refer to last page.

ABBREVIATIONS IN THIS LIST ARE AS FOLLOWS:

C.A.EL.CHP	: CHIP ALUMI.ELECTROLYTIC CAP	L.EMIT	: LIGHT EMITTING MODULE
C.CE	: CERAMIC CAP	LED.DSPLY	: LED DISPLAY
C.CE.ARRAY	: CERAMIC CAP ARRAY	LED.INFRD	: LED,INFRARED
C.CE.CHP	: CHIP CERAMIC CAP	MODUL.RF	: MODULATOR,RF
C.CE.ML	: MULTILAYER CERAMIC CAP	PHOT.CPL	: PHOTO COUPLER
C.CE.M.CHP	: CHIP MULTILAYER CERAMIC CAP	PHOT.INTR	: PHOTO INTERRUPTER
C.CE.SAFTY	: RECOGNIZED CERAMIC CAP	PHOT.RFLCT	: PHOTO REFLECTOR
C.CE.TUBLR	: CERAMIC TUBULAR CAP	PIN.TEST	: PIN,TEST POINT
C.CE.SMI	: SEMI CONDUCTIVE CERAMIC CAP	PLST.RIVET	: PLASTIC RIVET
C.EL	: ELECTROLYTIC CAP	R.ARRAY	: RESISTOR ARRAY
C.MICA	: MICA CAP	R.CAR.	: CARBON RESISTOR
C.ML.FLM	: MULTILAYER FILM CAP	R.CAR.CHP	: CHIP RESISTOR
C.MP	: METALLIZED PAPER CAP	R.CAR.FP	: FLAME PROOF CARBON RESISTOR
C.MYLAR	: MYLAR FILM CAP	R.FUS	: FUSABLE RESISTOR
C.MYLAR.ML	: MULTILAYER MYLAR FILM CAP	R.MTL.CHP	: CHIP METAL FILM RESISTOR
C.PAPER	: PAPER CAPACITOR	R.MTL.FLM	: METAL FILM RESISTOR
C.PLS	: POLYSTYRENE FILM CAP	R.MTL.OXD	: METAL OXIDE FILM RESISTOR
C.POL	: POLYESTER FILM CAP	R.MTL.PLAT	: METAL PLATE RESISTOR
C.POLY	: POLYETHYLENE FILM CAP	RSNR.CE	: CERAMIC RESONATOR
C.PP	: POLYPROPYLENE FILM CAP	RSNR.CRYS	: CRYSTAL RESONATOR
C.TNTL	: TANTALUM CAP	R.TW.CEM	: TWIN CEMENT FIXED RESISTOR
C.TNTL.CHP	: CHIP TANTALUM CAP	R.WW	: WIRE WOUND RESISTOR
C.TRIM	: TRIMMER CAP	SCR.BND.HD	: BIND HEAD B-TITE SCREW
CN	: CONNECTOR	SCR.BW.HD	: BW HEAD TAPPING SCREW
CN.BS.PIN	: CONNECTOR,BASE PIN	SCR.CUP	: CUP TITE SCREW
CN.CANNON	: CONNECTOR,CANNON	SCR.TERM	: SCREW TERMINAL
CN.DIN	: CONNECTOR,DIN	SCR.TR	: SCREW,TRANSISTOR
CN.FLAT	: CONNECTOR,FLAT CABLE	SUPRT.PCB	: SUPPORT,P.C.B.
CN.POST	: CONNECTOR,BASE POST	SURG.PRTCT	: SURGE PROTECTOR
COIL.MX.AM	: COIL,AM MIX	SW.TACT	: TACT SWITCH
COIL.AT.FM	: COIL,FM ANTENNA	SW.LEAF	: LEAF SWITCH
COIL.DT.FM	: COIL,FM DETECT	SW.LEVER	: LEVER SWITCH
COIL.MX.FM	: COIL,FM MIX	SW.MICRO	: MICRO SWITCH
COIL.OUTPT	: OUTPUT COIL	SW.PUSH	: PUSH SWITCH
DIOD.ARRAY	: DIODE ARRAY	SW.RT.ENC	: ROTARY ENCODER
DIODE.BRG	: DIODE BRIDGE	SW.RT.MTR	: ROTARY SWITCH WITH MOTOR
DIODE.CHP	: CHIP DIODE	SW.RT	: ROTARY SWITCH
DIODE.SHOT	: SCHOTTKY BARRIER DIODE	SW.SLIDE	: SLIDE SWITCH
DIODE.VAR	: VARACTOR DIODE	TERM.SP	: SPEAKER TERMINAL
DIOD.Z.CHP	: CHIP ZENER DIODE	TERM.WRAP	: WRAPPING TERMINAL
DIODE.ZENR	: ZENER DIODE	THRMST.CHP	: CHIP THERMISTOR
DSCR.CE	: CERAMIC DISCRIMINATOR	TR.CHP	: CHIP TRANSISTOR
FER.BEAD	: FERRITE BEADS	TR.DGT	: DIGITAL TRANSISTOR
FER.CORE	: FERRITE CORE	TR.DGT.CHP	: CHIP DIGITAL TRANSISTOR
FET.CHP	: CHIP FET	TRANS	: TRANSFORMER
FL.DSPLY	: FLUORESCENT DISPLAY	TRANS.PULS	: PULSE TRANSFORMER
FLTR.CE	: CERAMIC FILTER	TRANS.PWR	: POWER TRANSFORMER ASS'Y
FLTR.COMB	: COMB FILTER MODULE	TUNER.AM	: TUNER PACK,AM
FLTR.LC.RF	: LC FILTER,EMI	TUNER.FM	: TUNER PACK,FM
GND.MTL	: GROUND PLATE	TUNER.PK	: FRONT-END TUNER PACK
GND.TERM	: GROUND TERMINAL	VR	: ROTARY POTENTIOMETER
HOLDER.FUS	: FUSE HOLDER	VR.MTR	: POTENTIOMETER WITH MOTOR
IC.PRTCT	: IC PROTECTOR	VR.SW	: POTENTIOMETER WITH ROTARY SW
JUMPER.CN	: JUMPER CONNECTOR	VR.SLIDE	: SLIDE POTENTIOMETER
JUMPER.TST	: JUMPER,TEST POINT	VR.TRIM	: TRIMMER POTENTIOMETER
L.DTCT	: LIGHT DETECTING MODULE		

Note) Those parts marked with “#” are not included in the P.C.B. ass'y.

P.C.B. FUNCTION

Schm Ref.	PART NO.	Description	Markets
	V7944400	P. C. B.	FUNCTION V1200
	V7944500	P. C. B.	FUNCTION V1200
	V7944600	P. C. B.	FUNCTION V1200
	V7944700	P. C. B.	FUNCTION V1200RDS
	V7944800	P. C. B.	FUNCTION 5490
	V7944900	P. C. B.	FUNCTION 5490
	V7945100	P. C. B.	FUNCTION V2200
	V7945200	P. C. B.	FUNCTION V2200
	V7945300	P. C. B.	FUNCTION V2200
CB501	V7826000	CN	10P TE TUC SERIES
CB502	V7826100	CN	11P TE TUC SERIES
CB503	V7828200	SOCKET	15P TE TUC SERIES
CB504	VQ048000	CN.BS. PIN	31P
CB505	VF982300	CN.BS. PIN	17P
CB506	V7827800	SOCKET	11P TE TUC SERIES
CB507	VQ047400	CN.BS. PIN	19P
CB508	V7827900	SOCKET	12P TE TUC SERIES
CB509	VQ044900	CN.BS. PIN	19P
CB510	VQ044600	CN.BS. PIN	13P
C501	UU166470	C. EL	4.7uF 50V
C502	UU166470	C. EL	4.7uF 50V
C503	UU166470	C. EL	4.7uF 50V
C504	UU166100	C. EL	1uF 50V
C505	UU166100	C. EL	1uF 50V
C506	UU118220	C. EL	220uF 6.3V
C507	UU118220	C. EL	220uF 6.3V
C508	UU166220	C. EL	2.2uF 50V (V2200)
C509	UU166220	C. EL	2.2uF 50V (V2200)
C510	UU147100	C. EL	10uF 25V
C511	UU147100	C. EL	10uF 25V
C512	UU147100	C. EL	10uF 25V
C513	UU147100	C. EL	10uF 25V
C514	UU147100	C. EL	10uF 25V
C515	UU137470	C. EL	47uF 16V
C516	UU137470	C. EL	47uF 16V
C517	UU147100	C. EL	10uF 25V (V2200)
C518	UU147100	C. EL	10uF 25V (V2200)
C519	UU138100	C. EL	100uF 16V
C520	UU138100	C. EL	100uF 16V
C521	UU147100	C. EL	10uF 25V (V2200)
C522	UU147100	C. EL	10uF 25V (V2200)
C523	UU166470	C. EL	4.7uF 50V
C524	UU166470	C. EL	4.7uF 50V
C525	UU166470	C. EL	4.7uF 50V
C526	UU166470	C. EL	4.7uF 50V
C527	UU147100	C. EL	10uF 25V
C528	UU147100	C. EL	10uF 25V
C529	UU147100	C. EL	10uF 25V
C530	UU147100	C. EL	10uF 25V
C531	UU137470	C. EL	47uF 16V
C532	UU137470	C. EL	47uF 16V
C533	UU166220	C. EL	2.2uF 50V
C534	UU137220	C. EL	22uF 16V
C535	UU137220	C. EL	22uF 16V
C536	UU147100	C. EL	10uF 25V
C537	UU147100	C. EL	10uF 25V
C538	UU147100	C. EL	10uF 25V
C539	UU147100	C. EL	10uF 25V
C540	UU147100	C. EL	10uF 25V
C541	UU137470	C. EL	47uF 16V
C542	UU137470	C. EL	47uF 16V
C543	UU166330	C. EL	3.3uF 50V
C544	UU166330	C. EL	3.3uF 50V

* New Parts

Schm Ref.	PART NO.	Description	Markets
C545	UU147100	C. EL	10uF 25V
C546	UU147100	C. EL	10uF 25V
C547	UU147100	C. EL	10uF 25V
C548	UU147100	C. EL	10uF 25V
C549	UU147100	C. EL	10uF 25V
C550	UU147100	C. EL	10uF 25V
C551	UR865220	C. EL	0.22uF 50V
C552	UU147100	C. EL	10uF 25V
C553	UU147100	C. EL	10uF 25V
C554	UU166330	C. EL	3.3uF 50V
C555	UU166330	C. EL	3.3uF 50V
C556	UU166330	C. EL	3.3uF 50V
C557	UU166330	C. EL	3.3uF 50V
C558	UU166330	C. EL	3.3uF 50V
C559	UU166330	C. EL	3.3uF 50V
C560	UU167100	C. EL	10uF 50V
C561	UU138100	C. EL	100uF 16V
C562	UU138100	C. EL	100uF 16V
C563	UR865470	C. EL	0.47uF 50V
C564	UU147100	C. EL	10uF 25V
C565	UU147100	C. EL	10uF 25V
C566	UU147100	C. EL	10uF 25V
C567	UU147100	C. EL	10uF 25V
C568	UU137470	C. EL	47uF 16V
C569	UU147100	C. EL	10uF 25V
C570	UU147100	C. EL	10uF 25V
C571	UU138100	C. EL	100uF 16V
C572	UU138100	C. EL	100uF 16V
C573	UU147100	C. EL	10uF 25V
C574	UU147100	C. EL	10uF 25V
C575	UU147100	C. EL	10uF 25V
C576	UR848100	C. EL	100uF 25V
C576	UR848220	C. EL	220uF 25V
C577	UU137470	C. EL	47uF 16V
C578	UU138100	C. EL	100uF 16V
C579	UU138100	C. EL	100uF 16V
C580	VU545000	C. EL	47000uF 5.5V
C581	UU147100	C. EL	10uF 25V
C582	UU147100	C. EL	10uF 25V
C583	UU147100	C. EL	10uF 25V
C584	UU137470	C. EL	47uF 16V
C585	UU137470	C. EL	47uF 16V
C586	UR819100	C. EL	1000uF 6.3V
C587	UR819100	C. EL	1000uF 6.3V
C588	UU147100	C. EL	10uF 25V
C589	UU147100	C. EL	10uF 25V
C590	UU147100	C. EL	10uF 25V
C591	UU147100	C. EL	10uF 25V
C592	UU147100	C. EL	10uF 25V
C593	UU138100	C. EL	100uF 16V
C594	UU147100	C. EL	10uF 25V
C595	UU166220	C. EL	2.2uF 50V
C596	UU166220	C. EL	2.2uF 50V
C597	UU166220	C. EL	2.2uF 50V
C598	UU166220	C. EL	2.2uF 50V
C599	UU166220	C. EL	2.2uF 50V
C600	UU166220	C. EL	2.2uF 50V
C601	VD930900	C. CE. SMI	0.1uF 25V
C602	US135100	C. CE. CHP	0.1uF 16V
C603	UP652220	C. POL	220pF 100V
C603	UP652220	C. POL	220pF 100V
C604	UP652220	C. POL	220pF 100V
C605	UP652470	C. POL	470pF 100V

* New Parts

UCABG
RTKABG
ABG

P.C.B. FUNCTION

Schm Ref.	PART NO.	Description	Markets
C606	UP652470	C. POL 470pF 100V	
C607	UP652470	C. POL 470pF 100V	
C608	UP652470	C. POL 470pF 100V	
C609	UP652470	C. POL 470pF 100V	
C610	UP652470	C. POL 470pF 100V	
C611	UP652470	C. POL 470pF 100V	
C612	UP652470	C. POL 470pF 100V	
C613	UP652470	C. POL 470pF 100V	
C614	UP652470	C. POL 470pF 100V	
C615	UP652220	C. POL 220pF 100V	
C616	UP652220	C. POL 220pF 100V	
C617	UP652470	C. POL 470pF 100V	
C618	UP652470	C. POL 470pF 100V	
C619	UP652470	C. POL 470pF 100V	
C620	UP652470	C. POL 470pF 100V	
C621	UP652470	C. POL 470pF 100V	
C622	UP652470	C. POL 470pF 100V	
C623	UA654390	C. MYLAR 0.039uF 50V	
C624	UA654390	C. MYLAR 0.039uF 50V	
C625	UP652100	C. POL 100pF 100V	(V2200)
C626	UP652100	C. POL 100pF 100V	(V2200)
C627	UA654110	C. MYLAR 0.011uF 50V	
C628	UA654110	C. MYLAR 0.011uF 50V	
C629	UA653100	C. MYLAR 1000pF 50V	
C630	UA653100	C. MYLAR 1000pF 50V	
C631	UP652100	C. POL 100pF 100V	
C632	UP652100	C. POL 100pF 100V	
C633	US135100	C. CE. CHP 0.1uF 16V	
C634	US135100	C. CE. CHP 0.1uF 16V	
C635	UP654270	C. POL 0.027uF 100V	
C636	UP654270	C. POL 0.027uF 100V	
C637	UP654270	C. POL 0.027uF 100V	
C638	UP654270	C. POL 0.027uF 100V	
C639	US135100	C. CE. CHP 0.1uF 16V	
C640	UP652100	C. POL 100pF 100V	
C641	UP652100	C. POL 100pF 100V	
C642	US135100	C. CE. CHP 0.1uF 16V	
C643	US135100	C. CE. CHP 0.1uF 16V	
C644	US063100	C. CE. M. CHP 1000pF 50V	
C645	US135100	C. CE. CHP 0.1uF 16V	
C646	US135100	C. CE. CHP 0.1uF 16V	
C647	US135100	C. CE. CHP 0.1uF 16V	
C648	US135100	C. CE. CHP 0.1uF 16V	
C649	US135100	C. CE. CHP 0.1uF 16V	
C650	US135100	C. CE. CHP 0.1uF 16V	
C651	US135100	C. CE. CHP 0.1uF 16V	
C652	US135100	C. CE. CHP 0.1uF 16V	
C653	US135100	C. CE. CHP 0.1uF 16V	
C654	US135100	C. CE. CHP 0.1uF 16V	
C655	US135100	C. CE. CHP 0.1uF 16V	
C656	US135100	C. CE. CHP 0.1uF 16V	
C657	US135100	C. CE. CHP 0.1uF 16V	
C658	UP652100	C. POL 100pF 100V	
C659	UP652100	C. POL 100pF 100V	
C660	UP652100	C. POL 100pF 100V	
C661	US135100	C. CE. CHP 0.1uF 16V	
C662	UP652100	C. POL 100pF 100V	
C663	UP652100	C. POL 100pF 100V	
C664	US135100	C. CE. CHP 0.1uF 16V	
C665	US135100	C. CE. CHP 0.1uF 16V	
C666	US135100	C. CE. CHP 0.1uF 16V	
C667	UP652100	C. POL 100pF 100V	
C668	UP652100	C. POL 100pF 100V	

* New Parts

Schm Ref.	PART NO.	Description	Markets
C669	US135100	C. CE. CHP 0.1uF 16V	
C670	US135100	C. CE. CHP 0.1uF 16V	
C671	US135100	C. CE. CHP 0.1uF 16V	UCABG
C672	US135100	C. CE. CHP 0.1uF 16V	
C673	US135100	C. CE. CHP 0.1uF 16V	
C675	US063100	C. CE. M. CHP 1000pF 50V	
C676	US135100	C. CE. CHP 0.1uF 16V	UCABG
C677	US063100	C. CE. M. CHP 1000pF 50V	
C678	US135100	C. CE. CHP 0.1uF 16V	UCABG
C679	US135100	C. CE. CHP 0.1uF 16V	RTKABG
C680	US135100	C. CE. CHP 0.1uF 16V	
C681	US135100	C. CE. CHP 0.1uF 16V	
C682	US135100	C. CE. CHP 0.1uF 16V	
C691	UR867470	C. EL 47uF 50V	
C692	UR848100	C. EL 100uF 25V	RTKABG
D501	VU992600	DIODE. ZENR MA8051-M 5.1V	
D502	VT332900	DIODE 1SS355	
D503	VT332900	DIODE 1SS355	
D504	VT332900	DIODE 1SS355	
D505	VT332900	DIODE 1SS355	
D506	VU992900	DIODE. ZENR MA8056-L 5.4V	RTK
D506	VU993500	DIODE. ZENR MA8062-H 6.4V	UCABG
D507	VT332900	DIODE 1SS355	
D508	VT332900	DIODE 1SS355	
D509	VT332900	DIODE 1SS355	
D510	VT332900	DIODE 1SS355	
D511	VV833200	DIODE 1SS380	
D512	VT332900	DIODE 1SS355	
D513	VU992600	DIODE. ZENR MA8051-M 5.1V	
D514	VT332900	DIODE 1SS355	
D515	VU993000	DIODE. ZENR MA8056-M 5.6V	
D517	VT332900	DIODE 1SS355	
D518	VT332900	DIODE 1SS355	
D519	VV220700	DIODE. SHOT RB501V-40	
D520	VT332900	DIODE 1SS355	
D521	VV220700	DIODE. SHOT RB501V-40	
D522	VT332900	DIODE 1SS355	
D523	VV220700	DIODE. SHOT RB501V-40	
D524	VT332900	DIODE 1SS355	
D525	VV220700	DIODE. SHOT RB501V-40	
D526	VT332900	DIODE 1SS355	
D531	VT332900	DIODE 1SS355	
D532	VT332900	DIODE 1SS355	
IC501	XJ553A00	IC NJM2068MD	
IC502	XP895A00	IC LC78212	
IC503	XP894A00	IC LC78211	
IC504	XP895A00	IC LC78212	(V2200)
IC505	XP896A00	IC LC78213	(V2200)
IC506	XF291A00	IC uPC4570G2	
IC507	XF291A00	IC uPC4570G2	
IC508	XF291A00	IC uPC4570G2	(V2200)
IC509	XP894A00	IC LC78211	
IC510	XP896A00	IC LC78213	
IC511	XF291A00	IC uPC4570G2	
IC512	X0601A00	IC MBM29F400BC-70	
IC513	XF291A00	IC uPC4570G2	
IC514	XF291A00	IC uPC4570G2	
IC515	XF291A00	IC uPC4570G2	
IC516	XZ545A00	IC YAC520-EE2	
IC517	XZ545A00	IC YAC520-EE2	
IC518	XZ545A00	IC YAC520-EE2	
IC519	XZ545A00	IC YAC520-EE2	
IC520	XY892A00	IC. CPU M30802SGP CPU	

* New Parts

P.C.B. FUNCTION & P.C.B. OPERATION

Schm Ref.	PART NO.	Description	Markets
IC521	XF291A00	IC	uPC4570G2
IC522	XJ604A00	IC	NJM78M05FA
IC523	XF291A00	IC	uPC4570G2
IC524	XF291A00	IC	uPC4570G2
IC525	XF291A00	IC	uPC4570G2
L501	VY656400	COIL. CHP	120uH
L502	VY656400	COIL. CHP	120uH
L503	VP133800	FER. BEAD	BL02RN1-R62T4
PJ501	V3855600	JACK. PIN	4P
PJ502	V3855600	JACK. PIN	4P
PJ503	V4198900	JACK. PIN	4P
PJ504	V4199200	JACK. PIN	6P
PN501	V3750200	PIN	L=70
Q501	VD303700	TR	2SC3326 A,B
Q502	VD303700	TR	2SC3326 A,B
Q503	VD303700	TR	2SC3326 A,B
Q504	VD303700	TR	2SC3326 A,B
Q505	VD303700	TR	2SC3326 A,B
Q506	VD303700	TR	2SC3326 A,B
Q507	VV556500	TR	2SA1037K Q, R, S
Q508	VV556500	TR	2SA1037K Q, R, S
Q509	VV655700	TR. DGT	DTC144EKA
Q510	VV655700	TR. DGT	DTC144EKA
Q511	VV556500	TR	2SA1037K Q, R, S
Q512	VV655700	TR. DGT	DTC144EKA
Q513	VD303700	TR	2SC3326 A,B
Q514	VD303700	TR	2SC3326 A,B
Q515	VD303700	TR	2SC3326 A,B
Q516	VD303700	TR	2SC3326 A,B
Q517	VD303700	TR	2SC3326 A,B
Q518	VD303700	TR	2SC3326 A,B
Q519	VD303700	TR	2SC3326 A,B
Q520	VV556500	TR	2SA1037K Q, R, S
Q521	VV556500	TR	2SA1037K Q, R, S
Q522	VV556500	TR	2SA1037K Q, R, S
Q523	VV556500	TR	2SA1037K Q, R, S
Q524	VV556500	TR	2SA1037K Q, R, S
Q525	VV556500	TR	2SA1037K Q, R, S
Q526	VP872700	TR	2SC4488 S,T
Q527	VV556500	TR	2SA1037K Q, R, S
Q528	VV556500	TR	2SA1037K Q, R, S
Q529	VV556500	TR	2SA1037K Q, R, S
Q530	VV556500	TR	2SA1037K Q, R, S
Q531	VV556500	TR	2SA1037K Q, R, S
Q532	VV556500	TR	2SA1037K Q, R, S
Q533	VD303700	TR	2SC3326 A,B
Q534	VD303700	TR	2SC3326 A,B
Q535	VP872600	TR	2SA1708 S,T
Q536	VV655700	TR. DGT	DTC144EKA
Q537	VD303700	TR	2SC3326 A,B
Q538	VD303700	TR	2SC3326 A,B
Q539	VD303700	TR	2SC3326 A,B
Q540	VD303700	TR	2SC3326 A,B
Q541	VD303700	TR	2SC3326 A,B
Q542	VD303700	TR	2SC3326 A,B
Q543	VD303700	TR	2SC3326 A,B
Q544	VD303700	TR	2SC3326 A,B
Q544	VD303700	TR	2SC3326 A,B
Q546	VD303700	TR	2SC3326 A,B
Q547	VD303700	TR	2SC3326 A,B
R561	HV755100	R. CAR. FP	100Ω 1/4W
R562	HV755100	R. CAR. FP	100Ω 1/4W
R636	HV753220	R. CAR. FP	2.2Ω 1/4W

* New Parts

Schm Ref.	PART NO.	Description	Markets
R637	HV753220	R. CAR. FP	2.2Ω 1/4W
R664	HV753470	R. CAR. FP	4.7Ω 1/4W
R703	HV753220	R. CAR. FP	2.2Ω 1/4W
R704	HV753220	R. CAR. FP	2.2Ω 1/4W
R803	HV754100	R. CAR. FP	10Ω 1/4W
ST501	V4040500	SCR. TERM	M3
ST502	V4040500	SCR. TERM	M3
XL501	V4738900	RSNR. CE	12MHz
	V7950900	P. C. B.	OPERATION V1200
	V7951000	P. C. B.	OPERATION V1200
	V7951100	P. C. B.	OPERATION V1200
	V7951300	P. C. B.	OPERATION V2200
CB801	VM973500	CN. BS. PIN	17P
CB802	Vi878200	CN. BS. PIN	4P
CB901	Vi878500	CN. BS. PIN	7P
CB902	VQ044900	CN. BS. PIN	19P
CB941	Vi878100	CN. BS. PIN	3P
CB961	VK026200	CN. BS. PIN	3P
CB962	VK026600	CN. BS. PIN	7P
CB971	V7680700	CN. PHOT. SN	1P GP1FA512RZ
CB972	VQ047100	CN. BS. PIN	7P
CB973	Vi878200	CN. BS. PIN	4P
CB974	VB389900	CN. BS. PIN	3P
CB975	VB390000	CN. BS. PIN	4P
C801	UU137470	C. EL	47uF 16V
C802	UU137470	C. EL	47uF 16V
C803	UU137470	C. EL	47uF 16V
C804	UU137470	C. EL	47uF 16V
C805	UU165100	C. EL	0.1uF 50V
C806	UU165100	C. EL	0.1uF 50V
C807	UU165100	C. EL	0.1uF 50V
C808	UU165100	C. EL	0.1uF 50V
C809	UU166100	C. EL	1uF 50V
C810	UU166100	C. EL	1uF 50V
C811	UU166220	C. EL	2.2uF 50V
C812	UU166220	C. EL	2.2uF 50V
C813	VQ645600	C. MYLAR	100pF 50V
C814	VQ645600	C. MYLAR	100pF 50V
C815	UU137470	C. EL	47uF 16V
C816	UU137470	C. EL	47uF 16V
C817	UA655120	C. MYLAR	0.12uF 50V
C818	UA655120	C. MYLAR	0.12uF 50V
C819	UA654330	C. MYLAR	0.033uF 50V
C820	UA654330	C. MYLAR	0.033uF 50V
C821	UU147100	C. EL	10uF 25V
C822	UU147100	C. EL	10uF 25V
C823	UU147100	C. EL	10uF 25V
C824	UU147100	C. EL	10uF 25V
C825	UU147100	C. EL	10uF 25V
C826	UU147100	C. EL	10uF 25V
C827	UA652100	C. MYLAR	100pF 50V
C828	UA652100	C. MYLAR	100pF 50V
C829	UA652100	C. MYLAR	100pF 50V
C830	UA652100	C. MYLAR	100pF 50V
C831	UU147100	C. EL	10uF 25V
C832	UU147100	C. EL	10uF 25V
C833	VF466600	C. CE. TUBLR	10pF 50V
C834	VF466600	C. CE. TUBLR	10pF 50V
C835	UU139100	C. EL	1000uF 16V
C836	UU139100	C. EL	1000uF 16V

* New Parts

P.C.B. OPERATION & P.C.B. DSP

Schm Ref.	PART NO.	Description	Markets
C837	UA655120	C. MYLAR 0.12uF 50V	
C838	UA655120	C. MYLAR 0.12uF 50V	
C901	VJ599100	C. CE. TUBLR 0.1uF 50V	
C902	VJ599100	C. CE. TUBLR 0.1uF 50V	
C903	VJ599100	C. CE. TUBLR 0.1uF 50V	
C905	UM388100	C. EL 100uF 10V	
C906	VJ599100	C. CE. TUBLR 0.1uF 50V	
C907	VG277000	C. CE. TUBLR 33pF 50V	
C908	VJ599100	C. CE. TUBLR 0.1uF 50V	
C909	VJ599100	C. CE. TUBLR 0.1uF 50V	
C910	V6295600	C. EL 330uF 6.3V	
C911	VJ599100	C. CE. TUBLR 0.1uF 50V	
C912	VJ599100	C. CE. TUBLR 0.1uF 50V	
C961	VJ599100	C. CE. TUBLR 0.1uF 50V	
C971	VJ599100	C. CE. TUBLR 0.1uF 50V	
C972	UR837470	C. EL 47uF 16V	
C973	VF466900	C. CE. TUBLR 470pF 50V	
C974	VF466900	C. CE. TUBLR 470pF 50V	
C975	VJ599100	C. CE. TUBLR 0.1uF 50V	
C976	VJ599100	C. CE. TUBLR 0.1uF 50V	
C977	VF467000	C. CE. TUBLR 1000pF 50V	
C978	VF467000	C. CE. TUBLR 1000pF 50V	
C979	VF467300	C. CE. TUBLR 0.01uF 16V	
C980	VF467000	C. CE. TUBLR 1000pF 50V	
C981	VJ599100	C. CE. TUBLR 0.1uF 50V	
C983	VJ599100	C. CE. TUBLR 0.1uF 50V	
C984	VJ599100	C. CE. TUBLR 0.1uF 50V	
C985	VJ599100	C. CE. TUBLR 0.1uF 50V	
D801	VG439100	DIODE. ZENR MTZJ9. 1A 9.1V	
D802	VG439100	DIODE. ZENR MTZJ9. 1A 9.1V	
D803	VU264100	DIODE 1SR139-400	
D804	VU264100	DIODE 1SR139-400	
D901	VM974700	DIODE. ZENR HZS7B2TD 7.0V	
D902	V2598200	LED SIR-505ST	UCA (V1200)
D902	V2598200	LED SIR-505ST	UCRTA (V2200)
G961	V8880000	TERM. GND M3.5 RJP9899	
IC801	iG001270	IC TC4066BP	
IC802	XM356A00	IC NJM2068LD	
IC803	XM356A00	IC NJM2068LD	
IC804	XP844A00	IC NJM4556AL	
IC901	XV160A00	IC LC75712E FLD	
JK971	V2589500	CN 1P	
JK972	V4164400	JACK. PHONE YKB21-5209	
L971	V2726500	COIL 68uH	
PJ971	V6222800	JACK. PIN 3P	
PN901	V3750200	PIN L=70	
Q801	VG721700	TR. DGT DTA144ES	
Q802	VG722000	TR. DGT DTC144ES	
Q803	VK432900	TR 2SD1915F S,T	
Q804	VK432900	TR 2SD1915F S,T	
Q901	VV900500	TR 2SD1991A Q,R,S	
Q902	VV900500	TR 2SD1991A Q,R,S	
Q905	VV900500	TR 2SD1991A Q,R,S	
Q906	VV900500	TR 2SD1991A Q,R,S	
Q907	VV900500	TR 2SD1991A Q,R,S	
Q908	VV900500	TR 2SD1991A Q,R,S	
Q909	VV900500	TR 2SD1991A Q,R,S	
Q910	VV900500	TR 2SD1991A Q,R,S	
Q971	iC174020	TR 2SC1740S R,S	
Q972	iA093320	TR 2SA933S Q,R	
R803	VP940200	R. MTL. OXD 47Ω 1W	
R804	VP940200	R. MTL. OXD 47Ω 1W	
R841	VP940600	R. MTL. OXD 220Ω 1W	

* New Parts

Schm Ref.	PART NO.	Description	Markets
R842	VP940600	R. MTL. OXD 220Ω 1W	
R847	HB026220	R. MTL. FLM 2.2KΩ 1/4W	(V2200)
R848	HB026220	R. MTL. FLM 2.2KΩ 1/4W	(V2200)
R849	HB026220	R. MTL. FLM 2.2KΩ 1/4W	(V2200)
R850	HB026220	R. MTL. FLM 2.2KΩ 1/4W	(V2200)
R851	HB027120	R. MTL. FLM 12KΩ 1/4W	(V2200)
R852	HB027120	R. MTL. FLM 12KΩ 1/4W	(V2200)
R853	HB027120	R. MTL. FLM 12KΩ 1/4W	(V2200)
R854	HB027240	R. MTL. FLM 24KΩ 1/4W	(V2200)
R855	HB027240	R. MTL. FLM 24KΩ 1/4W	(V2200)
R856	HB027240	R. MTL. FLM 24KΩ 1/4W	(V2200)
R857	HB027240	R. MTL. FLM 24KΩ 1/4W	(V2200)
R858	HB027240	R. MTL. FLM 24KΩ 1/4W	(V2200)
ST971	V4040500	SCR. TERM M3	
ST972	V4040500	SCR. TERM M3	
ST973	V4040500	SCR. TERM M3	
SW801	V6154000	SW. RT. ENC SDB161PH20FS-1-4	(V2200)
SW901	VG392900	SW. TACT SKHVAA	
SW902	VG392900	SW. TACT SKHVAA	
SW903	V6322700	SW. RT. ENC REB161 (9X7) PVB	
SW904	VG392900	SW. TACT SKHVAA	
SW905	VG392900	SW. TACT SKHVAA	BG (V1200)
SW941	VG392900	SW. TACT SKHVAA	BG (V1200)
SW942	VG392900	SW. TACT SKHVAA	BG (V1200)
SW943	VG392900	SW. TACT SKHVAA	BG (V1200)
SW944	VG392900	SW. TACT SKHVAA	BG (V1200)
SW945	VG392900	SW. TACT SKHVAA	
SW946	VG392900	SW. TACT SKHVAA	
SW947	VG392900	SW. TACT SKHVAA	
SW948	VG392900	SW. TACT SKHVAA	
SW949	VG392900	SW. TACT SKHVAA	
SW950	VG392900	SW. TACT SKHVAA	
SW951	VG392900	SW. TACT SKHVAA	
SW952	VG392900	SW. TACT SKHVAA	
SW953	VG392900	SW. TACT SKHVAA	
SW954	VG392900	SW. TACT SKHVAA	
SW961	VG392900	SW. TACT SKHVAA	
SW962	VG392900	SW. TACT SKHVAA	
SW963	VG392900	SW. TACT SKHVAA	
SW964	VG392900	SW. TACT SKHVAA	
SW965	VG392900	SW. TACT SKHVAA	
U901	VU591000	L. DTCT GP1U271X	
V901	V7683200	FL. DSPLY 16-BT-91GK	
VR801	VP741800	VR B20KΩ	
VR802	VP741900	VR G25KΩ	
	V6007100	SPACER 4.6/10/32	
	V6007000	SHEET	
	V7946700	P. C. B.	DSP
CB503	VQ046000	CN. BS. PIN 31P	
CB504	VQ047000	CN. BS. PIN 6P	
C501	US135100	C. CE. CHP 0.1uF 16V	
C502	US135100	C. CE. CHP 0.1uF 16V	
C503	US135100	C. CE. CHP 0.1uF 16V	
C504	US135100	C. CE. CHP 0.1uF 16V	
C505	US135100	C. CE. CHP 0.1uF 16V	
C506	US135100	C. CE. CHP 0.1uF 16V	
C507	US061220	C. CE. M. CHP 22pF 50V	
C508	US061220	C. CE. M. CHP 22pF 50V	
C509	UR847220	C. EL 22uF 25V	
C510	UR847220	C. EL 22uF 25V	

* New Parts

P.C.B. DSP

Schm Ref.	PART NO.	Description	Markets
C511	US135100	C. CE. CHP 0. 1uF 16V	
C512	US135100	C. CE. CHP 0. 1uF 16V	
C513	UR819100	C. EL 1000uF 6. 3V	
C514	US061100	C. CE. M. CHP 10pF 50V	
C515	US061100	C. CE. M. CHP 10pF 50V	
C516	US135100	C. CE. CHP 0. 1uF 16V	
C517	US061470	C. CE. M. CHP 47pF 50V	
C518	US061470	C. CE. M. CHP 47pF 50V	
C519	US135100	C. CE. CHP 0. 1uF 16V	
C520	US063100	C. CE. M. CHP 1000pF 50V	
C521	US063100	C. CE. M. CHP 1000pF 50V	
C522	UR819100	C. EL 1000uF 6. 3V	
C523	UR819100	C. EL 1000uF 6. 3V	
C524	US135100	C. CE. CHP 0. 1uF 16V	
C525	US135100	C. CE. CHP 0. 1uF 16V	
C526	US135100	C. CE. CHP 0. 1uF 16V	
C527	US135100	C. CE. CHP 0. 1uF 16V	
C528	US135100	C. CE. CHP 0. 1uF 16V	
C529	US135100	C. CE. CHP 0. 1uF 16V	
C530	US135100	C. CE. CHP 0. 1uF 16V	
C531	UR819100	C. EL 1000uF 6. 3V	
C532	US135100	C. CE. CHP 0. 1uF 16V	
C533	UR819100	C. EL 1000uF 6. 3V	
C534	US135100	C. CE. CHP 0. 1uF 16V	
C535	US135100	C. CE. CHP 0. 1uF 16V	
C536	US135100	C. CE. CHP 0. 1uF 16V	
C537	US135100	C. CE. CHP 0. 1uF 16V	
C538	UR818100	C. EL 100uF 6. 3V	
C539	US135100	C. CE. CHP 0. 1uF 16V	
C540	US135100	C. CE. CHP 0. 1uF 16V	
C543	US135100	C. CE. CHP 0. 1uF 16V	
C544	UU147100	C. EL 10uF 25V	
C545	UU147100	C. EL 10uF 25V	
C546	UU147100	C. EL 10uF 25V	
C547	UA652150	C. MYLAR 150pF 50V	
C548	UA652150	C. MYLAR 150pF 50V	
C549	UA652680	C. MYLAR 680pF 50V	
C550	UA652470	C. MYLAR 470pF 50V	
C551	UR818470	C. EL 470uF 6. 3V	
C552	UA652100	C. MYLAR 100pF 50V	
C553	UA652100	C. MYLAR 100pF 50V	
C554	UA652100	C. MYLAR 100pF 50V	
C555	UA652100	C. MYLAR 100pF 50V	
C556	UA653150	C. MYLAR 1500pF 50V	
C557	UR818100	C. EL 100uF 6. 3V	
C558	UU137220	C. EL 22uF 16V	
C559	UU137220	C. EL 22uF 16V	
C560	UU128100	C. EL 100uF 10V	
C561	UU166220	C. EL 2. 2uF 50V	
C562	UU118100	C. EL 100uF 6. 3V	
C563	UU118100	C. EL 100uF 6. 3V	
C564	US061100	C. CE. M. CHP 10pF 50V	
C565	US063100	C. CE. M. CHP 1000pF 50V	
C566	US061330	C. CE. M. CHP 33pF 50V	
C567	US044220	C. CE. M. CHP 0. 022uF 25V	
C568	UR818100	C. EL 100uF 6. 3V	
C569	UR818100	C. EL 100uF 6. 3V	
C571	US062470	C. CE. M. CHP 470pF 50V	
C572	US063470	C. CE. CHP 4700pF 50V	
C573	US063470	C. CE. CHP 4700pF 50V	
C574	UR818470	C. EL 470uF 6. 3V	
C575	US061470	C. CE. M. CHP 47pF 50V	
C576	US135100	C. CE. CHP 0. 1uF 16V	

* New Parts

Schm Ref.	PART NO.	Description	Markets
C577	US135100	C. CE. CHP 0. 1uF 16V	
C578	US135100	C. CE. CHP 0. 1uF 16V	
C580	US061470	C. CE. M. CHP 47pF 50V	
C581	US061470	C. CE. M. CHP 47pF 50V	
C582	US061470	C. CE. M. CHP 47pF 50V	
C584	US135100	C. CE. CHP 0. 1uF 16V	
C585	US061470	C. CE. M. CHP 47pF 50V	
C586	US061470	C. CE. M. CHP 47pF 50V	
C587	US135100	C. CE. CHP 0. 1uF 16V	
C588	US135100	C. CE. CHP 0. 1uF 16V	
C590	US135100	C. CE. CHP 0. 1uF 16V	
C591	UR818100	C. EL 100uF 6. 3V	
C592	US135100	C. CE. CHP 0. 1uF 16V	
C593	US135100	C. CE. CHP 0. 1uF 16V	
C594	UR819100	C. EL 1000uF 6. 3V	
C595	US064100	C. CE. M. CHP 0. 01uF 50V	
C596	US135100	C. CE. CHP 0. 1uF 16V	
C597	US135100	C. CE. CHP 0. 1uF 16V	
C598	US061470	C. CE. M. CHP 47pF 50V	
C599	US061470	C. CE. M. CHP 47pF 50V	
C600	US061470	C. CE. M. CHP 47pF 50V	
C601	US061470	C. CE. M. CHP 47pF 50V	
C602	US061470	C. CE. M. CHP 47pF 50V	
C603	US061470	C. CE. M. CHP 47pF 50V	
C604	US061470	C. CE. M. CHP 47pF 50V	
C605	US061470	C. CE. M. CHP 47pF 50V	
C606	US061470	C. CE. M. CHP 47pF 50V	
C607	US135100	C. CE. CHP 0. 1uF 16V	
C608	US135100	C. CE. CHP 0. 1uF 16V	
C609	US135100	C. CE. CHP 0. 1uF 16V	
C610	UU137470	C. EL 47uF 16V	
C611	UU137470	C. EL 47uF 16V	
C612	US135100	C. CE. CHP 0. 1uF 16V	
C613	US135100	C. CE. CHP 0. 1uF 16V	
C614	US135100	C. CE. CHP 0. 1uF 16V	
C615	UU137470	C. EL 47uF 16V	
C616	US135100	C. CE. CHP 0. 1uF 16V	
C617	UU137470	C. EL 47uF 16V	
C618	US135100	C. CE. CHP 0. 1uF 16V	
C619	UU137470	C. EL 47uF 16V	
C620	US135100	C. CE. CHP 0. 1uF 16V	
C621	UU137470	C. EL 47uF 16V	
C622	US135100	C. CE. CHP 0. 1uF 16V	
C623	UU137470	C. EL 47uF 16V	
C624	US135100	C. CE. CHP 0. 1uF 16V	
C625	UU137470	C. EL 47uF 16V	
C626	US135100	C. CE. CHP 0. 1uF 16V	
C627	UU147100	C. EL 10uF 25V	
C628	UU147100	C. EL 10uF 25V	
C629	UU147100	C. EL 10uF 25V	
C630	UU147100	C. EL 10uF 25V	
C631	UU147100	C. EL 10uF 25V	
C632	UU147100	C. EL 10uF 25V	
C633	UU147100	C. EL 10uF 25V	
C634	UU147100	C. EL 10uF 25V	
C635	UU147100	C. EL 10uF 25V	
C636	UU147100	C. EL 10uF 25V	
C637	UA653150	C. MYLAR 1500pF 50V	
C638	US135100	C. CE. CHP 0. 1uF 16V	
C639	US135100	C. CE. CHP 0. 1uF 16V	
C640	US135100	C. CE. CHP 0. 1uF 16V	
C641	US135100	C. CE. CHP 0. 1uF 16V	
C642	US135100	C. CE. CHP 0. 1uF 16V	

* New Parts

P.C.B. DSP

Schm Ref.	PART NO.	Description	Markets
C643	US135100	C. CE. CHP	0. 1uF 16V
C644	UA652680	C. MYLAR	680pF 50V
C645	UA652680	C. MYLAR	680pF 50V
C646	UA652150	C. MYLAR	150pF 50V
C647	UA652150	C. MYLAR	150pF 50V
C648	UU147100	C. EL	10uF 25V
C649	UU147100	C. EL	10uF 25V
C650	UU147100	C. EL	10uF 25V
C651	UU147100	C. EL	10uF 25V
C652	UU147100	C. EL	10uF 25V
C653	UU147100	C. EL	10uF 25V
C654	UA652150	C. MYLAR	150pF 50V
C655	UA652150	C. MYLAR	150pF 50V
C656	US135100	C. CE. CHP	0. 1uF 16V
C657	US135100	C. CE. CHP	0. 1uF 16V
C658	UU147100	C. EL	10uF 25V
C659	UU147100	C. EL	10uF 25V
C660	UA652470	C. MYLAR	470pF 50V
C661	UA652470	C. MYLAR	470pF 50V
C662	UA652470	C. MYLAR	470pF 50V
C663	UA652470	C. MYLAR	470pF 50V
C664	UA652470	C. MYLAR	470pF 50V
C665	UU147100	C. EL	10uF 25V
C666	UU147100	C. EL	10uF 25V
C667	UU147100	C. EL	10uF 25V
C668	UU147100	C. EL	10uF 25V
C669	UU147100	C. EL	10uF 25V
C670	UU147100	C. EL	10uF 25V
C671	UU147100	C. EL	10uF 25V
C672	US135100	C. CE. CHP	0. 1uF 16V
C673	UU137470	C. EL	47uF 16V
C674	UU137470	C. EL	47uF 16V
C675	UU137470	C. EL	47uF 16V
C676	UU137470	C. EL	47uF 16V
C677	US135100	C. CE. CHP	0. 1uF 16V
C678	US135100	C. CE. CHP	0. 1uF 16V
C679	US135100	C. CE. CHP	0. 1uF 16V
C680	US135100	C. CE. CHP	0. 1uF 16V
C681	US062220	C. CE. CHP	220pF 50V
C682	US062220	C. CE. CHP	220pF 50V
C683	UR866220	C. EL	2. 2uF 50V
C684	US062470	C. CE. M. CHP	470pF 50V
C686	UR817470	C. EL	47uF 6. 3V
* C687	US061300	C. CE. M. CHP	30pF 50V
C688	UR818100	C. EL	100uF 6. 3V
C689	US135100	C. CE. CHP	0. 1uF 16V
C691	US135100	C. CE. CHP	0. 1uF 16V
C692	UR818100	C. EL	100uF 6. 3V
C695	UR818100	C. EL	100uF 6. 3V
C696	UR818100	C. EL	100uF 6. 3V
C697	US135100	C. CE. CHP	0. 1uF 16V
C698	US135100	C. CE. CHP	0. 1uF 16V
C699	UR818100	C. EL	100uF 6. 3V
C700	US135100	C. CE. CHP	0. 1uF 16V
C701	US064100	C. CE. M. CHP	0. 01uF 50V
C702	US135100	C. CE. CHP	0. 1uF 16V
C703	UR818100	C. EL	100uF 6. 3V
C706	US061470	C. CE. M. CHP	47pF 50V
C707	US061470	C. CE. M. CHP	47pF 50V
C708	US135100	C. CE. CHP	0. 1uF 16V
C709	US135100	C. CE. CHP	0. 1uF 16V
C710	UR818100	C. EL	100uF 6. 3V
C711	UR818100	C. EL	100uF 6. 3V

* New Parts

Schm Ref.	PART NO.	Description	Markets
C712	UR818100	C. EL	100uF 6. 3V
C713	US061470	C. CE. M. CHP	47pF 50V
C716	US135100	C. CE. CHP	0. 1uF 16V
C717	US135100	C. CE. CHP	0. 1uF 16V
C718	US135100	C. CE. CHP	0. 1uF 16V
C719	US135100	C. CE. CHP	0. 1uF 16V
C720	UR818100	C. EL	100uF 6. 3V
C722	UR818100	C. EL	100uF 6. 3V
C723	US135100	C. CE. CHP	0. 1uF 16V
C724	UR818100	C. EL	100uF 6. 3V
C725	US135100	C. CE. CHP	0. 1uF 16V
C726	US135100	C. CE. CHP	0. 1uF 16V
C727	US135100	C. CE. CHP	0. 1uF 16V
C728	US135100	C. CE. CHP	0. 1uF 16V
C729	US135100	C. CE. CHP	0. 1uF 16V
C730	US135100	C. CE. CHP	0. 1uF 16V
C731	US135100	C. CE. CHP	0. 1uF 16V
C732	UR819100	C. EL	1000uF 6. 3V
C733	US135100	C. CE. CHP	0. 1uF 16V
C734	US062100	C. CE. M. CHP	100pF 50V
C735	US061470	C. CE. M. CHP	47pF 50V
D501	VT332900	DIODE	1SS355
D502	VT332900	DIODE	1SS355
D503	VT332900	DIODE	1SS355
D504	VV220700	DIODE. SHOT	RB501V-40
D505	VV220700	DIODE. SHOT	RB501V-40
D506	VT332900	DIODE	1SS355
D507	VT332900	DIODE	1SS355
D508	VV220700	DIODE. SHOT	RB501V-40
D509	VV220700	DIODE. SHOT	RB501V-40
D510	VV220700	DIODE. SHOT	RB501V-40
D511	VV220700	DIODE. SHOT	RB501V-40
D512	VV220700	DIODE. SHOT	RB501V-40
D513	VV220700	DIODE. SHOT	RB501V-40
D514	VV220700	DIODE. SHOT	RB501V-40
D515	VV220700	DIODE. SHOT	RB501V-40
D516	VT332900	DIODE	1SS355
D517	VT332900	DIODE	1SS355
D518	VT332900	DIODE	1SS355
D519	VT332900	DIODE	1SS355
D520	VT332900	DIODE	1SS355
D521	VT332900	DIODE	1SS355
D522	VT332900	DIODE	1SS355
D523	VT332900	DIODE	1SS355
D524	VT332900	DIODE	1SS355
D525	VT332900	DIODE	1SS355
D526	VT332900	DIODE	1SS355
D527	VT332900	DIODE	1SS355
D528	VT332900	DIODE	1SS355
D529	VT332900	DIODE	1SS355
D530	VT332900	DIODE	1SS355
D531	VT332900	DIODE	1SS355
D532	VT332900	DIODE	1SS355
D533	VT332900	DIODE	1SS355
D534	VT332900	DIODE	1SS355
D537	VT332900	DIODE	1SS355
D538	VT332900	DIODE	1SS355
IC501	XD660A00	IC	TC74HCU04AF-TP1
IC502	XD660A00	IC	TC74HCU04AF-TP1
IC503	XY120A00	IC	TC74HCT00AF(EL) NA
IC508	XW029A00	IC	AK4393-VF-E2
IC509	XF291A00	IC	uPC4570G2
IC510	X0237A00	IC	AK4527BVQ

* New Parts

P.C.B. DSP & P.C.B. VIDEO

Schm Ref.	PART NO.	Description	Markets
IC512	XZ012A00	IC TC74HCT08AF(EL)	
IC513	XR038A00	IC NJM2904M OP AMP	
IC514	X0238A00	IC YSS938-F	
IC515	XV077A00	IC MSM514260C-60JS	
IC516	XU965A00	IC uPC29M33T-E1 3.3V	
IC517	XZ003A00	IC PQ025EZ5MZP 2.5V	
IC518	XF291A00	IC uPC4570G2	
IC519	XF291A00	IC uPC4570G2	
IC520	XF291A00	IC uPC4570G2	
IC521	XF291A00	IC uPC4570G2	
IC522	XF291A00	IC uPC4570G2	
IC523	XF291A00	IC uPC4570G2	
IC524	XW029A00	IC AK4393-VF-E2	
IC525	X0594A00	IC CS493292-CLR	
IC526	X0318C00	IC XC9572XL-10TQ100C	
IC527	XW433A00	IC CY62256LL-70SNCT	
IC528	X0604A00	IC MBM29F400BC-70PFTN	
L501	V2726500	COIL 68uH	
L502	V2726500	COIL 68uH	
L503	V2726500	COIL 68uH	
L504	V2726500	COIL 68uH	
PJ501	V5715300	JACK.PIN 2P OR/OR	
Q501	VV655300	TR.DGT DTA144EKA	
Q502	VV655300	TR.DGT DTA144EKA	
Q503	VV655300	TR.DGT DTA144EKA	
Q504	VV655300	TR.DGT DTA144EKA	
Q505	VV655300	TR.DGT DTA144EKA	
Q506	VV655300	TR.DGT DTA144EKA	
Q507	VV655300	TR.DGT DTA144EKA	
Q508	VD303700	TR 2SC3326 A,B	
Q509	VV655300	TR.DGT DTA144EKA	
Q510	VD303700	TR 2SC3326 A,B	
Q511	VD303700	TR 2SC3326 A,B	
Q512	VD303700	TR 2SC3326 A,B	
Q513	VD303700	TR 2SC3326 A,B	
Q514	VD303700	TR 2SC3326 A,B	
Q515	VD303700	TR 2SC3326 A,B	
Q516	VD303700	TR 2SC3326 A,B	
Q517	VD303700	TR 2SC3326 A,B	
R533	VU224000	R.MTL.FLM 0.22Ω 1W J	
R534	HV753220	R.CAR.FP 2.2Ω 1/4W	
R535	VU224000	R.MTL.FLM 0.22Ω 1W J	
R553	HV753220	R.CAR.FP 2.2Ω 1/4W	
R555	VU224000	R.MTL.FLM 0.22Ω 1W J	
R591	HV753100	R.CAR.FP 1Ω 1/4W	
R592	HV753100	R.CAR.FP 1Ω 1/4W	
R619	HV753220	R.CAR.FP 2.2Ω 1/4W	
R626	HV753220	R.CAR.FP 2.2Ω 1/4W	
R661	HV753220	R.CAR.FP 2.2Ω 1/4W	
R662	HV753220	R.CAR.FP 2.2Ω 1/4W	
R666	HV753220	R.CAR.FP 2.2Ω 1/4W	
R671	HV753220	R.CAR.FP 2.2Ω 1/4W	
TP1	VL448600	JUMPER.TST	
TP2	VL448600	JUMPER.TST	
TP3	VL448600	JUMPER.TST	
U501	V7680700	CN.PHOT.SN 1P GP1FA512RZ	
U502	V7680700	CN.PHOT.SN 1P GP1FA512RZ	
U503	V7680700	CN.PHOT.SN 1P GP1FA512RZ	
U504	V7680700	CN.PHOT.SN 1P GP1FA512RZ	
U505	V7680800	CN.PHOT.SN 1P GP1FA512TZ	
U506	V7680800	CN.PHOT.SN 1P GP1FA512TZ	
XL503	V6931900	RESONATOR 24.576MHz DS0751SV	

* New Parts

Schm Ref.	PART NO.	Description	Markets
	V7947100	P.C.B. VIDEO V1200	UC
	V7947200	P.C.B. VIDEO V1200	RTK
	V7947300	P.C.B. VIDEO V1200	A
	V7947400	P.C.B. VIDEO V1200RDS	BG
	V7947500	P.C.B. VIDEO 5490	UC
	V7947600	P.C.B. VIDEO 5490	T
	V7947700	P.C.B. VIDEO 5490	A
	V7947900	P.C.B. VIDEO V2200	UC
	V7948000	P.C.B. VIDEO V2200	RT
	V7948100	P.C.B. VIDEO V2200	A
CB551	V7827700	SOCKET 10P TE TUC SERIES	
CB552	V7827800	SOCKET 11P TE TUC SERIES	
CB581	V7826500	CN 15P TE TUC SERIES	
CB582	VM929900	CN.BS.PIN 15P	
CB583	V7826100	CN 11P TE TUC SERIES	
CB584	VQ044500	CN.BS.PIN 11P	
CB585	V7826200	CN 12P TE TUC SERIES	
CB586	V7826200	CN 12P TE TUC SERIES	
CB587	V7826500	CN 15P TE TUC SERIES	
CB588	V7826500	CN 15P TE TUC SERIES	
CB589	V7825400	CN 4P TE TUC SERIES	
CB590	V7825500	CN 5P TE TUC SERIES	
CB591	V7826000	CN 10P TE TUC SERIES	
CB592	V7827700	SOCKET 10P TE TUC SERIES	
CB593	V7826100	CN 11P TE TUC SERIES	
CB594	V7827800	SOCKET 11P TE TUC SERIES	
CB601	V7828200	SOCKET 15P TE TUC SERIES	
CB602	V7827900	SOCKET 12P TE TUC SERIES	
CB603	V7827100	SOCKET 4P TE TUC SERIES	
CB604	VQ044300	CN.BS.PIN 7P	
CB605	V7827100	SOCKET 4P TE TUC SERIES	
CB701	V7828200	SOCKET 15P TE TUC SERIES	
CB751	V7827200	SOCKET 5P TE TUC SERIES	
CB755	V7827100	SOCKET 4P TE TUC SERIES	
CB861	V7825400	CN 4P TE TUC SERIES	
CB862	V7825400	CN 4P TE TUC SERIES	
C551	US135100	C.CE.CHP 0.1uF 16V	
C552	US135100	C.CE.CHP 0.1uF 16V	
C553	UA652470	C.MYLAR 470pF 50V	
C554	UA652470	C.MYLAR 470pF 50V	
C555	UA652470	C.MYLAR 470pF 50V	
C556	UA652470	C.MYLAR 470pF 50V	
C557	UA652470	C.MYLAR 470pF 50V	
C558	UA652470	C.MYLAR 470pF 50V	
C559	UA652470	C.MYLAR 470pF 50V	
C560	UA652470	C.MYLAR 470pF 50V	
C561	UA652470	C.MYLAR 470pF 50V	
C562	UA652470	C.MYLAR 470pF 50V	
C563	UA652470	C.MYLAR 470pF 50V	
C564	UA652470	C.MYLAR 470pF 50V	
C565	UA652470	C.MYLAR 470pF 50V	
C566	UA652470	C.MYLAR 470pF 50V	
C567	UA652470	C.MYLAR 470pF 50V	
C568	UA652470	C.MYLAR 470pF 50V	
C581	US063100	C.CE.M.CHP 1000pF 50V	
C582	US063100	C.CE.M.CHP 1000pF 50V	
C583	US064100	C.CE.M.CHP 0.01uF 50V	
C584	US063100	C.CE.M.CHP 1000pF 50V	
C585	US063100	C.CE.M.CHP 1000pF 50V	
C586	US062100	C.CE.M.CHP 100pF 50V	
C587	UR866100	C.EL 1uF 50V	
C588	UR837470	C.EL 47uF 16V	
C591	US062330	C.CE.M.CHP 330pF 50V	BG (V1200)

* New Parts

P.C.B. VIDEO

Schm Ref.	PART NO.	Description	Markets
C592	US062330	C. CE. M. CHP	BG (V1200)
C593	US062560	C. CE. CHP	BG (V1200)
C594	UR837470	C. EL	BG (V1200)
C595	UR837470	C. EL	BG (V1200)
C596	US061270	C. CE. M. CHP	BG (V1200)
C597	US061270	C. CE. M. CHP	BG (V1200)
C598	US135100	C. CE. CHP	BG (V1200)
C599	UR837470	C. EL	BG (V1200)
C601	US062100	C. CE. M. CHP	
C602	US062100	C. CE. M. CHP	
C603	US062100	C. CE. M. CHP	
C604	US062100	C. CE. M. CHP	
C605	US062100	C. CE. M. CHP	
C606	US062100	C. CE. M. CHP	
C607	US135100	C. CE. CHP	
C608	US135100	C. CE. CHP	
C609	US135100	C. CE. CHP	
C610	UR829100	C. EL	
C611	UR837470	C. EL	
C612	UM397470	C. EL	
C613	UR837100	C. EL	
C614	US135100	C. CE. CHP	(V2200)
C616	US135100	C. CE. CHP	(V2200)
C617	UM397470	C. EL	
C618	UM397470	C. EL	
C619	US062820	C. CE. CHP	ABG
C619	US063150	C. CE. M. CHP	UCRTK
C620	US062270	C. CE. M. CHP	ABG
C620	US062390	C. CE. CHP	UCRTK
C621	UM397470	C. EL	
C622	UR837470	C. EL	
C623	UR818220	C. EL	
C624	UR818220	C. EL	
C625	UM397100	C. EL	
C626	UR837470	C. EL	
C627	UR837100	C. EL	
C628	US135100	C. CE. CHP	
C629	US135100	C. CE. CHP	
C630	US060800	C. CE. CHP	
C631	UR837470	C. EL	
C632	UM397470	C. EL	
C633	US061330	C. CE. M. CHP	
C634	US064100	C. CE. M. CHP	
C635	UR837470	C. EL	
C636	UR866470	C. EL	
C637	UR818330	C. EL	
C638	US135100	C. CE. CHP	
C639	US063120	C. CE. M. CHP	
C640	US062470	C. CE. M. CHP	
C641	UR866100	C. EL	
C642	UR866100	C. EL	
C643	US060700	C. CE. CHP	
C644	US061240	C. CE. CHP	
C645	US061240	C. CE. CHP	
C646	US062220	C. CE. CHP	
C647	US062120	C. CE. CHP	
C648	UR837470	C. EL	
C650	US135100	C. CE. CHP	
C651	US135100	C. CE. CHP	
C652	US135100	C. CE. CHP	
C653	US062470	C. CE. CHP	
C701	US062100	C. CE. M. CHP	
C702	US062100	C. CE. M. CHP	

* New Parts

Schm Ref.	PART NO.	Description	Markets
C703	US062100	C. CE. M. CHP	(V2200)
C704	US062100	C. CE. M. CHP	
C705	UR837470	C. EL	
C706	UR829100	C. EL	
C707	UR837470	C. EL	
C708	US135100	C. CE. CHP	
C709	US135100	C. CE. CHP	
C710	UR837470	C. EL	
C711	UR837470	C. EL	(V2200)
C712	UR837470	C. EL	
C713	UR837470	C. EL	
C714	UR837470	C. EL	
C715	US135100	C. CE. CHP	
C751	US061240	C. CE. CHP	
C752	US061240	C. CE. CHP	
C753	US061240	C. CE. CHP	
C754	US135100	C. CE. CHP	
C755	US135100	C. CE. CHP	
C756	UR837470	C. EL	
C757	UR837470	C. EL	
C758	US064100	C. CE. M. CHP	(V2200)
C759	US064100	C. CE. M. CHP	(V2200)
C760	US064100	C. CE. M. CHP	(V2200)
C761	US064100	C. CE. M. CHP	(V2200)
C762	US064100	C. CE. M. CHP	(V2200)
C763	US064100	C. CE. M. CHP	(V2200)
C764	US064100	C. CE. M. CHP	(V2200)
C765	US064100	C. CE. M. CHP	(V2200)
D581	VU172000	DIODE. ZENR	UDZ5.6BTE-17 5.6V
D601	VT332900	DIODE	1SS355
D602	VT332900	DIODE	1SS355
D603	VT332900	DIODE	1SS355
D604	VT332900	DIODE	1SS355
D605	VT332900	DIODE	1SS355
D606	VT332900	DIODE	1SS355
D607	VT332900	DIODE	1SS355
D608	VT332900	DIODE	1SS355
D609	VT332900	DIODE	1SS355
D610	VT332900	DIODE	1SS355
G581	V8880000	TERM. GND	M3.5 RJP9899
IC581	XY534A00	IC	LC72722
IC601	XW939A00	IC	TK15420M VIDEO AMP
IC602	XL493A00	IC	TC74HC4051AP
IC603	XL493A00	IC	TC74HC4051AP
IC604	XZ830A00	IC	MM74HC4051N MULTI
IC605	XZ830A00	IC	MM74HC4051N MULTI
IC606	X2093A00	IC	MM74HC4053N MULTI
IC607	iR405300	IC	TC74HC4053AP
IC608	XD598A00	IC	TC74HCU04AFEL INV
IC609	XY443A00	IC	LA7109 6CH
IC610	XZ060A00	IC	LC74781-9798
IC611	XW416A00	IC	BU2092 SER/PAR
IC701	XW911A00	IC	LA7108M VIDEO AMP
IC702	XY549A00	IC	TC74HC4051AFEL
IC703	XY550A00	IC	MM74HC4051SJX
IC704	XY877A00	IC	MM74HC4053SJX
IC751	XY877A00	IC	MM74HC4053SJX
IC752	X0428A00	IC	OPA2652U OP AMP
IC753	X0428A00	IC	OPA2652U OP AMP
JK601	VP113600	CN. DIN	2P
JK602	VP113600	CN. DIN	2P
JK603	VP113600	CN. DIN	2P
JK604	VU245200	CN. DIN	1P

* New Parts

P.C.B. VIDEO & P.C.B. MAIN

Schm Ref.	PART NO.	Description	Markets
JK605	VQ960400	CN.DIN	1P
L581	VK267500	COIL	220uH
L602	V3233700	COIL	1.5uH
L603	V6236000	COIL	4.7uH LAV35VB4R7K
L605	V2726100	COIL	33uH
L606	VK267500	COIL	220uH
PJ551	V4199100	JACK. PIN	6P
PJ552	VJ696300	JACK. PIN	4P
PJ553	V4199100	JACK. PIN	6P
PJ553	VJ696300	JACK. PIN	4P
PJ701	V2773400	JACK. PIN	1P
PJ702	VV325000	JACK. PIN	2P
PJ703	VV325000	JACK. PIN	2P
PJ704	VV325000	JACK. PIN	2P
PJ705	V2773400	JACK. PIN	1P
PJ705	VV325000	JACK. PIN	2P
PJ751	V8143900	JACK PIN	SHIELD YKC21-4348
PN581	V3750200	PIN	L=70
Q581	iC174020	TR	2SC1740S R, S
Q582	iC181510	TR	2SC1815 Y
Q601	iC174020	TR	2SC1740S R, S
Q602	VK432900	TR	2SD1915F S, T
Q603	VD678700	TR. DGT	DTC114ES
Q604	iC174020	TR	2SC1740S R, S
Q605	iC174020	TR	2SC1740S R, S
Q606	iA101510	TR	2SA1015 Y
Q607	iC224030	TR	2SC2240 GR, BL
Q608	iC053540	TR	2SC535 A, B, C
Q609	VK432900	TR	2SD1915F S, T
Q701	iC174020	TR	2SC1740S R, S
R625	HV755330	R. CAR. FP	330Ω 1/4W
R626	HV753220	R. CAR. FP	2.2Ω 1/4W
R635	HV755470	R. CAR. FP	470Ω 1/4W
R641	HV753100	R. CAR. FP	1Ω 1/4W
R642	HV753100	R. CAR. FP	1Ω 1/4W
R643	HV755470	R. CAR. FP	470Ω 1/4W
R648	HV755470	R. CAR. FP	470Ω 1/4W
R650	HV755470	R. CAR. FP	470Ω 1/4W
R686	HV755470	R. CAR. FP	470Ω 1/4W
R688	HV753470	R. CAR. FP	4.7Ω 1/4W
R716	HV755270	R. CAR. FP	270Ω 1/4W
R717	HV753220	R. CAR. FP	2.2Ω 1/4W
R719	HV753220	R. CAR. FP	2.2Ω 1/4W
R785	HV753220	R. CAR. FP	2.2Ω 1/4W
R786	HV753220	R. CAR. FP	2.2Ω 1/4W
R851	HV754470	R. CAR. FP	47Ω 1/4W
R859	HV755120	R. CAR. FP	120Ω 1/4W
R859	HV755120	R. CAR. FP	120Ω 1/4W
ST751	V4040500	SCR. TERM	M3
SW551	VY811700	SW. SLIDE	SS029-P2022BJ6-PA6
SW551	VY811700	SW. SLIDE	SS029-P2022BJ6-PA6
XL581	V7556000	RSNR. CRYST	4.332MHz HC-49U
XL601	VV949800	RSNR. CRYST	14.31818MHz
XL601	VV949900	RSNR. CRYST	17.734475MHz
	V7950100	P. C. B.	MAIN V1200
	V7950200	P. C. B.	MAIN V1200
	V7950300	P. C. B.	MAIN V1200RDS
	V7950400	P. C. B.	MAIN 5490
	V7950500	P. C. B.	MAIN 5490
	V7950700	P. C. B.	MAIN V2200

* New Parts

Schm Ref.	PART NO.	Description	Markets
	V7950800	P. C. B.	MAIN V2200
	V7950800	P. C. B.	MAIN V2200
CB1	V7826600	CN	16P TE TUC SERIES
CB2	LB918050	CN. BS. PIN	5P
CB4	Vi878500	CN. BS. PIN	7P
CB5	VM923600	CN. BS. PIN	13P
CB7	Vi878500	CN. BS. PIN	7P
CB8	Vi878500	CN. BS. PIN	7P
CB9	Vi878500	CN. BS. PIN	7P
CB12	Vi878200	CN. BS. PIN	4P
CB13	VK026300	CN. BS. PIN	4P
CB14	Vi878000	CN. BS. PIN	2P
CB15	V7825400	CN	4P TE TUC SERIES
CB16	Vi878000	CN. BS. PIN	2P
CB17	VB858200	CN. BS. PIN	3P
CB18	Vi878300	CN. BS. PIN	5P
CB19	Vi878300	CN. BS. PIN	5P
CB20	V7825500	CN	5P TE TUC SERIES
CB21	VB390300	CN. BS. PIN	7P
CB22	VB389800	CN. BS. PIN	2P
CB23	VB389800	CN. BS. PIN	2P
C1	UU177470	C. EL	47uF 63V
C2	UU167470	C. EL	47uF 50V
C3	UU167470	C. EL	47uF 50V
C4	UU167470	C. EL	47uF 50V
C5	VR325000	C. MYLAR	100pF 100V
C6	UU147470	C. EL	47uF 25V
C7	VR325000	C. MYLAR	100pF 100V
C8	VR325000	C. MYLAR	100pF 100V
C9	UU147470	C. EL	47uF 25V
C10	VR325000	C. MYLAR	100pF 100V
C11	UU167470	C. EL	47uF 50V
C12	UU167470	C. EL	47uF 50V
C13	VK533900	C. PP	100pF 200V
C14	UU147470	C. EL	47uF 25V
C15	VK533900	C. PP	100pF 200V
C16	VK533900	C. PP	100pF 200V
C17	UU147470	C. EL	47uF 25V
C18	VK533900	C. PP	100pF 200V
C19	VK533900	C. PP	100pF 200V
C20	UU147470	C. EL	47uF 25V
C21	VK533900	C. PP	100pF 200V
C22	UU197100	C. EL	10uF 100V
C23	VK399200	C. MYLAR. ML	0.39uF 50V
C24	VK399200	C. MYLAR. ML	0.39uF 50V
C25	UA654680	C. MYLAR	0.068uF 50V
C26	UA654680	C. MYLAR	0.068uF 50V
C27	UA654680	C. MYLAR	0.068uF 50V
C30	UU197100	C. EL	10uF 100V
C31	UU197100	C. EL	10uF 100V
C32	UU197100	C. EL	10uF 100V
C33	UU197100	C. EL	10uF 100V
C34	UU166470	C. EL	4.7uF 50V
C35	UU166470	C. EL	4.7uF 50V
C36	UU166470	C. EL	4.7uF 50V
C37	UU167470	C. EL	47uF 50V
C38	UU168100	C. EL	100uF 50V
C39	VR325000	C. MYLAR	100pF 100V
C40	UU147470	C. EL	47uF 25V
C41	VR325000	C. MYLAR	100pF 100V
C44	UU18220	C. EL	220uF 6.3V
C45	UU197100	C. EL	10uF 100V
C46	UU197100	C. EL	10uF 100V
C47	UU147100	C. EL	10uF 25V

* New Parts

P.C.B. MAIN

Schm Ref.	PART NO.	Description	Markets
C48	UU137470	C. EL 47uF 16V	
C49	UA654680	C. MYLAR 0.068uF 50V	
C50	V7405600	C. EL 12000uF 63V	
C51	V7405600	C. EL 12000uF 63V	
C52	VK534100	C. PP 0.01uF 100V	
C53	VF467300	C. CE. TUBLR 0.01uF 16V	
C54	VF467300	C. CE. TUBLR 0.01uF 16V	
C55	UU168100	C. EL 100uF 50V	
C56	UU168100	C. EL 100uF 50V	
C57	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C58	VE326400	C. MYLAR.ML 0.22uF 50V	
C61	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C62	UT652100	C. PP 100pF 100V	
C63	UT652100	C. PP 100pF 100V	
C64	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C65	UA653470	C. MYLAR 4700pF 50V	RTKA
C65	UA654100	C. MYLAR 0.01uF 50V	BG
C66	UA653470	C. MYLAR 4700pF 50V	RTKABG
C67	VJ599100	C. CE. TUBLR 0.1uF 50V	
C68	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C69	UT652100	C. PP 100pF 100V	
C70	UT652100	C. PP 100pF 100V	
C71	UT652100	C. PP 100pF 100V	
C72	UT652100	C. PP 100pF 100V	
C73	VT898000	C. MYLAR 0.1uF 100V	
C74	VT898000	C. MYLAR 0.1uF 100V	
C75	UA654150	C. MYLAR 0.015uF 50V	RTKA
C75	UA654220	C. MYLAR 0.022uF 50V	BG
C76	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C77	UA654220	C. MYLAR 0.022uF 50V	RTKA
C77	UA654220	C. MYLAR 0.022uF 50V	BG
C78	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C79	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C80	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C81	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C82	UA654100	C. MYLAR 0.01uF 50V	RTKABG
C83	VF467300	C. CE. TUBLR 0.01uF 16V	
C84	UA655100	C. MYLAR 0.1uF 50V	
C85	UA655100	C. MYLAR 0.1uF 50V	
C86	VJ599100	C. CE. TUBLR 0.1uF 50V	
C87	UA654680	C. MYLAR 0.068uF 50V	
C88	UA654680	C. MYLAR 0.068uF 50V	
C89	UU168100	C. EL 100uF 50V	RTKABG
C90	UU167100	C. EL 10uF 50V	RTKABG
C92	UA655100	C. MYLAR 0.1uF 50V	
D1	VD631600	DIODE 1SS133, 176	
D2	VN008700	DIODE 1SS270A	
D3	VN008700	DIODE 1SS270A	
D4	VD631600	DIODE 1SS133, 176	
D5	VN008700	DIODE 1SS270A	
D6	VN008700	DIODE 1SS270A	
D7	VN008700	DIODE 1SS270A	
D8	VN008700	DIODE 1SS270A	
D9	VN008700	DIODE 1SS270A	
D10	VN008700	DIODE 1SS270A	
D11	VN008700	DIODE 1SS270A	
D12	VN008700	DIODE 1SS270A	
D13	VD631600	DIODE 1SS133, 176	
D14	VD631600	DIODE 1SS133, 176	
D15	VN008700	DIODE 1SS270A	
D16	VG443700	DIODE. ZENR MTZ J 33.0B 33.0V	
D18	VG442600	DIODE. ZENR MTZJ24C 24V	RTKABG
D21	VN008700	DIODE 1SS270A	

* New Parts

Schm Ref.	PART NO.	Description	Markets
D22	VG437200	DIODE. ZENR MTZJ4.7C 4.7V	
D23	VG440300	DIODE. ZENR MTZJ12C 12V	
D24	VG440300	DIODE. ZENR MTZJ12C 12V	
D25	VG440300	DIODE. ZENR MTZJ12C 12V	
D26	VG440300	DIODE. ZENR MTZJ12C 12V	
D27	VG440300	DIODE. ZENR MTZJ12C 12V	
D28	VG440300	DIODE. ZENR MTZJ12C 12V	
D29	VG440300	DIODE. ZENR MTZJ12C 12V	
D30	VG440300	DIODE. ZENR MTZJ12C 12V	
D31	VN008700	DIODE 1SS270A	
D32	VN008700	DIODE 1SS270A	
D33	VN008700	DIODE 1SS270A	
D34	VN008700	DIODE 1SS270A	
D35	VN008700	DIODE 1SS270A	
D36	iH000920	DIODE. BRG S5VB20 3.5A 200V	
D37	VN008700	DIODE 1SS270A	
D38	VS997800	DIODE 1T2	
D39	VS997800	DIODE 1T2	
D40	VS997800	DIODE 1T2	
D41	VS997800	DIODE 1T2	
G1	V8880000	TERM. GND M3.5 RJP9899	
G2	V8880000	TERM. GND M3.5 RJP9899	
HS2	VR506800	HEAT. SINK PUH16-25	
IC1	X0515A00	IC LM61C1Z THERMAL	
L1	V2604200	COIL 1uH	
L2	V2604200	COIL 1uH	
L3	VU038200	COIL 0.95uH	
L4	VU038200	COIL 0.95uH	
L5	VU038200	COIL 0.95uH	
L6	V2604200	COIL 1uH	
PJ1	VP768000	JACK. PIN 2P	
PJ2	VP768000	JACK. PIN 2P	
PJ4	VP768000	JACK. PIN 2P	
PJ5	VK437600	JACK. PIN 1P	
PN1	V3750200	PIN L=70	
PN2	V3750200	PIN L=70	
PN3	V3750200	PIN L=70	
PN4	V3750200	PIN L=70	
PN5	V3750200	PIN L=70	
Q1	VS883300	TR 2SB1565 E, F	
Q2	VP883000	TR 2SA893A D, E	
Q3	VK432900	TR 2SD1915F S, T	
Q4	VK432900	TR 2SD1915F S, T	
Q5	VK432900	TR 2SD1915F S, T	
Q6	VP883000	TR 2SA893A D, E	
Q7	VK432900	TR 2SD1915F S, T	
Q8	VK432900	TR 2SD1915F S, T	
Q9	V4096100	TR 2SC4614 S, T	
Q10	V4096000	TR 2SA1770 S, T	
Q11	V4096100	TR 2SC4614 S, T	
Q12	V4096000	TR 2SA1770 S, T	
Q13	V4096100	TR 2SC4614 S, T	
Q14	V4096000	TR 2SA1770 S, T	
Q15	V4096100	TR 2SC4614 S, T	
Q16	V4096000	TR 2SA1770 S, T	
Q17	V4096100	TR 2SC4614 S, T	
Q18	V4096000	TR 2SA1770 S, T	
Q19A	iX630850	TR 2SA1695 O, P, Y	(V1200)
Q19A	iX606460	TR 2SA1492 O, P, Y	(V2200)
Q19C	iX630860	TR 2SC4468 O, P, Y	(V1200)
Q19C	iX606470	TR 2SC3856 O, P, Y	(V2200)
Q21A	iX630850	TR 2SA1695 O, P, Y	(V1200)
Q21A	iX606460	TR 2SA1492 O, P, Y	(V2200)

* New Parts

P.C.B. MAIN

Schm Ref.	PART NO.	Description	Markets
Q21C	iX630860	TR 2SC4468 O,P,Y	(V1200)
Q21C	iX606470	TR 2SC3856 O,P,Y	(V2200)
Q23A	iX630850	TR 2SA1695 O,P,Y	(V1200)
Q23A	iX606460	TR 2SA1492 O,P,Y	(V2200)
Q23C	iX630860	TR 2SC4468 O,P,Y	(V1200)
Q23C	iX606470	TR 2SC3856 O,P,Y	(V2200)
Q25A	iX630850	TR 2SA1695 O,P,Y	(V1200)
Q25A	iX606460	TR 2SA1492 O,P,Y	(V2200)
Q25C	iX630860	TR 2SC4468 O,P,Y	(V1200)
Q25C	iX606470	TR 2SC3856 O,P,Y	(V2200)
Q27A	iX630850	TR 2SA1695 O,P,Y	(V1200)
Q27A	iX606460	TR 2SA1492 O,P,Y	(V2200)
Q27C	iX630860	TR 2SC4468 O,P,Y	(V1200)
Q27C	iX606470	TR 2SC3856 O,P,Y	(V2200)
Q29	iC181510	TR 2SC1815 Y	
Q30	VP883100	TR 2SC1890A D,E	
Q31	VP883100	TR 2SC1890A D,E	
Q32	VP883100	TR 2SC1890A D,E	
Q33	VP883100	TR 2SC1890A D,E	
Q34	VP883100	TR 2SC1890A D,E	
Q35	iA101510	TR 2SA1015 Y	
Q36	iC224030	TR 2SC2240 GR,BL	
Q37	iA097030	TR 2SA970 GR,BL	
Q38	V4096100	TR 2SC4614 S,T	
Q39	V4096000	TR 2SA1770 S,T	
Q40	VC141900	TR 2SB941 P,Q	RTKABG
Q41A	iX630850	TR 2SA1695 O,P,Y	(V1200)
Q41A	iX606460	TR 2SA1492 O,P,Y	(V2200)
Q41C	iX630860	TR 2SC4468 O,P,Y	(V1200)
Q41C	iX606470	TR 2SC3856 O,P,Y	(V2200)
Q43	iC181510	TR 2SC1815 Y	RTKABG
Q44	VP883100	TR 2SC1890A D,E	
Q45	iC181510	TR 2SC1815 Y	
Q46	iC181510	TR 2SC1815 Y	
Q47	iC181510	TR 2SC1815 Y	
Q48	iC287820	TR 2SC2878 A,B	
Q49	iC287820	TR 2SC2878 A,B	
R3	HV755100	R. CAR. FP 100Ω 1/4W	
R4	HV755100	R. CAR. FP 100Ω 1/4W	
R5	HV755100	R. CAR. FP 100Ω 1/4W	
R6	HV755100	R. CAR. FP 100Ω 1/4W	
R7	HV755100	R. CAR. FP 100Ω 1/4W	
R8	V3946100	R. MTL. OXD 2.7KΩ 0.5W	
R9	V3945100	R. MTL. OXD 390Ω 0.5W	
R10	V3945500	R. MTL. OXD 820Ω 0.5W	(V1200)
R10	V3945600	R. MTL. OXD 1KΩ 0.5W	(V2200)
R11	VP941600	R. MTL. OXD 5.6KΩ 1W	
R12	VP941600	R. MTL. OXD 5.6KΩ 1W	
R13	V3946100	R. MTL. OXD 2.7KΩ 0.5W	
R14	V3945100	R. MTL. OXD 390Ω 0.5W	
R15	V3945500	R. MTL. OXD 820Ω 0.5W	(V1200)
R15	V3945600	R. MTL. OXD 1KΩ 0.5W	(V2200)
R16	VP941600	R. MTL. OXD 5.6KΩ 1W	
R17	VP941600	R. MTL. OXD 5.6KΩ 1W	
R19	V3946100	R. MTL. OXD 2.7KΩ 0.5W	
R20	V3945100	R. MTL. OXD 390Ω 0.5W	
R21	V3945500	R. MTL. OXD 820Ω 0.5W	(V1200)
R21	V3945600	R. MTL. OXD 1KΩ 0.5W	(V2200)
R22	VP941600	R. MTL. OXD 5.6KΩ 1W	
R23	VP941600	R. MTL. OXD 5.6KΩ 1W	
R24	V3946100	R. MTL. OXD 2.7KΩ 0.5W	
R25	V3945100	R. MTL. OXD 390Ω 0.5W	
R26	V3945500	R. MTL. OXD 820Ω 0.5W	(V1200)

* New Parts

Schm Ref.	PART NO.	Description	Markets
R26	V3945600	R. MTL. OXD 1KΩ 0.5W	(V2200)
R27	VP941600	R. MTL. OXD 5.6KΩ 1W	
R28	VP941600	R. MTL. OXD 5.6KΩ 1W	
R29	V3946100	R. MTL. OXD 2.7KΩ 0.5W	
R30	V3945100	R. MTL. OXD 390Ω 0.5W	
R31	V3945500	R. MTL. OXD 820Ω 0.5W	(V1200)
R31	V3945600	R. MTL. OXD 1KΩ 0.5W	(V2200)
R32	VP941600	R. MTL. OXD 5.6KΩ 1W	
R33	VP941600	R. MTL. OXD 5.6KΩ 1W	
R34	V3945600	R. MTL. OXD 1KΩ 0.5W	(V1200)
R34	V3945500	R. MTL. OXD 820Ω 0.5W	(V2200)
R35	V3945600	R. MTL. OXD 1KΩ 0.5W	(V1200)
R35	V3945500	R. MTL. OXD 820Ω 0.5W	(V2200)
R37	V3945600	R. MTL. OXD 1KΩ 0.5W	(V1200)
R37	V3945500	R. MTL. OXD 820Ω 0.5W	(V2200)
R38	HV754100	R. CAR. FP 10Ω 1/4W	
R39	V3945600	R. MTL. OXD 1KΩ 0.5W	(V1200)
R39	V3945500	R. MTL. OXD 820Ω 0.5W	(V2200)
R40	V3945600	R. MTL. OXD 1KΩ 0.5W	(V1200)
R40	V3945500	R. MTL. OXD 820Ω 0.5W	(V2200)
R41	V3944800	R. MTL. OXD 220Ω 0.5W	
R42	V3944800	R. MTL. OXD 220Ω 0.5W	
R44	V3944800	R. MTL. OXD 220Ω 0.5W	
R45	VP939700	R. MTL. FLM 4.7Ω 1W	
R46	VP939700	R. MTL. FLM 4.7Ω 1W	
R47	VP939700	R. MTL. FLM 4.7Ω 1W	
R48	VP939700	R. MTL. FLM 4.7Ω 1W	
R50	V3944800	R. MTL. OXD 220Ω 0.5W	
R51	V3944800	R. MTL. OXD 220Ω 0.5W	
R52	VP939700	R. MTL. FLM 4.7Ω 1W	
R53	VP939700	R. MTL. FLM 4.7Ω 1W	
R54	VP939700	R. MTL. FLM 4.7Ω 1W	
R55	VP939700	R. MTL. FLM 4.7Ω 1W	
R56	VP939700	R. MTL. FLM 4.7Ω 1W	
R57	VP939700	R. MTL. FLM 4.7Ω 1W	
R58	HV756150	R. CAR. FP 1.5KΩ 1/4W	
R59	VU981700	R. MTL. PLAT 0.22Ω+0.22 3W	
R60	VU981700	R. MTL. PLAT 0.22Ω+0.22 3W	
R61	V3873200	R. WW 0.22Ω 3W	
R64	V3873200	R. WW 0.22Ω 3W	
R65	V3873200	R. WW 0.22Ω 3W	
R84	VP939800	R. MTL. OXD 10Ω 1W	
R86	VP939800	R. MTL. OXD 10Ω 1W	
R88	VP939800	R. MTL. OXD 10Ω 1W	
R93	HV754100	R. CAR. FP 10Ω 1/4W	
R94	HV754100	R. CAR. FP 10Ω 1/4W	
R98	HV754100	R. CAR. FP 10Ω 1/4W	
R100	HV754100	R. CAR. FP 10Ω 1/4W	
R101	HV754100	R. CAR. FP 10Ω 1/4W	
R105	HV753100	R. CAR. FP 1Ω 1/4W	
R106	HV753100	R. CAR. FP 1Ω 1/4W	
R107	HV756100	R. CAR. FP 1KΩ 1/4W	
R108	HV755100	R. CAR. FP 100Ω 1/4W	
R110	HV755100	R. CAR. FP 100Ω 1/4W	
R112	V3946100	R. MTL. OXD 2.7KΩ 0.5W	
R113	V3945100	R. MTL. OXD 390Ω 0.5W	
R114	V3945600	R. MTL. OXD 1KΩ 0.5W	
R115	VP941600	R. MTL. OXD 5.6KΩ 1W	
R116	VP941600	R. MTL. OXD 5.6KΩ 1W	
R117	V3945500	R. MTL. OXD 820Ω 0.5W	
R119	V3944800	R. MTL. OXD 220Ω 0.5W	
R120	VP939700	R. MTL. FLM 4.7Ω 1W	
R121	VP939700	R. MTL. FLM 4.7Ω 1W	

* New Parts

P.C.B. MAIN & P.C.B. POWER

Schm Ref.	PART NO.	Description	Markets
R122	VK187800	R. FUS	100Ω 1/4W
R122	VK187800	R. FUS	100Ω 1/4W
R123	HV756470	R. CAR. FP	4.7KΩ 1/4W
⚠ R126	VU981700	R. MTL. PLAT	0.22Ω +0.22 3W
⚠ R127	HV756330	R. CAR. FP	3.3KΩ 1/4W
R130	HV753100	R. CAR. FP	1Ω 1/4W
R132	HV754100	R. CAR. FP	10Ω 1/4W
R132	HV754100	R. CAR. FP	10Ω 1/4W
R139	VP939800	R. MTL. OXD	10Ω 1W
R141	HV754100	R. CAR. FP	10Ω 1/4W
R143	VP940900	R. MTL. OXD	560Ω 1W
R144	VP940900	R. MTL. OXD	560Ω 1W
R147	VP940900	R. MTL. OXD	560Ω 1W
R148	VP940900	R. MTL. OXD	560Ω 1W
⚠ R185	HV753100	R. CAR. FP	1Ω 1/4W
⚠ R186	HV753100	R. CAR. FP	1Ω 1/4W
R187	VP939800	R. MTL. OXD	10Ω 1W
R188	VP939800	R. MTL. OXD	10Ω 1W
R189	VP939800	R. MTL. OXD	10Ω 1W
RY3	V6322600	RELAY	DC DH24D2-OT(M)-SL
RY4	V6322600	RELAY	DC DH24D2-OT(M)-SL
RY5	V6322600	RELAY	DC DH24D2-OT(M)-SL
RY6	V6322600	RELAY	DC DH24D2-OT(M)-SL
ST1	V4040500	SCR. TERM	M3
ST2	V4040500	SCR. TERM	M3
⚠ SW1	VZ075500	SW. SLIDE	SL14-22AM5F
TE1	V5912200	TERM. SP	8P LTS0810
TE1	V5912300	TERM. SP	6P LTS0810
TE2	V5912200	TERM. SP	8P LTS0810
TE2	V5912300	TERM. SP	6P LTS0810
	V5995800	PLATE. GND	
	V2128100	SCR. BW. HD	3x12-8 MFZN2Y
	EP600140	SCR. BND. HD	3x10 MFZN2BL
	V7945500	P. C. B.	POWER V1200
	V7945600	P. C. B.	POWER V1200
	V7945700	P. C. B.	POWER V1200
	V7945800	P. C. B.	POWER V1200
	V7945900	P. C. B.	POWER V1200RDS
	V7946000	P. C. B.	POWER V1200RDS
	V8024100	P. C. B.	POWER 5490
	V8024200	P. C. B.	POWER 5490
	V8024500	P. C. B.	POWER 5490
	V7946200	P. C. B.	POWER V2200
	V7946300	P. C. B.	POWER V2200
	V7946400	P. C. B.	POWER V2200
	V7946500	P. C. B.	POWER V2200
CB201	V7827100	SOCKET	4P TE TUC SERIES
CB204	VP206500	HOLDER. FUS	EYF-52BCT
CB205	VP206500	HOLDER. FUS	EYF-52BCT
CB206	VG879900	CN. BS. PIN	2P
CB207	VP206500	HOLDER. FUS	EYF-52BCT
CB208	VP206500	HOLDER. FUS	EYF-52BCT
CB209	VP206500	HOLDER. FUS	EYF-52BCT
CB210	VP206500	HOLDER. FUS	EYF-52BCT
CB211	VB858800	CN. BS. PIN	9P
CB212	VQ044900	CN. BS. PIN	19P
CB213	V7827200	SOCKET	5P TE TUC SERIES
CB215	V7828300	SOCKET	16P TE TUC SERIES
CB216	VB389800	CN. BS. PIN	2P RTKABG
CB217	V6561200	AC INLET	2P M1908-G

* New Parts

Schm Ref.	PART NO.	Description	Markets
CB218	VQ584900	CN. BS. PIN	7P
CB219	VQ584900	CN. BS. PIN	7P
CB851	VQ044500	CN. BS. PIN	11P
CB852	VQ044400	CN. BS. PIN	9P
C201	UR848470	C. EL	470uF 25V
C202	UU147100	C. EL	10uF 25V
C202	UU147100	C. EL	10uF 25V
C203	UR897100	C. EL	10uF 100V
C204	UU167100	C. EL	10uF 50V
C206	UA655100	C. MYLAR	0.1uF 50V
C207	UA655100	C. MYLAR	0.1uF 50V
C208	UA655100	C. MYLAR	0.1uF 50V
C209	UA655100	C. MYLAR	0.1uF 50V
C210	UU149680	C. EL	6800uF 25V
C211	UU149330	C. EL	3300uF 25V
C212	UU13A100	C. EL	10000uF 16V
C213	UU13A100	C. EL	10000uF 16V
C214	UU13A100	C. EL	10000uF 16V
C215	UU139680	C. EL	6800uF 16V
C216	Vi716700	C. MYLAR	0.01uF 50V
C217	VL884600	C. PP	0.01uF 100V
C218	Vi716700	C. MYLAR	0.01uF 50V
C219	UU147100	C. EL	10uF 25V
C220	UU13A100	C. EL	10000uF 16V
C221	UU13A100	C. EL	10000uF 16V
⚠ C222	V6185300	C. CE. SAFTY	0.01uF 275V
C223	UU138100	C. EL	100uF 16V
C224	UU147100	C. EL	10uF 25V
C225	UU147100	C. EL	10uF 25V
C226	UU147100	C. EL	10uF 25V
C227	UU138100	C. EL	100uF 16V
C228	UU147100	C. EL	10uF 25V
C229	UU147100	C. EL	10uF 25V
C230	UU138100	C. EL	100uF 16V
C231	UU138100	C. EL	100uF 16V
C232	UU138100	C. EL	100uF 16V
C233	UU138100	C. EL	100uF 16V
C234	UU147100	C. EL	10uF 25V
C235	UU147100	C. EL	10uF 25V
C236	UU147100	C. EL	10uF 25V
C237	UU147100	C. EL	10uF 25V
C238	UU147100	C. EL	10uF 25V
C239	UU147100	C. EL	10uF 25V
C240	VK534000	C. PP	220pF 200V
C241	UU177220	C. EL	22uF 63V
C242	UR819100	C. EL	1000uF 6.3V
C243	UR819100	C. EL	1000uF 6.3V
C244	VQ462600	C. MYLAR	220pF 50V
C244	VQ645600	C. MYLAR	100pF 50V
C245	VQ462600	C. MYLAR	220pF 50V
C246	VQ462600	C. MYLAR	220pF 50V
C246	VQ645600	C. MYLAR	100pF 50V
C247	VQ462600	C. MYLAR	220pF 50V
C248	VQ462600	C. MYLAR	220pF 50V
C248	VQ645600	C. MYLAR	100pF 50V
C249	UA652220	C. MYLAR	220pF 50V
C250	VQ462600	C. MYLAR	220pF 50V
C250	VQ462600	C. MYLAR	220pF 50V
C250	VQ645600	C. MYLAR	100pF 50V
C251	UA652220	C. MYLAR	220pF 50V
C252	VQ462600	C. MYLAR	220pF 50V
C252	VQ645600	C. MYLAR	100pF 50V
C253	VQ462600	C. MYLAR	220pF 50V

* New Parts

P.C.B. POWER

Schm Ref.	PART NO.	Description	Markets
C254	VQ462600	C. MYLAR 220pF 50V	RTKABG
C254	VQ645600	C. MYLAR 100pF 50V	UC
C255	UA652220	C. MYLAR 220pF 50V	
C256	UU138100	C. EL 100uF 16V	
C257	UU177220	C. EL 22uF 63V	
C258	UA653100	C. MYLAR 1000pF 50V	
C259	VQ463300	C. PP 22pF 630V	
C260	UU168100	C. EL 100uF 50V	
C261	UA653100	C. MYLAR 1000pF 50V	
C262	VQ463300	C. PP 22pF 630V	
C263	UU168100	C. EL 100uF 50V	
C264	UA653100	C. MYLAR 1000pF 50V	
C265	VS696700	C. CE 33pF 500V	
C266	UU157470	C. EL 47uF 35V	
C267	UA653100	C. MYLAR 1000pF 50V	
C268	VS696700	C. CE 33pF 500V	
C269	UU157470	C. EL 47uF 35V	
C270	UA653100	C. MYLAR 1000pF 50V	
C271	VQ245400	C. PP 33pF 200V	
C272	UU157470	C. EL 47uF 35V	
C273	UA653100	C. MYLAR 1000pF 50V	
C274	VS696700	C. CE 33pF 500V	
C275	UU157470	C. EL 47uF 35V	
C851	VJ599100	C. CE. TUBLR 0. 1uF 50V	UCA
C852	VF467000	C. CE. TUBLR 1000pF 50V	
D201	VD631600	DIODE 1SS133, 176	RTK
D201	VD631600	DIODE 1SS133, 176	RTK
D202	VS997800	DIODE 1T2	
D202	VS997800	DIODE 1T2	
D203	VS997800	DIODE 1T2	
D204	VS997800	DIODE 1T2	
D205	VS997800	DIODE 1T2	
D206	VS997800	DIODE 1T2	
D207	VG439900	DIODE. ZENR MTZJ11B 11V	RTK
D207	VG439900	DIODE. ZENR MTZJ11B 11V	
D208	V4269600	DIODE. BRG D2SBA20 1. 5A 200V	
D209	V4269600	DIODE. BRG D2SBA20 1. 5A 200V	
D210	VD631600	DIODE 1SS133, 176	
D211	VD631600	DIODE 1SS133, 176	
D212	VG440300	DIODE. ZENR MTZJ12C 12V	UC (V1200)
D213	VG439100	DIODE. ZENR MTZJ9. 1A 9. 1V	EX
D214	VG440300	DIODE. ZENR MTZJ12C 12V	RTKABG
D215	VG440100	DIODE. ZENR MTZJ12A 12V	RTA (V2200)
D215	VG441600	DIODE. ZENR MTZJ20A 20V	UC (V2200)
D215	VG440800	DIODE. ZENR MTZJ15B 15V	
D215	VG441600	DIODE. ZENR MTZJ20A 20V	
D216	VD631600	DIODE 1SS133, 176	UCA
D217	VD631600	DIODE 1SS133, 176	U
D851	VD631600	DIODE 1SS133, 176	G
F201	VS823300	FUSE T8. 0A 125V	ABG
F201	VT942900	FUSE TH2. 5A 250V	UCRTK
F202	KB000790	FUSE T4. 0A 250V	RTK
F202	VS823300	FUSE T8. 0A 125V	
F203	KB000790	FUSE T4. 0A 250V	
IC201	XJ607A00	IC NJM7805FA 5V	
IC202	XJ607A00	IC NJM7805FA 5V	
IC203	XJ602A00	IC NJM78M12FA	
IC204	XD343A00	IC NJM79M12FA	
IC205	XJ607A00	IC NJM7805FA 5V	
IC206	XE436A00	IC NJM79M05FA	
JK851	VJ726800	JACK. MNI	UCA
JK852	VJ726800	JACK. MNI	UCA
JK853	VJ726800	JACK. MNI	UCA

* New Parts

Schm Ref.	PART NO.	Description	Markets
L201	VP133800	FER. BEAD	
PN2	V3750200	PIN L=70	
PN3	V3750200	PIN L=70	
PN4	V3750200	PIN L=70	
PN851	V3750200	PIN L=70	
Q201	VR510800	TR 2SD2396 J, K	RTK
Q202	VR510800	TR 2SD2396 J, K	RTK
Q203	iE102620	FET 2SK246 Y	RTK
Q204	iC174020	TR 2SC1740S R, S	
Q205	VR510800	TR 2SD2396 J, K	
Q206	VP883100	TR 2SC1890A D, E EX	
Q206	VP883100	TR 2SC1890A D, E	
Q207	VP883100	TR 2SC1890A D, E	
Q208	VP883100	TR 2SC1890A D, E	
Q209	VP883100	TR 2SC1890A D, E	
Q210	VP883100	TR 2SC1890A D, E	
Q211	VP883100	TR 2SC1890A D, E	
Q212	VP883100	TR 2SC1890A D, E	
Q213	VP883100	TR 2SC1890A D, E	
Q214	V3966800	TR 2SB949 O, Y	
Q215	VP883100	TR 2SC1890A D, E	
Q216	V3966800	TR 2SB949 O, Y	
Q217	VP883100	TR 2SC1890A D, E	
Q218	V3966800	TR 2SB949 O, Y	
Q219	VP883100	TR 2SC1890A D, E	
Q220	V3966800	TR 2SB949 O, Y	
Q221	VP883100	TR 2SC1890A D, E	
Q222	V3966800	TR 2SB949 O, Y	
Q223	VP883100	TR 2SC1890A D, E	
Q224	V3966800	TR 2SB949 O, Y	
Q225	VP883100	TR 2SC1890A D, E	
R209	V6730000	R. CAR. 2. 2MΩ 1/2W	UC
R210	VP939500	R. MTL. FLM 1Ω 1W	
R211	VP939500	R. MTL. FLM 1Ω 1W	
R212	HV753100	R. CAR. FP 1Ω 1/4W	
R213	HV753100	R. CAR. FP 1Ω 1/4W	
R214	VP939500	R. MTL. FLM 1Ω 1W	
R215	VP939500	R. MTL. FLM 1Ω 1W	
R248	HV754100	R. CAR. FP 10Ω 1/4W	
R249	HV756470	R. CAR. FP 4. 7KΩ 1/4W	
R252	HV754470	R. CAR. FP 47Ω 1/4W	
R258	HV754470	R. CAR. FP 47Ω 1/4W	
R264	HV754470	R. CAR. FP 47Ω 1/4W	
R270	HV754470	R. CAR. FP 47Ω 1/4W	
R276	HV754470	R. CAR. FP 47Ω 1/4W	
R282	HV754470	R. CAR. FP 47Ω 1/4W	
RY201	V6017400	RELAY DC SDT-S-112LMR2	URTKABG
RY201	V6434900	RELAY DC DLS12D1-0(M)	C
ST2	V4040500	SCR. TERM M3	
ST3	V4040500	SCR. TERM M3	
ST4	V4040500	SCR. TERM M3	UC
ST851	V4040500	SCR. TERM M3	
ST852	V4040500	SCR. TERM M3	
SW202	V7182300	VOLT. SELCT R8140213	RTK
T201	XZ228A00	TRANS. PWR	UC
T201	XZ229A00	TRANS. PWR	RTK
T201	XZ230A00	TRANS. PWR	A
T201	XZ231A00	TRANS. PWR	BG
TE201	V5867400	OUTLET. AC 2P AC-182-GB-11V	RTK
TE201	VT915000	OUTLET. AC 2P	A
TE201	VU543100	OUTLET. AC 2P	UC
TE201	VU543300	OUTLET. AC 1P	B
TE201	VU543400	OUTLET. AC 2P	G

* New Parts

RX-V1200/RX-V1200RDS/HTR-5490 MECHANICAL PARTS

Ref. No.	PART NO.	Description	Remarks	Markets
*	1-1	V7619300 FRONT PANEL	V1200BL	
*	1-1	V7619400 FRONT PANEL	V1200GD	
*	1-1	V7619600 FRONT PANEL	V1200RDSBL	
*	1-1	V7619700 FRONT PANEL	V1200RDSGD	
*	1-1	V7619900 FRONT PANEL	V1200RDSTI	
*	1-1	V7620300 FRONT PANEL	5490GD	
*	1-1	V7620200 FRONT PANEL	5490BL	
	1-4	V6003800 ESCUTCHEON/POWER	V1200BL, 5490BL	
	1-4	V6003900 ESCUTCHEON/POWER	V1200GD, 5490GD	
	1-4	V6004000 ESCUTCHEON/POWER	V1200TI	
	1-5	V6004100 ESCUTCHEON/INPUT	V1200BL, 5490BL	
	1-5	V6004200 ESCUTCHEON/INPUT	V1200GD, 5490GD	
	1-5	V6004300 ESCUTCHEON/INPUT	V1200TI	
	1-6	V6004400 ESCUTCHEON/D5		
	1-7	V6034100 EMBLEM	V1200BL, V1200TI	
	1-7	V6034200 EMBLEM	V1200GD, 5490G/B	
*	1-9	V7622500 ESCUTCHEON/TC	V1200BL, 5490BL	
*	1-9	V7622600 ESCUTCHEON/TC	V1200GD, 5490GD	
*	1-9	V7622800 ESCUTCHEON/TC	V1200TI	
*	2-1	V7951000 P.C.B. ASS'Y	OPERATION	UCA
*	2-1	V7951100 P.C.B. ASS'Y	OPERATION	BG
*	2-1	V7950900 P.C.B. ASS'Y	OPERATION	RTK
	2-11	MF207350 S FLEXIBLE FLAT CABLE	7P 350mm	
	2-12	MF117160 FLEXIBLE FLAT CABLE	17P 160mm	
*	2-13	MF219250 S FLEXIBLE FLAT CABLE	19P 250mm P=1.25	
	2-22	V6000000 SUB PANEL/CASE	V1200BL, 5490BL	
	2-22	V6019600 SUB PANEL/CASE	V1200RDSBL	
	2-22	V6000100 SUB PANEL/CASE	V1200GD, 5490GD	
	2-22	V6019700 SUB PANEL/CASE	V1200RDSGD	
	2-22	V6019800 SUB PANEL/CASE	V1200RDSTI	
*	2-25	V7794700 BUTTON P/S	V1200BL	
*	2-25	V7794800 BUTTON P/S	V1200GD	
*	2-25	V7794900 BUTTON P/S	V1200TI, 5490GD	
*	2-25	V7795000 BUTTON P/S	5490BL	
	2-26	V6000400 BUTTON/INPUT	V1200GD	
	2-26	V6000500 BUTTON/INPUT	V1200TI, 5490GD	
	2-26	V6000300 BUTTON/INPUT	V1200BL, 5490BL	
	2-27	V6004500 ESCUTCHEON, VOL	V1200BL, 5490BL	
	2-27	V6004600 ESCUTCHEON, VOL	V1200GD	
	2-27	V6004700 ESCUTCHEON, VOL	V1200TI, 5490GD	
*	2-28	V7621500 PANEL, LID	V1200BL, 5490BL	
*	2-28	V7621800 PANEL, LID	V1200TI	
*	2-28	V7621600 PANEL, LID	V1200GD, 5490GD	
*	2-29	V7795100 PLATE, SP	V1200BL	
*	2-29	V7795400 PLATE, SP	V1200RDSBL	
*	2-29	V7795600 PLATE, SP	V1200RDSTI	
*	2-29	V7795300 PLATE, SP	5490BL	
*	2-29	V7795200 PLATE, SP	V1200GD, 5490GD	
*	2-29	V7795500 PLATE, SP	V1200RDSGD	
	2-30	V6005100 HINGE, L	V1200GD, 5490GD	
	2-30	V6005200 HINGE, L	V1200TI	
	2-30	V6005000 HINGE, L	V1200BL, 5490BL	
	2-31	V6005300 HINGE, R	V1200BL, 5490BL	

* New Parts

Ref. No.	PART NO.	Description		Remarks	Markets
2-31	V6005400	HINGE, R		V1200GD, 5490GD	
2-31	V6005500	HINGE, R		V1200TI	
2-32	V4593300	SPRING, LID			
2-33	VZ830300	DAMPER, GEAR	15G		
2-34	VQ368600	PUSH RIVET	P3555-B		
2-36	VY940400	CUSHION, LID	T=0.8		
2-37	VV982000	DAMPER	1x12x12		
2-52	VN413300	BIND HEAD BONDING B-T. SCREW	3x8 MFZN2BL		
2-54	VG893800	BIND HEAD P-TITE SCREW	2x6 MFZN2BL		
2-55	VG863900	BIND HEAD TAPPING SCREW	2.6x6 MFZN2BL		
2-56	EP630290	BIND HEAD P-TITE SCREW	3x6 MFC2BL		
2-57	EP600250	BIND HEAD B-TITE SCREW	3x8 MFZN2Y		
* 2-58	V8205900	SHEET/SHIELD			
2-60	VJ204800	PW HEAD S-TITE SCREW	3x6-8 MFC2BL		
* 3-1	V7950100	P.C.B. ASS'Y	MAIN	V1200	UC
* 3-1	V7950400	P.C.B. ASS'Y	MAIN	5490	UC
* 3-1	V7950300	P.C.B. ASS'Y	MAIN	V1200RDS	BG
* 3-1	V7950200	P.C.B. ASS'Y	MAIN	V1200	RTKA
* 3-1	V7950500	P.C.B. ASS'Y	MAIN	5490	T
3-8	MF113250	FLEXIBLE FLAT CABLE	13P 250mm		
3-22	VV849300	SHEET	19x24		
3-23	V5454200	DAMPER	2/10/260		
3-25	VQ368600	PUSH RIVET	P3555-B		
* 3-27	V8152100	SHEET			
3-31	VK173200	SCREW, TRANSISTOR	3x15 SP MFC2		
3-33	V7669300	PW HEAD B-TITE SCREW	3x8-8 MFC2		
3-34	VB770200	PW HEAD P-TITE SCREW	3x10-8 MFC2		
3-35	EP630210	BIND HEAD S-TITE SCREW	3x6 MFZN2BL		
* 6	V7945500	P.C.B. ASS'Y	POWER	V1200	U
* 6	V7945600	P.C.B. ASS'Y	POWER	V1200	C
* 6	V7945700	P.C.B. ASS'Y	POWER	V1200, 5490	RTK
* 6	V7945800	P.C.B. ASS'Y	POWER	V1200	A
* 6	V7945900	P.C.B. ASS'Y	POWER	V1200	B
* 6	V7946000	P.C.B. ASS'Y	POWER	V1200	G
* 6	V8024100	P.C.B. ASS'Y	POWER	5490	U
* 6	V8024200	P.C.B. ASS'Y	POWER	5490	C
* 6	V8024500	P.C.B. ASS'Y	POWER	5490	A
* 7	V7946700	P.C.B. ASS'Y	DSP	V1200, 5490	
* 8	V7944400	P.C.B. ASS'Y	FUNCTION	V1200	UC
* 8	V7944500	P.C.B. ASS'Y	FUNCTION	V1200, 5490	RTK
* 8	V7944600	P.C.B. ASS'Y	FUNCTION	V1200	A
* 8	V7944700	P.C.B. ASS'Y	FUNCTION	V1200RDS	BG
* 8	V7944800	P.C.B. ASS'Y	FUNCTION	5490	UC
* 8	V7944900	P.C.B. ASS'Y	FUNCTION	5490	A
* 9	V7947100	P.C.B. ASS'Y	VIDEO	V1200	UC
* 9	V7947200	P.C.B. ASS'Y	VIDEO	V1200	RTK
* 9	V7947300	P.C.B. ASS'Y	VIDEO	V1200	A
* 9	V7947400	P.C.B. ASS'Y	VIDEO	V1200RDS	BG
* 9	V7947500	P.C.B. ASS'Y	VIDEO	5490	UC
* 9	V7947600	P.C.B. ASS'Y	VIDEO	5490	T
* 9	V7947700	P.C.B. ASS'Y	VIDEO	5490	A
11	V7424300	AM/FM TUNER	FAE350-A10F UCRTK		UCRTK
11	V7424400	AM/FM TUNER	FAE404-E10F ABGL		ABG

* New Parts

	Ref. No.	PART NO.	Description	Remarks	Markets
* ⚠	14	X0464A00	POWER TRANSFORMER		U
* ⚠	14	X0465A00	POWER TRANSFORMER		C
* ⚠	14	X0466A00	POWER TRANSFORMER		RTK
* ⚠	14	X0467A00	POWER TRANSFORMER		A
* ⚠	14	X0468A00	POWER TRANSFORMER		BG
⚠	16	V2296800	POWER CORD ASS'Y		A
⚠	16	V2363800	POWER CORD ASS'Y	5490	UC
* ⚠	16	V8013000	POWER CORD ASS'Y		K
⚠	16	VN363700	POWER CORD ASS'Y		G
⚠	16	VV437300	POWER CORD ASS'Y		B
⚠	16	VZ542500	POWER CORD ASS'Y		RT
	17	V2438700	CORD STOPPER	10P1	
	21	VZ625600	BINDING TIE	SE140 L=140	
	22	VV272500	DC FAN MOTOR	2410ML-05W-B20-L00	RTKABG
	25	MF111100	FLEXIBLE FLAT CABLE	11P 100mm	
	27	MF115100	FLEXIBLE FLAT CABLE C&C	15P 100mm	
*	28	MF119160	FLEXIBLE FLAT CABLE	19P 160mm P=1.25	
	29	MF131100	FLEXIBLE FLAT CABLE	31P 100mm	
	31	Vi491100	FERRITE CORE	BP53RB19012080M	
*	101	V7640600	TOP COVER	BL	
*	101	V7640700	TOP COVER	GD	
*	101	V7640800	TOP COVER	TI	
*	103	V7617300	REAR PANEL	V1200	U
*	103	V7617400	REAR PANEL	V1200	C
*	103	V7617500	REAR PANEL	V1200	RTK
*	103	V7617600	REAR PANEL	V1200	A
*	103	V7617900	REAR PANEL	V1200RDS	B
*	103	V7618000	REAR PANEL	V1200RDS	G
*	103	V7618900	REAR PANEL	5490	U
*	103	V7619000	REAR PANEL	5490	C
*	103	V7619100	REAR PANEL	5490	T
*	103	V7619200	REAR PANEL	5490	A
*	117	V7623000	BRACKET/FAN		RTKABG
*	118	V7622900	DUCT/FAN		RTKABG
	119	VQ775900	GROUND PLATE		
	120	V0042500	LEG	D60xH21	V1200GD,5490GD
	120	VS025000	LEG	D60xH21	V1200BL,V1200TI
	120	VV544300	LEG	D60xH21	5490BL
	132	V6002200	KNOB D43		5490BL
	132	V6002300	KNOB D43		5490GD
	132	V6068000	KNOB/D43		V1200BL
	132	V6068100	KNOB/D43		V1200GD
	132	V6077800	KNOB D43		V1200TI
	133	V6001300	KNOB D20		BL
	133	V6001400	KNOB D20		GD
	133	V6001500	KNOB D20		TI
	136	VQ368600	PUSH RIVET	P3555-B	
*	142	V7796200	SHEET, WINDOW		
	143	V6002500	PLATE/SIDE L		BL
	143	V6002700	PLATE/SIDE L		GD
	143	V6002800	PLATE/SIDE L		TI
	144	V6002900	PLATE/SIDE R		BL
	144	V6003000	PLATE/SIDE R		GD

* New Parts

	Ref. No.	PART NO.	Description	Remarks	Markets
	144	V6003100	PLATE/SIDE R	TI	
	150	V8466300	COVER/AC OUTLETS		K
	161	VN413300	BIND HEAD BONDING B-T. SCREW	3x8 MFZN2BL	
	164	VT669400	PW HEAD B-TITE SCREW	3x15-8 MFC2	
	165	21991500	PW HEAD S-TITE SCREW	4x8-10 MFC2BL	
	166	EP600250	BIND HEAD B-TITE SCREW	3x8 MFZN2Y	
	167	VT669300	PW HEAD B-TITE SCREW	3x8-8 MFC2	
	168	VY731200	BONDING HEAD TAPPING SCREW	3x10 MFNI33	
	169	VK522000	SPECIAL SCREW S-TITE	4x8-10 MFC2BL	BL
	169	VK522100	SPECIAL SCREW S-TITE	4x8-10 MFC2BL	TI
	169	VZ893000	DECORATED SCREW S-TIGHT	4x8-10 MFNI33	GD
	170	AA627310	GROUND TERMINAL		
	171	21991500	PW HEAD S-TITE SCREW	4x8-10 MFC2BL	BL
	171	VD069600	PW HEAD S-TITE SCREW	4x8-10 MFNI33	GD
	171	VH313200	BW HEAD S-TITE SCREW	4x8-10 MFNI3BL	TI
	172	EP630210	BIND HEAD S-TITE SCREW	3x6 MFZN2BL	
	173	VV220300	BIND HEAD B-TITE SCREW	3x30 MFZN2BL	RTKABG
	174	VB770200	PW HEAD P-TITE SCREW	3x10-8 MFC2	
	175	EP600130	BIND HEAD B-TITE SCREW	3x6 MFZN2Y	
			ACCESSORIES		
*	200	V7545800	REMOTE CONTROL TRANSMITTER	RAV230	BW0900
*	200	V7545900	REMOTE CONTROL TRANSMITTER	RAV231	BW0901
*	200-1	AAX31620	LID	71-0900-02000	71 0900 02000
	201	V6267000	ANTENNA, FM	1.4m 1pc	UCRTK
	201	VQ147100	ANTENNA, FM	1.4m 1pc	ABG
	202	VR248500	ANTENNA, AM LOOP	1.0m 1pc	
	203	VE364900	ANTENNA ADAPTER	PAL 75-300Ω	B
⚠	204	V6545800	POWER CORD ASS'Y	INLET 2.0m	V1200
			BATTERY, MANGANESE	UM-4NE (2PC)	UC

* New Parts



RX-V2200 MECHANICAL PARTS

Ref. No.	PART NO.	Description	Remarks	Markets
*	1-1	V7620600 FRONT PANEL	RXV2200GD	
*	1-1	V7620500 FRONT PANEL	RXV2200BL	
	1-4	V6003900 ESCUTCHEON/POWER	GD	
	1-4	V6003800 ESCUTCHEON/POWER	BL	
	1-5	V6004200 ESCUTCHEON/INPUT	GD	
	1-5	V6004100 ESCUTCHEON/INPUT	BL	
	1-6	V6004400 ESCUTCHEON/D5		
	1-7	V6034200 EMBLEM	GD	
	1-7	V6034100 EMBLEM	BL	
*	1-9	V7622600 ESCUTCHEON/TC	GD	
*	1-9	V7622500 ESCUTCHEON/TC	BL	
*	2-1	V7951300 P.C.B. ASS'Y	OPERATION	
	2-11	MF207350 S FLEXIBLE FLAT CABLE	7P 350mm	
	2-12	MF117160 FLEXIBLE FLAT CABLE	17P 160mm	
*	2-13	MF219250 S FLEXIBLE FLAT CABLE	19P 250mm P=1.25	
	2-22	V6000100 SUB PANEL/CASE	GD	
	2-22	V6000000 SUB PANEL/CASE	BL	
*	2-25	V7794800 BUTTON P/S	GD	
*	2-25	V7794700 BUTTON P/S	BL	
	2-26	V6000400 BUTTON/INPUT	GD	
	2-26	V6000300 BUTTON/INPUT	BL	
	2-27	V6004600 ESCUTCHEON, VOL	GD	
	2-27	V6004500 ESCUTCHEON, VOL	BL	
*	2-28	V7622000 PANEL, LID	GD	
*	2-28	V7621900 PANEL, LID	BL	
*	2-29	V7795800 PLATE, SP	GD	
*	2-29	V7795700 PLATE, SP	BL	
	2-30	V6005100 HINGE, L	GD	
	2-30	V6005000 HINGE, L	BL	
	2-31	V6005400 HINGE, R	GD	
	2-31	V6005300 HINGE, R	BL	
	2-32	V4593300 SPRING, LID		
	2-33	VZ830300 DAMPER, GEAR	15G	
	2-34	VQ368600 PUSH RIVET	P3555-B	
	2-36	VY940400 CUSHION, LID	T=0.8	
	2-37	VV982000 DAMPER	1x12x12	
	2-52	VN413300 BIND HEAD BONDING B-T. SCREW	3x8 MFZN2BL	
	2-54	VG893800 BIND HEAD P-TITE SCREW	2x6 MFZN2BL	
	2-55	VG863900 BIND HEAD TAPPING SCREW	2.6x6 MFZN2BL	
	2-56	EP630290 BIND HEAD P-TITE SCREW	3x6 MFC2BL	
	2-57	EP600250 BIND HEAD B-TITE SCREW	3x8 MFZN2Y	
	2-60	VJ204800 PW HEAD S-TITE SCREW	3x6-8 MFC2BL	
* 	3-1	V7950700 P.C.B. ASS'Y	MAIN	UC RTA
* 	3-1	V7950800 P.C.B. ASS'Y	MAIN	
	3-8	MF113250 FLEXIBLE FLAT CABLE	13P 250mm	
	3-22	VV849300 SHEET	19x24	
	3-23	V5454200 DAMPER	2/10/260	
	3-25	VQ368600 PUSH RIVET	P3555-B	
*	3-27	V8152100 SHEET		
	3-31	VK173200 SCREW, TRANSISTOR	3x15 SP MFC2	
	3-33	VT669300 PW HEAD B-TITE SCREW	3x8-8 MFC2	
	3-34	VB770200 PW HEAD P-TITE SCREW	3x10-8 MFC2	
	3-35	EP630210 BIND HEAD S-TITE SCREW	3x6 MFZN2BL	

* New Parts

	Ref. No.	PART NO.	Description	Remarks	Markets
*	6	V7946200	P.C.B. ASS'Y	POWER	U
*	6	V7946300	P.C.B. ASS'Y	POWER	C
*	6	V7946400	P.C.B. ASS'Y	POWER	RT
*	6	V7946500	P.C.B. ASS'Y	POWER	A
*	7	V7946700	P.C.B. ASS'Y	DSP	
*	8	V7945100	P.C.B. ASS'Y	FUNCTION	UC
*	8	V7945200	P.C.B. ASS'Y	FUNCTION	RT
*	8	V7945300	P.C.B. ASS'Y	FUNCTION	A
*	9	V7947900	P.C.B. ASS'Y	VIDEO	UC
*	9	V7948000	P.C.B. ASS'Y	VIDEO	RT
*	9	V7948100	P.C.B. ASS'Y	VIDEO	A
	11	V7424300	AM/FM TUNER	FAE350-A10F	UCRT
	11	V7424400	AM/FM TUNER	FAE404-E10F	A
*	14	X0457A00	POWER TRANSFORMER		U
*	14	X0458A00	POWER TRANSFORMER		C
*	14	X0459A00	POWER TRANSFORMER		RT
*	14	X0460A00	POWER TRANSFORMER		A
	16	V2296800	POWER CORD ASS'Y		A
	16	VZ542500	POWER CORD ASS'Y		RT
	17	V2438700	CORD STOPPER	10P1	RTA
	21	VZ625600	BINDING TIE	SE140 L=140	
	22	VV272500	DC FAN MOTOR	2410ML-05W-B20-L00	
	25	MF111100	FLEXIBLE FLAT CABLE	11P 100mm	
	27	MF115100	FLEXIBLE FLAT CABLE C&C	15P 100mm	
*	28	MF119160	FLEXIBLE FLAT CABLE	19P 160mm P=1.25	
	29	MF131100	FLEXIBLE FLAT CABLE	31P 100mm	
	31	Vi491100	FERRITE CORE	BP53RB19012080M	
*	101	V7640700	TOP COVER		GD
*	101	V7640600	TOP COVER		BL
*	103	V7618100	REAR PANEL		U
*	103	V7618200	REAR PANEL		C
*	103	V7618300	REAR PANEL		RT
*	103	V7618400	REAR PANEL		A
*	117	V7623000	BRACKET/FAN		
*	118	V7622900	DUCT/FAN		
	119	VQ775900	GROUND PLATE		
	120	V0042500	LEG	D60xH21	GD
	120	VS025000	LEG	D60xH21	BL
	132	V6068100	KNOB/D43		GD
	132	V6068000	KNOB/D43		BL
	133	V6001400	KNOB D20		GD
	133	V6001300	KNOB D20		BL
	134	V6001700	KNOB D15		GD
	134	V6001600	KNOB D15		BL
	136	VQ368600	PUSH RIVET	P3555-B	
*	142	V7796200	SHEET, WINDOW		
	143	V6002700	PLATE/SIDE L		GD
	143	V6002500	PLATE/SIDE L		BL
	144	V6003000	PLATE/SIDE R		GD
	144	V6002900	PLATE/SIDE R		BL
	148	V6742400	DAMPER	3/10/50	
	161	VN413300	BIND HEAD BONDING B-T. SCREW	3x8 MFZN2BL	
	164	VT669400	PW HEAD B-TITE SCREW	3x15-8 MFC2	



* New Parts

Ref. No.	PART NO.	Description			Remarks	Markets
165	21991500	PW HEAD S-TITE SCREW	4x8-10	MFC2BL	BL	
166	EP600250	BIND HEAD B-TITE SCREW	3x8	MFZN2Y		
167	VT669300	PW HEAD B-TITE SCREW	3x8-8	MFC2		
168	VY731200	BONDING HEAD TAPPING SCREW	3x10	MFNI33		
169	VZ893000	DECORATED SCREW S-TIGHT	4x8-10	MFNI33	GD	
169	VK522000	DECORATED SCREW S-TIGHT	4x8-10	MFC2BL	BL	
170	AA627310	GROUND TERMINAL				
171	VD069600	PW HEAD S-TITE SCREW	4x8-10	MFNI33	GD	
171	21991500	PW HEAD S-TITE SCREW	4x8-10	MFC2BL	BL	
172	EP630210	BIND HEAD S-TITE SCREW	3x6	MFZN2BL		
173	VV220300	BIND HEAD B-TITE SCREW	3x30	MFZN2BL		
174	VB770200	PW HEAD P-TITE SCREW	3x10-8	MFC2		
175	EP600130	BIND HEAD B-TITE SCREW	3x6	MFZN2Y		
		ACCESSORIES				
* 200	V7720100	REMOTE CONTROL TRANSMITTER	RAV224		RRC4001-0001L	
200-1	AAX12830	LID	103RRC-170-01R		103RRC-170-01R	
201	V6267000	ANTENNA, FM	1.4m 1pc			UCRT
201	VQ147100	ANTENNA, FM	1.4m 1pc			A
202	VR248500	ANTENNA, AM LOOP	1.0m 1pc			
⚠ 203	V6545800	POWER CORD ASS'Y	INLET 2.0m			UC
	V6507100	BATTERY (MANGANESE DRY)	R6PPTT/3ST(R6P)			

* New Parts


Parts List for Carbon Resistors


Value	1/4W Type Part No.	1/6W Type Part No.	Value	1/4W Type Part No.	1/6W Type Part No.
1.0 Ω	HJ35 3100	HF85 3100	10 k Ω	HF45 7100	HF45 7100
1.8 Ω	HJ35 3180	*	11 k Ω	HF45 7110	HF45 7110
2.2 Ω	HJ35 3220	HF85 3220	12 k Ω	HJ35 7120	HF85 7120
3.3 Ω	HJ35 3330	HF85 3330	13 k Ω	HF45 7130	HF45 7130
4.7 Ω	HJ35 3470	HF85 3470	15 k Ω	HF45 7150	HF45 7150
5.6 Ω	HJ35 3560	HF85 3560	18 k Ω	HF45 7180	HF45 7180
10 Ω	HF45 4100	HF45 4100	22 k Ω	HF45 7220	HF45 7220
15 Ω	HJ35 4150	HF85 4150	24 k Ω	HF45 7240	HF45 7240
22 Ω	HF45 4220	HF45 4220	27 k Ω	HJ35 7270	HF85 7270
27 Ω	HJ35 4270	HF85 4270	30 k Ω	HF45 7300	HF45 7300
33 Ω	HF45 4330	HF45 4330	33 k Ω	HF45 7330	HF45 7330
39 Ω	HJ35 4470	HF85 4390	36 k Ω	HF45 7360	HF45 7360
47 Ω	HF45 4470	HF45 4470	39 k Ω	HF45 7390	HF45 7390
56 Ω	HF45 4560	HF45 4560	47 k Ω	HF45 7470	HF45 7470
68 Ω	HF45 4680	HF45 4680	51 k Ω	HF45 7510	HF45 7510
75 Ω	HF45 4750	HF45 4750	56 k Ω	HF45 7560	HF45 7560
82 Ω	HF45 4820	HF45 4820	62 k Ω	HF45 7620	HF45 7620
91 Ω	HF45 4910	HF45 4910	68 k Ω	HF45 7680	HF45 7680
100 Ω	HF45 5100	HF45 5100	82 k Ω	HF45 7820	HF45 7820
110 Ω	HJ35 5110	HF85 5110	91 k Ω	HF45 7910	HF45 7910
120 Ω	HF45 5120	HF45 5120	100 k Ω	HF45 8100	HF45 8100
150 Ω	HF45 5150	HF45 5150	110 k Ω	HF45 8110	HF45 8110
160 Ω	HJ35 5160	*	120 k Ω	HF45 8120	HF45 8120
180 Ω	HF45 5180	HF45 5180	150 k Ω	HF45 8150	HF45 8150
200 Ω	HF45 5200	HF45 5200	180 k Ω	HF45 8180	HF45 8180
220 Ω	HF45 5220	HF45 5220	220 k Ω	HJ35 8220	HF85 8220
270 Ω	HF45 5270	HF45 5270	270 k Ω	HF45 8270	HF45 8270
330 Ω	HF45 5330	HF45 5330	300 k Ω	HF45 8300	HF45 8300
390 Ω	HF45 5390	HF45 5390	330 k Ω	HF45 8330	HF45 8330
430 Ω	HF45 5430	HF45 5430	390 k Ω	HJ35 8390	HF85 8390
470 Ω	HF45 5470	HF45 5470	470 k Ω	HF45 8470	HF45 8470
510 Ω	HF45 5510	HF45 5510	560 k Ω	HJ35 8560	HF85 8560
560 Ω	HF45 5560	HF45 5560	680 k Ω	HJ35 8680	HF85 8680
680 Ω	HF45 5680	HF45 5680	820 k Ω	HJ35 8820	HF85 8820
820 Ω	HF45 5820	HF45 5820	1.0 M Ω	HF45 9100	HF45 9100
910 Ω	HF45 5910	HF45 5910	1.2 M Ω	HJ35 9120	*
1.0 k Ω	HF45 6100	HF45 6100	1.5 M Ω	HJ35 9150	HF85 9150
1.2 k Ω	HF45 6120	HF45 6120	1.8 M Ω	HJ35 9180	HF85 9180
1.5 k Ω	HF45 6150	HF45 6150	2.2 M Ω	HJ35 9220	HF85 9220
1.8 k Ω	HF45 6180	HF45 6180	3.3 M Ω	HJ35 9330	HF85 9330
2.0 k Ω	HJ35 6200	HF85 6200	3.9 M Ω	HJ35 9390	*
2.2 k Ω	HF45 6220	HF45 6220	4.7 M Ω	HJ35 9470	HF85 9470
2.4 k Ω	HJ35 6240	HF85 6240			
2.7 k Ω	HF45 6270	HF45 6270			
3.0 k Ω	HF45 6300	HF45 6300			
3.3 k Ω	HF45 6330	HF45 6330			
3.6 k Ω	HJ35 6360	HF85 6360			
3.9 k Ω	HF45 6390	HF45 6390			
4.7 k Ω	HF45 6470	HF45 6470			
5.1 k Ω	HF45 6510	HF45 6510			
5.6 k Ω	HF45 6560	HF45 6560			
6.8 k Ω	HF45 6680	HF45 6680			
8.2 k Ω	HF45 6820	HF45 6820			
9.1 k Ω	HF45 6910	HF45 6910			



RX-V1200/RX-V1200RDS/HTR-5490 REMOTE CONTROL TRANSMITTER

SCHEMATIC DIAGRAM








Key No.	Function	Default Code	Schematic Key No.
4	SYSTEM POWER	7A-1D	K10
5	STANDBY	7A-1E	K12
6	SLEEP	7A-57	K4
7	6CH INPUT	7A-87	K3
8		—	K14
9	PHONO	7A-14	K11
10	TUNER	7A-16	K2
11	CD	7A-15	K5
12	V-AUX	7A-55	K9
13	CBL/SAT	7A-C0	K13
14	MD/TAPE	7A-18	K1
15	CD-R	7A-19	K6
16	D-TV/LD	7A-54	K15
17	VCR 1	7A-0F	K16
18	VCR2/DVR	7A-13	K8
19	DVD	7A-C1	K7
20		—	K55
21		—	K54
22	POWER [TV]	—	K25
23	POWER [AV]	7C-80	K50
25	REC [O]	7C-8B	K32
26		7C-83	K27
27	AUDIO	7C-AD	K51
28		7C-B9	K31
29		7C-82	K26
30		7C-BA	K49
31		7C-86	K30
32		7C-85	K23
33		7C-87	K24
34	VOL +	7A-1A	K52
35	VOL -	7A-1B	K17
36	LEVEL [TITLE]	7C-B1	K29
37	TV VOL +	7C-B4	K22
38	SET MENU [MENU]	7C-B2	K19
39	CH -	7C-B5	K28
40	TV MUTE SELECT	7C-B8	K21
41	CH +	7C-B6	K20
42	MUTE	7A-1C	K18
43	TEST [RETURN]	7C-B7	K47
44	TV VOL -	7C-B3	K48
45	ON SCREEN [DISPLAY]	7C-A6	K39
46	STEREO	7A-56	K40
47	1	7C-94	K46
48	2	7C-95	K45
49	3	7C-96	K38
50	4	7C-97	K37
51	5	7C-98	K43
52	6	7C-99	K44
53	7	7C-9A	K35
54	8	7C-9B	K36
55	9	7C-9C	K42
56	10	7C-93	K41
57	11	7C-9D	K34
58	12	7C-9E	K33

RX-V2200 REMOTE CONTROL TRANSMITTER

● SCHEMATIC DIAGRAM





Initial Code

Key No.	Key Name	YPC	DSP *1	Zone2 *2
1	—	—	—	—
2	RE-NAME	—	—	—
3	CLEAR	—	—	—
4	LEARN	—	—	—
5	MACRO	—	—	—
6	POWER on	*7A-1D	7D-90	*7A-1D
7	STANDBY	7A-1E	7D-91	7A-1E
8	A	—	—	—
9	B	—	—	—
10	PHONO	7A-14	7D-88	7A-D0
11	V-AUX	7A-55	7D-8A	7A-D8
12	TUNER	7A-16	7D-89	7A-D2
13	MD/TAPE	7A-18	7D-8B	7A-D3
14	CD-R	7A-19	7D-99	7A-D4
15	CD	7A-15	7D-87	7A-D1
16	D-TV/LD	7A-54	7D-84	7A-D9
17	CBL/SAT	7A-13	7D-82	7A-CC
18	VCR1	7A-0F	7D-81	7A-D6
19	VCR2/DVR	7A-13	7D-82	7A-D7
20	DVD	7A-C1	7D-97	7A-CD
21	EXT. DEC.	7A-87	7D-8C	7A-87

*1: These code are transmitted when "DSP" is set-up as AMP library.

*2: These code are transmitted when "ZONE2" is chosen with Select key.
CAUTION! This is displayed as a possible selection when the AMP library is set in ZONE 2.

*: Transmitting Code of K6, "7A-1D"
Full word transmitted twice.

Any device not listed on this table has no initial code.

*1: AMPライブラリーをDSPに設定することで送信されます。
*2: SelectキーによりZONE2を選択することで送信されます。
注意) AMPライブラリーをZONE2に設定した場合に選択肢として表示されます。

*: K6送信コード"7A-1D"について
ワード部が2回送信されます。

本表に記載なきデバイスの初期コードはありません。

21	EXT. DELC.	7A-87	7D-8C	7A-87	DVD (K20)	CD-R (K14)	CD (K15)	MD/TAPE (K13)	TUNER (K12)	A (K8)
Device										
22	Up	→	→	→	7C-B4	—	—	—	—	—
23	TITLE	→	→	→	7C-B1	—	—	—	—	—
24	Left	→	→	→	7C-B5	—	—	—	—	—
25	ENTER	→	→	→	7C-B8	—	—	—	—	—
26	Right	→	→	→	7C-B6	—	—	—	—	—
27	SOUND	→	→	→	7C-AD	—	—	—	—	7C-12
28	Down	→	→	→	7C-B3	—	—	—	—	—
29	MENU	→	→	→	7C-B2	—	—	—	—	—
30	DISPLAY	→	→	→	7C-A6	7F-9E	79-0A	79-A5	—	7C-13
31	REW	→	→	→	7C-86	7F-88	7A-0D	79-AC	—	7C-06
32	FF	→	→	→	7C-87	7F-89	7A-0C	79-AD	—	7C-07
33	CHP/SKIP -	→	→	→	7C-89	7F-86	7A-0B	79-AB	—	7C-02
34	CHP/SKIP +	→	→	→	7C-BA	7F-87	7A-0A	79-AE	—	7C-03
35	PLAY	→	→	→	7C-82	7F-82	7A-08	79-A8	—	7C-05
36	PAUSE	→	→	→	7C-83	7F-83	7A-09	79-A9	—	7C-5A
37	STOP	→	→	→	7C-85	7F-84	7A-09	79-AA	—	7C-5B
38	REC	→	→	→	7C-B7	—	—	79-AF	—	—
39	POWER	→	→	→	—	—	—	—	—	—
40	SELECT down	—	—	—	—	—	—	—	—	—
41	SELECT up	—	—	—	—	—	—	—	—	—
SW2		DSP			10 key					
42	PRG1	7A-88	7D-D0	7A-88	7C-94	7F-91	79-11	79-85	7A-E5	7C-17
43	PRG2	7A-89	7D-D1	7A-89	7C-95	7F-92	79-12	79-86	7A-E6	7C-18
44	PRG3	7A-8A	7D-D2	7A-8A	7C-96	7F-93	79-13	79-87	7A-E7	7C-19
45	PRG4	7A-8B	7D-D3	7A-8B	7C-97	7F-94	79-14	79-88	7A-E8	7C-1A
46	PRG5	7A-8C	7D-D4	7A-8C	7C-98	7F-95	79-15	79-89	7A-E9	7C-1B
47	PRG6	7A-8D	7D-D5	7A-8D	7C-99	7F-96	79-16	79-8A	7A-EA	7C-1C
48	PRG7	7A-8E	7D-D6	7A-8E	7C-9A	7F-97	79-17	79-8B	7A-EB	7C-1D
49	PRG8	7A-8F	7D-D7	7A-8F	7C-9B	7F-98	79-18	79-8C	7A-EC	7C-1E
50	PRG9	7A-90	7D-D8	7A-90	7C-9C	7F-99	79-19	79-8D	7A-E1	7C-1F
51	PRG10	7A-91	7D-D9	7A-91	7C-93	7F-90	79-10	79-8E	7A-E2	7C-1D
52	PRG11	7A-92	7D-DA	7A-92	7C-9D	7F-9A	79-1A	79-8F	7A-E3	7C-56
53	PRG12	7A-93	7D-DB	7A-96	7C-9F	7F-8C	79-0D	—	7A-E4	7C-5E
54	6.1/ES	7A-97	7D-DF	7A-97	7C-9E	7F-8A	79-0B	—	7A-E0	7C-15
55	TV VOL up	→	→	→	—	—	—	—	—	—
56	TV VOL down	→	→	→	—	—	—	—	—	—
57	TV INPUT	→	→	→	—	—	—	—	7A-12	—
58	TV MUTE	→	→	→	—	—	—	—	—	—
59	CH up	→	→	→	7C-8B	—	7A-4F	—	7A-10	—
60	CH down	→	→	→	7C-8A	—	7A-50	—	7A-11	—
61	MUTE	7A-1C	7D-94	7A-DC						
62	EFFECT	7A-56	7D-C1	7A-56						
63	VOLUME up	7A-1A	7D-8D	7A-DA						
64	VOLUME down	7A-1B	7D-8E	7A-DB						
SW3		Parameter	Set Menu	Parameter	Set Menu	Parameter	Set Menu			
65	ON SCREEN	7A-C2	7D-C2	7A-C2						
66	SLEEP	7A-57	7D-93	7A-57						
67	LEVEL	7A-86	7D-95	7A-86						
68	TEST	7A-85	7D-CA	7A-85						
69	LEFT	7A-C7	7A-9F	7D-C7	7D-9F	7A-C7	7A-9F			
70	UP	7A-C5	7A-9D	7D-C5	7D-9D	7A-C5	7A-9D			
71	DOWN	7A-C4	7A-9C	7D-C4	7D-9C	7A-C4	7A-9C			
72	RIGHT	7A-C6	7A-9E	7D-C6	7D-9E	7A-C6	7A-9E			

Initial Macro setup

Key No.	Key Name	1	2	3	4~10
6	POWER on	K6	K39 TV	—	—
7	STANDBY	K7	—	—	—
8	A	K6	K8	—	—
9	B	K6	K9	—	—
10	PHONO	K6	K10	—	—
11	V-AUX	K6	K11	—	—
12	TUNER	K6	K12	—	—
13	MD/TAPE	K6	K13	K35 MD	—
14	CD-R	K6	K14	K35 CD-R	—
15	CD	K6	K15	K35 CD	—
16	D-TV/LD	K6	K16	—	—
17	CBL/SAT	K6	K17	—	—
18	VCR1	K6	K18	K35 VCR1	—
19	VCR2/DVR	K6	K19	K35 VCR2	—
20	DVD	K6	K20	K35 DVD	—