

AV RECEIVER

RX-V675/HTR-6066/ RX-A730/TSR-6750

SERVICE MANUAL

Note:

When the DIGITAL P.C.B. or IC82 on DIGITAL (1) P.C.B. is replaced, this unit will display "Internal Error" and will not operate properly. The model name MUST be written to the backup IC (EEPROM: IC82 on DIGITAL (1) P.C.B.) to have proper operation. (For detailed procedure, refer to related Service News or Service Bulletin. Or contact your local Yamaha representative.)

IMPORTANT NOTICE

This manual has been provided for the use of authorized Yamaha Retailers and their service personnel.

It has been assumed that basic service procedures inherent to the industry, and more specifically Yamaha Products, are already known and understood by the users, and have therefore not been restated.

WARNING: Failure to follow appropriate service and safety procedures when servicing this product may result in personal injury, destruction of expensive components, and failure of the product to perform as specified. For these reasons, we advise all Yamaha product owners that any service required should be performed by an authorized Yamaha Retailer or the appointed service representative.

IMPORTANT: The presentation or sale of this manual to any individual or firm does not constitute authorization, certification or recognition of any applicable technical capabilities, or establish a principle-agent relationship of any form.

The data provided is believed to be accurate and applicable to the unit(s) indicated on the cover. The research, engineering, and service departments of Yamaha are continually striving to improve Yamaha products. Modifications are, therefore, inevitable and specifications are subject to change without notice or obligation to retrofit. Should any discrepancy appear to exist, please contact the distributor's Service Division.

WARNING: Static discharges can destroy expensive components. Discharge any static electricity your body may have accumulated by grounding yourself to the ground buss in the unit (heavy gauge black wires connect to this buss).

IMPORTANT: Turn the unit OFF during disassembly and part replacement. Recheck all work before you apply power to the unit.

■ CONTENTS

TO SERVICE PERSONNEL	2
FRONT PANELS	3-4
REAR PANELS	5-8
REMOTE CONTROL PANEL	9
SPECIFICATIONS	10-14
INTERNAL VIEW	15-16
SERVICE PRECAUTIONS	16
DISASSEMBLY PROCEDURES	17-24
UPDATING FIRMWARE	25-27
SELF-DIAGNOSTIC FUNCTION	28-70
POWER AMPLIFIER ADJUSTMENT	71

DISPLAY DATA	72-73
IC DATA	74-94
PIN CONNECTION DIAGRAMS	95-97
BLOCK DIAGRAMS	98-101
WIRING DIAGRAMS	102-103
PRINTED CIRCUIT BOARDS	104-125
SCHEMATIC DIAGRAMS	127-142
REPLACEMENT PARTS LIST	143-163
REMOTE CONTROL	164-166
ADVANCED SETUP	167-168
FIRMWARE UPDATING PROCEDURE	169-180



■ TO SERVICE PERSONNEL


1. Critical Components Information

Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.

2. Leakage Current Measurement (For 120V Models Only)

When service has been completed, it is imperative to verify that all exposed conductive surfaces are properly insulated from supply circuits.

- Meter impedance should be equivalent to 1500 ohms shunted by 0.15 μ F.



- Leakage current must not exceed 0.5mA.
- Be sure to test for leakage with the AC plug in both polarities.



For U model

“CAUTION”

“F3701: FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE 2A, 250V FUSE.”

“F3702: FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE 8A, 125V FUSE.”

For C model

CAUTION

F3701: REPLACE WITH SAME TYPE 2A, 250V FUSE.

F3702: REPLACE WITH SAME TYPE 8A, 125V FUSE.

ATTENTION

F3701: UTILISER UN FUSIBLE DE RECHANGE DE MÊME TYPE DE 2A, 250V.

F3702: UTILISER UN FUSIBLE DE RECHANGE DE MÊME TYPE DE 8A, 125V.

WARNING: CHEMICAL CONTENT NOTICE!

This product contains chemicals known to the State of California to cause cancer, or birth defects or other reproductive harm.

DO NOT PLACE SOLDER, ELECTRICAL/ELECTRONIC OR PLASTIC COMPONENTS IN YOUR MOUTH FOR ANY REASON WHATSOEVER!

Avoid prolonged, unprotected contact between solder and your skin! When soldering, do not inhale solder fumes or expose eyes to solder/flux vapor!

If you come in contact with solder or components located inside the enclosure of this product, wash your hands before handling food.

About lead free solder

All of the P.C.B.s installed in this unit and solder joints are soldered using the lead free solder.

Among some types of lead free solder currently available, it is recommended to use one of the following types for the repair work.


- Sn + Ag + Cu (tin + silver + copper)
- Sn + Cu (tin + copper)
- Sn + Zn + Bi (tin + zinc + bismuth)

Caution:


As the melting point temperature of the lead free solder is about 30°C to 40°C (50°F to 70°F) higher than that of the lead solder, be sure to use a soldering iron suitable to each solder.

FRONT PANELS

RX-V675 (U, C, R, T, A, B, G, F, L, S, H models)




HTR-6066 (G, F models)




RX-V675/HTR-6066/
RX-A730/TSR-6750

RX-A730 (U, C, A, B, G, L models)





TSR-6750 (U model)




RX-V675/HTR-6066/
RX-A730/TSR-6750


RX-V675 (U, C models)




RX-V675 (A model)




RX-V675 (B, G, F models)




RX-V675 (L, H models)




HTR-6066 (G, F models)



RX-A730 (U, C models)



RX-A730 (A model)



THX OUT
THX OUT

DO OUT
DO OUT

NETWORK
(NET)

HDMI OUT
HDMI OUT

COMPONENT VIDEO
COMPONENT VIDEO

MONITOR OUT
MONITOR OUT

ZONE OUT
ZONE OUT

SPEAKERS
SPEAKERS

CAUTION : NO INSERTION MANUAL FOR CORRECT RETURN.

POWER
POWER

YAMAHA
YAMAHA

MADE IN MALAYSIA
MADE IN MALAYSIA

AV RECEIVER RX-A750
AV RECEIVER RX-A750

80 Hz
80 Hz

500 W
500 W

CE
CE



PG
PG

REPL. P.C.
REPL. P.C.

[illegible][illegible]

■ REMOTE CONTROL PANEL

RAV501



SPECIFICATIONS

Audio Section

Rated Output Power (Power Amp. Section)

(1 kHz, 0.9 % THD)

– 1 channel driven –

U, C, R, T, A, B, G, F, L, S, H models (8 ohms)

FRONT L/R 125 W/ch

CENTER 125 W

SURROUND L/R 125 W/ch

SURROUND BACK L/R 125 W/ch

B, G, F models (4 ohms)

FRONT L/R 150 W/ch

– 2 channels driven simultaneously –

U, C, R, T, A, B, G, F, L, S, H models (8 ohms)

FRONT L/R 105 W + 105 W

CENTER 105 W

SURROUND L/R 105 W + 105 W

SURROUND BACK L/R 105 W + 105 W

(20 Hz to 20 kHz, 0.09 % THD)

– 2 channels driven simultaneously –

U, C, R, T, A, B, G, F, L, S, H models (8 ohms)

FRONT L/R 90 W + 90 W

Maximum Effective Output Power (JEITA) [R, T, L, H models]

(1 channel driven, 1 kHz, 10 % THD, 8 ohms)

FRONT L/R 150 W/ch

CENTER 150 W

SURROUND L/R 150 W/ch

SURROUND BACK L/R 150 W/ch

Dynamic Power Per Channel (IHF)

FRONT L/R (1 channel driven)

(8 / 6 / 4 / 2 ohms) 130 / 170 / 200 / 240 W

Damping Factor (20 Hz to 20 kHz, 8 ohms)

FRONT L/R to SPEAKER-A 100 or more

Input Sensitivity/Input Impedance (1 kHz, 100 W/8 ohms)

AV5 etc. 200 mV / 47 k-ohms

Maximum Input Signal (1 kHz, 0.5 % THD)

AV5 etc. (EFFECT ON) 2.3 V

Output Level/Output Impedance

AV OUT 200 mV / 1.2 k-ohms

SUBWOOFER (2 ch stereo and FRONT SP: small)

..... 1 V / 1.2 k-ohms

ZONE2 OUT 200 mV / 1.2 k-ohms

Headphone Jack Rated Output/Output Impedance

(1 kHz, 50 mV, 8 ohms)

AV5 etc. input 100 mV / 560 ohms

Frequency Response (10 Hz to 100 kHz)

AV5 etc., FRONT 0 / -3 dB

Total Harmonic Distortion (20 Hz to 20 kHz, 50 W/8 ohms)

AV5 etc. (PURE DIRECT) to FRONT SP OUT 0.06 % or less

Signal to Noise Ratio (IHF-A Network) (Input shorted 250 mV)

AV5 etc. (PURE DIRECT) to SP OUT 100 dB or more

Residual Noise (IHF-A Network)

FRONT L/R to SP OUT 150 μ V or less

Channel Separation (1 kHz / 10 kHz)

AV5 etc. (Input 5.1 k-ohms shorted)

..... 60 dB or more / 45 dB or more

Volume Control/Step

..... MUTE / -80 dB to +16.5 dB / 0.5 dB step

Tone Control Characteristics

Bass

Boost/Cut ± 6 dB / 0.5 dB step, at 50 Hz

Turnover frequency 350 Hz

Treble

Boost/Cut ± 6 dB / 0.5 dB step, at 20 kHz

Turnover frequency 3.5 kHz

Filter Characteristics

FRONT, CENTER, SURROUND, SURROUND BACK small (H.P.F.)

..... fc=40/60/80/90/100/110/120/160/200 Hz, 12 dB/oct.

SUBWOOFER small (L.P.F.)

..... fc=40/60/80/90/100/110/120/160/200 Hz, 24 dB/oct.

Optical Jack, Coaxial Jack Support Frequencies

..... 32 kHz to 96 kHz

Video Section

Video Signal Type

Monitor out (Wall paper)

U, C, R models NTSC

T, A, B, G, F, L, S, H models PAL

Video conversion

..... NTSC/PAL

Composite Video Signal Level

..... 1 Vp-p / 75 ohms

Component Video Signal Level

Y 1 Vp-p / 75 ohms

Pb/Pr 0.7 Vp-p / 75 ohms

Video Maximum Input Level (VIDEO Conversion Off)

..... 1.5 Vp-p or more

Video Signal to Noise Ratio

..... 50 dB or more

Monitor Out Frequency Response (VIDEO Conversion Off)

Component video signal level 5 Hz to 60 MHz, -3 dB

FM Section

Tuning Range

U, C models 87.5 to 107.9 MHz

R, L, S, H models 87.5 to 108.0 / 87.50 to 108.00 MHz

T, A, B, G, F models 87.50 to 108.00 MHz

50 dB Quieting Sensitivity (IHF) (1 kHz, 100 % MOD.)

Mono 3 μ V (20.8 dBf)

Signal to Noise Ratio (IHF)

Mono 71 dB

Stereo 69 dB

Harmonic Distortion (1 kHz)

Mono 0.3 %

Stereo 0.5 %

Antenna Input

..... 75 ohms unbalanced

■ AM Section**Tuning Range**

U, C models	530 to 1,710 kHz
R, L, S, H models	530 to 1,710 / 531 to 1,611 kHz
T, A, B, G, F models	531 to 1,611 kHz

Antenna

	Loop antenna
--	--------------

■ General**Power Supply**

U, C models	AC 120 V, 60 Hz
R, S models	AC 110–120/220–240 V, 50/60 Hz
T model	AC 220 V, 50 Hz
A model	AC 240 V, 50 Hz
B, G, F models	AC 230 V, 50 Hz
L, H models	AC 220–240 V, 50/60 Hz

Power Consumption

U, C models	400 W / 500 VA
R, T, L, S, H models	270 W
A, B, G, F models	300 W

Standby Power Consumption (reference data)

HDMI control: OFF / Standby through: OFF	
U, C models	0.10 W or less
R, T, A, B, G, F, L, S, H models	0.15 W or less
HDMI control: ON / Standby through: ON	
INPUT: HDMI1 (HDMI no signal)	
	3.0 W or less
Network standby: ON	
	3.0 W or less

Maximum Power Consumption [R, L, S, H models]

	590 W
--	-------

Dimensions (W x H x D)

[RX-V675/HTR-6066/TSR-6750]	
	435 x 171 x 364 mm (17-1/8" x 6-3/4" x 14-3/8")
[RX-A730]	
	435 x 171 x 367 mm (17-1/8" x 6-3/4" x 14-1/2")

Weight

[RX-V675/HTR-6066/TSR-6750]	
	10.0 kg (22 lbs.)
[RX-A730]	
	10.4 kg (22.9 lbs.)

Finish

[RX-V675]	
T model	Gold color
U, C, R, T, A, B, G, F, L, S, H models	Black color
U, A, B, G, F, L, H models	Titanium color
[HTR-6066]	
G, F models	Black color
[RX-A730]	
U, C, A, B, G, L models	Black color
B, G models	Titanium color
[TSR-6750]	
U model	Black color

Accessories

Remote control	x 1
Batteries (R03, AAA, UM-4)	x 2
FM antenna (1.4 m)	x 1
AM antenna (1.0 m)	x 1
YPAO microphone (6.0 m)	x 1
Remote control sheet (T model)	x 1
Antenna isolator (T model)	x 1
Conversion plug (T model)	x 1
Power cable (2.0 m) (RX-A730)	x 1

* Specifications are subject to change without notice.

U U.S.A. model	G European model
C Canadian model	F Russian model
R General model	L Singapore model
T Chinese model	S Brazilian model
A Australian model	H Thai model
B British model	



Manufactured under license from Dolby Laboratories. Dolby, Pro Logic, Surround EX and the double-D symbol are trademarks of Dolby Laboratories.



DTS-HD, the Symbol, & DTS-HD and the Symbol together are registered trademarks & DTS-HD Master Audio is a trademark of DTS, Inc.

Product includes software. © DTS, Inc. All Rights Reserved.



AirPlay, the AirPlay logo, iPad, iPhone, iPod, iPod nano, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.



Fraunhofer Institut
Integrierte Schaltungen

MPEG Layer-3 audio coding technology licensed from Fraunhofer IIS and Thomson.



This receiver supports network connections.



HDMI, the HDMI Logo, and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries.



MHL and the MHL logo are a trademark, registered trademark or service mark of MHL, LLC in the United States and/or other countries.

x.v.Color™

“x.v.Color” is a trademark of Sony Corporation.

**SILENT™
CINEMA**

“SILENT CINEMA” is a trademark of Yamaha Corporation.



DLNA™ and DLNA CERTIFIED™ are trademarks or registered trademarks of Digital Living Network Alliance. All rights reserved. Unauthorized use is strictly prohibited.

Windows™

Windows is a registered trademark of Microsoft Corporation in the United States and other countries.


Internet Explorer, Windows Media Audio and Windows Media Player are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.

Android™


Android is a trademark of Google Inc.

DIMENSIONS

RX-V675/HTR-6066/TSR-6750



RX-A730



Unit: mm (inch)

Unit: mm (inch)

RX-V675/HTR-6066/
RX-A730/TSR-6750


• SET MENU TABLE

MAIN MENU	SUB-MENU	PARAMETER		VALUE [INITIAL VALUE]
Speaker Setup	Auto	Measure		Optimizes the speaker configuration automatically using YPAO.
		Result		Not Available
	Manual	Power Amp Assign		[Basic] / 7ch +1ZONE / 5ch BI-AMP
		Configuration	Front	Large / [Small] * "Front" is automatically set to "Large" when "Subwoofer" is set to "None".
			Center	Large / [Small] / None
			Surround	
			Surround Back	Large x1 / Large x2 / Small x1 / [Small x2] / None * This setting is not available when "Power Amp Assign" is set to "5ch BI-AMP"; or when "Surround" is set to "None".
			Front Presence	[Use] / None
			Subwoofer	Use / None └─> [Normal] / Reverse
			Extra Bass	[Off] / On * This setting is not available when "Subwoofer" is set to "None", or when "Front" is set to "Small".
			Bass Cross Over	40 / 60 / [80] / 90 / 100 / 110 / 120 / 160 / 200 Hz
		Distance	Meter / Feet	
			Front L	0.30 to 24.00 m, [3.00 m], 0.05 m step 1.0 to 80.0 ft, [10.0 ft], 0.2 ft step
			Front R	
			Center	
			Surround L	
			Surround R	
			Surround Back L	
			Surround Back R	
			Front Presence L	
			Front Presence R	
			Subwoofer	
		Level	Front L	-10.0 to +10.0 dB, [0.0 dB], 0.5 dB step
			Front R	
			Center	
			Surround L	
			Surround R	
			Surround Back L	
			Surround Back R	
			Front Presence L	
			Front Presence R	
			Subwoofer	
		Parametric EQ		Manual / YPAO : Flat / YPAO : Front / YPAO : Natural / Through * Select "ENTER"
		Front L Front R Center Surround L Surround R Surround Back L Surround Back R Front Presence L Front Presence R	Band	► Band: #1 to #7
			/ Gain	▲ Gain: -20.0 to +6.0 dB, [0.0 dB], 0.5 dB step
			Frequency	► Frequency: 31.3 Hz to 16.0 kHz, [62.5 Hz]
			/ Gain	▲ Gain: -20.0 to +6.0 dB, [0.0 dB], 0.5 dB step
			Q	► Q: 0.500 to 10.080, [1.000]
			/ Gain	▲ Gain: -20.0 to +6.0 dB, [0.0 dB], 0.5 dB step
		PEQ Data Copy		Flat > Manual / Front > Manual / Natural > Manual * Select "ENTER"
		PEQ Data Clear		OK / CANCEL * Select "ENTER"
		Test Tone		[Off] / On
Sound Setup	Lipsync	Delay Enable	HDMI1 / HDMI2 / HDMI3 / HDMI4 / HDMI5 / AV1 / AV2 / AV3 / AV4 / AV5 / AV6 / V-AUX / AUDIO1 / AUDIO2	Disable / [Enable]
		Auto/Manual Select		[Auto] / Manual
		Adjustment		0 to 500 ms, [0 ms], 1 ms step

MAIN MENU	SUB-MENU		PARAMETER		VALUE [INITIAL VALUE]
Sound Setup	Dynamic Range				[Maximum] / Standard / Minimum/Auto
	Max. Volume				-30.0 to +15.0 dB, 5.0 dB step / [+16.5 dB (Maximum volume)]
	Initial Volume				[Off] / On
		Select "On"			Mute, -80.0 to +16.5 dB, [-40.0 dB], 0.5 dB step
	Adaptive DSP Level				Off / [On]
Video Setup	Video Mode				[Direct] / Processing
		Select "Processing"	Resolution	Through / [Auto] / 480p/576p / 720p / 1080i / 1080p / 4K * Select "ENTER"	
			Aspect	[Through] / 16:9 Normal	
HDMI Setup	HDMI Control				[Off] / On
			TV Audio Input		AV1 / AV2 / AV3 / [AV4] / AV5 / AV6 / AUDIO1 / AUDIO2
			ARC (Audio Return Channel)		Off / [On]
			Standby Sync		Off / On / [Auto]
	Audio Output	Amp		Off / [On]	
		HDMI OUT (TV)		[Off] / On	
	* This setting is available only when "HDMI Control" is set to "Off".				
	Standby Through				[Off] / On * This setting is available only when "HDMI Control" is set to "Off".
Network Setup	IP Address	DHCP	Select "Off"	IP Address	xxx.xxx.xxx. x
				Subnet Mask	xxx.xxx.xxx. x
				Default Gateway	xxx.xxx.xxx. x
				DNS Server (P) Primary	x. x. x. x
				DNS Server (S) Secondary	x. x. x. x
				Network Standby	
	MAC Address	Filter	[Off] / On		
	Filter		Select "On"	MAC Address 1–5	xx : xx : xx : xx : xx : xx
				MAC Address 6–10	xx : xx : xx : xx : xx : xx
	Network Name				Input is possible to 15 characters
	Multi Zone Setup	Main Zone Set	Zone Rename		Input is possible to 9 characters
Zone2 Set		Max. Volume		-30.0 to +15.0 dB, 5.0 dB step / [+16.5 dB (Maximum volume)] * This setting is available only when "Power Amp Assign" is set to "7ch +1ZONE"	
		Initial Volume		[Off] / On	
			Select "On"	Mute, -80.0 to +16.5 dB, [-40.0 dB], 0.5 dB step	
		* This setting is available only when "Power Amp Assign" is set to "7ch +1ZONE"			
Zone Rename		Input is possible to 9 characters			
Function Setup	Display Set	Dimmer (Front Display)		-4 to 0 (higher to brighten), [0], 1 step	
		Short Message		[On] / Off	
		Wall Paper		[Picture1] / Picture2 / Picture3 / Gray	
	Trigger Output	Trigger Mode		[Power] / Source / Manual	
			Select "Source"	HDMI1–5, AV1–6, V-AUX, AUDIO1–2, TUNER, Rhapsody, Pandora, AirPlay, SERVER, NET RADIO, USB Low / [High]	
			Select "Manual"	Low / [High]	
		Target Zone		Main / Zone2 / [All]	
	DC OUT	Power Mode		[Continuous] / Main Zone Power Sync.	
	Memory Guard		[Off] / On		
ECO Setup	Auto Power Standby		Off / 2 Hours / 4 Hours / 8 Hours / 12 Hours U, C, R, T, K, A, L, S, H models: [Off] B, G, F models: [8 Hours]		
	ECO Mode		[Off] / On		
Language Setup					[English (English)] / 日本語 (Japanese) / Français (French) / Deutsch (German) / Español (Spanish) / Русский (Russian) / Italiano (Italian) / 中文 (Chinese)


INTERNAL VIEW

RX-V675/HTR-6066/TSR-6750




RX-A730

Top view



Front view



- ① OPERATION (3) P.C.B.
- ② OPERATION (8) P.C.B.
- ③ DIGITAL (1) P.C.B.
- ④ OPERATION (2) P.C.B.
- ⑤ AM/FM TUNER
- ⑥ OPERATION (9) P.C.B.
- ⑦ OPERATION (4) P.C.B.
- ⑧ MAIN (6) P.C.B.
- ⑨ MAIN (4) P.C.B.
- ⑩ MAIN (3) P.C.B.
- ⑪ MAIN (1) P.C.B.
- ⑫ MAIN (5) P.C.B.
- ⑬ POWER TRANSFORMER
- ⑭ OPERATION (5) P.C.B.
- ⑮ OPERATION (1) P.C.B.
- ⑯ OPERATION (12) P.C.B.
- ⑰ DIGITAL (2) P.C.B.
- ⑱ OPERATION (11) P.C.B.
- ⑲ OPERATION (6) P.C.B.
- ⑳ OPERATION (7) P.C.B.
- ㉑ OPERATION (10) P.C.B.

■ SERVICE PRECAUTIONS

Safety measures

- Some internal parts in this product contain high voltages and are dangerous.
Be sure to take safety measures during servicing, such as wearing insulating gloves.
- Note that the capacitors indicated below are dangerous even after the power is turned off because an electric charge remains and a high voltage continues to exist there.
Before starting any repair work, connect a discharging resistor (5 k-ohms/10 W) to the terminals of each capacitor indicated below to discharge electricity.
The time required for discharging is about 30 seconds per each.

C1084 and C1085 on MAIN (1) P.C.B.

C3706 on OPERATION (3) P.C.B.

For details, refer to "PRINTED CIRCUIT BOARDS".

■ DISASSEMBLY PROCEDURES

RX-V675/HTR-6066/TSR-6750

(Remove parts in the order as numbered.)
Disconnect the power cable from the AC outlet.

1. Removal of Top Cover

- a. Remove 4 screws (①) and 5 screws (②). (Fig. 1)
- b. Lift the rear of the top cover to remove it. (Fig. 1)

2. Removal of Front Panel Unit

- a. Remove 6 screws (③), and remove W3001 and W3007. (Fig. 1)
- b. Remove CB8, CB82, CB308, CB343, CB411, CB412, CB947 and CB952. (Fig. 1)
- c. Release 2 hooks, and remove the front panel unit. (Fig. 1)





Fig. 1

3. Removal of DIGITAL (1) P.C.B.

- Remove screw (4) and 7 screws (5). (Fig. 3)
- Remove 3 screws. (6). (Fig. 2)
- Remove CB76, CB78, CB79, CB80, CB942 and CB944. (Fig. 2)
- Unlock and remove CB946 and CB948. (Fig. 2)
- Remove the DIGITAL (1) P.C.B. which is connected directly to the OPERATION (4) P.C.B. with board-to-board connectors. (Fig. 2)



4. Removal of AMP Unit and Power Transformer

- Remove screw (7), 2 screws (8), 3 screws (9) and 4 screws (10). (Fig. 2)
- Remove 3 screws (11). (Fig. 3)
- Remove the AMP unit together with the power transformer. (Fig. 2)




Fig. 2





Fig. 3


When checking the MAIN (1) P.C.B.:

- Place the P.C.B.s (with rear panel) upright. (Fig. 4)
- Connect the heatsink and rear panel to the chassis with a ground lead or the like. (Fig. 4)
- Reconnect all cables (connectors) that have been disconnected.
- When connecting the flexible flat cable, be careful with polarity.

**Fig. 4**

When checking the DIGITAL (1) P.C.B.:

- Put the rubber sheet and cloth over this unit, and place the DIGITAL (1) P.C.B. on them. (Fig. 5)
- Connect ST951 on DIGITAL (1) P.C.B. to the chassis with a ground lead. (Fig. 5)
- Reconnect all cables (connectors) that have been disconnected. Be sure to use the P.C.B. CHECKING JIG (Part No. ZF454800) to connect between the following connectors.
CB945 on DIGITAL (1) P.C.B. – CB381 on OPERATION (4) P.C.B.
- When connecting the flexible flat cable, be careful with polarity.

**Fig. 5**

RX-A730

(Remove parts in the order as numbered.)
Disconnect the power cable from the AC outlet.

1. Removal of Top Cover

- a. Remove 4 screws (①), 5 screws (②) and screw (③). (Fig. 1)
- b. Lift the rear of the top cover to remove it. (Fig. 1)

2. Removal of Front Panel Unit and Sub-Chassis Unit

- a. Remove knob (INPUT) and knob (VOLUME). (Fig. 1)
- b. Remove 6 screws (④) and then remove the front panel unit. (Fig. 1)
- c. Remove 2 push rivets and then remove the side plate (L) and side plate (R). (Fig. 1)
- d. Remove CB8, CB82, CB302, CB343, CB411, CB412, CB947 and CB952. (Fig. 1)
- e. Remove 2 screws (⑤) and then remove the sub-chassis unit. (Fig. 1)




Fig. 1

3. Removal of DIGITAL (1) P.C.B.

- Remove screw (⑥) and 7 screws (⑦). (Fig. 3)
- Remove 3 screws. (⑧). (Fig. 2)
- Remove CB76, CB78, CB79, CB80, CB942 and CB944. (Fig. 2)
- Unlock and remove CB946 and CB948. (Fig. 2)
- Remove the DIGITAL (1) P.C.B. which is connected directly to the OPERATION (4) P.C.B. with board-to-board connectors. (Fig. 2)

4. Removal of AMP Unit and Power Transformer

- Remove screw (⑨), 2 screws (⑩), 3 screws (⑪) and 4 screws (⑫). (Fig. 2)
- Remove 3 screws (⑬). (Fig. 3)
- Remove the AMP unit together with the power transformer. (Fig. 2)




Fig. 2





Fig. 3


When checking the MAIN (1) P.C.B.:

- Place the P.C.B.s (with rear panel) upright. (Fig. 4)
- Connect the heatsink and rear panel to the chassis with a ground lead or the like. (Fig. 4)
- Reconnect all cables (connectors) that have been disconnected.
- When connecting the flexible flat cable, be careful with polarity.

**Fig. 4**

When checking the DIGITAL (1) P.C.B.:

- Put the rubber sheet and cloth over this unit, and place the DIGITAL (1) P.C.B. on them. (Fig. 5)
- Connect ST951 on DIGITAL (1) P.C.B. to the chassis with a ground lead. (Fig. 5)
- Reconnect all cables (connectors) that have been disconnected. Be sure to use the P.C.B. CHECKING JIG (Part No. ZF454800) to connect between the following connectors.
CB945 on DIGITAL (1) P.C.B. – CB381 on OPERATION (4) P.C.B.
- When connecting the flexible flat cable, be careful with polarity.

**Fig. 5**

■ UPDATING FIRMWARE

When the following parts are replaced, the firmware must be updated to the latest version.

DIGITAL P.C.B.

FPGA Flash ROM: IC77 on DIGITAL (1) P.C.B.

DSP (TI) Flash ROM: IC923 on DIGITAL (1) P.C.B.

NETWORK Flash ROM: IC953 on DIGITAL (1) P.C.B.

● Confirmation of firmware version and checksum

Before and after updating the firmware, check the firmware version and checksum by using the self-diagnostic function menu.

Start up the self-diagnostic function and select "S4. ROM VERSION/CHECKSUM" menu.

Using the sub-menu, have the firmware version and checksum displayed, and note them down.
(For details, refer to "SELF-DIAGNOSTIC FUNCTION")

* When the firmware version is different from written one after updating, perform the updating procedure again from the beginning again.

● Initializing the back-up IC (EEPROM: IC82 on DIGITAL P.C.B.)

After updating the firmware, the back-up IC MUST be initialized by the following procedure to store the setting information (soundfield parameters, system memory and tuner presetting, etc.) properly.

Start up the self-diagnostic function and select "S3. FACTORY PRESET" menu.
(For details, refer to "SELF-DIAGNOSTIC FUNCTION")

Select "PRESET RSRV", press the "MAIN ZONE  key to turn off the power once and turn on the power again. Then the back-up IC is initialized.

● Required Tools

- USB storage device
- Firmware
R0331-xxxx.bin

● Preparation

1. Download the latest firmware from the specified download source to the folder of the PC.
2. Copy the latest firmware from the PC to the root folder of the USB storage device.

Note: When the latest firmware is copied to a sub-folder of the USB storage device, the update will not proceed.

● Operation Procedures

1. Insert the USB storage device to the USB jack. (Fig. 1)
2. While pressing the "PURE DIRECT" key, connect the power cable to the AC outlet. (Fig. 1)




Fig. 1

3. The USB UPDATE mode is activated and "USB UPDATE" is displayed. Writing of the firmware starts automatically. (Fig. 2)

Writing is started.

Writing being executed.




Fig. 2

- * If "ERROR! xxxx" is displayed during writing of the firmware, refer to "List of Error Messages" to determine the cause and perform the updating procedure again from the beginning.

4. When writing of the firmware is completed, "UPDATE SUCCESS", "PLEASE..." and "POWER OFF!" are displayed repeatedly. (Fig. 3)

Writing is completed.




Fig. 3

5. Press the "MAIN ZONE" key to turn off the power. (Fig. 1)
6. Remove the USB storage device from the USB jack. (Fig. 1)
7. Start up the self-diagnostic function and check that the firmware version and checksum are the same as written ones. (For details, refer to "Confirmation of firmware version and checksum")

List of Error Messages

Display



Error number

Error Number	Error Message	Cause
0001	Microprocessor clearing error	Microprocessor failure
0002	Microprocessor writing error	
0004	Microprocessor checksum error	Microprocessor failure / Mismatch of checksum
0008	DSP1 status port error	DSP1 failure / Malfunction of communication with microprocessor
0010	DSP1 checksum error	
0020	DSP1 data reception time out	
0040	DSP1 checksum calculation time out	
0080	DSP2 status port error	DSP2 failure / Malfunction of communication with microprocessor
0100	DSP2 checksum error	
0200	DSP2 data reception time out	
0400	DSP2 checksum calculation time out	
0800	GUI Flash ROM clearing error	GUI Flash ROM failure / Malfunction of communication with microprocessor
1000	GUI Flash ROM writing error	
2000	GUI Flash ROM checksum error	
4000	Destination judging error	No destination is written on EEPROM.

* The error number is displayed in the 4-digit hexadecimal notation.

* The error numbers are added when a multiple number of errors occur at the same time.

Example If errors by the error number "0002" and "0008" occur at the same time, the error number will be displayed as "000A"

■ SELF-DIAGNOSTIC FUNCTION

This unit has self-diagnostic functions that are intended for inspection, measurement and location of faulty point.

There are 26 main menu items, each of which has sub-menu items.

Listed in the table below are main menu items and sub-menu items.

Note: Some of the menu items listed below may not apply to the models covered in this service manual.

No.	Main menu	No.	Sub-menu
A: Audio system			
A1	DSP AUDIO	1	DSP MARGIN
		2	DSP NON MARGIN
		3	INVALID ITEM (Not for service)
		4	DSP FULL CENTER
		5	DSP FULL SURROUND
		6	DSP FULL SURROUND BACK
		7	DSP FULL SUBWOOFER
A2	DIRECT AUDIO	1	ANALOG DIRECT VH
		2	ANALOG DIRECT VL
A3	HDMI AUDIO	1	HDMI AUTO
		2	INVALID ITEM (Not for service)
		3	ARC1
		4	INVALID ITEM (Not for service)
		5	INVALID ITEM (Not for service)
A4	SPEAKERS SET	1	BI-AMP
		2	ZONE/TONE=MAX
		3	ZONE/TONE=MIN
		4	INVALID ITEM (Not for service)
		5	INVALID ITEM (Not for service)
		6	D-PARTY MODE
		7	FULL MUTE
		8	INVALID ITEM (Not for service)
		9	INVALID ITEM (Not for service)
		10	INVALID ITEM (Not for service)
		11	INVALID ITEM (Not for service)
		12	INVALID ITEM (Not for service)
		13	INVALID ITEM (Not for service)
A5	MULTI CHANNEL INPUT (Not for service)	1	MULTI CHANNEL INPUT 8 ohms
		2	MULTI CHANNEL INPUT 6 ohms
A6	MIC CHECK	1	MIC ROUTE CHECK
A7	MANUAL TEST	1	TEST ALL
		2	TEST FRONT L
		3	TEST CENTER
		4	TEST FRONT R
		5	TEST SURROUND R
		6	TEST SURROUND BACK R
		7	TEST SURROUND BACK L
		8	TEST SURROUND L
		9	TEST FRONT PRESENCE L
		10	TEST FRONT PRESENCE R
		11	INVALID ITEM (Not for service)
		12	INVALID ITEM (Not for service)
		13	TEST LFE 1
		14	INVALID ITEM (Not for service)

No.	Main menu	No.	Sub-menu
D: Display system			
D1	FL CHECK	1	FL CHECK
		2	ALL SEGMENT OFF
		3	ALL SEGMENT ON
		4	CHECK PATTERN 1
		5	CHECK PATTERN 2
Z: Zone system			
Z1	ZONE TEST	1	AV1 (Not for service)
		2	AV2 (Not for service)
		3	AV3 (Not for service)
		4	AV4 (Not for service)
		5	AV5
		6	AV6
		7	AUDIO1
		8	AUDIO2
		9	V-AUX (Not for service)
		10	PHONO (Not for service)
U: Universal system			
U1	USB	1	USB FRONT 1 TRACK
		2	USB FRONT 2 TRACK
		3	USB_VBUS HIGH POWER
N: Network system			
N1	NETWORK	1	IP ADDRESS CHECK
		2	MAC ADDRESS CHECK
		3	LINE NOISE 100 MDI (Not for service)
		4	LINE NOISE 100 MDIX (Not for service)
		5	LINE NOISE 10 MDI (Not for service)
		6	LINE NOISE 10 MDIX (Not for service)
		7	EXT TEST
		8	MAC ADDRESS
C: Communication system			
C1	DIGITAL PCB CHECK	1	ALL
		2	BUS FLASH ROM
		3	BUS FPGA
		4	I2C
		5	FPGA RAM
		6	BUS DIR
		7	BUS DSP
		8	EEPROM
		9	INVALID ITEM (Not for service)
		10	INVALID ITEM (Not for service)
C2	NETWORK IC CHECK	1	ALL
		2	LINK CHECK
		3	PHY TEST
		4	BUS RAM
		5	APL ID CHECK

No.	Main menu	No.	Sub-menu
V: Video system			
V1	ANALOG VIDEO CHECK	1	ANALOG BYPASS
		2	INVALID ITEM (Not for service)
		3	INVALID ITEM (Not for service)
		4	MUTE CHECK
		5	TEST PATTERN (Not for service)
		6	VIDEO IN
V2	DIGITAL VIDEO CHECK	1	LOOPBACK TEST 1
		2	LOOPBACK TEST 2
		3	LOOPBACK TEST 3
		4	INVALID ITEM (Not for service)
		5	INVALID ITEM (Not for service)
		6	INVALID ITEM (Not for service)
		7	HDMI REPEAT
		8	DIGITAL CVBS
		9	INVALID ITEM (Not for service)
		10	DIGITAL COMPONENT
		11	DIGITAL COMPONENT SC
		12	GUI-VIDEO OUT
V3	TEST PATTERN	1	480i
		2	480p
		3	720p 60Hz
		4	1080i 60Hz
		5	1080p 60Hz
		6	576i
		7	576p
		8	720p 50Hz
		9	1080i 50Hz
		10	1080p 50Hz
		11	1080p 24Hz
		12	1080p 24Hz 3D/FP
		13	720p 60Hz 3D/FP
		14	720p 50Hz 3D/FP
		15	1080i 60Hz 3D/FP
		16	1080i 60Hz 3D/SS
		17	1080i 50Hz 3D/SS
		18	720p 60Hz 3D/TB
		19	720p 50Hz 3D/TB
		20	1080p 24Hz 3D/TB
		21	4k 24Hz
T: Troubleshooting Information			
T1	TROUBLE SHOOTING INFORMATION	1	OPERATING TIME
		2	POWER-RELAY ON
		3	POWER AMP B
		4	OUTPUT LEVEL
		5	POWER OFF TIME-OUT
T2	USAGE ENVIRONMENT	1	MAIN ZONE HIGHEST VOLUME
		2	ZONE 2 HIGHEST VOLUME
		3	INVALID ITEM (Not for service)
		4	THM1/THM2 HIGHEST TEMPERATURE
		5	THM3/THM4 HIGHEST TEMPERATURE (Not for service)

No.	Main menu	No.	Sub-menu
T3	EXTERNAL EVENT	1	HISTORY 1
		2	HISTORY 2
		3	HISTORY 3
		4	HISTORY 4
		5	HISTORY 5
		6	HISTORY 6
		7	HISTORY 7
		8	HISTORY 8
T4	INTERNAL INFOMATION	1	DSP INFORMATION
		2	BU ERROR (Not for service)
		3	NRC (Net Restart Counter) (Not for service)
		4	INVALID ITEM (Not for service)
P: Power and protection system			
P1	SYSTEM MONITOR	1	DC
		2	PS
		3	THM
		4	INVALID ITEM (Not for service)
		5	OUTPUT LEVEL
		6	LIMITER CONTROL
		7	L3 (J model) (Not for service)
		8	KEY
		9	USB-VBUS (Not for service)
P2	PROTECTION HISTORY	1	HISTORY 1
		2	HISTORY 2
		3	HISTORY 3
		4	HISTORY 4
S: System and version system			
S1	FIRMWARE UPDATE	1	FIRMWARE UPDATE (Not for service)
S2	SET INFORMATION	1	MODEL
		2	DESTINATION
S3	FACTORY PRESET	1	PRESET INHIBIT/RESERVE
S4	ROM VERSION/CHECKSUM	1	SYSTEM VERSION
		2	MICROPROCESSOR VERSION
		3	MICROPROCESSOR CHECKSUM
		4	FLASH ROM VERSION
		5	FLASH ROM CHECKSUM
		6	NETWORK MICROPROCESSOR VERSION
		7	NETWORK MICROPROCESSOR CHECKSUM
		8	DSP1 VERSION
		9	DSP1 CHECKSUM
		10	INVALID ITEM (Not for service)
		11	INVALID ITEM (Not for service)
		12	GUI VERSION
		13	FPGA GUI VERSION
		14	FPGA SD VERSION
		15	FPGA HD VERSION
		16	INVALID ITEM (Not for service)


● Starting Self-Diagnostic Function

While pressing the “TONE CONTROL” and “INFO” keys, press the “MAIN ZONE ” key to turn on the power, and release those 2 keys.


The self-diagnostic function mode is activated.

Keys of this unit

RX-V675/HTR-6066/TSR-6750



RX-A730



● Starting Self-Diagnostic Function in the protection cancel mode

If the protection function works and causes hindrance to troubleshooting, cancel the protection function by the procedure below, and it will be possible to enter the self-diagnostic function mode. (The protection functions other than the excess current detect function will be disabled.)

While pressing the “TONE CONTROL” and “INFO” keys, press the “MAIN ZONE ” key to turn on the power and keep pressing those 2 keys and “MAIN ZONE ” key for 3 seconds or longer.

The self-diagnostic function mode is activated with the protection functions disabled.

In this mode, the “SLEEP” segment of the FL display flashes to indicate that the mode is self-diagnostic function mode with the protection functions disabled.

CAUTION!

Using this unit with the protection function disabled may cause further damage to this unit. Use special care for this point when using this mode.

● Canceling Self-Diagnostic Function


- Before canceling self-diagnostic function, execute setting for "S3. FACTORY PRESET" menu. (Memory initialization inhibited or Memory initialized).
 - * In order to keep the user memory preserved, be sure to select PRESET INHIBIT (Memory initialization inhibited).
- Press the "MAIN ZONE ϕ " key to turn off the power.

● Display provided when Self-Diagnostic Function started

The display is as described below depending on the situation when the power to this unit is turned off.

1. When the power is turned off by usual operation:

"NO PROTECT" is displayed. Then "A1-1. DSP MARGIN" is displayed in a few seconds.



2. When the protection function worked to turn off the power:

The information of protection function which worked at that time is displayed. Then "A1-1. DSP MARGIN" is displayed in a few seconds.

Note: At that time if you restart the self-diagnostic function after turning off the power once, "NO PROTECT" will be displayed. That is because that situation is equal to "1. When the power is turned off by usual operation:".

However history of the protection function is stored in memory as backup data. For details, refer to "P2. PROTECTION HISTORY" menu.

2-1. When there is a history of protection function due to excess current.

I PROTECT

Cause: An excessive current flowed through the power amplifier.


Supplementary information: As over current of the power amplifier is detected, check condition of each power transistor.

Turning on the power without correcting the abnormality will cause the protection function to work immediately and the power supply will instantly be shut off.

Notes:

- Applying the power to this unit without correcting the abnormality can be dangerous and cause additional circuit damage. To avoid this, if "I PROTECT" protection function works 1 time, the power will not turn on even when the "MAIN ZONE ϕ " key is pressed. In order to turn on the power again, start up the self-diagnostic function.
- The output transistors in each amplifier channel should be checked for damage before applying power to this unit.
- Amplifier current should be monitored by measuring DC voltage across the emitter resistors for each channel.

2-2. When the protection function worked due to abnormal DC output.




Cause: DC output of the power amplifier is abnormal.

Supplementary information: The protection function worked due to a DC voltage appearing at the speaker terminal. A cause could be a defect in the amplifier.

Turning on the power without correcting the abnormality will cause the protection function to work in 5 seconds and the power supply will be shut off.

2-3. When the protection function worked due to abnormal voltage in the power supply section.



Cause: The voltage in the power supply section is abnormal.


Supplementary information: The protection function worked due to a defect or overload in the power supply.

Turning on the power without correcting the abnormality will cause the protection function to work in 1 seconds and the power supply will be shut off.

Notes:

- Applying the power to this unit without correcting the abnormality can be dangerous and cause additional circuit damage. To avoid this, if "PS" and "DC" protection function works 3 times consecutively, the power will not turn on even when the "MAIN ZONE ⏻" key is pressed. In order to turn on the power again, start up the self-diagnostic function.
- The output transistors in each amplifier channel should be checked for damage before applying power to this unit.
- Amplifier current should be monitored by measuring DC voltage across the emitter resistors for each channel.

2-4. When the protection function worked due to excessive heatsink temperature.



Cause: The temperature of the heatsink is excessive.

Supplementary information: The protection function worked due to the temperature limit being exceeded. Causes could be poor ventilation or a defect related to the thermal sensor.

Turning on the power without correcting the abnormality will cause the protection function to work in 1 seconds and the power supply will be shut off.

● History of protection function

When the protection function has worked, its history is stored in memory as backup data.

Even if no abnormality is noted while servicing the unit, an abnormality which has occurred previously can be defined as long as the backup data has been stored.

For details, refer to "P2. PROTECTION HISTORY" menu.

● Operation procedure of Main menu and Sub-menu


There are 26 main menu items, each of which has sub-menu items.

Main menu selection

Select the main menu using "SCENE TV" (forward) and "SCENE BD/DVD" (reverse) keys.

Sub-menu selection

Select the sub-menu using "SCENE RADIO" (forward) and "SCENE NET" (reverse) keys.



● Functions in Self-Diagnostic Function mode

In addition to the self-diagnostic function menu items, functions listed below are available.

- Power ON/OFF
- Master volume
- Muting
- Input selection
- Zone control

* Functions related to the tuner and the set menu are not available.

● Initial settings when Self-Diagnostic Function started

The following initial settings are used when self-diagnostic function is started.

- Master volume: -20 dB / Zone volume: +2.5dB
- Input: HDMI1 / Zone input: AUDIO1
- Main menu: A1-1. DSP MARGIN
- Speaker setting: LARGE, Bass out to SWFR (All channels)
- HDMI Control: Off
- Zone 2: On

* When self-diagnostic function is canceled, these settings are restored to those before starting self-diagnostic function.

● **Details of Self-Diagnostic Function menu**

A1. DSP AUDIO

This menu is used to check audio signal route via DSP.

A1-1. DSP MARGIN

The audio signal is output including the head margin via DSP.

* When input source is stereo, signal is assigned as below.

Front L: Front L, Center, Surround L, Surround Back L
Front R: Front R, Surround R, Surround Back R
Front L +10 dB: Subwoofer

A1-1
DSP MARGIN

A1-2. DSP NON MARGIN

The SUBWOOFER signal is output including the head margin via DSP.

The audio signal other than SUBWOOFER is output without including the head margin via DSP.

A1-2
DSP NON MARGIN

A1-3. INVALID ITEM

Not for service.

A1-3
INVALID ITEM

A1-4. DSP FULL CENTER

The audio signal is output to only CENTER channel in digital full bit without including the head margin.

A1-4
DSP FULL C

A1-5. DSP FULL SURROUND

The audio signal is output to only SURROUND L/R channels in digital full bit without including the head margin.

A1-5
DSP FULL SUR

A1-6. DSP FULL SURROUND BACK

The audio signal is output to only SURROUND BACK L/R channel in digital full bit without including the head margin.

```
A1-6
DSP FULL SB
```

A1-7. DSP FULL SUBWOOFER

The audio signal is output to only SUBWOOFER channel in digital full bit without including the head margin.

```
A1-7
DSP FULL SW
```

A2. DIRECT AUDIO

This menu is used to check audio signal route of PURE DIRECT mode.

A2-1. DIRECT VH

The analog input audio signal is output to FRONT L/R in PURE DIRECT mode.

VH: Voltage High, RY101 on MAIN (1) P.C.B.: Off

```
A2-1
DIRECT :VH
```

A2-2. DIRECT VL

The analog input audio signal is output to FRONT L/R in PURE DIRECT mode.


VL: Voltage Low, RY101 on MAIN (1) P.C.B.: On

```
A2-2
DIRECT :VL
```

A3. HDMI AUDIO


This menu is used to check the route of audio signal input to HDMI IN/OUT jack.

* Before check using “A3-3. ARC 1” menu, be sure to connect a TV monitor equipped with Audio Return Channel function to this unit in advance.



A4. SPEAKERS SET

This menu is used to check the speaker output.



A5. MULTI CHANNEL INPUT

Not for service.



A6. MIC CHECK

A6-1. MIC ROUTE CHECK


The audio signal input to the YPAO MIC jack is output to FRONT L and FRONT R channels via A/D-D/A.




A7. MANUAL TEST

The test noise generated by built-in noise generator in DSP is output to the channels specified by the sub-menu.

	Test noise	Test tone
for SUBWOOFER	30 Hz to 80 Hz pink noise	50 Hz sine wave
for other than SUBWOOFER	500 Hz to 2 kHz pink noise	1 kHz sine wave






RX-V675/HTR-6066/
RX-A730/TSR-6750

D1. FL CHECK


This menu is used to check operation of the FL display.

FL display

D1-1. INITIAL DISPLAY



D1-2. ALL SEGMENT OFF



D1-3. ALL SEGMENT ON




* After check, change to next menu at once.

D1-4. CHECK PATTERN 1



D1-5. CHECK PATTERN 2




Example
Lighting on segments in lattice.

Short	Normal
-------	--------

Segment conditions of the FL tube is checked by turning ON and OFF all segments.
Next, a short between segments next to each other is checked by turning ON and OFF all segments alternately (in lattice).
(In the above example, the segments in the second row from the top are shorted.)

Z1. ZONE TEST

This menu is used to check audio signal route to ZONE2 OUT jack.




RX-V675/HTR-6066/
RX-A730/TSR-6750

U1. USB

This menu is used to check the audio signal route from USB storage device.


U1-1. USB FRONT 1 TRACK

The 1st music file stored in the USB storage device connected to the USB jack is reproduced.
* Copy 2 or more music files from PC to the root folder of the USB storage device in advance.



U1-2. USB FRONT 2 TRACK

The 2nd music file stored in the USB storage device connected to the USB jack is reproduced.



U1-3. USB_VBUS HIGH POWER

The output current (USB_VBUS) of USB jack is output at up to 2.1A/5V.



N1. NETWORK

This menu is used to check functions related to NETWORK.
Connect between LAN port of broadband router and NETWORK jack of this unit with a network cable.

- * When the network condition varies while sub-menu is displayed (e.g., the network is deactivated once), the correct result will not be displayed.
In that case, once turn off the power to this unit, then start up the self-diagnostic function again and select this menu.

N1-1. IP ADDRESS CHECK


This menu is used to check that IP address can be obtained.



OK: Connected (IP address obtained)
NG: No traffic / Disconnected

N1-2. MAC ADDRESS CHECK

This menu is used to check that MAC address is written.



OK: Normal
NG: Unwritten

N1-3. LINE NOISE 100 MDI

Not for service.

N1-3
LN MDI 100

N1-4. LINE NOISE 100 MDIX

Not for service.

N1-4
LN MDIX 100

N1-5. LINE NOISE 10 MDI

Not for service.

N1-5
LN MDI 10

N1-6. LINE NOISE 10 MDIX


Not for service.

N1-6
LN MDIX 10

N1-7. EXT TEST

Transmission/reception of the NETWORK jack is checked.
With the power turned off, short the pins of the NETWORK jack as shown in the figure below.
Start up the self-diagnostic function and select this menu.
Transmission/reception test is executed and its result is displayed.

Note: Be sure to return the shorted pins to their original condition after executing this test.



N1-7
EXT TEST:OK

- OK: Normal
- NG: Abnormal
- : Checking

N1-8. MAC ADDRESS

Written MAC address is displayed.


N1-8
00A0DExxxxxx

C1. DIGITAL P.C.B. CHECK

This menu is used to check the communication and bus line connection between devices on DIGITAL P.C.B.


C1-1. ALL

The synthetic judgment result of sub-menu C1-2 to C1-8 is displayed.




C1-2. BUS FLASH ROM

FLASH ROM (IC77)'s reading/writing are checked.




C1-3. BUS FPGA

Communication and bus line connection between microprocessor (IC83) and FPGA (IC50) are checked.



C1-4. I2C

The I2C (Inter integrated circuit) bus line connection is checked.



C1-5. FPGA RAM

SDRAM (IC53)'s reading/writing are checked.

```
C1-5
FPGA_RAM:OK
```

OK: No error detected

NG: An error is detected

C1-6. BUS DIR1

Communication and bus line connection between microprocessor (IC83) and DIR (IC924) are checked.

```
C1-6
DIR_BUS:OK
```

OK: No error detected

NG: An error is detected

C1-7. BUS DSP1

Communication and bus line connection between microprocessor (IC83) and DSP (IC921) are checked.

```
C1-7
DSP_BUS:OK
```

OK: No error detected

NG: An error is detected

C1-8. EEPROM

EEPROM (IC82)'s reading is checked.

```
C1-8
EEPROM:OK
```

OK: No error detected

NG: An error is detected

C1-9. INVALID ITEM

Not for service.

```
C1-9
INVALID ITEM
```

C1-10. INVALID ITEM

Not for service.

```
C1-10
INVALID ITEM
```

C2. NETWORK IC CHECK

This menu is used to check the communication and bus line connection between devices related to network.

C2-1. ALL

The synthetic judgment result of sub-menu C2-2 to C2-5 is displayed.



When test result using the "C2-2. LINK CHECK" menu is NG, the sub-menu C2-2 is NG, "Ext. JIG" is displayed.

OK: No error detected
NG: An error is detected
--: Checking

C2-2. LINK CHECK

LAN cable connection is checked.

Connect between NETWORK jack of this unit and LAN port of broadband router with a network cable.

- * When the network condition varies while sub-menu is displayed (e.g., the network is deactivated once), the correct result will not be displayed. In that case, once turn off the power to this unit, then start up the self-diagnostic function again and select this menu.



OK: Normal
NG: Disconnected
--: Checking

C2-3. PHY (Ethernet PHYceiver) TEST

Communication and bus line connection between PHY (IC955) and NETWORK microprocessor (IC951) are checked.



OK: No error detected
NG: An error is detected
--: Checking

C2-4. BUS RAM

Communication and bus line connection between SDRAM (IC952) and NETWORK microprocessor (IC951) are checked.



OK: No error detected
NG: An error is detected
--: Checking

C2-5. APL (Apple) ID CHECK

Apple authentication IC (IC956) device ID is checked.

C2-5
APL ID:OK

OK: No error detected

NG: An error is detected

--: Checking

V1. ANALOG VIDEO CHECK


This menu is used to check the analog video signal route.

V1-1. ANALOG BYPASS

The video signal is converted and output as shown below.

V1-1
ANALOG BYPASS

ANALOG BYPASS

**V1-2. INVALID ITEM**

Not for service.

V1-2
INVALID ITEM

V1-3. INVALID ITEM


Not for service.

V1-3
INVALID ITEM

V1-4. MUTE CHECK

The video signal is muted.

V1-4
MUTE CHECK



V1-5. TEST PATTERN

Not for service.

V1-5
TEST PATTERN

V1-6. VIDEO INFORMATION

The information of input analog video signals is displayed.

V1-6
VID IN:480i60


V2. DIGITAL VIDEO CHECK

This menu is used to check the digital video signal route.

V2-1. LOOPBACK TEST 1

Execute the test for all HDMI IN jacks by repeating the procedure below.



1. Select sub-menu other than V2-1.
2. Connect between any of the HDMI IN jacks and HDMI OUT jack with an HDMI cable.
3. Select V2-1. The test result is displayed in a few seconds.



V2-2. LOOPBACK TEST 2

Execute the test for all HDMI IN jacks by repeating the procedure below.



1. Select sub-menu other than V2-2.
2. Connect between any of the HDMI IN jacks and HDMI OUT jack with an HDMI cable.
3. Select the input source corresponding to the connected HDMI IN jack by using "INPUT ◀" and "INPUT ▶" keys (RX-V675/HTR-6066/TSR-6750) / "INPUT" knob (RX-A730).
4. Select V2-2. The test result is displayed in a few seconds.



V2-3. LOOPBACK TEST 3

Execute the test for all HDMI IN jacks by repeating the procedure below.

1. Select sub-menu other than V2-3.
2. Connect between any of the HDMI IN jacks and HDMI OUT jack with an HDMI cable.
3. Select the input source corresponding to the connected HDMI IN jack by using "INPUT <" and "INPUT >" keys (RX-V675/HTR-6066/TSR-6750) / "INPUT" knob (RX-A730).
4. Select V2-3. The test result is displayed in a few seconds.

**V2-4. INVALID ITEM**

Not for service.

V2-4
INVALID ITEM

V2-5. INVALID ITEM

Not for service.

V2-5
INVALID ITEM


V2-6. INVALID ITEM

Not for service.

V2-6
INVALID ITEM


V2-7. HDMI REPEAT

The video/audio signals input to HDMI IN jack are output to HDMI OUT jack.



V2-8. DIGITAL CVBS

The video (CVBS) signal is converted and output as shown below.



V2-9. INVALID ITEM


Not for service.

V2-9
INVALID ITEM

V2-10. DIGITAL COMPONENT

The component video (Y, Cb, Cr) signal is converted and output as shown below.


V2-10
DIGITAL Cmp



V2-11. DIGITAL COMPONENT SC


The component video (Y, Cb, Cr) signal is converted and output as shown below.

HDMI video output up-scaling: 480i/p, 576i/p only => 1080p




V2-12. GUI (Graphical User Interface)-VIDEO OUT

The GUI is output from FPGA (IC50 on DIGITAL P.C.B.).



V3. TEST PATTERN

The video signal is output to HDMI OUT jack with its resolution converted as shown below.



T1. TROUBLE SHOOTING INFORMATION


This menu is used to display the operating time and operation frequency of this unit.

* The operating time and operation frequency during the self-diagnostic function mode will not be stored.

T1-1. OPERATING TIME

The operating time of this unit is displayed.


The operating time will be erased by pressing the “STRAIGHT” key.



T1-2. POWER-RELAY ON

The operation frequency of the power relay (RY371) is displayed in hexadecimal notation.


The operation frequency will be erased by pressing the “STRAIGHT” key.



T1-3. POWER AMP B

The operation frequency of the POWER AMP B relay (RY101) is displayed in hexadecimal notation.


The operation frequency will be erased by pressing the “STRAIGHT” key.



T1-4. OUTPUT LEVEL

The maximum value of the speaker output level is displayed in hexadecimal notation.


The maximum value will be erased by pressing the “STRAIGHT” key.



T1-5. POWER OFF TIME-OUT

The number of time-out times of each module when the power is turned off will be displayed in hexadecimal notation.

All the number of time-out times will be erased by pressing the “STRAIGHT” key.



T2. USAGE ENVIRONMENT

This menu is used to display the maximum level of the MAIN ZONE / ZONE 2 volume and the maximum value of the detected heatsink temperature when this unit is operated.

- * The maximum level of the MAIN ZONE / ZONE 2 volume and the maximum value of the detected heatsink temperature during the self-diagnostic function mode will not be stored.

T2-1. MAIN ZONE HIGHEST VOLUME

The maximum value of the MAIN ZONE volume level maintained for longer than 1 minute is displayed.

The maximum value of the MAIN ZONE volume level will be erased by pressing the "STRAIGHT" key.

```
T2-1
MAIN VOL: .....
```

Maximum value / -80.0 to +16.5 dB

T2-2. ZONE 2 HIGHEST VOLUME

The maximum value of the ZONE 2 volume level maintained for longer than 1 minute is displayed.

The maximum value of the ZONE 2 volume level will be erased by pressing the "STRAIGHT" key.

```
T2-2
Z2 VOL: .....
```

Maximum value / -80.0 to +16.5 dB

T2-3. INVALID ITEM

Not for service.

```
T2-3
INVALID ITEM
```

T2-4. THM1/THM2 HIGHEST TEMPERATURE

The minimum value of the detected heatsink temperature is displayed in hexadecimal notation.

The minimum value of the detected heat sink temperature will be erased by pressing the "STRAIGHT" key.

Normal value

THM1: 51 to FF

THM2: 51 to FF

```
T2-4
THM MIN: 6E/67
```

Heatsink temperature / 0 (High) to FF (Low)

THM2

THM1

T2-5. THM3/THM4 HIGHEST TEMPERATURE

Not for service.

```
T2-5
THM MIN: ---/---
```


T3. EXTERNAL EVENT

This menu is used to display the history of key operation.

- * No matter how many times the same key is pressed, it will be stored only once as its history.
- * The key operation during the self-diagnostic function mode will not be stored.

All history of key operation will be erased by pressing the “STRAIGHT” key.

- * Numeric values in the figure are given as reference only.




List of key operation

Display				Key name
Key number	AD value 1	AD value 2	AD value 3	
0205	77 – 89	FF	FF	MAIN ZONE ϕ
0208	40 – 53	FF	FF	ZONE 2
020F	77 – 89	00 – 09	FF	MAIN ZONE ϕ + STRAIGHT (Advanced setup mode)
0211	xx	FF	FF	HD Radio CDM mode (U model)
0212	xx	FF	FF	HD Radio SPLIT mode (U model)
0300	2D – 3F	FF	FF	SCENE 1 (BD/DVD)
0301	1C – 2C	FF	FF	SCENE 2 (TV)
0302	0A – 1B	FF	FF	SCENE 3 (NET)
0303	00 – 09	FF	FF	SCENE 4 (RADIO)
0500	FF	9C – AD	FF	PROGRAM $\triangleright$
0501	FF	8A – 9B	FF	PROGRAM $\triangleleft$
0526	FF	0 – 9	FF	STRAIGHT
0529	FF	FF	9C – AD	PURE DIRECT
0800	FF	0A – 1B	FF	TONE CONTROL
0A00	FF	FF	2D – 3F	INFO
0C00	FF	FF	D2 – E3	ZONE CONTROL
2C00	FF	FF	8A – 9B	TUNING $\gg$
2C01	FF	FF	77 – 89	TUNING $\ll$
2C02	FF	FF	65 – 76	AM
2C03	FF	FF	54 – 64	FM
2C04	FF	FF	00 – 09	PRESET $\triangleright$
2C05	FF	FF	0A – 1B	PRESET $\triangleleft$
2C06	FF	FF	40 – 53	MEMORY
0101				VOLUME knob (–)
0102				VOLUME knob (+)
0103				INPUT knob (–) (RX-A730)
0104				INPUT knob (+) (RX-A730)
7A	xxxx			* For the details of the remote control key display, refer to “REMOTE CONTROL”
7E	xxxx			

T4. INTERNAL INFORMATION

T4-1. DSP INFORMATION

This menu is used to display the DSP information stored in memory as backup data before rebooting.
The DSP information will be erased by pressing the 'STRAIGHT " key.



Sampling frequency

Display	Sampling frequency [kHz]
0	32
1	44.1
2	48
3	64
4	88.2
5	96
6	128
7	176.4
8	192
10	8
11	11
12	12
13	16
14	22.05
15	24
16	"Unknown"

Channels

Display	Channels
0	Dual Mono
1	1/0
2	2/0
3	3/0
4	2/1
5	3/1
6	2/2
7	3/2
8	2/3
9	3/3
10	2/4
11	3/4
12	HD Multi channel
13	"Unknown"

Decode format

Display	Decode format
0	Analog
1	PCM
2	Dolby Digital
3	Dolby Digital EX
4	DTS
5	DTS 9624
6	DTS ES Matrix
7	DTS ES Discrete
8	DTS 96 ES Matrix
9	AAC
10	DSD
11	Multi PCM
12	Dolby Digital Plus
13	Dolby Digital Plus EX
14	Dolby True HD
15	Dolby True HD EX
16	DTS Express
17	DTS HD
18	DTS HD Master Audio
19	Digital
20	MP3
21	WMA
22	FLAC
25	"Unknown"

T4-2. BU ERROR

Not for service.




T4-3. NRC (Net Restart Counter)

Not for service.



T4-4. INVALID ITEM

Not for service.



P1. SYSTEM MONITOR

This menu is used to display the A/D conversion value of the microprocessor which detects panel keys and protection functions by using the sub-menu.

When "P1-8. KEY" sub-menu is selected, keys become inoperable due to detection of the values of all keys.

However, it is possible to advance to the next menu by pressing the "SCENE RADIO" (forward) key or "SCENE NET" (reverse) key on the remote control.

* Numeric values in the figure are given as reference only.

P1-1. DC

Power amplifier DC (DC voltage) output is detected.

The voltage at 5 pin (DC_PRT) of IC78 is displayed.

Normal value: 32 to 74

(Reference voltage: 3.3 V=255)

* If DC becomes out of the normal value range, the protection function works to turn off the power.



P1-1
DC: 50

P1-2. PS

Power supply voltage (PS) protection detection.

The voltage at 2 pin (PS1_PRT)/1 pin (PS2_PRT)/13 pin (PS3_PRT) of IC78 are displayed.

Voltage detects

PS1: ACBL, AC12, AC5, ± 7

PS2: -VP, +5T, $\pm 5V$

PS3: +5.5V

Normal value


PS1: 51 to 179

PS2: 92 to 147 (PURE DIRECT mode: 139 to 193)

PS3: 132 to 168

(Reference voltage: 3.3 V=255)

* If PS1, PS2 or PS3 becomes out of the normal value range, the protection function works to turn off the power.




P1-2
PS: 117/120/153

PS3
PS2
PS1

P1-3. THM

Temperature of the heatsink (THM) is detected.
The voltage at 12 pin (THM1) of IC78/1 pin (THM2) of IC76 are displayed.
Normal value
THM1: 42 to 255
THM2: 42 to 255 (U, C models)
(Reference voltage: 3.3 V=255)

* If THM1 or THM2 becomes out of the normal value range, the protection function works to turn off the power.



P1-4. INVALID ITEM

Not for service.



P1-5. OUTPUT LEVEL

Output level of speaker output is detected.
The voltage at 4 pin (AMP_OLV) of IC78 is displayed.
(Reference voltage: 3.3 V=255)




P1-6. LIMITER CONTROL

Power limiter control is detected.
The voltage at 4 pin (AMP_LMT) of IC83 is displayed.
(Reference voltage: 3.3 V=255)



P1-7. L3 (J model)

Not for service.



P1-8. KEY


Panel key is detected.

When the A/D conversion value of the panel key becomes out of the specified range, normal operation will not be available.

In that case, check the constant of voltage dividing resistor, solder condition, etc. Refer to table.

* When “P1-8. KEY” menu is selected, keys become inoperable due to detection of the values of all keys. However, it is possible to advance to the next menu by pressing the “SCENE RADIO” (forward) key or “SCENE NET” (reverse) key on the remote control.

(Reference voltage: 3.3 V=255)



Display	KEY1
0 – 11	RADIO (SCENE4)
12 – 32	NET (SCENE3)
33 – 54	TV (SCENE2)
55 – 75	BD/DVD (SCENE1)
76 – 96	ZONE CONTROL
97 – 119	ZONE2
120 – 142	INPUT > (RX-V675/HTR-6066/TSR-6750 models)
143 – 172	INPUT < (RX-V675/HTR-6066/TSR-6750 models)
173 – 202	MAIN ZONE ⏻
203 – 235	ZONE CONTROL
255	Key off

Display	KEY2
0 – 11	PURE DIRECT
12 – 32	TUNING >>
33 – 54	TUNING <<
55 – 77	AM
78 – 99	FM
100 – 121	PRESET >
122 – 144	PRESET <
145 – 166	MEMORY
167 – 186	INFO
187 – 205	STRAIGHT
206 – 226	PROGRAM >
227 – 246	PROGRAM <
255	Key off


P1-9. USB-VBUS

Not for service.




P2. PROTECTION HISTORY

This menu is used to display the history of protection function.
All history of protection function will be erased by pressing the "STRAIGHT" key.
* Numeric values in the figure are given as reference only.



S1. FIRMWARE UPDATE

Not for service.



S2. SET INFORMATION

The model name and destination of this unit are displayed.

S2-1. MODEL


The model name of this unit is displayed.



- Not for service.
- Model name
 - V675 : RX-V675
 - 6066 : HTR-6066
 - A730 : RX-A730
 - 6750 : TSR-6750

S2-2. DESTINATION

The destination of this unit is displayed.




- A/D conversion value
- Destination

Destination	J	U	C	R (R, S)	T	K	A	BG (B, G, F)	L (L, H)
A/D conversion value (3.3 V=255)	0 – 12	13 – 39	40 – 67	68 – 92	93 – 115	116 – 140	141 – 169	199 – 221	222 – 244

S3. FACTORY PRESET

This menu is used to reserve/inhibit initialization of the back-up IC (EEPROM: IC82 on DIGITAL P.C.B.).



- S3-1. PRESET INHIBIT** (Initialization inhibited)
Initialization of the back-up IC is not executed. Select this sub-menu to protect the values set by the user.





- S3-1. PRESET RESERVED** (Initialization reserved)
Initialization of the back-up IC is reserved. (Actual initialization is executed when the power is turned on next.) To reset to the original factory settings or to reset the backup IC, select this sub-menu and press the “MAIN ZONE  ” key to turn off the power.

CAUTION: Before setting to the PRESET RESERVED, write down the existing preset memory content of the tuner. (This is because setting to the PRESET RESERVED will cause the user memory content to be erased.)

S4. ROM VERSION/CHECKSUM

The firmware version and checksum values are displayed.
The checksum is obtained by adding the data at every 8-bit and expressing the result as a hexadecimal notation.
* Numeric values in the figure are given as reference only.






■ POWER AMPLIFIER ADJUSTMENT

1. Right after power is turned on, confirm that the voltage across the terminals of R1152 (SURROUND BACK Rch), R1154 (SURROUND Rch), R1150 (FRONT Rch), R1148 (CENTER), R1149 (FRONT Lch), R1153 (SURROUND Lch) and R1151 (SURROUND BACK Lch) are within the confines of 0.1 mV to 10 mV.
2. If measured voltage exceeds 10 mV, open (cut off) R1104 (SURROUND BACK Rch), R1106 (SURROUND Rch), R1102 (FRONT Rch), R1100 (CENTER), R1101 (FRONT Lch), R1105 (SURROUND Lch) and R1103 (SURROUND BACK Lch), and then reconfirm the voltage.

Attention


If the measured voltage exceeds 10 mV after repairing the power amplifier, check other parts again for any possible defect before cutting the resistor.

3. Confirm that the voltage is within the confines of 0.2 mV to 15 mV after 60 minutes.



■ DISPLAY DATA

● V3001 : 18-MT-11GNAK (OPERATION P.C.B.)







● PIN CONNECTION

Pin No.	69	68	67	66	65	64	63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35
Connection	F2	NX	NP	NP	P1	P2	P3	P4	P5	P6	P7	P8	P9	P10	P11	P12	P13	P14	P15	P16	P17	P18	P19	P20	P21	P22	P23	P24	P25	P26	P27	P28	P29	P30	P31

Pin No.	34	33	32	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
Connection	P32	P33	P34	P35	P36	NX	NX	NX	NX	NX	NX	NX	18G	17G	16G	15G	14G	13G	12G	11G	10G	9G	8G	7G	6G	5G	4G	3G	2G	1G	NP	NP	NX	F1

Note : 1) F1, F2 Filament pin 2) NP No pin 3) NX No extend pin 4) 1G-18G Grid pin

● GRID ASSIGNMENT





● ANODE CONNECTION

	18G	17G	16G	15G	1G-14G
P1	1a	1a	1a	S5	1-1
P2	1h	1h	1h	S7	2-1
P3	1j	1j	1j	1d	3-1
P4	1k	1k	1k	2d	4-1
P5	1b	1b	1b	S2	5-1
P6	1f	1f	1f	1e	1-2
P7	1m	1m	1m	2e	2-2
P8	1g	1g	1g	S3	3-2
P9	1c	1c	1c	1c	4-2
P10	1e	1e	1e	2c	5-2
P11	1r	1r	1r	S4	1-3
P12	1p	1p	1p	1g	2-3
P13	1n	1n	1n	2g	3-3
P14	1d	1d	1d	1f	4-3
P15	2a	2a	2a	2f	5-3
P16	2h	2h	2h	1b	1-4
P17	2j	2j	2j	2b	2-4
P18	2k	2k	2k	1a	3-4
P19	2b	2b	2b	2a	4-4
P20	2f	2f	2f	PL	5-4
P21	2m	2m	2m	SW	1-5
P22	2g	2g	2g	PR	2-5
P23	2c	2c	2c	L	3-5
P24	2e	2e	2e	C	4-5
P25	2r	2r	2r	R	5-5
P26	2p	2p	2p	SL	1-6
P27	2n	2n	2n	SR	2-6
P28	2d	2d	2d	SBL	3-6
P29	SIRIUS	S8	HD	SB	4-6
P30	OUT	S9	TAG	SBR	5-6
P31	HDMI	iPod CHARGE	CINEMA DSP	S6	1-7
P32	1	SP B	3	S13	2-7
P33	2	S15	STEREO	MUTE	3-7
P34	S12	SP A	TUNED	ZONE 2	4-7
P35	S10	PARTY	ENHANCER	ZONE 3	5-7
P36	S11	—	ADAPTIVE DRC	SLEEP	S1

IC DATA

IC921: D80YK113CTP400 (DIGITAL (1) P.C.B.)
DSP (Digital signal processor)



Pin No.	Function Name	TYPE (1)	PULL (2)	Detail of Function
1	AXR1[0]/GP4[0]	I/O	IPD	McASP1 serial data
2	UART0_RXD/I2C0_SDA/TM64P0_IN12/GP5[8]/BOOT[8]	I	IPU	BOOT[8]
		I	IPU	UART0 receive data
		I/O	IPU	I2C0 serial data
		I	IPU	Timer0 lower input
3	UART0_TXD/I2C0_SCL/TM64P0_OUT12/GP5[9]/BOOT[9]	I	IPU	BOOT[9]
		O	IPU	UART0 transmit data
		I/O	IPU	I2C0 serial clock
		O	IPU	Timer0 lower output
4	AXR1[10]/GP5[10]	I/O	IPU	McASP1 serial data
5	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
6	AXR1[11]/GP5[11]	I/O	IPU	McASP1 serial data
7	SPI1_ENA /UART2_RXD/GP5[12]	I/O	IPU	SPI1 enable
		I	IPU	UART2 receive data
8	SPI1_SCS[0] /UART2_TXD/GP5[13]	I/O	IPU	SPI1 chip select
		O	IPU	UART2 transmit data
9	SPI0_SCS[0] /UART0_RTS/EQEP0B/GP5[4]/BOOT[4]	I/O	IPU	SPI0 chip select
		I	IPU	eQEP0B quadrature input
		I	IPU	BOOT[4]
		O	IPU	UART0 ready-to-send output
10	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
11	SPI0_CLK/EQEP11/GP5[2]/BOOT[2]	I/O	IPD	SPI0 clock
		I	IPD	eQEP1 index
		I	IPD	BOOT[2]
12	SPI0_ENA /UART0_CTS/EQEP0A/GP5[3]/BOOT[3]	I/O	IPU	SPI0 enable
		I	IPU	eQEP0A quadrature input
		I	IPU	BOOT[3]
		I	IPU	UART0 clear-to-send input
13	SPI1_SOMI[0]/I2C1_SCL/GP5[5]/BOOT[5]	I/O	IPU	SPI1 data/slave-out-master-in
		I	IPU	BOOT[5]
		I/O	IPU	I2C1 serial clock
14	SPI1_SIMO[0]/I2C1_SDA/GP5[6]/BOOT[6]	I/O	IPU	SPI1 data/slave-in-master-out
		I	IPU	BOOT[6]
		I/O	IPU	I2C1 serial Data
15	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
16	SPI1_CLK/EQEP1S/GP5[7]/BOOT[7]	I/O	IPD	SPI1 clock
		I	IPD	eQEP1 strobe
		I	IPD	BOOT[7]
17	SPI0_SOMI[0]/EQEP0I/GP5[0]/BOOT[0]	I/O	IPD	SPI0 data/slave-out-master-in
		I	IPD	eQEP0 index
		I	IPD	BOOT[0]
18	SPI0_SIMO[0]/EQEP0S/GP5[1]/BOOT[1]	I/O	IPD	SPI0 data/slave-in-master-out
		I	IPD	eQEP0 strobe
		I	IPD	BOOT[1]
19	EMA_WAIT[0]/ UHPI_HRDY/GP2[10]	I	IPU	EMIFA wait input/interrupt
		I/O	IPU	UHPI ready
20	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
21	EMA_CS[3] /AMUTE2/GP2[6]	O	IPU	EMIFA Async chip select
		O	IPU	McASP2 mute output
22	EMA_OE /UHPI_HDS1/AXR0[13]/GP2[7]	O	IPU	EMIFA output enable
		I/O	IPU	UHPI data strobe
23	EMA_CS[2] /UHPI_HCS/GP2[5]/BOOT[15]	O	IPU	EMIFA Async chip select
		I	IPU	BOOT[15]
		I/O	IPU	UHPI chip select
24	EMA_OE/UHPI_HDS1/AXR0[13]/GP2[7] DVDD (I/O supply)	I/O	IPU	McASP0 serial data
		PWR		3.3-V I/O supply voltage pins
25	EMA_BA[0]/ GP1[14]	O	IPU	EMIFA bank address
26	EMA_BA[1]/ UHPI_HHWIL/GP1[13]	O	IPU	EMIFA bank address
		I/O	IPU	UHPI half-word identification control

Pin No.	Function Name	TYPE (1)	PULL (2)	Detail of Function
27	EMA_A[10]/ GP1[10]	O	IPU	EMIFA address bus
28	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
29	EMA_A[0]/ GP1[0]	O	IPD	EMIFA address bus
30	EMA_A[1]/MMCSA_CLK/UHPI_HCNTL0/GP1[1]	O	IPU	EMIFA address bus
		I/O	IPU	UHPI access control
		O	IPU	MMCSA_CLK
31	EMA_A[2]/MMCSA_CMD/UHPI_HCNTL1/GP1[2]	O	IPU	EMIFA address bus
		I/O	IPU	UHPI access control
		I/O	IPU	MMCSA_CMD
32	EMA_A[3]/ GP1[3]	O	IPD	EMIFA address bus
33	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
34	EMA_A[4]/ GP1[4]	O	IPD	EMIFA address bus
35	EMA_A[5]/ GP1[5]	O	IPD	EMIFA address bus
36	EMA_A[6]/ GP1[6]	O	IPD	EMIFA address bus
37	EMA_A[7]/ GP1[7]	O	IPD	EMIFA address bus
38	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
39	EMA_A[8]/ GP1[8]	O	IPU	EMIFA address bus
40	EMA_A[9]/ GP1[9]	O	IPU	EMIFA address bus
41	EMA_A[11]/ GP1[11]	O	IPU	EMIFA address bus
42	EMA_A[12]/ GP1[12]	O	IPU	EMIFA address bus
43	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
		I/O	IPU	EMIFA data bus
		I	IPU	BOOT[12]
		I/O	IPU	UHPI data bus
44	EMA_D[0]/MMCSA_DAT[0]/UHPI_HD[0]/GP0[0]/BOOT[12]	I/O	IPU	MMC/SD data
		I/O	IPU	EMIFA data bus
		I/O	IPU	UHPI data bus
		I/O	IPU	MMC/SD data
45	EMA_D[1]/MMCSA_DAT[1]/UHPI_HD[1]/GP0[1]	I/O	IPU	EMIFA data bus
		I/O	IPU	UHPI data bus
		I/O	IPU	MMC/SD data
46	EMA_D[2]/MMCSA_DAT[2]/UHPI_HD[2]/GP0[2]	I/O	IPU	EMIFA data bus
		I/O	IPU	UHPI data bus
		I/O	IPU	MMC/SD data
47	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
48	EMA_D[3]/MMCSA_DAT[3]/UHPI_HD[3]/GP0[3]	I/O	IPU	EMIFA data bus
		I/O	IPU	UHPI data bus
		I/O	IPU	MMC/SD data
49	EMA_D[4]/MMCSA_DAT[4]/UHPI_HD[4]/GP0[4]	I/O	IPU	EMIFA data bus
		I/O	IPU	UHPI data bus
		I/O	IPU	MMC/SD data
50	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
51	EMA_D[5]/MMCSA_DAT[5]/UHPI_HD[5]/GP0[5]	I/O	IPU	EMIFA data bus
		I/O	IPU	UHPI data bus
		I/O	IPU	MMC/SD data
52	EMA_D[6]/MMCSA_DAT[6]/UHPI_HD[6]/GP0[6]	I/O	IPU	EMIFA data bus
		I/O	IPU	UHPI data bus
		I/O	IPU	MMC/SD data
53	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
54	EMA_D[7]/MMCSA_DAT[7]/UHPI_HD[7]/GP0[7]/BOOT[13]	I/O	IPU	EMIFA data bus
		I	IPU	BOOT[13]
		I/O	IPU	UHPI data bus
		I/O	IPU	MMC/SD data
55	EMA_WE /UHPI_HRW/AXR0[12]/GP2[3]/BOOT[14]	O	IPU	EMIFA SDRAM write enable
		I	IPU	BOOT[14]
		I/O	IPU	UHPI read/write
		I/O	IPU	McASP0 serial data
56	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
57	EMB_CAS	O	IPU	EMIFB column address strobe
58	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
59	EMB_WE	O	IPU	EMIFB write enable
60	EMB_WE_DQM[0]/GP5[15]	O	IPU	EMIFB write enable/data mask for EMB_D.

Pin No.	Function Name	TYPE (1)	PULL (2)	Detail of Function
61	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
62	EMB_D[7]/GP6[7]	I/O	IPD	EMIFB SDRAM data bus
63	EMB_D[6]/GP6[6]	I/O	IPD	EMIFB SDRAM data bus
64	EMB_D[5]/GP6[5]	I/O	IPD	EMIFB SDRAM data bus
65	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
66	EMB_D[4]/GP6[4]	I/O	IPD	EMIFB SDRAM data bus
67	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
68	EMB_D[3]/GP6[3]	I/O	IPD	EMIFB SDRAM data bus
69	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
70	EMB_D[2]/GP6[2]	I/O	IPD	EMIFB SDRAM data bus
71	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
72	EMB_D[1]/GP6[1]	I/O	IPD	EMIFB SDRAM data bus
73	EMB_D[0]/GP6[0]	I/O	IPD	EMIFB SDRAM data bus
74	EMB_D[15]/GP6[15]	I/O	IPD	EMIFB SDRAM data bus
75	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
76	EMB_D[14]/GP6[14]	I/O	IPD	EMIFB SDRAM data bus
77	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
78	EMB_D[13]/GP6[13]	I/O	IPD	EMIFB SDRAM data bus
79	EMB_D[12]/GP6[12]	I/O	IPD	EMIFB SDRAM data bus
80	EMB_D[11]/GP6[11]	I/O	IPD	EMIFB SDRAM data bus
81	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
82	EMB_D[10]/GP6[10]	I/O	IPD	EMIFB SDRAM data bus
83	EMB_D[9]/GP6[9]	I/O	IPD	EMIFB SDRAM data bus
84	EMB_D[8]/GP6[8]	I/O	IPD	EMIFB SDRAM data bus
85	EMB_WE_DQM[1]/GP5[14]	O	IPU	EMIFB write enable/data mask for EMB_D
86	EMB_CLK	O	IPU	EMIF SDRAM clock
87	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
88	EMB_SDCKE	I/O	IPU	EMIFB SDRAM clock enable
89	EMB_A[12]/GP3[13]	O	IPD	EMIFB SDRAM row/column address bus
90	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
91	EMB_A[11]/GP7[13]	O	IPD	EMIFB SDRAM row/column address bus
92	EMB_A[9]/GP7[11]	O	IPD	EMIFB SDRAM row/column address bus
93	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
94	EMB_A[8]/GP7[10]	O	IPD	EMIFB SDRAM row/column address bus
95	EMB_A[7]/GP7[9]	O	IPD	EMIFB SDRAM row/column address bus
96	EMB_A[6]/GP7[8]	O	IPD	EMIFB SDRAM row/column address bus
97	EMB_A[5]/GP7[7]	O	IPD	EMIFB SDRAM row/column address bus
98	EMB_A[4]/GP7[6]	O	IPD	EMIFB SDRAM row/column address
99	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
100	EMB_A[3]/GP7[5]	O	IPD	EMIFB SDRAM row/column address
101	EMB_A[2]/GP7[4]	O	IPD	EMIFB SDRAM row/column address
102	EMB_A[1]/GP7[3]	O	IPD	EMIFB SDRAM row/column address
103	EMB_A[0]/GP7[2]	O	IPD	EMIFB SDRAM row/column address
104	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
105	EMB_A[10]/GP7[12]	O	IPD	EMIFB SDRAM row/column address bus
106	EMB_BA[1]/GP7[0]	O	IPU	EMIFB SDRAM bank address
107	EMB_BA[0]/GP7[1]	O	IPU	EMIFB SDRAM bank address
108	EMB_CS[0]	O	IPU	EMIFB SDRAM chip select 0
109	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
110	EMB_RAS	O	IPU	EMIFB SDRAM row address strobe
111	AXR0[0]/AFSR2/GP3[0]	I/O	IPD	McASP0 serial data
		O	IPD	McASP2 serial data
112	AXR0[1]/ACLKX2/GP3[1]	I/O	IPD	McASP0 serial data
		O	IPD	McASP2 transmit bit clock
113	AXR0[2]/AXR2[3]/GP3[2]	I/O	IPD	McASP0 serial data
		O	IPD	McASP2 serial data
114	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
115	AXR0[3]/AXR2[2]/GP3[3]	I/O	IPD	McASP0 serial data
		O	IPD	McASP2 serial data

Pin No.	Function Name	TYPE (1)	PULL (2)	Detail of Function
116	AXR0[4]/ AXR2[1]/GP3[4]	I/O	IPD	McASP0 serial data
		O	IPD	McASP2 serial data
117	AXR0[5]/AFSX2/GP3[5]	I/O	IPD	McASP0 serial data
		O	IPD	McASP2 transmit frame sync
118	AXR0[6]/ACLKR2/GP3[6]	I/O	IPD	McASP0 serial data
		I/O	IPD	McASP2 receive bit clock
119	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
120	AXR0[7]/GP3[7]	I/O	IPD	McASP0 serial data
121	AXR0[8]/GP3[8]	I/O	IPU	McASP0 serial data
122	UART1_RXD/AXR0[9]/GP3[9]	I	IPD	UART1 receive data
		(3) I/O	IPD	McASP0 serial data
123	UART1_TXD/AXR0[10]/GP3[10]	O	IPD	UART1 transmit data
		(3) I/O	IPD	McASP0 serial data
124	AXR0[11]/ AXR2[0]/GP3[11]	I/O	IPD	McASP0 serial data
		O	IPD	McASP2 serial data
125	AHCLKX0/AHCLKX2/USB_REFCLKIN/GP2[11]	I/O	IPD	McASP0 transmit master clock
		O	IPD	McASP2 transmit master clock
		I	IPD	USB_REFCLKIN. Optional 48 MHz clock input
126	ACLKX0/ECAP0/APWM0/GP2[12]	I/O	IPD	Enhanced capture 0/input or auxiliary PWM 0 output
		I/O	IPD	McASP0 transmit bit clock
127	AFSX0/GP2[13]/BOOT[10]	I	IPD	BOOT[10]
		I/O	IPD	McASP0 transmit frame sync
128	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
129	AHCLKR0/GP2[14]/BOOT[11]	I	IPD	BOOT[11]
		I/O	IPD	McASP0 receive master clock
130	ACLKR0/ECAP1/APWM1/GP2[15]	I/O	IPD	Enhanced capture 1/input or auxiliary PWM 1 output
		I/O	IPD	McASP0 receive bit clock
131	AFSR0/GP3[12]	I/O	IPD	McASP0 receive frame sync
132	AMUTE1/EPWMTZ/GP4[14]	I/O	IPD	eHRPWM0 trip zone input
		I/O	IPD	eHRPWM1 trip zone input
		I/O	IPD	eHRPWM2 trip zone input
		O	IPD	McASP1 mute output
133	RSV2	PWR		Reserved. For proper device operation, this pin must be tied directly to CVDD
134	USB0_VDDA12	(4) PWR		USB0 PHY 1.2-V LDO output for bypass cap
135	USB0_VDDA18	PWR		USB0 PHY 1.8-V supply input
136	NC	–	–	–
137	USB0_DP	A		USB0 PHY data plus
138	USB0_DM	A		USB0 PHY data minus
139	NC	–	–	–
140	USB0_VDDA33	PWR		USB0 PHY 3.3-V supply
141	PLL0_VDDA	PWR		PLL analog VDD (1.2-V filtered supply)
142	PLL0_VSSA	GND		PLL analog VSS (for filter)
143	OSCIN	I		Oscillator input
144	OSCVSS	GND		Oscillator ground (for filter only)
145	OSCOUT	O		Oscillator output
146	RESET	I		Device reset input
147	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
148	RTC_XI	I		Low-frequency (32-kHz) oscillator receiver for real-time clock
149	RTC_CVDD	PWR		RTC module core power (isolated from rest of chip CVDD)
150	TRST	I	IPD	JTAG test reset
151	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
152	TMS	I	IPU	JTAG test mode select
153	TDI	I	IPU	JTAG test data input
154	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
155	TCK	I	IPU	JTAG test clock
156	TDO	O	IPD	JTAG test data output
157	GP7[14]	(5) I/O	IPD	General-Purpose IO signal
158	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
159	CVDD (Core supply)	PWR		1.2-V core supply voltage pins

Pin No.	Function Name	TYPE (1)	PULL (2)	Detail of Function
160	AHCLKX1/EPWM0B/GP3[14]	I/O	IPD	eHRPWM0 B output
		I/O	IPD	McASP1 transmit master clock
161	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
162	ACLKX1/EPWM0A/GP3[15]	I/O	IPD	eHRPWM0 A output
		I/O	IPD	McASP1 transmit bit clock
163	AFSX1/EPWMSYNCl/EPWMSYNCO/GP4[10]	I/O	IPD	Sync input to eHRPWM0 module or sync output to external PWM
		I/O	IPD	McASP1 transmit frame sync
164	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
165	ACLKR1/ECAP2/APWM2/GP4[12]	I/O	IPD	enhanced capture 2/input or auxiliary PWM 2 output
		I/O	IPD	McASP1 receive bit clock
166	AFSR1/GP4[13]	I/O	IPD	McASP1 receive frame sync
167	CVDD (Core supply)	PWR		1.2-V core supply voltage pins
168	AXR1[8]/EPWM1A/GP4[8]	I/O	IPD	eHRPWM1 A (with high-resolution)
		I/O	IPD	McASP1 serial data
169	AXR1[7]/EPWM1B/GP4[7]	I/O	IPD	eHRPWM1 B
		I/O	IPD	McASP1 serial data
170	AXR1[6]/EPWM2A/GP4[6]	I/O	IPD	eHRPWM2 A (with high-resolution)
		I/O	IPD	McASP1 serial data
171	AXR1[5]/EPWM2B/GP4[5]	I/O	IPD	eHRPWM2 B
		I/O	IPD	McASP1 serial data
172	DVDD (I/O supply)	PWR		3.3-V I/O supply voltage pins
173	AXR1[4]/EQEP1B/GP4[4]	I	IPD	eQEP1B quadrature input
		I/O	IPD	McASP1 serial data
174	AXR1[3]/EQEP1A/GP4[3]	I	IPD	eQEP1A quadrature input
		I/O	IPD	McASP1 serial data
175	AXR1[2]/GP4[2]	I/O	IPD	McASP1 serial data
176	AXR1[1]/GP4[1]	I/O	IPD	McASP1 serial data

(1) I = Input, O = Output, I/O = Bidirectional, Z = High impedance, PWR = Supply voltage, GND = Ground, A = Analog signal.

Note: The pin type shown refers to the input, output or high-impedance state of the pin function when configured as the the signal name highlighted in bold. All multiplexed signals may enter a high-impedance state when the configured function is input-only or the configured function supports high-Z operation. All GPIO signals can be used as input or output. For multiplexed pins where functions have different types (ie., input versus output), the table reflects the pin function direction for that particular peripheral.

(2) IPD = Internal Pulldown resistor, IPU = Internal Pullup resistor


(3) 122, 123 pin: As these signals are internally pulled down while the device is in reset, it is necessary to externally pull them high with resistors if UART1 boot mode is used.

(4) 134 pin: Core power supply LDO output for USB PHY. This pin must be connected via a 0.22-mF capacitor to VSS. When the USB peripheral is not used, the USB_VDDA12 signal should still be connected via a 1-mF capacitor to VSS.

(5) 157 pin: GP7[14] is initially configured as a reserved function after reset and will not be in a predictable state. This signal will only be stable after the GPIO configuration for this pin has been completed. Users should carefully consider the system implications of this pin being in an unknown state after reset.

IC951: DM860A (DIGITAL (1) P.C.B.)
Network microprocessor

* No replacement part available.



	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	
A	USBDN	VDD33 USBC	VSS33 USBC	n.c.	n.c.	VDD33	RFCLKP	RFRXQP	RFRXIP	HIGHZ	SSMD0	SSMD4	SSMCMD	RXD1	TDO	TDI	A0	A1	A
B	USBDP	VDD33 USBT	VSS33 USBT	n.c.	n.c.	VSS	RFCLKN	RFRXQN	RFRXIN	TEST1	SSMD1	SSMD5	TXD1	RXD0	TMS	SPICLK	SPINCS1	A2	B
C	VSS12 USB	USBREXT	USBXO	USBXI	NRES12 OUT	VSS	RREF	n.c.	n.c.	SSMCLK	SSMD2	SSMD6	TXD0	TCK	SPINCS0	A3	A4	A5	C
D	VDD12 USB	USBVBUS	USBATST	NRES33 OUT	NRES33 REF	NRES12 REF	VDD33	VDD12	SSMWP	SSMCP	SSMD3	SSMD7	NRESET	SPDI	SPIDO	A6	A7	A8	D
E	VSS33 RTC	USBDI	USBV8 USDRV	NC		VDD12 CORE	VDD12 CORE	VDD33IO	VDD33IO	VDD12 CORE	VDD12 CORE	VDD33IO	VDD33IO		A9	A10	A11	A12	E
F	VDD33 RTC	RTCXIN	VDD33 PLL	NC	VDD33IO	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD12 CORE	A13_RAS	A14_CAS	A15_BA0	A16_BA1	F
G	VDD12 DCO	RTXCOUT	VSS33 PLL	NC	VDD33IO	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD12 CORE	A17_DQ M0	A18_DQ M1	A19	A20	G
H	VSS12 DCO	VSS12 PLL	VDD12 PLL	NC	VDD12 CORE	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD33IO	A21	A22	A23	NCS3	H
J	PDOUT1	VCO1	XTALO	NC	VDD12 CORE	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD33IO	NCS0	NCS1	NCS2	MEMCKE	J
K	PDOUT0	VCO0	XTALI	AOUTLP	VDD33IO	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD12 CORE	MEMCLK	NWE	NOE	NWAIT	K
L	AV0CLK	AOUTLN	AOUTRN	AOUTRP	VDD33IO	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD12 CORE	D3	D2	D1	D0	L
M	AV0 CTRL0	AV0 CTRL1	AV0 CTRL2	AV0 DATA3	VDD12 CORE	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD33IO	D7	D6	D5	D4	M
N	AV0 DATA2	AV0 DATA1	AV0 DATA0	AV1 DATA3	VDD12 CORE	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD33IO	D11	D10	D9	D8	N
P	AV1 DATA2	AV1 DATA1	AV1 DATA0	AV2 DATA3		VDD33IO	VDD33IO	VDD12 CORE	VDD12 CORE	VDD33IO	VDD33IO	VDD12 CORE	VDD12 CORE		FD0	FD1	D13	D12	P
R	AV2CLK	AV2 CTRL1	AV2 CTRL2	AV3CLK	AV3 DATA1	LCDD11	LCDD7	LCDD3	LCD CTRL0	VPP	MIITXEN	MIITXCLK	MIIRXER	MIICRS	FD2	FD3	FD4	D14	R
T	AV2 CTRL0	AV2 DATA1	AV3 CTRL1	AV3 DATA0	LCDD14	LCDD10	LCDD6	LCDD2	LCD CTRL1	LCCLK	MIITXER	MIIRXCLK	MIICOL	MII RXDV	FD5	FD6	FD7	D15	T
U	AV2 DATA2	AV3 CTRL0	AV4 DATA1	LCDD16	LCDD13	LCDD9	LCDD5	LCDD1	LCD CTRL2	MIITXD0	MIITXD2	MIIRXD0	MIIRXD2	MIIMDIO	NFCE0	FCLE	NFWE	NFRB	U
V	NC	AV4 DATA0	LCDD17	LCDD15	LCDD12	LCDD8	LCDD4	LCDD0	LCD CTRL3	MIITXD1	MIITXD3	MIIRXD1	MIIRXD3	MIIMDC	MIIPHY CLK	NFWP	NFRE	FALE	V
	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	

AV-Port 0

Pin No.	Function Name	I/O	Detail of Function
M4	AV0DATA[3:0]	I/O	Audio/video data. Several formats are supported.
N1			
N2			
N3			
N4	AV1DATA[3:0]	I/O	Video data, together with AV0DATA[3:0]: AV0DATA[3:0] = video[3:0] AV1DATA[3:0] = video[7:4]
P1			
P2			
P3			
L1	AV0CLK	I/O	Data clock. Depending on the AV-Port 0 configuration, this clock is a bit- or byte-clock which is used to transmit or receive the AV0DATA[*] synchronously.
M1	AV0CTRL0	I/O	Configurable sync signal: • Serial audio formats: LRCK input or output. • Video formats: PSYNC input or output.
M2	AV0CTRL1	I/O	Configurable sync signal: • Serial audio formats: Master clock output. • Video formats: DVALID input or output.
M3	AV0CTRL2	I/O	Configurable sync signal: • Video formats: FSYNC input or output.

AV-Port 2

Pin No.	Function Name	I/O	Detail of Function
P4	AV2DATA[3:0]	I/O	Audio data. Several formats are supported.
R3			
T2			
U1			
R1	AV2CLK	I/O	Data clock. Depending on the AV-Port 2 configuration this clock is a bit-clock which is used to transmit or receive the AV2DATA[*] synchronously.
T1	AV2CTRL0	I/O	Configurable sync signal: Serial audio formats: LRCK input or output.
R2	AV2CTRL1	I/O	Configurable sync signal: Serial audio formats: Master clock output.

AV-Port 3

Pin No.	Function Name	I/O	Detail of Function
R5	AV3DATA[1:0]	I/O	Audio data. Several formats are supported.
T4			
R4	AV3CLK	I/O	Data clock. Depending on the AV-Port 3 configuration this clock is a bit-clock which is used to transmit or receive the AV3DATA[*] synchronously.
U2	AV3CTRL0	I/O	Configurable sync signal: Serial audio formats: LRCK input or output.
T3	AV3CTRL1	I/O	Configurable sync signal: Serial audio formats: Master clock output.

AV-Port 4

Pin No.	Function Name	I/O	Detail of Function
U3	AV4DATA[1:0]	I/O	Audio data. Several formats are supported.
V2			

PWM-DAC

Pin No.	Function Name	I/O	Detail of Function
K4	AOUTLP	O	Left channel PWM output (positive).
L2	AOUTLN	O	Left channel PWM output (negative).
L4	AOUTRP	O	Right channel PWM output (positive).
L3	AOUTRN	O	Right channel PWM output (negative).

UART Interface

Pin No.	Function Name	I/O	Detail of Function
B14	RXD0	I	UART-0 receive signal.
C13	TXD0	O	UART-0 transmit signal.
A14	RXD1	I	UART-1 receive signal.
B13	TXD1	O	UART-1 transmit signal.

Serial Peripheral Interface (SPI)

Pin No.	Function Name	I/O	Detail of Function
D14	SPIDIN	I	SPI data receive.
D15	SPIDOUT	O	SPI data transmit.
B16	SPICLK	I/O	SPI clock.
C15	SPINCS0	I/O	Multi-master mode: Chip-select input (used to detect bus conflict). Master only mode: Chip-select 1 output. Slave mode: Chip-select input.
B17	SPINCS1	I/O	Multi-master mode: Chip-select 2 output. Master only mode: Chip-select 2 output. Slave mode: Not used.

External Memory Interface

Pin No.	Function Name	I/O	Detail of Function
T18	D[15:0]	I/O	Data bus for external memory and peripheral access.
R18			
P17			
P18			
N15			
N16			
N17			
N18			
M15			
M16			
M17			
M18			
L15			
L16			
L17			
L18			
E18	A[12:0]	O	Address bus for external memory and peripheral access.
E17			
E16			
E15			
D18			
D17			
D16			
C18			
C17			
C16			
B18			
A18			
A17			
F15	A13_RAS	O	SRAM: Address output SDRAM: Row access strobe
F16	A14_CAS	O	SRAM: Address output SDRAM: Column access strobe
F17	A15_BA0	O	SRAM: Address output SDRAM: Bank select
F18	A16_BA1	O	SRAM: Address output SDRAM: Bank select
G15	A17_DQM0	O	SRAM: Address output SDRAM: Data mask
G16	A18_DQM1	O	SRAM: Address output SDRAM: Data mask
H17	A[23:19]	O	Address bus for external memory and peripheral access.
H16			
H15			
G18			
G17			

Pin No.	Function Name	I/O	Detail of Function
H18	NCS[3:0]	O	Chip select signals. The active memory range for NCS[n] (active low) can be configured. • NCS[0] supports SRAM, can be used for booting. • NCS[1] supports SDRAM or SRAM. • NCS[2] supports SRAM. • NCS[3] supports SRAM.
J17			
J16			
J15			
K17	NOE	O	Output enable, asserted (low) for read operations.
K16	NWE	O	Write enable, asserted (low) for write operations.
K18	NWAIT	I	External wait line. If NWAIT is asserted, memory access will be stalled. Can be configured as either low-active (default) or high-active.
K15	MEMCLK	O	SDRAM system clock.
J18	MEMCKE	O	SDRAM clock enable.

NAND-Flash Interface

Pin No.	Function Name	I/O	Detail of Function
T17	FD[7:0]	I/O	Bi-directional data bus.
T16			
T15			
R17			
R16			
R15			
P16			
P15			
V18	FALE	O	Address latch enable; pull-up/down defines boot mode.
U16	FCLE	O	Command latch enable; pull-up/down defines boot mode.
U15	NFCE0	O	Chip-enable, low-active.
U18	NFRB	I	Ready/busy. NAND flash is busy when NFRB is low.
V17	NFRE	O	Read enable, low-active.
U17	NFWE	O	Write enable, low-active.
V16	NFWP	O	Write protect, low-active.

Ethernet MAC-Phy Interface (MII)

Pin No.	Function Name	I/O	MII	RMII	SMII
U14	MIIDIO	I/O	Management data	Management data	
V14	MIIMDC	O	Management clock	Management clock	
V13	MIIRXD[3]	I	RxD 3	RxD 1	
U13	MIIRXD[2]	I	RxD 2	RxD 0	
V12	MIIRXD[1]	I	RxD 1		Rx-Sync
U12	MIIRXD[0]	I	RxD 0		RxD
T12	MIIRXCLK	I	Receive clock		Receive clock
R13	MIIRXER	I	Receive error	Receive error	
T14	MIIRXDV	I	Receive data valid	Carrier sense/data valid	
V11	MIITXD[3]	O	TxD 3	TxD 1	
U11	MIITXD[2]	O	TxD 2	TxD 0	
V10	MIITXD[1]	O	TxD 1		Tx-Sync
U10	MIITXD[0]	O	TxD 0		TxD
R12	MIITXCLK	I	Transmit clock		Transmit clock
T11	MIITXER	O	Transmit error		
R11	MIITXEN	O	Transmit data enable	Transmit data enable	
T13	MIICOL	I	MII ethernet collision		
R14	MIICRS	I	MII carrier sense		
V15	MIIPHYCLK	O	25.000 MHz clock	50.000 MHz clock	125.000 MHz clock

USB 2.0 OTG

Pin No.	Function Name	I/O	Detail of Function
B1	USBD+	I/O	Positive data line that is connected to the serial USB cable.
A1	USBD-	I/O	Negative data line that is connected to the serial USB cable.
E2	USBID	I	USB ID pin of mini-AB receptacle.
C2	USBREXT	I	External bias resistor (2K7, 1%); connect resistor to VSSUSB.
D2	USBVBUS	I	VBUS voltage sense.
E3	USBVBUSDRV	O	Control signal to control VBUS 5V voltage source.
C4	USBXTALI	I	Oscillator circuit input for a 24.000 MHz crystal (optional). Without external crystal, pull this pin to GND.
C3	USBXTALO	O	Oscillator circuit output for a 24.000 MHz crystal (optional). Without external crystal, leave this pin open.
D3	USBATST	-	Do not connect.

Power-on Reset Pins

Pin No.	Function Name	I/O	Detail of Function
D6	NRES12REF	I	Voltage reference input. NRES12OUT is release when this input voltage exceeds VTH12.
C5	NRES12OUT	O	Open-drain reset (active low) for 1.2V core power supply.
D5	NRES33REF	I	Voltage reference input. NRES33OUT is release when this input voltage exceeds VTH33.
D4	NRES33OUT	O	Open-drain reset (active low) for 3.3V core power supply

Real-Time Clock (RTC) Pins (RTC is Not Supported)

Pin No.	Function Name	I/O	Detail of Function
F2	RTCXIN	I	No connection. Leave this pin open circuit.
G2	RTCXOUT	O	No connection. Leave this pin open circuit.
F1	VDD33RTC	Power	No connection. Leave this pin open circuit.
E1	VSS33RTC	Power	Ground (0 V) for RTC

LCD Interface

Pin No.	Function Name	I/O	TFT Mode	LCD STN monochr.	LCD STN monochr. (double)	LCD STN color	LCD STN color (bias)
V3	LCDD[17]	O	RED5				
U4	LCDD[16]	O	RED4				
V4	LCDD[15]	O	RED3				
T5	LCDD[14]	O	RED2				
U5	LCDD[13]	O	RED1				
V5	LCDD[12]	O	(RED0)				
R6	LCDD[11]	O	GREEN5				
T6	LCDD[10]	O	GREEN4				
U6	LCDD[9]	O	GREEN3				
V6	LCDD[8]	O	GREEN2				
R7	LCDD[7]	O	GREEN1		DATAHIGH3	DATA7	DATA7
T7	LCDD[6]	O	GREEN0		DATAHIGH2	DATA6	DATA6
U7	LCDD[5]	O	BLUE5		DATAHIGH1	DATA5	DATA5
V7	LCDD[4]	O	BLUE4		DATAHIGH0	DATA4	DATA4
R8	LCDD[3]	O	BLUE3	DATA3	DATALOW3	DATA3	DATA3
T8	LCDD[2]	O	BLUE2	DATA2	DATALOW2	DATA2	DATA2
U8	LCDD[1]	O	BLUE1	DATA1	DATALOW1	DATA1	DATA1
V8	LCDD[0]	O	(BLUE0)	DATA0	DATALOW0	DATA0	DATA0
T10	LCDDCLK	O	Byte clock	CL2	CL2	CL2	CL2
V9	LCDCTRL[3]	O	Display off	Display off	Display off	Display off	Display off
U9	LCDCTRL[2]	O	Vsync	FLM	FLM	FLM	FLM
T9	LCDCTRL[1]	O	HSync	CL1	CL1	CL1	CL1
R9	LCDCTRL[0]	O	DVALID			M/Bias	

SSM Interface

Pin No.	Function Name	I/O	Detail of Function
D12	SSMD[7:0]	I/O	Data lines.
C12			
B12			
A12			
D11			
C11			
B11			
A11			
C10	SSMCLK	O	Clock output.
A13	SSMCMD	O	Command output.
D10	SSMCP	I	Card power input (high = off).
D9	SSMWP	I	Write protect input (low = protect).

External PLL Pins

Pin No.	Function Name	I/O	Detail of Function
J2	VCO[1:0]	I	External oscillator inputs, typically coming from an external VCO. Together with the external loop-filter and the internal clock dividers, each PDOUT/VCO pair can form a complete PLL.
K2			
J1	PDOUT[1:0]	O	Phase discriminator outputs. These signals are charge-pump type outputs. Each of them can be used to feed the loop-filter of a PLL structure.
K1			

Global Pins

Pin No.	Function Name	I/O	Detail of Function
D13	NRESET	I	Reset (active low). When asserted, the chip is placed in the reset state and the peripheral pins are configured as inputs. After deassertion of NRESET, the chip is clocked by XTALI and starts booting from the port configured by the FCLE, FALE pins. The NRESET signal must be asserted after power-up.
K3	XTALI	I	Oscillator circuit input. Internal system clock will be derived from XTALI (internal clock multiplier).
J3	XTALO	O	Oscillator circuit output.
C7	RREF	I	Reference current. Connect a 3.0 k-ohms $\pm 1\%$ resistor to GND.
B10	TEST1	I	Reserved. Connect to VDD for normal operation.
A10	HIGHZ	I	Reserved. Connect to VDD for normal operation.
E4	n.c.	—	Pins must be left unconnected (18x).
F4			
G4			
H4			
J4			
V1			
A4			
A5			
B4			
B5			
C8			
C9			

JTAG Interface


Pin No.	Function Name	I/O	Detail of Function
B15	TMS	I	JTAG mode select.
C14	TCK	I	JTAG clock.
A16	TDI	I	JTAG serial data input.
A15	TDO	O	JTAG serial data output.

Power Supply Pins

Pin No.	Function Name	Detail of Function	Pin No.	Function Name	Detail of Function
A6	VDD33	I/O power supply (+3.3 V).	K13	VSS	Ground (0 V).
E8			L6		
E9			L7		
E12			L8		
E13			L9		
F5			L10		
G5			L11		
H14			L12		
J14			L13		
K5			M6		
L5			M7		
M14			M8		
N14			M9		
P6			M10		
P7			M11		
P10			M12		
P11			M13		
D7			N6		
F6			N7		
F7			N8		
F8			N9		
F9	VSS	Ground (0 V).	N10		
F10			N11		
F11			N12		
F12			N13		
F13			B6		
G6			C6		
G7			R10	VPP	
G8			A2	VDD33USB	Power supply (+3.3 V) for USB interface. Ground (0 V).
G9			B2		
G10			A3	VSS33USB	
G11			B3		
G12			F3	VDD33PLL	Power supply (+3.3V) for PLL.
G13			G3	VSS33PLL	Ground (0 V).
H6			E6	VDD12	Power supply (+1.2V).
H7			E7		
H8			E10		
H9			E11		
H10			F14		
H11			G14		
H12			H5		
H13			J5		
J6			K14		
J7			L14		
J8			M5		
J9			N5		
J10			P8		
J11			P9		
J12			P12		
J13			P13		
K6	VDD12	Power supply (+1.2V).	D8	VDD12USB	Power supply (+1.2V) for USB interface.
K7			D1		
K8			C1	VSS12USB	Ground (0 V).
K9			H3	VDD12PLL	Power supply (+1.2V) for PLL.
K10			H2	VSS12PLL	Ground (0 V).
K11			G1	VDD12DCO	Power supply (+1.2V) for DCO.
K12			H1	VSS12DCO	Ground (0 V).

IC83: R5F6416MADFE (DIGITAL (1) P.C.B.)
Microprocessor

* No replacement part available.



Pin No.	Port Name	Function Name	I/O			Detail of Function
			Related Power Supply			
				OFF	ON	
1	SRXD4/SDA4/TXD4/ANEX1/P9_6	TUN_SDA	PRY	O	I/O	Tuner I2C data
		HDR_MOSI	PRY	O	O	HD radio transmission data
2	CLK4/ANEX0/P9_5	VOL1_SCK	PRY/DSP_PON	O	O	VOL1 (R2A15220FP #1) communication clock
3	N_CTS4/N_N_RTS4/N_SS4/TB4IN/DA1/P9_4	VOL_MOSI	PRY/DSP_PON	O	O	VOL1 communication data
4	N_CTS3/N_N_RTS3/N_SS3/TB3IN/DA0/P9_3	AMP_LMT	PRY	I	O	Limiter control
5	IEOUT/ISTXD2/OUTC2_0/SRXD3/SDA3/TXD3/TB2IN/P9_2	HDMI_SDA	HDMI_PON	O	I/O	HDMI 400k I2C data
6	IEIN/ISRXD2/STXD3/SCL3/RXD3/TB1IN/P9_1	HDMI_SCL	HDMI_PON	O	O	HDMI 400k I2C clock
7	CLK3/TB0IN/P9_0	SPRY_5CH	PRY	O	O	SP relay 5CH (L, C, R, SRL, SRR)
8	P19_7	PA_B_RY	PRY	O	O	Power amplifier B power supply control
9	N_INT8/P14_6	HAU_INT	HDMI_PON	O	I	Mute signal from HDMI, RX1 and RX2
10	P19_6	HRX1_MT	HDMI_PON	O	I	Mute signal from HDMI RX1 (for HAU_N_INT distinction)
11	N_INT7/P14_5	HTX1_N_INT	HDMI_PON	O	I	HDMI TX CEC interrupt
12	N_INT6/P14_4	PWR_DET	AC	I	I	AC power detect
13	P14_3	FLD_N_CS	FLD_PON	O	O	FLD chip select
14	VDC0	VDC0				---
15	P14_1 (for exclusive use of the input)	I_PRT	PRY	I	I	Current protection
16	VDC1	VDC1				---
17	NSD	NSD				Debugger
18	CNVSS	DBG_CNVSS				---
19	XCIN/P8_7	MIC_N_DET	DSP_PON	O	I	Microphone detection
20	XCOU/P8_6	PD_LED	PRY	O	O	Pure direct LED
21	RESET	MCPU_N_RST				---
22	XOUT	XOUT				---
23	VSS	VSS				---
24	XIN	XIN				---
25	VCC	VCC				---
26	NMI/P8_5	NMI				---
27	N_INT2/P8_4	WAKEUP_INT	AC	O	I	Power switch, MISO interrupt of RS-232C (sleep return)
28	N_INT1/P8_3	REM_IN2	AC	O	I	Remote control pulse input 2
29	N_INT0/P8_2	REM_IN1	AC	O	I	Remote control pulse input 1
30	UD0B/UD1B/IIO1_5/N_RTS5/N_CTS5/N_SS5/U/TA4IN/P8_1	TUN_N_INT	PRY	O	I	Interrupt from tuner
		---	AC	O	O	No used
31	UD0A/UD1A/RXD5/SCL5/STXD5/U/TA4OUT/P8_0	---	AC	O	O	No used
32	P18_1	HSW2_N_INT	HDMI_PON	O	I	Sii9589 (2) interrupt
33	P18_0	HSW1_N_INT	HDMI_PON	O	I	Sii9589 (1) interrupt
34	UD0B/UD1B/IIO1_4/CLK5/TA3IN/P7_7	FHDMI_N_INT	HDMI_PON	O	I	Front HDMI interrupt
35	UD0A/UD1A/IIO1_3/N_RTS8/N_CTS8/TXD5/SDA5/SRXD5/TA3OUT/P7_6	---	AC	O	O	No used
36	IIO1_2/RXD8/W/TA2IN/P7_5	DAU_N_INT	DSP_PON	O	I	Interrupt from DIR1, DIR2 and DSP
37	IIO1_1/CLK8/W/TA2OUT/P7_4	---	AC	O	O	No used
38	P17_7	---	AC	O	O	No used
39	P17_6	---	AC	O	O	No used
40	P17_5	VOL_RA	AC	I	I	Volume A
41	P17_4	VOL_RB	AC	I	I	Volume B
42	IIO1_0/TXD8/N_SS2/N_RTS2/N_CTS2/V/TA1IN/P7_3	HRX_N_INT	HDMI_PON	O	I	HDMI RX (ADV7619) interrupt
43	CLK2/V/TA1OUT/P7_2	NCPU_SPI_REQ	NCPU_PON	O	I	BridgeCO request
44	MSCL/IEIN/ISRXD2/OUTC2_2/IIO1_7/STXD2/SCL2/RXD2/TA0IN/TB5IN/P7_1	DV_SCL	HDMI_PON	O	O	D-VIDEO/A-VIDEO/F-HDMI 400k I2C clock
45	TA0OUT/TXD2/SDA2/SRXD2/IIO1_6/OUTC2_0/ISTXD2/IEOUT/MSDA/P7_0	DV_SDA	HDMI_PON	O	I/O	D-VIDEO/A-VIDEO/F-HDMI 400k I2C data
46	TXD1/SDA1/SRXD1/P6_7	232C_DBG_MOSI	AC	O	O	RS-232C transmission data / Debug / E8a
47	P14_7	DSP_PON	DSP_PON	O	O	DSP power supply

Pin No.	Port Name	Function Name	I/O			Detail of Function
			Related Power Supply			
				OFF	ON	
48	RXD1/SCL1/STXD1/P6_6	232C_DBG_MISO	AC	O	I	RS-232C reception data / Debug / E8a
49	P11_7	---	AC	O	O	No used
50	CLK1/P6_5	DBG_SCK	AC	O	I	E8a
51	N_CTS1/N_RTS1/N_SS1/OUTC2_1/ ISCLK2/P6_4	DBG_BUSY	AC	O	O	E8a
52	TXD0/SDA0/SRXD0/P6_3	DSP_MOSI	DSP_PON	O	O	DSP/DIR/DAC transmission data
53	TB2IN/RXD0/SCL0/STXD0/P6_2	DSP_MISO	DSP_PON	I	I	DSP/DIR/DAC reception data
54	TB1IN/CLK0/P6_1	DSP_SCK	DSP_PON	O	O	DSP/DIR/DAC communication clock
55	TB0IN/N_CTS0/N_RTS0/N_SS0/P6_0	NCPU_SPI_RDY	NCPU_PON	O	I	BridgeCO data ready
56	P19_5	---	AC	O	O	No used
57	D31/OUTC2_7/P13_7	DSP1_N_RST	DSP_PON	O	O	DSP1 reset
58	D30/OUTC2_1/ISCLK2/P13_6	---				Serial spare
59	D29/OUTC2_2/ISRXD2/IEIN/P13_5	---				Serial spare
60	D28/OUTC2_0/ISTXD2/IEOUT/P13_4	---				Serial spare
61	P19_4	EEP_N_CS	AC	O	O	EEPROM chip select
62	RDY/CS3/N_CTS7/N_RTS7/P5_7	FPGA_N_CS	HDMI_PON	O	B	External bus FPGA chip select
63	ALE/CS2/RXD7/P5_6	DFF2_N_CS	AC	O	B	External bus DFF2 chip select
64	HOLD/CLK7/P5_5	DBG_EPM	AC	I	I	E8a
65	HLDA/CS1/TXD7/P5_4	DFF1_N_CS	AC	O	B	External bus DFF1 chip select
66	D27/OUTC2_3/P13_3	---	AC	O	O	No used
67	VSS	VSS				---
68	D26/OUTC2_6/P13_2	DSP1_N_SPIRDY	DSP_PON	O	I	DSP1 SPI ready
69	VCC	VCC				---
70	D25/OUTC2_5/P13_1	---	AC	O	O	No used
71	D24/OUTC2_4/P13_0	DSP1_N_CS	DSP_PON	O	O	DSP1 chip select
72	CLKOUT/BCLK/P5_3	NC(BCLK)	AC	O	B	External bus
73	RD/P5_2	MCBUS_N_RD	AC	O	B	External bus
74	WR1/BC1/P5_1	NC(BC1)	AC	O	B	External bus
75	WR0/WR/P5_0	MCBUS_N_WR	HDMI_PON	I	B	External bus
		DBG_N_CE	AC	I	I	E8a
76	D23/P12_7	MT_DA	DSP_PON	O	O	Mute digital audio
77	D22/P12_6	DIR1_N_CS	DSP_PON	O	O	DIR1 chip select
78	D21/P12_5	DIR_N_RST	DSP_PON	O	O	DIR reset
79	P19_3	---	AC	O	O	No used
80	P17_3	DIR1_N_INT	DSP_PON	O	I	Interrupt from DIR1 (for DAU_N_INT distinction)
81	P17_2	---	AC	O	O	No used
82	P17_1	NCPU_PON	NCPU_PON	O	O	NET / USB power supply
83	P17_0	NCPU_VBUSDRV	NCPU_PON	O	I	USB VBUS drive
84	P19_2	USB_VBUS_PON	NCPU_PON	O	O	USB VBUS power supply control
85	CS0/A23/TXD6/SDA6/SRXD6/P4_7	FLASH_N_CS	AC	O	O	External bus flash ROM chip select
86	CS1/A22/RXD6/SCL6/STXD6/P4_6	A[22]	AC	O	B	External bus
87	CS2/A21/CLK6/P4_5	A[21]	AC	O	B	External bus
88	CS3/A20/N_CTS6/N_RTS6/N_SS6/ P4_4	A[20]	AC	O	B	External bus
89	A19/TXD3/SDA3/SRXD3/OUTC2_0/ ISTXD2/IEOUT/P4_3	A[19]	AC	O	B	External bus
90	P11_6	HTX2_AUSEL	DSP_PON	O	O	HDMI TX2 sound select (main/zone ADC)
91	A18/RXD3/SCL3/STXD3/ISRXD2/IEIN/ P4_2	A[18]	AC	O	B	External bus
92	P11_5	DFF_FROM_N_RST	AC	O	O	Reset of DFF and external ROM
93	A17/CLK3/P4_1	A[17]	AC	O	B	External bus
94	A16/N_CTS3/N_RTS3/N_SS3/P4_0	A[16]	AC	O	B	External bus
95	P16_7/TXD10	EX_MOSI	AC	O	O	FL/EEPROM transmission data
96	P16_6/RXD10	EEP_MISO	AC	O	I	EEPROM reception data
97	P16_5/CLK10	EX_SCK	AC	O	O	FL/EEPROM communication clock
98	P16_4/N_CTS10/N_RTS10	NCPU_AMUTE	NCPU_PON	O	I	Mute signal from BridgeCO
99	A15/[A15/D15]/TA4IN/U/P3_7	A[15]	AC	O	B	External bus
100	A14/[A14/D14]/TA4OUT/U/P3_6	A[14]	AC	O	B	External bus

Pin No.	Port Name	Function Name	I/O			Detail of Function
				Related Power Supply		
				OFF	ON	
101	A13/[A13/D13]/TA2IN/W/P3_5	A[13]	AC	O	B	External bus
102	A12/[A12/D12]/TA2OUT/W/P3_4	A[12]	AC	O	B	External bus
103	P16_3/TXD9	NCPU_SPI_MOSI	NCPU_PON	O	O	Data (master out slave in)
104	P16_2/RXD9	NCPU_SPI_MISO	NCPU_PON	O	I	Data (master in slave out)
105	P16_1/CLK9	NCPU_SPI_SCK	NCPU_PON	O	O	Clock (master out slave in)
106	P16_0/N_CTS9/N_RTS9	NCPU_N_RST	NCPU_PON	O	O	Network microprocessor reset
107	A11/[A11/D11]/TA1IN/V/P3_3	A[11]	AC	O	B	External bus
108	A10/[A10/D10]/TA1OUT/V/P3_2	A[10]	AC	O	B	External bus
109	A9/[A9/D9]/TA3OUT/UD0B/UD1B/P3_1	A[9]	AC	O	B	External bus
110	D20/P12_4	AD_SEL_A	+3.3S_PON	O	O	AD select A
111	D19/N_CTS6/N_RTS6/N_SS6/P12_3	AD_SEL_B	+3.3S_PON	O	O	AD select B
112	D18/RXD6/SCL6/STXD6/P12_2	AD_SEL_C	+3.3S_PON	O	O	AD select C
113	D17/CLK6/P12_1	FPGA_SCK	HDMI_PON	O	O	FPGA clock (at Boot)
114	D16/TXD6/SDA6/SRXD6/P12_0	FPGA_MOSI	HDMI_PON	O	O	FPGA transmission data (at Boot)
115	VCC	VCC				---
116	A8/[A8/D8]/TA0OUT/UD0A/UD1A/P3_0	A[8]	AC	O	B	External bus
117	VSS	VSS				---
118	A7/[A7/D7]/AN2_7/P2_7/TXD10	A[7]	AC	O	B	External bus
119	A6/[A6/D6]/AN2_6/P2_6/RXD10	A[6]	AC	O	B	External bus
120	A5/[A5/D5]/AN2_5/P2_5/CLK10	A[5]	AC	O	B	External bus
121	A4/[A4/D4]/AN2_4/P2_4/N_CTS10/N_RTS10	A[4]	AC	O	B	External bus
122	A3/[A3/D3]/AN2_3/P2_3/TXD9	A[3]	AC	O	B	External bus
123	A2/[A2/D2]/AN2_2/P2_2/RXD9	A[2]	AC	O	B	External bus
124	A1/[A1/D1]/BC2/[BC2/D1]/AN2_1/P2_1/CLK9	A[1]	AC	O	B	External bus
125	A0/[A0/D0]/BC0/[BC0/D0]/AN2_0/P2_0/N_CTS9/N_RTS9	A[0]	AC	O	B	External bus
126	D15/N_INT5/IIO0_7/IIO1_7/P1_7	D[15]	AC	I	B	External bus
127	D14/N_INT4/IIO0_6/IIO1_6/P1_6	D[14]	AC	I	B	External bus
128	D13/N_INT3/IIO0_5/IIO1_5/P1_5	D[13]	AC	I	B	External bus
129	D12/IIO0_4/IIO1_4/P1_4	D[12]	AC	I	B	External bus
130	D11/IIO0_3/IIO1_3/P1_3	D[11]	AC	I	B	External bus
131	D10/IIO0_2/IIO1_2/P1_2	D[10]	AC	I	B	External bus
132	D9/IIO0_1/IIO1_1/P1_1	D[9]	AC	I	B	External bus
133	IIO0_0/IIO1_0/D8/P1_0	D[8]	AC	I	B	External bus
134	AN0_7/D7/P0_7	D[7]	AC	I	B	External bus
135	AN0_6/D6/P0_6	D[6]	AC	I	B	External bus
136	AN0_5/D5/P0_5	D[5]	AC	I	B	External bus
137	AN0_4/D4/P0_4	D[4]	AC	I	B	External bus
138	P19_1	FPGA_N_CFG	HDMI_PON	O	O	FPGA nCONF
139	WR3/BC3/P11_4	FPGA_N_STA	HDMI_PON	I	I	FPGA nSTATUS
140	P19_0	FPGA_CDONE	HDMI_PON	I	I	FPGA CONF DONE
141	IIO1_3/N_RTS8/N_CTS8/WR2/CS3/P11_3	DIAG_CHECK	AC	O	O	Diag inspection result output / OK=High, NG=Low
142	IIO1_2/RXD8/CS2/P11_2	NDAC_N_MT	DSP_PON	O	O	Net zone DAC mute
143	IIO1_1/CLK8/CS1/P11_1	SPRY_Z2&FP	PRY	O	O	SP relay zone 2 and front presence
144	IIO1_0/TXD8/CS0/P11_0	NCPU_SPI_N_CS	NCPU_PON	O	O	Network microprocessor SPI chip select
145	P18_7	HPRY	PRY	O	O	HP relay
146	P18_6	MT_N_Z2	+3.3S_PON	O	O	Mute zone2 (line out)
147	P18_5	SPRY_SB&BA	PRY	O	O	SP relay surround back and Bi-Amp
148	P18_4	MT_N_5CH	+3.3S_PON	O	O	Mute 5ch (L, C, R, SRL, SRR preout/main in)
149	P18_3	MT_N_SW	+3.3S_PON	O	O	Mute subwoofer (Preout)
150	P18_2	MT_N_SB	+3.3S_PON	O	O	Mute SB/BA/Z2/FP (Preout/Main in)
151	AN0_3/D3/P0_3	D[3]	AC	I	B	External bus
152	AN0_2/D2/P0_2	D[2]	AC	I	B	External bus
153	AN0_1/D1/P0_1	D[1]	AC	I	B	External bus
154	AN0_0/D0/P0_0	D[0]	AC	I	B	External bus

Pin No.	Port Name	Function Name	I/O			Detail of Function
			Related Power Supply			
				OFF	ON	
155	IIO0_7/N_RTS6/N_CTS6/N_SS6/ AN15_7/P15_7	SVID_DET	VID_PON	I	I	S-video detect
156	IIO0_6/CLK6/AN15_6/P15_6	HP_N_DET	DSP_PON	O	I	Headphone detection
157	IIO0_5/RXD6/SCL6/STXD6/AN15_5/ P15_5	---	AC	O	O	No used
158	IIO0_4/TXD6/SDA6/SRXD6/AN15_4/ P15_4	DC_TRG1	PRY	O	O	Control out 1
159	IIO0_3/N_RTS7/N_CTS7/AN15_3/ P15_3	DSP1_N_INT	DSP_PON	O	I	Interrupt from DSP1 (for DAU_N_INT distinction)
160	IIO0_2/RXD7/AN15_2/P15_2	UART spare	AC	O	O	No used, spare for UART
161	IIO0_1/CLK7/AN15_1/P15_1	---	AC	O	O	No used
162	VSS	VSS				---
163	IIO0_0/TXD7/AN15_0/P15_0	UART spare	AC	O	O	No used, spare for UART
164	VCC	VCC				---
165	KI3/AN_7/P10_7	+3.3S_PON	+3.3S_PON	O	O	+3.3S power supply
166	KI2/AN_6/P10_6	AD2_COM	+3.3S_PON	O	I	AD selector 2 COM input
167	KI1/AN_5/P10_5	AD1_COM	+3.3S_PON	O	I	AD selector 1 COM input
168	KI0/AN_4/P10_4	HSW_2CHIP	AC	I	I	HDMI SW number distinction
169	AN_3/P10_3	---	AC	O	O	No used
170	AN_2/P10_2	KY_AD2	AC	O	I	Key 2
171	AN_1/P10_1	KY_AD1	AC	O	I	Key 1
172	AVSS	AVSS				---
173	AN_0/P10_0	TUN_N_RST	PRY	O	O	Tuner reset
		HDR_N_RST	PRY	O	O	HD radio reset
174	VREF	VREF				---
175	AVCC	AVCC				---
176	STXD4/SCL4/RXD4/ADTRG/P9_7	TUN_SCL	PRY	O	O	Tuner I2C clock
		HDR_MISO	PRY	O	I	HD radio reception data

Key detection for A/D port

Key input (A/D) pull-up resistance 10 k-ohms

	0 Ω	+ 1.0 kΩ	+ 1.0 kΩ	+ 1.5 kΩ	+ 1.5 kΩ	+ 2.2 kΩ	+ 3.3 kΩ	+ 4.7 kΩ	22 kΩ	33 kΩ
Detected voltage value at 171 pin	0 – 0.15 V	0.15 – 0.42 V	0.43 – 0.70 V	0.71 – 0.97 V	0.98 – 1.24 V	1.25 – 1.53 V	1.54 – 1.84 V	1.85 – 2.22 V	2.23 – 2.62 V	2.63 – 3.04 V
A/D value (3.3 V=255)	0 – 11	12 – 32	33 – 54	55 – 75	76 – 96	97 – 119	120 – 142	143 – 163	182 – 197	198 – 209
KEY1	RADIO (SCENE4)	NET (SCENE3)	TV (SCENE2)	BD/DVD (SCENE1)	ZONE CONTROL	ZONE2	INPUT > (RX-V675/HTR-6066/TSR-6750 models)	INPUT <	MAIN ZONE Ⓟ (power)	TONE CONTROL

	0 Ω	+ 1.0 kΩ	+ 1.0 kΩ	+ 1.5 kΩ	+ 1.8 kΩ	+ 2.2 kΩ	+ 3.3 kΩ	+ 4.7 kΩ	+ 6.8 kΩ	+ 10 kΩ	+ 22 kΩ	+ 68 kΩ
Detected voltage value at 170 pin	0 – 0.15 V	0.16 – 0.42 V	0.43 – 0.70 V	0.71 – 0.99 V	1.00 – 1.27 V	1.28 – 1.56 V	1.57 – 1.86 V	1.87 – 2.14 V	2.15 – 2.39 V	2.40 – 2.65 V	2.66 – 2.91 V	2.92 – 3.17 V
A/D value (3.3 V=255)	0 – 11	12 – 32	33 – 54	55 – 77	78 – 99	100 – 121	122 – 144	145 – 166	167 – 186	187 – 205	206 – 226	227 – 246
KEY2	PURE DIRECT	TUNING >>	TUNING <<	AM	FM	PRESET >	PRESET <	MEMORY	INFO	STRAIGHT	PROGRAM >	PROGRAM <


Destination detection for A/D port

Pull-up resistance 10 k-ohms

R753 on DIGITAL P.C.B.	0 Ω	1.2 kΩ	2.7 kΩ	4.7 kΩ	6.8 kΩ	10 kΩ	15 kΩ	47 kΩ	100 kΩ
Detected voltage value at 111 pin	0 – 0.16 V	0.17 – 0.51 V	0.52 – 0.87 V	0.88 – 1.92 V	1.93 – 1.49 V	1.50 – 1.81 V	1.82 – 2.35 V	2.36 – 2.86 V	2.87 – 3.15 V
A/D value (3.3 V=255)	0 – 12	13 – 39	40 – 67	68 – 92	93 – 115	116 – 140	141 – 169	199 – 221	222 – 244
Destination	J	U	C	R, S	T	K	A	B, G, F	L, H

• Microprocessor extended port

IC76, 78: SN74LV4051APWR (DIGITAL (1) P.C.B.)
8-channel analog multiplexers/demultiplexers




IC76

Pin No.	Port Name	Function Name	I/O			Detail of Function
			Related Power Supply			
				OFF	ON	
1	Y4	THM2	+3.3S_PON	I	I	Temperature detection 2
2	Y6	(Spare)	+3.3S_PON	I	I	---
4	Y7	(Spare)	+3.3S_PON	I	I	---
5	Y5	DEST	+3.3S_PON	I	I	Destination distinction
12	Y3	MODEL	+3.3S_PON	I	I	Model distinction
13	Y0	MHL_VBUS_PRT	+3.3S_PON	I	I	MHL overcurrent detection (spare)
14	Y1	USB_VBUS_PRT	+3.3S_PON	I	I	Front USB overcurrent detection
15	Y2	(Spare)	+3.3S_PON	I	I	---

IC78

Pin No.	Port Name	Function Name	I/O			Detail of Function
			Related Power Supply			
				OFF	ON	
1	Y4	PS2_PRT	+3.3S_PON	I	I	Power supply protection 2
2	Y6	PS1_PRT	+3.3S_PON	I	I	Power supply protection 1
4	Y7	AMP_OLV	PRY	I	I	Amplifier output level detection
5	Y5	DC_PRT	PRY	I	I	DC protection
12	Y3	THM1	+3.3S_PON	I	I	Temperature detection 1
13	Y0	PS3_PRT	AC	I	I	Power supply protection 3
14	Y1	L3_DET	VID_PON	I	I	D terminal L3 detection
15	Y2	MODE	+3.3S_PON	I	I	Special mode distinction

IC79, 81: TC74VHC273FT (EL,K) (DIGITAL (1) P.C.B.)
Octal D-type flip-flop with clear



Inputs			Output	Function
CLR	D	CK	Q	
L	X	X	L	Clear
H	L		L	-
H	H		H	-
H	X		Q _n	No Change


IC79

Pin No.	R32C external bus data	Function Name	I/O			Detail of Function
			Related Power Supply			
				OFF	ON	
2	D[8]	HDMI_PON	HDMI_PON	O	O	HDMI power supply (Necessary for DSP, A-VIDEO drive)
5	D[9]	HRTX_N_RST	HDMI_PON	O	O	HDMI receiver/transmitter reset
6	D[10]	MHLVB_PON	HDMI_PON	O	O	MHL VBUS power supply control H: feeding permission, L: feeding prohibition
9	D[11]	FLD_PON	FLD_PON	O	O	FL driver +3.3V power supply control
12	D[12]	FLD_N_RST	FLD_PON	O	O	FLD reset
15	D[13]	HTX_AUSEL	HDMI_PON	O	O	HDMI transmitter sound select
16	D[14]	HAU_N_OE	HDMI_PON	O	O	HDMI to DIR sound output enable
19	D[15]	STBY_LED	AC	O	O	Standby LED control

IC81

Pin No.	R32C external bus data	Function Name	I/O			Detail of Function
			Related Power Supply			
				OFF	ON	
2	D[0]	HSW_N_RST	HDMI_PON	O	O	HDMI switcher reset (L period: more than 5ms)
5	D[1]	VDEC_N_RST	HDMI_PON	O	O	Video decoder reset
6	D[2]	WIFI_PON	WIFI_PON	O	O	WiFi adaptor power supply control
9	D[3]	---	AC	O	O	No used
12	D[4]	FHDMI_N_RST	HDMI_PON	O	O	Front HDMI reset
15	D[5]	VID_PON	VID_PON	O	O	Video power supply
16	D[6]	+3.3D_PON	+3.3D_PON	O	O	OR of HDMI_PON, DSP_PON, NET_USB_PON
19	D[7]	PRY	PRY	O	O	Power relay

IC61: Sii9136CTU-3 (DIGITAL (1) P.C.B.)
HDMI transmitter































Pin No.	Port Name	Function Name	I/O			Detail of Function
			Related Power Supply			
				OFF	ON	
26	GPIO0	NC	HDMI_PON	---	O	Unconnected: output low setting
77	GPIO1	NC	HDMI_PON	---	O	Unconnected: output low setting
39	GPIO2	CEC_EN	HDMI_PON	---	O	CEC function of HDMI TX1 / effective/invalidity (spare)
49	GPIO3	5HT*_PON	HDMI_PON	---	O	HDMI out * 5VPWR output control

RX-V675/HTR-6066/
RX-A730/TSR-6750
















■ PIN CONNECTION DIAGRAMS

• ICs














A3V56S30FTP-G6 	ADV7180BSTZ 	ADV7619KSVZ 	BD00GA3WEFJ-E2 BD9328FJ BD9329AEFJ-E2 	BD7541G-TR 	BD7542F-E2 
D80YK113CPTP400 	DM860A-AQE 		EN29LV640AB-90TIP 		
EP4CE15F23C6N 		KIA7912PI 	LAN8700C-AEZG-TR 		LM19CIZ/LF 
M12L64164A-5TG 	M66003-0131FP-R 	MFI337S3959 	MX29GL256FLT2I-90Q 	NCP380HMUAJAATBG 	
NJM41033V (TE2) 	NJM4565M (TE1) 	NJM7812FA 	NJW1329FH3 	NT5SV8M16HS-6K 	
PCM5101PWR 	PCM9211PTR 	R2A15220FP 	R5F6416MADFE 	R1163N501B-TR-FE R1172N301D-TR-F 	
				R1171S501B-E2-FE 	

RX-V675/HTR-6066/
RX-A730/TSR-6750




















• ICs

R1172H121D-T1-F R1172H501D-T1-F RP170H331B-T1-FE 	R1EX25512ATA00A 	SiI9136CTU-3 SiI9589-3CTUC 	SiI9587CNUC-3 	STR-Y6753 	
RP130Q121D-TR-F RP130Q181D-TR-F RP130Q251D-TR-FE RP130Q331D-TR-F RP130Q501D-TR-F 					
SN74LV4051APWR 	SN74LVC1G17DCKR 	TC74LCX245FT 	TC74VHC157FT 	TC74VHC273FT (EL,K) 	
TC74VHCU04FT 	TC7SET08FU TC7SH08FU TC7SH32FU TC7SH86FU 	TC7WH126FU 	TL431ACLPR  1: CATHODE 2: ANODE 3: REF	W25Q80BVSSIG 	

• Diodes


1SS355VMTE-17 1SS400TE61 	DBL155G 	P6KE200A 	RB051L-40 	RB162L-40 	RB501V-40 RB521S-30 
RBQ30T65A 	RS103-B-D-V50 	RS603M-B-C-J80 	TFZGTR6.8B TFZGTR13B TFZGTR24B 	UDZV4.3B UDZV5.1B UDZV24B UDZV36B 	UF1K  US1002FL 

• Transistors

2N5401C-AT/P 	2N5551C-AT 	2SA1576UBTLR 	2SA1695 O,P,Y 2SC4468 O,P,Y 	2SA1708 	2SA1770S/T-AN 	2SA949 2SC2229 	2SC3906K 
2SC4081 T106 	2SC4081UBTLR 	2SC4115S 	2SC4614S/T-AN 	2SC5964-TD-E 	2SD2704 K 	DTA044EUBTL DTC014EUBTL DTC044EUBTL  DTC023JUBTL 	
HN4B01JE 	INA6002AC1-TH12-1W INC6002AC1-T112-1W 	KTA1046-Y-U/PFY KTA1837-U/P 	KTC3875S 	MCH6336-TL-E 	RAL035P01 	μPA672T-T1-A 	

BLOCK DIAGRAMS

AUDIO Section Block Diagram



1

2


3

4


5

6


7



VIDEO Section Block Diagram




Power Supply Section Block Diagram




WIRING DIAGRAMS

OVERALL ASSEMBLY




RX-V675/HTR-6066/TSR-6750

Front panel (View A)




Flexible flat cable




RX-A730



Front panel (View A)



Flexible flat cable







Flexible flat cable




• AMP UNIT

Top view
RX-V675/HTR-6066/TSR-6750



RX-A730




DIGITAL (1) (Side A)

Ref no.	Location	Ref no.	Location
D38	E5	D9401	C5
D602	H3	D9402	G5
D607	H2	D9403	G5
D608	H2	D9404	G5
D609	H2	D9405	G5
D4103	D5	D9501	I4
D4105	D5	D9502	I4
D4201	A6	IC1	D3
D4205	B6		

Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location	Ref no.	Location
IC3	E4	IC50	F4	IC65	G4	IC78	F5	IC84	G6	IC411	E5	IC481	I5	IC921	H5	IC929	G4	IC943	D5	IC951	I4	Q11	D4	Q253	C3
IC4	C4	IC56	F4	IC66	H3	IC79	E4	IC85	F6	IC412	E5	IC482	I4	IC922	H5	IC930	H5	IC944	D4	IC952	H3	Q12	D4	Q762	E5
IC8	C4	IC60	H3	IC75	F5	IC81	E5	IC91	G5	IC413	E5	IC483	I5	IC924	H5	IC931	I3	IC946	D6	IC953	H4	Q17	D4	Q763	G6
IC21	C4	IC61	G3	IC76	E5	IC82	G4	IC92	G5	IC421	A6	IC484	I5	IC926	H5	IC940	I3	IC947	E6	IC955	I3	Q21	D4	Q765	F6
IC27	C3	IC64	G4	IC77	F4	IC83	F5	IC93	G5	IC423	B6	IC485	I5	IC927	H4	IC942	C5	IC949	G5	IC956	I3	Q22	E5	Q4101	E5

No replacement part available.

Q250	C3	Q4102	E4
Q251	C3	Q4103	E5
Q252	C3	Q4104	E5
		Q4105	E4
		Q4106	E4
		Q4107	E5




Ref no.	Location
Q9401	E5
Q9402	E5
Q9404	D5
Q9405	D5
Q9406	D5
Q9408	E5

RX-V675/HTR-6066/TSR-6750

RX-A730

DIGITAL (1) (Side B)


No replacement part available.




• Semiconductor Location

Ref no.	Location
D750	D6
D4202	I6
D4203	I6
D4204	I6
D9406	B5
D9407	B5
IC6	F3
IC53	D4
IC55	E3
IC57	E3
IC80	D5
IC87	D5
IC424	I7
IC923	D5
IC954	C3
Q18	G4
Q750	E5
Q751	E5
Q752	E5
Q753	E5
Q754	E6
Q755	E5
Q756	C6
Q757	D6
Q758	C6
Q759	D6
Q760	C6
Q761	E5
Q9201	F4
Q9202	F4

DIGITAL (2) (Side B)



OPERATION (1) (Side A)




- Semiconductor Location

Ref no.	Location
D3005	I3
Q3015	J3

OPERATION (2) (Side A)

OPERATION (9) (Side A)




• Semiconductor Location


Ref no.	Location
Q3413	E3

RX-V675/HTR-6066/TSR-6750

OPERATION (2) (Side B)




OPERATION (9) (Side B)



• Semiconductor Location

Ref no.	Location	Ref no.	Location
D3403	F4	IC342	E3
D3404	B3	IC343	D3
D3406	D3	IC344	D3
D3407	D3	IC345	E3
D3408	D3	IC346	D3
D3409	D3	Q3401	F5
D3412	E4	Q3402	B3
D3413	E4	Q3404	F5
D3414	C3	Q3405	B3
D3415	C3	Q3407	F4
D3416	C3	Q3408	E4
D3417	C3	Q3409	C3
D3420	E4	Q3410	C3
D3421	E4	Q3420	D5
IC341	D5		


OPERATION (4) (Side A)




Ref no.	Location
D3701	C4
D3704	E4
D3716	D4
IC372	D3
IC373	E3
IC374	D6
IC375	C4
Q3801	J4
Q3802	J4
Q3803	J4
Q3804	J4

RX-V675/HTR-6066/TSR-6750

OPERATION (3) (Side B)




OPERATION (4) (Side B)




• Semiconductor Location

Ref no.	Location	Ref no.	Location
D3702	C4	D3713	C5
D3703	C5	D3714	C6
D3705	C3	D3715	C6
D3706	B4	D3801	I4
D3707	D6	D3802	I4
D3708	D6	IC381	H4
D3709	D6	IC382	H4
D3710	D6	Q3701	D6
D3711	D6	Q3702	D6
D3712	C6	Q3703	D6


OPERATION (5) (Side A)



OPERATION (6) (Side A)




OPERATION (7) (Side A)



• Semiconductor Location


Ref no.	Location
D3004	I3
D3013	C3

OPERATION (8) (Side A)




RX-V675/HTR-6066/TSR-6750


OPERATION (5) (Side B)



OPERATION (6) (Side B)




OPERATION (7) (Side B)



• Semiconductor Location

Ref no.	Location
D3001	H3
D3002	H3
D3003	H2
D3019	C6
D3020	C6
IC303	G3
Q3005	H3
Q3014	C3

OPERATION (8) (Side B)




OPERATION (1) (Side A)

DIGITAL (1)
(CB82)

FLD_N_RST FLD_N_CS
FLD_SCK FLD_MOST
MIC_N_DET REM_IN
RM- RM+
ISEL_RA ISEL_RB
PRV2 DGND
PSW_DET KEY1
KEY2 VOL_RA
VOL_RB PD_LED
FL_PON +3.3M
STBY_LED +5.6
+5.6 DGND

VAUX VAUXE
-12V E
MIC +12V

OPERATION (2)
(CB343)



OPERATION (10)
(W3004B)

ISEL_RB
DGND
ISEL_RA
+3.3M

MASW
DGND
DGND
+3.3M
STBY_LED


OPERATION (5)
(CB308)

+12V MIC
-12V MIC
MIC_N_DET
FG

OPERATION (6)
(CB301)


OPERATION (11) (Side A)

OPERATION (12) (Side A)




RX-A730


OPERATION (1) (Side B)



OPERATION (11) (Side B)




OPERATION (12) (Side B)



• Semiconductor Location

Ref no.	Location
D3009	E2
D3010	D2
D3015	C3
D3019	C2
D3020	C2
D3021	C2
D3022	C2
D3023	D6
D3024	D6
D3025	C2
IC301	E2
IC302	C3
Q3001	F2
Q3002	F2
Q3003	F2
Q3004	F2
Q3009	B3
Q3010	C3
Q3011	C3
Q3012	C2
Q3013	C2


OPERATION (9) (Side A)




Ref no.	Location
Q3413	E3

RX-A730

OPERATION (2) (Side B)



OPERATION (9) (Side B)




• Semiconductor Location


Ref no.	Location	Ref no.	Location
D3403	F4	IC342	E3
D3404	B3	IC343	D3
D3406	D3	IC344	D3
D3407	D3	IC345	E3
D3408	D3	IC346	D3
D3409	D3	Q3401	F5
D3412	E4	Q3402	B3
D3413	E4	Q3404	F5
D3414	C3	Q3405	B3
D3415	C3	Q3407	F4
D3416	C3	Q3408	E4
D3417	C3	Q3409	C3
D3420	E4	Q3410	D5
IC341	D5		

- Semiconductor Location

Ref no.	Location
D3701	C4
D3704	E4
D3716	D4
IC372	D3
IC373	E3
IC374	D6
IC375	C4
Q3801	J4
Q3802	J4
Q3803	J4
Q3804	J4



OPERATION (2)
(CB345)




- Some internal parts in this product contain high voltages and are dangerous. Be sure to take safety measures during servicing, such as wearing insulating gloves.
- Note that the capacitors indicated below are dangerous even after the power is turned off because an electric charge remains and a high voltage continues to exist there. Before starting any repair work, connect a discharging resistor (5 k-ohms/10 W) to the terminals of each capacitor indicated below to discharge electricity. The time required for discharging is about 30 seconds per each.


C3706 on OPERATION (3) P.C.B.

RX-A730

OPERATION (3) (Side B)



OPERATION (4) (Side B)




• Semiconductor Location


Ref no.	Location	Ref no.	Location
D3702	C4	D3713	C5
D3703	C5	D3714	C6
D3705	C3	D3715	C6
D3706	A4	D3801	I4
D3707	D6	D3802	I4
D3708	D6	IC381	H4
D3709	D6	IC382	H4
D3710	D6	Q3701	D6
D3711	D6	Q3702	D6
D3712	C6	Q3703	D6

RX-A730


OPERATION (5) (Side A)




OPERATION (6) (Side A)




OPERATION (7) (Side A)



OPERATION (8) (Side A)



OPERATION (10) (Side A)




• Semiconductor Location


Ref no.	Location
D3016	C2

RX-A730


OPERATION (5) (Side B)




OPERATION (6) (Side B)




OPERATION (7) (Side B)



OPERATION (8) (Side B)



OPERATION (10) (Side B)




• Semiconductor Location

Ref no.	Location
D3001	F2
D3002	H2
D3003	F2
D3004	H2
D3006	E3
IC303	E3
Q3014	B3

• Semiconductor Location

Ref no.	Location	Ref no.	Location
D1040	H4	Q1019	C5
D1051	F3	Q1020	C5
IC103	F4	Q1021	C5
IC104	F4	Q1022	H6
Q1015	E5	Q1023	G6
Q1016	E5	Q1024	F6
Q1017	D5	Q1025	E6
Q1018	D5	Q1026	D6
		Q1027	C6
		Q1028	B6
		Q1029	H5

MAIN (1) (Side A)



Safety measures


- Some internal parts in this product contain high voltages and are dangerous. Be sure to take safety measures during servicing, such as wearing insulating gloves.
- Note that the capacitors indicated below are dangerous even after the power is turned off because an electric charge remains and a high voltage continues to exist there. Before starting any repair work, connect a discharging resistor (5 k-ohms/10 W) to the terminals of each capacitor indicated below to discharge electricity. The time required for discharging is about 30 seconds per each.
C1084, C1085 on MAIN (1) P.C.B.

Ref no.	Location	Ref no.	Location	Ref no.	Location
Q1030	G5	Q1045	F6	Q1055A	C6
Q1031	F5	Q1046	E6	Q1055C	D6
Q1032	E5	Q1047	D6	Q1056A	B6
Q1033	E5	Q1048	C6	Q1056C	C6
Q1034	D5	Q1049	B6	Q1067	H5
Q1035	C5	Q1050A	G6	Q1068	G5
Q1036	H6	Q1050C	H6	Q1069	H5
Q1037	G6	Q1051A	G6	Q1070	H5
Q1038	F6	Q1051C	G6	Q1071	H5
Q1039	E6	Q1052A	F6	Q1072	B5
Q1040	E6	Q1052C	F6		
Q1041	D6	Q1053A	E6		
Q1042	C6	Q1053C	E6		
Q1043	G6	Q1054A	D6		
Q1044	F6	Q1054C	D6		

RX-V675/HTR-6066/TSR-6750

RX-A730

MAIN (1) (Side B)




• Semiconductor Location

Ref no.	Location	Ref no.	Location
D1001	D5	D1501	D3
D1002	D4	D1502	D3
D1003	G5	IC153	C3
D1004	G5	IC154	E3
D1005	G5	Q1001	E4
D1006	G5	Q1002	E4
D1007	F5	Q1003	D4
D1008	F5	Q1004	D4
D1009	E5	Q1005	D4
D1010	E5	Q1006	D4
D1011	D5	Q1007	C4
D1012	D5	Q1008	C4
D1013	C5	Q1009	C4
D1014	C5	Q1010	C4
D1015	B5	Q1011	B4
D1016	C5	Q1012	B4
D1017	G6	Q1013	B4
D1018	G6	Q1014	B4
D1019	F6	Q1057	G5
D1020	E4	Q1058	F6
D1021	D6	Q1059	E6
D1022	C6	Q1060	D5
D1023	B6	Q1061	C5
D1024	G5	Q1062	C5
D1025	F5	Q1063	B6
D1026	E5	Q1064	E5
D1027	D5	Q1065	F5
D1028	D5	Q1073	H4
D1029	C6	Q1074	F3
D1030	B5	Q1075	F3
D1031	F5	Q1076	H3
D1032	D5	Q1077	H3
D1033	D5	Q1078	G3
D1034	D5	Q1079	G3
D1035	F5	Q1501	D4
D1036	D5	Q1502	D4
D1037	F5	Q1504	E4
D1038	G5	Q1507	E3
D1039	G5	Q1509	E6
D1042	B5	Q1511	D2
D1043	F4	Q1512	D3
D1044	F3	Q1513	D2
D1045	F3	Q1514	D3
D1046	H3	Q1520	C4
D1047	H3	Q1521	C4
D1048	G3	Q1524	B4
D1049	G3	Q1525	B4
D1050	H4	Q1527	E4


MAIN (2) (Side A)

R, S models




MAIN (3) (Side A)

U, C models




MAIN (4) (Side A)




• Semiconductor Location

Ref no.	Location
IC101	E2
IC102	F2

MAIN (5) (Side A)



MAIN (6) (Side A)



RX-V675/HTR-6066/TSR-6750

RX-A730

MAIN (2)

(Side B)




R, S models

MAIN (3)

(Side B)

MAIN (4)

(Side B)





MAIN (5)

(Side B)



MAIN (6)

(Side B)









MEMO








MEMO






DIGITAL 2/8


IC21: ADV7180BSTZ
10-bit, 4 x oversampling SDTV video decoderIC27: RP130Q181D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable (H Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

- All voltages are measured with a 10M Ω /V DC electronic voltmeter.
- Components having special characteristics are marked Δ , and must be replaced with parts having specifications equal to those originally installed.
- Schematic diagram is subject to change without notice.



Pin No.	Symbol	Description
1	CE	Chip Enable Pin
2	GND	Ground Pin
3	NC	No Connection
4	Vin	Input Pin
5	Vout	Output Pin of Voltage Regulator



to DIGITAL (1)
001.sht
(HDMI Rx)

Page 127 F1
to DIGITAL (1)_CB8

DIGITAL (2)
IC/CB/XL: 421-429
OTHER : 4201-4299

DIGITAL (3)
IC/CB/XL: 30-39
OTHER : 350-399

Sheet2: VDec / F HDMI / 232C

IC424: TC7S08TFU
2 input AND gate

	A	B	Y
IN B	L	L	L
IN A	L	H	L
	H	L	L
	H	H	H

DIGITAL 3/8

to 001.sht
(HDMI Rx)
to DIGITAL 1/8

to 002.sht
(VDec)
to DIGITAL 2/8

to 005.sht
(u-Com)
to DIGITAL 5/8

to 005.sht
(u-Com)
to DIGITAL 5/8

No replacement part available.

IC50
EP4C15F23C6N
YD917A0

FPGA

IC50
EP4C15F23C6N
YD917A0

FPGA


to 004.sht
(HDMI Tx)
to DIGITAL 4/8

No replacement part available.

No replacement part available.

Sheet 3 : FPGA

IC53: NT58V8M16HS-6K
128 Mb synchronous DRAM



to DIGITAL 5/8
to 005.sht
(u-Com)

NOTICE (model)

- (J) JAPAN
- (U) U.S.A
- (C) CANADA
- (E) EUROPE
- (A) AFRICA
- (S) SOUTH AMERICA
- (I) INDIA
- (O) OCEANIA
- (M) MEXICO
- (K) KOREA
- (T) TAIWAN
- (H) HONG KONG
- (S) SINGAPORE
- (P) PHILIPPINES
- (B) BRAZIL
- (R) RUSSIA
- (E) ESTONIA
- (L) LATVIA
- (L) LITHUANIA
- (P) POLAND
- (P) PORTUGAL
- (R) ROMANIA
- (S) SLOVAKIA
- (S) SLOVENIA
- (U) UKRAINE
- (U) UZBEKISTAN
- (V) VIETNAM
- (Y) YUGOSLAVIA
- (Z) ZAMBIA
- (Z) ZIMBABWE

IC55: RP130Q251D-TR-FE
Voltage regulator



Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC56: R1172N301D-TR-F
Voltage regulator



Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC57: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC58: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC59: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC60: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC61: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC62: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC63: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC64: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC65: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC66: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC67: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC68: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC69: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC70: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC71: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC72: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC73: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC74: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC75: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC76: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC77: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC78: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC79: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC80: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC81: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC82: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC83: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC84: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC85: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC86: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC87: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC88: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC89: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin




IC90: RP130Q121D-TR-F
Voltage regulator

Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin
4	VDD	Input Pin

IC91:

DIGITAL 4/8


DIGITAL (1)




Sheet 4: HDMI Tx

IC/CB/XL: 60-74
OHTER: 600-749


IC60: R1163N501B-TR-FE
CMOS-based manual mode switching LDO regulator




IC61: SI19136CTU-3
HDMI deep color transmitter




IC64: TC74VHC157FT
Quad 2-channel multiplexer



IC65: TC74LCX245FT
Low voltage octal bus transceiver with 5-V tolerant inputs and outputs







IC66: TC74VHC04FT
Hex inverters



★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

Pin No.	Symbol	Description
1	V _{DD}	Input Pin
2	GND	Ground Pin
3	CE	Chip Enable Pin ("H" Active)
4	ECO	MODE Alternative Pin
5	V _{OUT}	Output Pin

DIGITAL (1)



CAPACITOR		PARTS	NAME
⊗	MARK	ELECTROLYTIC	CAPACITOR
⊗	MARK	TANTALUM	CAPACITOR
⊗	MARK	CERAMIC	CAPACITOR
⊗	MARK	CERAMIC	TUBULAR CAPACITOR
⊗	MARK	POLYESTER	FILM CAPACITOR
⊗	MARK	POLYSTYRENE	FILM CAPACITOR
⊗	MARK	MICA	CAPACITOR
⊗	MARK	POLYPROPYLENE	FILM CAPACITOR
⊗	MARK	SEMI CONDUCTIVE	CERAMIC CAPACITOR
⊗	MARK	POLYPHENYLENE	SULFIDE FILM CAPACITOR

NOTICE (model)

(J)	 JAPAN
(U)	 U.S.A
(C)	 CANADA
(R)	 GERMANY
(T)	 CHINA
(K)	 KOREA
(A)	 AUSTRALIA
(B)	 BRITISH
(G)	 EUROPE
(L)	 SINGAPORE
(E)	 SOUTH EUROPE
(V)	 TAIWAN
(F)	 RUSSIAN
(P)	 LATIN AMERIC
(S)	 BRAZIL
(R)	 THAI

Written by YEM : YF253A0
 MXIC Blank : X9697B0 MX29LV640EBTI-70G
 EON Blank : YC079B0 EN29LV640AB-90TIP

FLASH ROM

MICROPROCESSOR

No replacement part available.


EEPROM

```

EEPROM      43.3M
-E783  E1HX25513&TA00A  512

```


ANALOG





Sheet 5 : u - Com

IC/CB/XL:75-99
QUTED 050 000





OUTER 1750-999



IC82: R1EX25512ATA00A
64 K word x 8-bit serial peripheral interface EEPROM




Pin No.	Symbol	Description
1	CE	Chip Enable ("H" Active)
2	GND	Ground Pin
3	Vout	Output Pin




- ★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
- ★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
- ★ Schematic diagram is subject to change without notice.

DIGITAL 6/8




NETWORK MICROPROCESSOR




* Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
* Schematic diagram is subject to change without notice.

NETWORK MICROPROCESSOR
No replacement part available.




NETWORK MICROPROCESSOR
No replacement part available.



* Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
* Schematic diagram is subject to change without notice.

NOR FLASH 256Mbit
NOR FLASH



DIGITAL 7/8

NOTICE (model)
(J) JAPAN
(D) D.S.A.
(C) CANADA
(E) GERMANY
(F) FRANCE
(K) KOREA
(A) AUSTRALIA
(B) BRITISH
(G) EUROPE
(L) SINGAPORE
(S) SOUTH AFRICA
(V) TAIWAN
(P) RUSSIAN
(R) LATIN AMERICA
(S) BRAZIL
(H) THAI

RESISTOR	PARTS	NAME
NO MARK	CARBON FILM RESISTOR (0-5)	
0	CARBON FILM RESISTOR (0-10)	
1	METAL OXIDE FILM RESISTOR	
2	METAL FILM RESISTOR	
3	METAL STATE RESISTOR	
4	FILM PROOF CARBON FILM RESISTOR	
5	CERMET ROLDED RESISTOR	
6	SNOL VARIABLE RESISTOR	
7	CHIP RESISTOR	

CAPACITOR	PARTS	NAME
NO MARK	ELECTROLYTIC CAPACITOR	
0	TANTALUM CAPACITOR	
1	CERAMIC CAPACITOR	
2	CERAMIC VARIABLE CAPACITOR	
3	POLYESTER FILM CAPACITOR	
4	POLYESTER FILM CAPACITOR	
5	MICA CAPACITOR	
6	POLYESTER FILM CAPACITOR	
7	SPRINGSIDE CERAMIC CAPACITOR	
8	POLYETHYLENE SULFIDE FILM CAPACITOR	

DIGITAL IN

ANALOG IN

AVL_0

AVL_1

AVL_2

AVL_3

AVL_4

AVL_5

AVL_6

AVL_7

AVL_8

AVL_9

AVL_10

AVL_11

AVL_12

AVL_13

AVL_14

AVL_15

AVL_16

AVL_17

AVL_18

AVL_19

AVL_20

AVL_21

AVL_22

AVL_23

AVL_24

AVL_25

AVL_26

AVL_27

AVL_28

AVL_29

AVL_30

AVL_31

AVL_32

AVL_33

AVL_34

AVL_35

AVL_36

AVL_37

AVL_38

AVL_39

AVL_40

AVL_41

AVL_42

AVL_43

AVL_44

AVL_45

AVL_46

AVL_47

AVL_48

AVL_49

AVL_50

AVL_51

AVL_52

AVL_53

AVL_54

AVL_55

AVL_56

AVL_57

AVL_58

AVL_59

AVL_60

AVL_61

AVL_62

AVL_63

AVL_64

AVL_65

AVL_66

AVL_67

AVL_68

AVL_69

AVL_70

AVL_71

AVL_72

AVL_73

AVL_74

AVL_75

AVL_76

AVL_77

AVL_78

AVL_79

AVL_80

AVL_81

AVL_82

AVL_83

AVL_84

AVL_85

AVL_86

AVL_87

AVL_88

AVL_89

AVL_90

AVL_91

AVL_92

AVL_93

AVL_94

AVL_95

AVL_96

AVL_97

AVL_98

AVL_99

AVL_100

AVL_101

AVL_102

AVL_103

AVL_104

AVL_105

AVL_106

AVL_107

AVL_108

AVL_109

AVL_110

AVL_111

AVL_112

AVL_113

AVL_114

AVL_115

AVL_116

AVL_117

AVL_118

AVL_119

AVL_120

AVL_121

AVL_122

AVL_123

AVL_124

AVL_125

AVL_126

AVL_127

AVL_128

AVL_129

AVL_130

AVL_131

AVL_132

AVL_133

AVL_134

AVL_135

AVL_136

AVL_137

AVL_138

AVL_139

AVL_140

AVL_141

AVL_142

AVL_143

AVL_144

AVL_145

AVL_146

AVL_147

AVL_148

AVL_149

AVL_150

AVL_151

AVL_152

AVL_153

AVL_154

AVL_155

AVL_156

AVL_157

AVL_158

AVL_159

AVL_160

AVL_161

AVL_162

AVL_163

AVL_164

AVL_165

AVL_166

AVL_167

AVL_168

AVL_169

AVL_170

AVL_171

AVL_172

AVL_173

AVL_174

AVL_175

AVL_176

AVL_177

AVL_178

AVL_179

AVL_180

AVL_181

AVL_182

AVL_183

AVL_184

AVL_185

AVL_186

AVL_187

AVL_188

AVL_189

AVL_190

AVL_191

AVL_192

AVL_193

AVL_194

AVL_195

AVL_196

AVL_197

AVL_198

AVL_199

AVL_200

AVL_201

AVL_202

AVL_203

AVL_204

AVL_205

AVL_206

AVL_207

AVL_208

AVL_209

AVL_210

AVL_211

AVL_212

AVL_213

AVL_214

AVL_215

AVL_216

AVL_217

AVL_218

AVL_219

AVL_220

AVL_221

AVL_222

AVL_223

AVL_224

AVL_225

AVL_226

AVL_227

AVL_228

AVL_229

AVL_230

AVL_231

AVL_232

AVL_233

AVL_234

AVL_235

AVL_236

AVL_237

AVL_238

AVL_239

AVL_240

AVL_241

AVL_242

AVL_243

AVL_244

AVL_245

AVL_246

AVL_247

AVL_248

AVL_249

AVL_250

AVL_251

AVL_252

AVL_253

AVL_254

AVL_255

AVL_256

AVL_257

AVL_258

AVL_259

AVL_260

AVL_261

AVL_262

AVL_263

AVL_264

AVL_265

AVL_266

AVL_267

AVL_268

AVL_269

AVL_270

AVL_271

AVL_272

AVL_273

AVL_274

AVL_275

AVL_276

AVL_277

AVL_278

AVL_279

AVL_280

AVL_281

AVL_282

AVL_283

AVL_284

AVL_285

AVL_286

AVL_287

AVL_288

AVL_289

AVL_290

AVL_291

AVL_292

AVL_293

AVL_294

AVL_295

AVL_296

AVL_297

AVL_298

AVL_299

AVL_300

AVL_301

AVL_302

AVL_303

AVL_304

AVL_305

AVL_306

AVL_307

AVL_308

AVL_309

AVL_310

AVL_311

AVL_312

DIGITAL 8/8

DIGITAL (1)

WiFi/BT Adapter Power

DC OUT
5V±0.5A

to DIGITAL 4/8
(HDMI Tx)

to DIGITAL 1/8
(HDMI Tx)

No replacement part available.

No replacement part available. No replacement part available.

NET/USB +3.3V

(for service)

Page 137 [I9]
to OPERATION (3)_W3704
(RX-V675/HTR-6066/TSR-6750)

Page 140 [I9]
to OPERATION (3)_W3704
(RX-A730)

Page 137 [I10]
to OPERATION (3)_W3703
(RX-V675/HTR-6066/TSR-6750)

Page 140 [I10]
to OPERATION (3)_W3703
(RX-A730)

to DIGITAL 7/8
(DSF/DIF)


to DIGITAL 6/8
(Net/USB)

DIGITAL IN
ANALOG IN
FRONT L
SURROUND L
SURROUND BACK L
CENTER/
SUBWOOFER

to DIGITAL 5/8
(u-Com)


IC940: R1172H501D-T1-F

Voltage regulator




IC942, 944: BD9328EFJ

1ch step-down DC/DC converter




IC943: BD9329AEFJ-E2

1ch step-down DC/DC converter




IC946: RP130Q331D-TR-F

Voltage regulator




IC947: BD7542F-E2

Input/output full swing CMOS operational amplifier



IC949: SN74LVC1G17DCKR

Single schmitt-trigger buffer



RESISTOR	PARTS NAME
[Symbol]	CARBON FILM RESISTOR (P=5)
[Symbol]	CARBON FILM RESISTOR (P=10)
[Symbol]	METAL OXIDE FILM RESISTOR
[Symbol]	METAL FILM RESISTOR
[Symbol]	METAL PLATE RESISTOR
[Symbol]	FIRE PROOF CARBON FILM RESISTOR
[Symbol]	CHERRY WELDED RESISTOR
[Symbol]	SEMI VARIABLE RESISTOR
[Symbol]	CHIP RESISTOR

CAPACITOR	PARTS NAME
[Symbol]	ELECTROLYTIC CAPACITOR
[Symbol]	TANTALUM CAPACITOR
[Symbol]	CERAMIC CAPACITOR
[Symbol]	CERAMIC TUBULAR CAPACITOR
[Symbol]	POLYESTER FILM CAPACITOR
[Symbol]	POLYSTYRENE FILM CAPACITOR
[Symbol]	MICA CAPACITOR
[Symbol]	POLYPROPYLENE FILM CAPACITOR
[Symbol]	SEMICONDUCTIVE CERAMIC CAPACITOR
[Symbol]	POLYPHENYLENE SULFIDE FILM CAPACITOR

NOTICE (model)
(S) JAPAN
(U) U.S.A
(C) CANADA
(B) BRITISH
(T) CHINA
(K) KOREA
(A) AUSTRALIA
(S) SINGAPORE
(E) EUROPE
(L) LITHUANIA
(R) SOUTH KOREA
(V) TAIWAN
(F) RUSSIAN
(S) LATIN AMERICA
(H) THAI

Page 137 [J1]
to OPERATION (4)_CB381
(RX-V675/HTR-6066/TSR-6750)

Page 140 [J1]
to OPERATION (4)_CB381
(RX-A730)

Page 142 [C6]
to MAIN (1)_CB154


Page 142 [C6]
to MAIN (1)_CB155

Sheet8: Power

IC/CB/XL: 940-949 & 481-489
ST/PN/M: 941-949 & 481-489
QWTR: 9403-9499 & 4803-4899

IC481-485: PCM5101PWR

106 dB audio selector DAC with 32-bit, 384 kHz PCM interface



* All voltages are measured with a 10MΩ/V DC electronic voltmeter.
* Components having special characteristics are marked A, and must be replaced with parts having specifications equal to those originally installed.
* Schematic diagram is subject to change without notice.

OPERATION 1/3

RX-V675/HTR-6066/TSR-6750



3001-3400
301-340

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P-5)
△	CARBON FILM RESISTOR (P-10)
△	METAL OXIDE FILM RESISTOR
△	METAL FILM RESISTOR
△	METAL PLATE RESISTOR
△	FIBRE PROOF CARBON FILM RESISTOR
△	CEMENT MOLDED RESISTOR
△	SEMI VARIABLE RESISTOR
△	CHIP RESISTOR


REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
NO MARK	CERAMIC CAPACITOR
●	CERAMIC TUBULAR CAPACITOR
○	POLYESTER FILM CAPACITOR
○	POLYSTYRENE FILM CAPACITOR
○	MICA CAPACITOR
○	POLYPROPYLENE FILM CAPACITOR
○	SEMICONDUCTIVE CERAMIC CAPACITOR
○	POLYPHENYLENE SULFIDE FILM CAPACITOR

NOTICE (model)
(J)..... JAPAN
(U)..... U.S.A
(C)..... CANADA
(R)..... GENERAL
(T)..... CHINA
(K)..... KOREA
(A)..... AUSTRALIA
(S)..... BRITISH
(G)..... EUROPE
(L)..... SINGAPORE
(B)..... SOUTH EUROPE
(V)..... TAIWAN
(P)..... RUSSIAN
(I)..... LATIN AMERICA
(S)..... BRAZIL
(H)..... THAI

RX-V675/HTR-6066/RX-A730/TSR-6750




IC301: M66003-0131FP-R
18 digit 5 x 7 segment VFD controller/driver



OPERATION (7)


OPe (7)



Page 141
to MAIN (1)_W106

OPERATION (1)

OPe (1)



USB

to Digital

to Digital

to Digital

to Digital

to Digital

to Digital

to Digital

to Digital

to Digital

to Digital

to Digital


to Digital

to Digital

to Digital


to Digital

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked △ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.




OPERATION (5)

OPe (5)



OPERATION (6)

OPe (6)



Key detection for A/D port
Key input (A/D) pull-up resistance 10 k-ohms

Detected voltage value @170 μm	0.0	+10kΩ	+10kΩ	+10kΩ	+15kΩ	+15kΩ	+2.2kΩ	+3.3kΩ	+4.7kΩ	22kΩ	33kΩ
A/D value (3.3V±25%)	0-11	12-32	33-54	55-75	76-96	97-119	120-142	143-163	164-197	198-209	
KEY1	RADIO (SCENE4)	NET (SCENE3)	TV (SCENE2)	B/D/DVD (SCENE1)	ZONE CONTROL	ZONE2	INPUT >	INPUT <	MAIN ZONE ○ (power)	TO CONTROL	

Detected voltage value @170 μm	0.0	+10kΩ	+10kΩ	+15kΩ	+15kΩ	+2.2kΩ	+3.3kΩ	+4.7kΩ	+6.8kΩ	+10kΩ	+22kΩ	+68kΩ
A/D value (3.3V±25%)	0-11	12-32	33-54	55-77	78-99	100-121	122-144	145-166	167-198	199-205	206-226	227-246
KEY2	PURE DIRECT	TUNING >>	TUNING <<	AM	FM	PRESET >	PRESET <	MEMORY	INFO	STRAIGHT >	PROGRAM >	

Page 131
to DIGITAL (1)_CB343

Page 136
to OPERATION (2)_CB343

OPERATION 2/3

COMPONENT VIDEO

VIDEO

MONITOR OUT

MONITOR OUT

MONITOR OUT

- ★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
- ★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
- ★ Schematic diagram is subject to change without notice.

Page 135 **K9**
to OPERATION (1)_CB306
to OPE (1)

Page 137 **K4**
to OPERATION (4)_CB383
to OPE (4)


to AM/FM TUNER
to TUNER Pack

Page 141 **H9**
to MAIN (1)_W107


NOTICE (model)
(J)..... JAPAN
(U)..... U.S.A
(C)..... CANADA
(R)..... GENERAL
(Y)..... CHINA
(K)..... KOREA
(A)..... AUSTRALIA
(B)..... BRITISH
(G)..... EUROPE
(L)..... SINGAPORE
(S)..... SOUTH EUROPE
(V)..... TAIWAN
(P)..... RUSSIAN
(F)..... LATIN AMERICA
(B)..... BRAZIL
(H)..... THAI

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
□	CARBON FILM RESISTOR (P=10)
Δ	METAL OXIDE FILM RESISTOR
□	METAL FILM RESISTOR
□	METAL PLATE RESISTOR
□	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT WOUND RESISTOR
□	POT. VARIABLE RESISTOR
□	CHIP RESISTOR

REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
□	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
□	CERAMIC TUBULAR CAPACITOR
□	POLYESTER FILM CAPACITOR
□	POLYETHYLENE FILM CAPACITOR
□	MICA CAPACITOR
□	POLYPROPYLENE FILM CAPACITOR
□	SEMICONDUCTIVE CERAMIC CAPACITOR







IC341: NJW1329FH3
Multi input wide band video interface with I²C control




to DIGITAL

Page 131 **E9**
to DIGITAL (1)_CB76





Page 141 H9
to MAIN (1)_W110

Page 134 M2
to DIGITAL (1)_CB945
to DIGITAL

Page 141 H2
to MAIN (1)_W105

TRIGGER OUT 12V $\approx$ 0.1A



CONTROL OUT +12V MAX 100mA



to OPE (2)

Page 136 G1


to OPERATION (2)_CB345



```

graph LR
    subgraph 78C58 [78C58]
        StartUp[StartUp]
        UVLO[UVLO Reg/Iconst]
        Latch[Latch]
        OSC[OSC]
        Logic[Logic]
        DRV[DRV]
        OCPBS[OCP/BS]
        FBSTB[FB/STB OLP]
        BD[BD]
        Logic --- StartUp
        Logic --- UVLO
        Logic --- Latch
        Logic --- OSC
        Logic --- DRV
        Logic --- OCPBS
        Logic --- FBSTB
        Logic --- BD
    end
    Pin3((3)) --- UVLO
    Pin4((4)) --- OSC


```



Pin No.	Symbol	Description
1	VOUT	Output Pin
2	GND	Ground Pin
3	CE	Chip Enable Pin
4	NC	No Connection
5	VDD	Input Pin

OPE (3)

AC_DC
371~380
3701~3800



Safety measures

- Some internal parts in this product contain high voltages and are dangerous. Be sure to take safety measures during servicing, such as wearing insulating gloves.
 - Note that the capacitors indicated below are dangerous even after the power is turned off because an electric charge remains and a high voltage continues to exist there. Before starting any repair work, connect a discharging resistor (5 k-ohms/10 W) to the terminals of each capacitor indicated below to discharge electricity. The time required for discharging is about 30 seconds per each.
- C3706 on OPERATION (3) P.C.B.

C3706 on OPERATION (3) P.C.B.

Page 134 B6
to DIGITAL (1)_CB944


Page 134 B6
to DIGITAL (1)_CB942

Page 141 H9
to MAIN (1)_CB102

Destination Part List									
XXX	LOC	U	C	RS	T	A	ROP	LR	
#301	C3171	W68550	W68550	WQ00200	W78950	WQ00200	WQ00200	WQ00200	WQ00200
		200007/250	200007/250	200007/250	200007/250	200007/250	200007/250	200007/250	
#302	P3102	WQ01110	WQ01110	WQ01110		WQ01110	WQ01110	WQ01110	WQ01110
		8A125V	8A125V	8A125V	T4AL250V	T4AL250V	T4AL250V	T4AL250V	
#305	R3178	W895120	W895120	W815870	W895120		W895120	W895120	W895120
					SP15	SP15	SP15	SP15	
#306	C3107	W316120	W316120	W316120	W316120	W316120	W316120	W316120	W316120
		0.147/400	0.147/400	0.147/400	0.147/400	0.147/400	0.147/400	0.147/400	
#307	C3102	WQ00230	WQ00230	WQ00230	X	WQ00230	WQ00230	WQ00230	WQ00230
		10009/250	10009/250	10009/250		10009/250	10009/250	10009/250	
#308	P3176	W81100	W81100	W81100	W81100	W81100	W81100	W81100	W81100
		22N8	22N8	22N8	ELP20008AN	ELP20008AN	ELP20008AN	ELP20008AN	
#315	C3174	W860010	W860010	W860020	W85170	W85170	W85170	W85170	W85170
		200007/250	200007/250	200007/250	200007/250	200007/250	200007/250	200007/250	
#321	R3178	80154V	80154V	80154V	80154V	80154V	80154V	80154V	80154V
		1.2K	2.7K	4.7K	6.8K	10K	15K	47K	
#322	R3106								

- ★ All voltages are measured with a 10M Ω /V DC electronic voltmeter.
- ★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
- ★ Schematic diagram is subject to change without notice.









OPE (1)



RESISTOR	
REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P-5)
	CARBON FILM RESISTOR (P-10)
	METAL OXIDE FILM RESISTOR
	METAL FILM RESISTOR
	METAL PLATE RESISTOR
	FIRE PROOF CARBON FILM RESISTOR
	CEMENT MOLDED RESISTOR
	SEMI VARIABLE RESISTOR
	CHIP RESISTOR

NOTICE (model)

(J)..... JAPAN
(U)..... U.S.A
(C)..... CANADA
(R)..... GENERAL
(T)..... CHINA
(K)..... KOREA
(A)..... AUSTRALIA
(B)..... BRITISH
(G)..... EUROPE
(I)..... SINGAPORE
(E)..... SOUTH EUROPE
(V)..... TAIWAN
(F)..... RUSSIAN
(P)..... LATIN AMERICA
(S)..... BRAZIL
(H)..... THAI

Page 132 J9
to DIGITAL (1)_CB952

- ★ All voltages are measured with a 10M Ω /V DC electronic voltmeter.
- ★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
- ★ Schematic diagram is subject to change without notice.

OPERATION 2/3

RX-A730


RX-V675/HTR-6066/RX-A730/TSR-6750

Page 138 **H10**
to OPERATION (1)_CB305
to OPE (1)

Page 140 **K4**
to OPERATION (4)_CB383
to OPE (4)

to AM/FM TUNER
to TUNER Pack


Page 141 **H9**
to MAIN (1)_W107



NOTICE (model)
(J) JAPAN
(U) U.S.A
(C) CANADA
(R) GENERAL
(T) CHINA
(K) KOREA
(A) AUSTRALIA
(B) BRITISH
(G) EUROPE
(L) SINGAPORE
(S) SOUTH EUROPE
(V) TAIWAN
(P) RUSSIAN
(F) LATIN AMERICA
(S) BRAZIL
(R) THAI


REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
△	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
△	METAL FILM RESISTOR
△	METAL PLATE RESISTOR
△	FIRE PROOF CARBON FILM RESISTOR
△	CEMENT MOLDED RESISTOR
△	PWM VARIABLE RESISTOR
△	CHIP RESISTOR

REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
△	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
○	CERAMIC TUBULAR CAPACITOR
○	POLYESTER FILM CAPACITOR
○	POLYSTYRENE FILM CAPACITOR
○	MICA CAPACITOR
○	POLYPROPYLENE FILM CAPACITOR
○	SEMICONDUCTIVE CERAMIC CAPACITOR



OPERATION (9)

IC341: NJW1329FH3
Multi input wide band video interface with I²C control



OPE (2)





VIDEO

341-360

3401-3600

OPERATION (2)


to DIGITAL
Page 131 **E9**
to DIGITAL (1)_CB76



★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked △, and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

Page 141 H9
to MAIN (1)_W110




Page 134 M2
to DIGITAL (1)_CB945
to DIGITAL




TRIGGER OUT 12V $\Rightarrow$ 0.1A

CONTROL OUT


+12V MAX 100mA




IC375: STR-Y6753
Switching regulator



IC381: TC74VHCU04FT
Hex inverters



IC382: RP170H331B-T1-FE
Voltage regulator




Pin No.	Symbol	Description
1	VOUT	Output Pin
2	GND	Ground Pin
3	CE	Chip Enable Pin
4	NC	No Connection
5	VDD	Input Pin

Page 142 C5
to MAIN (1)_CB15

ОРЕ (3)

AC_DC
371~380
3701~3800



Safety measures

Safety measures

- Some internal parts in this product contain high voltages and are dangerous. Be sure to take safety measures during servicing, such as wearing insulating gloves.
- Note that the capacitors indicated below are dangerous even after the power is turned off because an electric charge remains and a high voltage continues to exist there. Before starting any repair work, connect a discharging resistor (5 k-ohms/10 W) to the terminals of each capacitor indicated below to discharge electricity. The time required for discharging is about 30 seconds per each.

C3706 on OPERATION (3) P.C.B.

Page 134 B6
to DIGITAL (1)_CB944Page 134 B6
to DIGITAL (1)_CB942Page 141 H9
to MAIN (1)_CB102

Destination Port List								
	#XX	LOC	U	C	A	DS	L	
	#101	C3111	W485500	31000750	W485550	W490020	W490020	W490220
			W485500	31000750	W485550	W490020	W490020	W490220
					W490020	W490020	W490020	W490220
					W490020	W490020	W490020	W490220
					W490020	W490020	W490020	W490220
					W490020	W490020	W490020	W490220
	#106	C3101	W481250	0.2874400	W481250	W481250	W481250	W481250
			0.2874400	0.2874400	0.2874400	0.2874400	0.2874400	0.2874400
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250
					W481250	W481250	W481250	W481250

- ★ All voltages are measured with a 10M Ω /V DC electronic voltmeter.
- ★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
- ★ Schematic diagram is subject to change without notice.

1





```

NOTICE (model)
(J)..... JAPAN
(U)..... U.S.A
(C)..... CANADA
(R)..... GENERAL
(T)..... CHINA
(K)..... KOREA
(A)..... AUSTRALIA
(B)..... BRITISH
(G)..... EUROPE
(L)..... SINGAPORE
(E)..... SOUTH EUROPE
(V)..... TAIWAN
(F)..... RUSSIAN
(P)..... LATIN AMERICA
(S)..... BRAZIL
(H)..... THAI

```

(P)..... LATIN AMERICA
(S)..... BRAZIL
(H)..... THAI

[illegible]



Safety measures

- Some internal parts in this product contain high voltages and are dangerous. Be sure to take safety measures during servicing, such as wearing insulating gloves.
- Note that the capacitors indicated below are dangerous even after the power is turned off because an electric charge remains and a high voltage continues to exist there. Before starting any repair work, connect a discharging resistor (5 k-ohms/10 W) to the terminals of each capacitor indicated below to discharge electricity. The time required for discharging is about 30 seconds per each.

C10B4, C10B5 on MAIN (1) P.C.B.

- ★ All voltages are measured with a 10M Ω /V DC electronic voltmeter.
- ★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
- ★ Schematic diagram is subject to change without notice.

MAIN (1)

Page 134 M3
to DIGITAL (1)_CB946Page 134 M4
to DIGITAL (1)_CB948Page 131 H9
to DIGITAL (1)_CB78

```

NOTICE (model)
(J)..... JAPAN
(U)..... U.S.A
(C)..... CANADA
(R)..... GENERAL
(T)..... CHINA
(K)..... KOREA
(A)..... AUSTRALIA
(B)..... BRITISH
(G)..... EUROPE
(L)..... SINGAPORE
(S)..... SOUTH EUROPE
(V)..... TAIWAN
(F)..... RUSSIAN
(P)..... LATIN AMERICA
(S)..... BRAZIL
(H)..... THAI

```

RESISTOR		
REMARKS	PARTS	NAME
NO MARK	CARBON FILM RESISTOR	(P=5)
	CARBON FILM RESISTOR	(P=10)
	METAL OXIDE FILM RESISTOR	
	METAL FILM RESISTOR	
	METAL PLATE RESISTOR	
	FIRE PROOF CARBON FILM RESISTOR	
	CEMENT MOLDED RESISTOR	
	SEMI VARIABLE RESISTOR	
	WIRE RESISTOR	

CAPACITOR		
REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	F
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	
⊙	CERAMIC TUBULAR CAPACITOR	
⊗	POLYESTER FILM CAPACITOR	
⊙	POLYSTYRENE FILM CAPACITOR	+
①	MICA CAPACITOR	
⊙	POLYPROPYLENE FILM CAPACITOR	
⊗	SEMICONDUCTIVE CERAMIC CAPACITOR	

- ★ All voltages are measured with a 10M Ω /V DC electronic voltmeter.
- ★ Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.
- ★ Schematic diagram is subject to change without notice.

■ REPLACEMENT PARTS LIST

• ELECTRICAL COMPONENT PARTS

WARNING

- Components having special characteristics are marked Δ and must be replaced with parts having specifications equal to those originally installed.

ABBREVIATIONS IN THIS LIST ARE AS FOLLOWS:

C.A.EL.CHP	: CHIP ALUMI.ELECTROLYTIC CAP	LED.CHP	: CHIP LED
C.CE	: CERAMIC CAP	LED.DSPLY	: LED DISPLAY
C.CE.ARRAY	: CERAMIC CAP ARRAY	LED.INFRD	: LED,INFRARED
C.CE.CHP	: CHIP CERAMIC CAP	PHOT.CPL	: PHOTO COUPLER
C.CE.M.CHP	: CHIP MULTILAYER CERAMIC CAP	PHOT.INTR	: PHOTO INTERRUPTER
C.CE.SAFTY	: RECOGNIZED CERAMIC CAP	PHOT.RFLCT	: PHOTO REFLECTOR
C.CE.TUBLR	: CERAMIC TUBULAR CAP	PHOT.TR	: PHOTO TRANSISTOR
C.CE.SMI	: SEMI CONDUCTIVE CERAMIC CAP	PIN.TEST	: PIN,TEST POINT
C.EL	: ELECTROLYTIC CAP	PTC.THERM	: POSITIVE TEMPERATURE COEFFICIENT THERMISTOR
C.EL.BP	: BIPOLAR ELECTROLYTIC CAP	R.ANTI.SURGE	: FIXED ANTI SURGE RESISTOR
C.EL.CHP	: CHIP ELECTROLYTIC CAP	R.ARRAY	: RESISTOR ARRAY
C.MICA	: MICA CAP	R.CAR.	: CARBON RESISTOR
C.ML.FLM	: MULTILAYER FILM CAP	R.CAR.CHP	: CHIP RESISTOR
C.MP	: METALLIZED POLYESTER FILM CAP	R.CAR.FP	: FLAME PROOF CARBON RESISTOR
C.MYLAR	: MYLAR FILM CAP	R.CEMENT	: CEMENT RESISTOR
C.MYLAR.ML	: MULTILAYER MYLAR FILM CAP	R.CHP	: CHIP RESISTOR
C.NIOB.OXD	: NIOBIUM OXIDE CAP	R.FUS	: FUSIBLE RESISTOR
C.PAPER	: PAPER CAPACITOR	R.MTL.CHP	: CHIP METAL FILM RESISTOR
C.PLS	: POLYSTYRENE FILM CAP	R.MTL.FLM	: METAL FILM RESISTOR
C.POL	: POLYESTER FILM CAP	R.MTL.OXD	: METAL OXIDE FILM RESISTOR
C.PP	: POLYPROPYLENE FILM CAP	R.MTL.PLAT	: METAL PLATE RESISTOR
C.PP.CHP	: CHIP POLYPROPYLENE FILM CAP	RSNR.CE	: CERAMIC RESONATOR
C.TNTL	: TANTALIUM CAP	RSNR.CRYS	: CRYSTAL RESONATOR
C.TNTL.CHP	: CHIP TANTALIUM CAP	SCR.BND.HD	: BIND HEAD B-TIGHT SCREW
C.TRIM	: TRIMMER CAP	SCR.TERM	: SCREW TERMINAL
CN	: CONNECTOR	SCR.TR	: SCREW,TRANSISTOR
CN.BS.PIN	: CONNECTOR,BASE PIN	SURG.PRTCT	: SURGE PROTECTOR
CN.CANNON	: CONNECTOR,CANNON	SUPRT.PCB	: P.C.B. SUPPORT
CN.DIN	: CONNECTOR,DIN	SW.LEVER	: LEVER SWITCH
CN.FLAT	: CONNECTOR,FLAT CABLE	SW.MICRO	: MICRO SWITCH
CN.FFC	: CONNECTOR,FLEXIBLE FLAT CABLE	SW.LEAF	: LEAF SWITCH
CN.HDMI	: HDMI CONNECTOR	SW.PUSH	: PUSH SWITCH
CN.PHOTO.R	: PHOTO FIBER SENSOR,RECEIVED	SW.RT	: ROTARY SWITCH
CN.PHOTO.T	: PHOTO FIBER SENSOR,TRANSMITTED	SW.RT.ENC	: ROTARY ENCODER
D.SCHOTTKY	: SCHOTTKY BARRIER DIODE	SW.RT.MTR	: ROTARY SWITCH WITH MOTOR
DIODE.ARRAY	: DIODE ARRAY	SW.SLIDE	: SLIDE SWITCH
DIODE.BRG	: DIODE BRIDGE	SW.TACT	: TACT SWITCH
DIODE.CHP	: CHIP DIODE	TERM.SP	: SPEAKER TERMINAL
DIODE.VAR	: VARACTOR DIODE	TERM.WRAP	: WRAPPING TERMINAL
DIODE.ZENR	: ZENER DIODE	THRMST.CHP	: CHIP THERMISTOR
DIODE.Z.CHP	: CHIP ZENER DIODE	TR	: TRANSISTOR
DIODE.PHOT	: PHOTO DIODE	TR.CHP	: CHIP TRANSISTOR
FER.BEAD	: FERRITE BEADS	TR.DGT	: DIGITAL TRANSISTOR
FER.CORE	: FERRITE CORE	TR.DGT.CHP	: CHIP DIGITAL TRANSISTOR
FET.CHP	: CHIP FET	TR.PAIR	: PAIR TRANSISTOR
FL.DSPLY	: FLUORESCENT DISPLAY	TRANS	: TRANSFORMER
FLTR.CE	: CERAMIC FILTER	TRANS.PULS	: PULSE TRANSFORMER
FLTR.COMB	: COMB FILTER MODULE	TRANS.PWR	: POWER TRANSFORMER
FLTR.LC.RF	: LC FILTER,EMI	VARISTOR.C	: CHIP VARISTOR
FUSE.CHP	: CHIP FUSE	VOLT.SELCT	: VOLTAGE SELECTOR
GND.MTL	: GROUND PLATE	VR	: ROTARY POTENTIOMETER
GND.TERM	: GROUND TERMINAL	VR.MTR	: POTENTIOMETER WITH MOTOR
JUMPER.CN	: JUMPER CONNECTOR	VR.SLIDE	: SLIDE POTENTIOMETER
JUMPER.TST	: JUMPER,TEST POINT	VR.SW	: POTENTIOMETER WITH SWITCH
L.DTCT	: LIGHT DETECTING MODULE	VR.TRIM	: TRIMMER POTENTIOMETER

DIGITAL

Ref No.	Part No.	Description	Markets
*	ZF534400	P. C. B.	DIGITAL
CB1-5	WW271700	CN. HDMI	19P HDMI
CB8	WD295800	CN. BS. PIN	22P 52793 SE
CB61	WW271700	CN. HDMI	19P HDMI
CB76	VQ044800	CN. BS. PIN	18P
CB78	VB390800	CN. BS. PIN	12P
CB79	VB390000	CN. BS. PIN	4P
CB80	VB390600	CN. BS. PIN	10P
CB82	VPO82900	CN. BS. PIN	25P
CB83	VG518300	PIN. BASE	2P RF TE
CB84	VQ047200	CN. BS. PIN	9P
CB411	LB918020	CN. BS. PIN	2P
CB412	VL844700	CN. BS. PIN	3P
CB421	WW271700	CN. HDMI	19P HDMI
CB422	VY939900	CN. BS. PIN	22P 52610 TE
CB940	WG939700	CN. USB	4P SE
CB942	LB919040	CN. BS. PIN	4P
CB943	VB389900	CN. BS. PIN	3P
CB944	VB858500	CN. BS. PIN	6P
CB945	VQ961800	CN. BS. PIN	15P
CB946	VF667600	CN. BS. PIN	15P
CB947	VL844800	CN. BS. PIN	4P
CB948	VK025100	CN. BS. PIN	7P
CB951	WH237300	CN. LAN	8P LU1T041A-LF
CB952	VB390100	CN. BS. PIN	5P
C2	WJ344400	C. CE. CHP	22uF 6. 3V
C10-11	US663100	C. CE. CHP	1000pF 50V
C13	US634100	C. CE. CHP	0. 01uF 16V
C17	US625100	C. CE. CHP	0. 1uF 10V
C26	US625100	C. CE. CHP	0. 1uF 10V
C27	US663390	C. CE. CHP	3900pF 50V
C28	WD758300	C. CE. CHP	10uF 10V
C53-54	US663100	C. CE. CHP	1000pF 50V
C55-56	WG888300	C. CE. M. CHP	10uF 6. 3V
C57	US625100	C. CE. CHP	0. 1uF 10V
C58-59	US634100	C. CE. CHP	0. 01uF 16V
C60-62	US625100	C. CE. CHP	0. 1uF 10V
C63	US634100	C. CE. CHP	0. 01uF 16V
C65	US625100	C. CE. CHP	0. 1uF 10V
C66	US634100	C. CE. CHP	0. 01uF 16V
C69	US625100	C. CE. CHP	0. 1uF 10V
C73	US663100	C. CE. CHP	1000pF 50V
C74	WG888300	C. CE. M. CHP	10uF 6. 3V
C75-76	US625100	C. CE. CHP	0. 1uF 10V
C77	US662100	C. CE. CHP	100pF 50V
C78	US663100	C. CE. CHP	1000pF 50V
C81	US625100	C. CE. CHP	0. 1uF 10V
C83-85	US046100	C. CE. CHP	1uF 25V
C93-94	US661100	C. CE. CHP	10pF 50V D
C95	US625100	C. CE. CHP	0. 1uF 10V
C96	US662100	C. CE. CHP	100pF 50V
C99	US663100	C. CE. CHP	1000pF 50V
C100	US046100	C. CE. CHP	1uF 25V
C101	US662470	C. CE. CHP	470pF 50V
C102	US663100	C. CE. CHP	1000pF 50V
C104-105	US625100	C. CE. CHP	0. 1uF 10V
C106	WG251600	C. CE. CHP	4. 7uF 6. 3V

* New Parts

Ref No.	Part No.	Description	Markets
C107	US625100	C. CE. CHP	0. 1uF 10V
C108	US046100	C. CE. CHP	1uF 25V
C109	US663100	C. CE. CHP	1000pF 50V
C110	US625100	C. CE. CHP	0. 1uF 10V
C111	US634100	C. CE. CHP	0. 01uF 16V
C112	US625100	C. CE. CHP	0. 1uF 10V
C113	WG888300	C. CE. M. CHP	10uF 6. 3V
C114-115	US625100	C. CE. CHP	0. 1uF 10V
C116	WJ344400	C. CE. CHP	22uF 6. 3V
C117-119	US625100	C. CE. CHP	0. 1uF 10V
C120-121	WG888300	C. CE. M. CHP	10uF 6. 3V
C122	US625100	C. CE. CHP	0. 1uF 10V
C123	US663100	C. CE. CHP	1000pF 50V
C124-125	US625100	C. CE. CHP	0. 1uF 10V
C126	WG888300	C. CE. M. CHP	10uF 6. 3V
C127-128	US663100	C. CE. CHP	1000pF 50V
C129-131	WG888300	C. CE. M. CHP	10uF 6. 3V
C133	US662100	C. CE. CHP	100pF 50V
C136	US662100	C. CE. CHP	100pF 50V
C137	WG888300	C. CE. M. CHP	10uF 6. 3V
C138-139	US625100	C. CE. CHP	0. 1uF 10V
C142	US634100	C. CE. CHP	0. 01uF 16V
C143-144	WG888300	C. CE. M. CHP	10uF 6. 3V
C145	US625100	C. CE. CHP	0. 1uF 10V
C147-148	US625100	C. CE. CHP	0. 1uF 10V
C149	US663100	C. CE. CHP	1000pF 50V
C150	US625100	C. CE. CHP	0. 1uF 10V
C152	US625100	C. CE. CHP	0. 1uF 10V
C153	US663100	C. CE. CHP	1000pF 50V
C154	WG888300	C. CE. M. CHP	10uF 6. 3V
C155	US625100	C. CE. CHP	0. 1uF 10V
C156	US663100	C. CE. CHP	1000pF 50V
C157	WG888300	C. CE. M. CHP	10uF 6. 3V
C159-160	US663100	C. CE. CHP	1000pF 50V
C161	WD758300	C. CE. CHP	10uF 10V
C162	US634100	C. CE. CHP	0. 01uF 16V
C163	WD758300	C. CE. CHP	10uF 10V
C250	WD758300	C. CE. CHP	10uF 10V
C251	US046100	C. CE. CHP	1uF 25V
C252-253	US625100	C. CE. CHP	0. 1uF 10V
C255	WG888300	C. CE. M. CHP	10uF 6. 3V
C257-258	US625100	C. CE. CHP	0. 1uF 10V
C261-262	US625100	C. CE. CHP	0. 1uF 10V
C271	WJ932500	C. CE. CHP	1uF 6. 3V
C273	US625100	C. CE. CHP	0. 1uF 10V
C277	US625100	C. CE. CHP	0. 1uF 10V
C279	WJ932500	C. CE. CHP	1uF 6. 3V
C281	US625100	C. CE. CHP	0. 1uF 10V
C286	US625100	C. CE. CHP	0. 1uF 10V
C288	US634100	C. CE. CHP	0. 01uF 16V
C289	US625100	C. CE. CHP	0. 1uF 10V
C291	US662470	C. CE. CHP	470pF 50V
C294	US034820	C. CE. CHP	0. 082uF 16V K
C295	US634100	C. CE. CHP	0. 01uF 16V
C297-298	US625100	C. CE. CHP	0. 1uF 10V
C299-300	US661100	C. CE. CHP	10pF 50V D
C301	WG888300	C. CE. M. CHP	10uF 6. 3V

* New Parts

RX-V675/HTR-6066/TSR-6750

RX-A730

DIGITAL

Ref No.	Part No.	Description	Markets
C302-303	US625100	C. CE. CHP 0.1uF 10V	
C304	WG888300	C. CE. M. CHP 10uF 6.3V	
C500-503	US663100	C. CE. CHP 1000pF 50V	
C504	UF417470	C. EL. CHP 47uF 6.3V	
C505	WG888300	C. CE. M. CHP 10uF 6.3V	
C506-507	UF417470	C. EL. CHP 47uF 6.3V	
C509-513	WG888300	C. CE. M. CHP 10uF 6.3V	
C514-554	US625100	C. CE. CHP 0.1uF 10V	
C556-565	US625100	C. CE. CHP 0.1uF 10V	
C568	US663100	C. CE. CHP 1000pF 50V	
C569	US625100	C. CE. CHP 0.1uF 10V	
C578	WG888300	C. CE. M. CHP 10uF 6.3V	
C579-585	US625100	C. CE. CHP 0.1uF 10V	
C591-594	WG888300	C. CE. M. CHP 10uF 6.3V	
C597	WG888300	C. CE. M. CHP 10uF 6.3V	
C634-635	US663100	C. CE. CHP 1000pF 50V	
C636-637	WG888300	C. CE. M. CHP 10uF 6.3V	
C638-643	US625100	C. CE. CHP 0.1uF 10V	
C644-645	US663100	C. CE. CHP 1000pF 50V	
C646	US625100	C. CE. CHP 0.1uF 10V	
C647	WG888300	C. CE. M. CHP 10uF 6.3V	
C649	US663100	C. CE. CHP 1000pF 50V	
C650	US625100	C. CE. CHP 0.1uF 10V	
C653	US625100	C. CE. CHP 0.1uF 10V	
C654-655	US662100	C. CE. CHP 100pF 50V	
C656	US663100	C. CE. CHP 1000pF 50V	
C662	US662100	C. CE. CHP 100pF 50V	
C664-665	US046100	C. CE. CHP 1uF 25V	
C666	WD758300	C. CE. CHP 10uF 10V	
C667	US662470	C. CE. CHP 470pF 50V	
C668	US661220	C. CE. CHP 22pF 50V	
C669	WD758300	C. CE. CHP 10uF 10V	
C670-671	US625100	C. CE. CHP 0.1uF 10V	
C672	US046100	C. CE. CHP 1uF 25V	
C673	US625100	C. CE. CHP 0.1uF 10V	
C750-753	US663100	C. CE. CHP 1000pF 50V	
C754	US625100	C. CE. CHP 0.1uF 10V	
C755-762	US663100	C. CE. CHP 1000pF 50V	
C763	US625100	C. CE. CHP 0.1uF 10V	
C764-767	US663100	C. CE. CHP 1000pF 50V	
C768	US625100	C. CE. CHP 0.1uF 10V	
C769	UF027330	C. EL. CHP 33uF 10V	
C770	US663100	C. CE. CHP 1000pF 50V	
C771-772	US625100	C. CE. CHP 0.1uF 10V	
C773-774	US662100	C. CE. CHP 100pF 50V	
C775	US625100	C. CE. CHP 0.1uF 10V	
C776-777	US663100	C. CE. CHP 1000pF 50V	
C778-779	US625100	C. CE. CHP 0.1uF 10V	
C780	US046100	C. CE. CHP 1uF 25V	
C781	US663100	C. CE. CHP 1000pF 50V	
C782	US662100	C. CE. CHP 100pF 50V	
C783	WG251600	C. CE. CHP 4.7uF 6.3V	
C784	US662100	C. CE. CHP 100pF 50V	
C785	US625100	C. CE. CHP 0.1uF 10V	
C786	US663100	C. CE. CHP 1000pF 50V	
C787-791	US625100	C. CE. CHP 0.1uF 10V	
C792-795	US046100	C. CE. CHP 1uF 25V	

* New Parts

Ref No.	Part No.	Description	Markets
C796	US625100	C. CE. CHP 0.1uF 10V	
C797	US046100	C. CE. CHP 1uF 25V	
C798	WG251600	C. CE. CHP 4.7uF 6.3V	
C799	US046100	C. CE. CHP 1uF 25V	
C800	US663100	C. CE. CHP 1000pF 50V	
C801-802	US625100	C. CE. CHP 0.1uF 10V	
C803	WG251600	C. CE. CHP 4.7uF 6.3V	
C805	US625100	C. CE. CHP 0.1uF 10V	
C808-809	US663100	C. CE. CHP 1000pF 50V	
C829-830	US662100	C. CE. CHP 100pF 50V	
C831-832	US663100	C. CE. CHP 1000pF 50V	
C834-848	US663100	C. CE. CHP 1000pF 50V	
C4101	US625100	C. CE. CHP 0.1uF 10V	
C4103-4104	US625100	C. CE. CHP 0.1uF 10V	
C4107-4108	US634100	C. CE. CHP 0.01uF 16V	
C4109	US625100	C. CE. CHP 0.1uF 10V	
C4110-4111	WD758300	C. CE. CHP 10uF 10V	
C4112	US046100	C. CE. CHP 1uF 25V	
C4201-4202	WK716800	C. CE. M. CHP 10uF 6.3V	
C4203	US046100	C. CE. CHP 1uF 25V	
C4204-4205	US625100	C. CE. CHP 0.1uF 10V	
C4206	US663100	C. CE. CHP 1000pF 50V	
C4207	WG888300	C. CE. M. CHP 10uF 6.3V	
C4208-4210	US625100	C. CE. CHP 0.1uF 10V	
C4211	US663100	C. CE. CHP 1000pF 50V	
C4212	US662100	C. CE. CHP 100pF 50V	
C4213	WK716800	C. CE. M. CHP 10uF 6.3V	
C4216	US663100	C. CE. CHP 1000pF 50V	
C4217	US624470	C. CE. CHP 0.047uF 10V	
C4218	US625100	C. CE. CHP 0.1uF 10V	
C4219	WG888300	C. CE. M. CHP 10uF 6.3V	
C4220-4221	US625100	C. CE. CHP 0.1uF 10V	
C4222	WG888300	C. CE. M. CHP 10uF 6.3V	
C4223	US625100	C. CE. CHP 0.1uF 10V	
C4224	WG251600	C. CE. CHP 4.7uF 6.3V	
C4225	US625100	C. CE. CHP 0.1uF 10V	
C4226	US663100	C. CE. CHP 1000pF 50V	
C4227	WG888300	C. CE. M. CHP 10uF 6.3V	
C4228-4230	US625100	C. CE. CHP 0.1uF 10V	
C4231	US663100	C. CE. CHP 1000pF 50V	
C4232	US662100	C. CE. CHP 100pF 50V	
C4233	WG888300	C. CE. M. CHP 10uF 6.3V	
C4234	US625100	C. CE. CHP 0.1uF 10V	
C4235	US663100	C. CE. CHP 1000pF 50V	
C4236	WJ344400	C. CE. CHP 22uF 6.3V	
C4237-4238	US625100	C. CE. CHP 0.1uF 10V	
C4239	US663100	C. CE. CHP 1000pF 50V	
C4240	US662100	C. CE. CHP 100pF 50V	
C4241	WG888300	C. CE. M. CHP 10uF 6.3V	
C4242-4243	US625100	C. CE. CHP 0.1uF 10V	
C4245	US625100	C. CE. CHP 0.1uF 10V	
C4246	US663100	C. CE. CHP 1000pF 50V	
C4801-4810	US625100	C. CE. CHP 0.1uF 10V	
C4811	WV169100	C. CE. CHP 2.2uF 10V	
C4812-4814	US625100	C. CE. CHP 0.1uF 10V	
C4815-4816	WV169100	C. CE. CHP 2.2uF 10V	
C4817	WD758300	C. CE. CHP 10uF 10V	

* New Parts

DIGITAL

Ref No.	Part No.	Description	Markets
C4818	WV169100	C. CE. CHP	2. 2uF 10V
C4819-4820	US625100	C. CE. CHP	0. 1uF 10V
C4821-4822	WD758300	C. CE. CHP	10uF 10V
C4823-4824	WV169100	C. CE. CHP	2. 2uF 10V
C4825-4826	US062680	C. CE. CHP	680pF 50V B
C4827-4830	WB571200	C. MYLA. CHP	0. 00082uF 16V
C4831-4838	US625100	C. CE. CHP	0. 1uF 10V
C4839-4840	WV169100	C. CE. CHP	2. 2uF 10V
C4841-4842	US625100	C. CE. CHP	0. 1uF 10V
C4843-4844	WD758300	C. CE. CHP	10uF 10V
C4845-4846	WV169100	C. CE. CHP	2. 2uF 10V
C4847-4850	WB571200	C. MYLA. CHP	0. 00082uF 16V
C4864	UF417470	C. EL. CHP	47uF 6. 3V
C4865	UF418100	C. EL. CHP	100uF 6. 3V
C9201-9207	WG888300	C. CE. M. CHP	10uF 6. 3V
C9210	US643470	C. CE. CHP	4700pF 25V
C9211	US625100	C. CE. CHP	0. 1uF 10V
C9212	UF437100	C. EL. CHP	10uF 16V
C9213	US625100	C. CE. CHP	0. 1uF 10V
C9214-9215	US661180	C. CE. CHP	18pF 50V
C9216	US625100	C. CE. CHP	0. 1uF 10V
C9217	US634100	C. CE. CHP	0. 01uF 16V
C9218-9251	US625100	C. CE. CHP	0. 1uF 10V
C9252-9253	UF437100	C. EL. CHP	10uF 16V
C9254-9255	US643470	C. CE. CHP	4700pF 25V
C9256-9265	US625100	C. CE. CHP	0. 1uF 10V
C9266	US634100	C. CE. CHP	0. 01uF 16V
C9267-9268	US625100	C. CE. CHP	0. 1uF 10V
C9269-9270	WB571200	C. MYLA. CHP	0. 00082uF 16V
C9271	US662470	C. CE. CHP	470pF 50V
C9272	WG888300	C. CE. M. CHP	10uF 6. 3V
C9273	US661120	C. CE. CHP	12pF 50V
C9274	US661150	C. CE. CHP	15pF 50V
C9275	WG888300	C. CE. M. CHP	10uF 6. 3V
C9276	UB214680	C. CE. CHP	0. 068uF 25V
C9278	US643470	C. CE. CHP	4700pF 25V
C9279-9283	US625100	C. CE. CHP	0. 1uF 10V
C9284-9285	WG888300	C. CE. M. CHP	10uF 6. 3V
C9286-9289	US046100	C. CE. CHP	1uF 25V
C9290-9293	US625100	C. CE. CHP	0. 1uF 10V
C9295	US662470	C. CE. CHP	470pF 50V
C9296	US663100	C. CE. CHP	1000pF 50V
C9315-9317	US634100	C. CE. CHP	0. 01uF 16V
C9318	US625100	C. CE. CHP	0. 1uF 10V
C9401	US625100	C. CE. CHP	0. 1uF 10V
C9402	WH772100	C. EL	1000uF 10V
C9417	US625100	C. CE. CHP	0. 1uF 10V
C9423	UF438100	C. EL. CHP	100uF 16V
C9425	WJ344400	C. CE. CHP	22uF 6. 3V
C9426	WG888300	C. CE. M. CHP	10uF 6. 3V
C9428-9429	US663100	C. CE. CHP	1000pF 50V
C9430	US634100	C. CE. CHP	0. 01uF 16V
C9431	US625100	C. CE. CHP	0. 1uF 10V
C9432	US044220	C. CE. CHP	0. 022uF 25V B
C9433	US663390	C. CE. CHP	3900pF 50V
C9434	WD758300	C. CE. CHP	10uF 10V
C9436	WJ344400	C. CE. CHP	22uF 6. 3V

* New Parts

Ref No.	Part No.	Description	Markets
C9438-9439	US663100	C. CE. CHP	1000pF 50V
C9440	US663330	C. CE. CHP	3300pF 50V
C9441-9442	US625100	C. CE. CHP	0. 1uF 10V
C9443	US663390	C. CE. CHP	3900pF 50V
C9444	WD758300	C. CE. CHP	10uF 10V
C9445	WG251600	C. CE. CHP	4. 7uF 6. 3V
C9447	WJ344400	C. CE. CHP	22uF 6. 3V
C9448	US643680	C. CE. CHP	6800pF 25V
C9450-9451	US663100	C. CE. CHP	1000pF 50V
C9452	US643680	C. CE. CHP	6800pF 25V
C9453-9454	US625100	C. CE. CHP	0. 1uF 10V
C9455	WG251600	C. CE. CHP	4. 7uF 6. 3V
C9456	US663390	C. CE. CHP	3900pF 50V
C9458	WD758300	C. CE. CHP	10uF 10V
C9461	US634100	C. CE. CHP	0. 01uF 16V
C9469	US625100	C. CE. CHP	0. 1uF 10V
C9470	US046100	C. CE. CHP	1uF 25V
C9471	WG251600	C. CE. CHP	4. 7uF 6. 3V
C9472	US625100	C. CE. CHP	0. 1uF 10V
C9473	US663150	C. CE. CHP	1500pF 50V
C9475	US663100	C. CE. CHP	1000pF 50V
C9476	UF128470	C. EL. CHP	470uF 10V
C9478	WD758300	C. CE. CHP	10uF 10V
C9480	US662100	C. CE. CHP	100pF 50V
C9481	US663100	C. CE. CHP	1000pF 50V
C9485	WD758300	C. CE. CHP	10uF 10V
C9501-9502	UF418100	C. EL. CHP	100uF 6. 3V
C9503-9509	WG888300	C. CE. M. CHP	10uF 6. 3V
C9510-9528	US625100	C. CE. CHP	0. 1uF 10V
C9530-9533	US663100	C. CE. CHP	1000pF 50V
C9535-9545	US663100	C. CE. CHP	1000pF 50V
C9548-9557	US634100	C. CE. CHP	0. 01uF 16V
C9562	US044220	C. CE. CHP	0. 022uF 25V B
C9563-9568	WG251600	C. CE. CHP	4. 7uF 6. 3V
C9570-9571	WJ932500	C. CE. CHP	1uF 6. 3V
C9572-9573	US661150	C. CE. CHP	15pF 50V
C9575	US634100	C. CE. CHP	0. 01uF 16V
C9577-9579	US634100	C. CE. CHP	0. 01uF 16V
C9585	US625100	C. CE. CHP	0. 1uF 10V
C9586-9587	WJ932500	C. CE. CHP	1uF 6. 3V
C9588-9589	US634100	C. CE. CHP	0. 01uF 16V
C9590-9591	US625100	C. CE. CHP	0. 1uF 10V
D38	WE674800	VARI STOR. C	AVRL161A1R1NTB
D602	VV220700	D. SCHOTTKY	RB501V-40
D750	WR148500	DIODE	RB521S-30TE61
D4103	WR148500	DIODE	RB521S-30TE61
D4105	V6267600	DIODE	RB051L-40
D4201-4202	WE674800	VARI STOR. C	AVRL161A1R1NTB
D4203-4204	WJ785100	DIODE	1SS400TE61 TE-
D9401-9402	WW783900	DIODE	1SS355VM
D9403-9404	WJ785100	DIODE	1SS400TE61 TE-
D9405	WR148500	DIODE	RB521S-30TE61
D9406-9407	WW783900	DIODE	1SS355VM
D9501-9502	WE674800	VARI STOR. C	AVRL161A1R1NTB
IC6	YC287A00	IC	RP130Q181D-TR-F
IC8	YC289A00	IC	RP130Q501D-TR
IC21	X8841A00	IC	ADV7180BSTZ

* New Parts

RX-V675/HTR-6066/TSR-6750

RX-A730

DIGITAL

Ref No.	Part No.	Description	Markets
IC27	YC287A00	IC RP130Q181D-TR-F	
IC53	YA560B00	IC NT5SV8M16HS-6K	
IC55	YD992A00	IC RP130Q251D-TR-FE	
IC56	YC827A00	IC R1172N301D-TR-F	
IC57	YC286A00	IC RP130Q121D-TR-F	
IC60	YD987A00	IC R1163N501B-TR-FE	
IC64	X0199B00	IC TC74VHC157FT (EL, K)	
IC65	X7787A00	IC TC74LCX245FT (EL, K)	
IC66	XZ509A00	IC TC74VHC04FT INVER	
IC75	XR680A00	IC TC7SH08FU (TE85L, JF)	
IC76	X5875A00	IC SN74LV4051APWR	
* IC77	YF253D00	IC. MEMORY EN29LV640AB-90TIP	(written)
IC78	X5875A00	IC SN74LV4051APWR	
IC79	X7942B00	IC TC74VHC273FT (EL, K)	
IC80	XW633A00	IC TC7SH32FU	
IC81	X7942B00	IC TC74VHC273FT (EL, K)	
IC82	YD355A00	IC. MEMORY R1EX25512ATA00A EE	
IC84-85	YC288A00	IC RP130Q331D-TR-F	
IC87	XR680A00	IC TC7SH08FU (TE85L, JF)	
IC91	X8121A00	IC TC7SH86FU EX-OR	
IC92	X4453A00	IC SN74LVC1G17DCKR	
IC93	X9692A00	IC TC7WH126FU	
IC411	YE997A00	IC NCP380HMMUJAATBG	
IC412	X8398A00	IC TC7SET08FU (T5L, JF)	
IC413	YF097A00	IC R1171S501B-E2-FE	
IC421	X9292A00	IC R1172H121D-T1-F	
IC424	X8398A00	IC TC7SET08FU (T5L, JF)	
IC481-485	YD570A00	IC PCM5101PWR	
IC922	X9625C00	IC. MEMORY M12L64164A-5TG2Y	
* IC923	YF271B00	IC. MEMORY W25Q80BVSSIG	(written)
IC924	YD216A00	IC PCM9211PTR	
IC926-927	XW633A00	IC TC7SH32FU	
IC929	X9292A00	IC R1172H121D-T1-F	
IC930	YC288A00	IC RP130Q331D-TR-F	
IC931	YC289A00	IC RP130Q501D-TR	
IC940	YA255A00	IC R1172H501D-T1-F	
IC946	YC288A00	IC RP130Q331D-TR-F	
IC947	YE478A00	IC BD7542F-E2 OPAMP	
IC949	X4453A00	IC SN74LVC1G17DCKR	
* IC953	YF254E00	IC. MEMORY MX29GL256FLT21-90Q	(written)
PN941-944	WS488500	STYLE. PIN L=90 #18	
PN946	WS488500	STYLE. PIN L=90 #18	
Q11	WZ703400	FET RAL035P01	
Q12	WW782000	TR. DGT DTA044EUBTL	
Q17	WZ703400	FET RAL035P01	
Q18	WW782000	TR. DGT DTA044EUBTL	
Q21-22	WE834500	FET UPA672T-T1-A	
Q250-251	WZ461800	TR. CHP 2SC4081UBTLR	
Q252	WZ461700	TR. CHP 2SA1576UBTLR	
Q253	WZ461800	TR. CHP 2SC4081UBTLR	
Q750-753	WY001400	TR. ARRAY HN4B01JE	
Q754-759	WZ461700	TR. CHP 2SA1576UBTLR	
Q760	WZ461800	TR. CHP 2SC4081UBTLR	
Q761	WZ461700	TR. CHP 2SA1576UBTLR	
Q762	WZ461800	TR. CHP 2SC4081UBTLR	
Q763	WZ461700	TR. CHP 2SA1576UBTLR	
Q765	WZ461700	TR. CHP 2SA1576UBTLR	

* New Parts

Ref No.	Part No.	Description	Markets
Q4101	WZ461700	TR. CHP 2SA1576UBTLR	
Q4102-4103	WZ703400	FET RAL035P01	
Q4104	WW782300	TR. DGT DTC044EUBTL	
Q4105-4106	WW782000	TR. DGT DTA044EUBTL	
Q4107	WW782300	TR. DGT DTC044EUBTL	
Q9201	WZ703400	FET RAL035P01	
Q9202	WW782000	TR. DGT DTA044EUBTL	
Q9401	WZ703400	FET RAL035P01	
Q9402	WW782000	TR. DGT DTA044EUBTL	
Q9404	WW782000	TR. DGT DTA044EUBTL	
Q9405	WW782100	TR. DGT DTC014EUBTL	
Q9406	WZ703400	FET RAL035P01	
Q9408	WZ703400	FET RAL035P01	
R9441	WZ713400	R. CHP 0.027Ω 1/3W	
R9610	WZ749000	R. CHP 12.4KΩ 1/16W	
R9614-9615	WZ748900	R. CHP 49.9Ω 1/16W	
R9617-9618	WZ748900	R. CHP 49.9Ω 1/16W	
XL1	WZ730400	RSNR. CRYST 28.63636MHz DSX321	
XL21	WZ730400	RSNR. CRYST 28.63636MHz DSX321	
XL51	WK841200	RESONATOR 27MHz DS0321SRAB	
XL75	WA782500	RSNR. CE 8MHz	
XL921	WS190000	RSNR. CRYST 24.576MHz DSX321G	
XL922	WN318100	RSNR. CRYST 20MHz DSX321G	
XL951	WJ081300	RSNR. CRYST 24MHz DSX321G	

* New Parts

OPERATION

Ref No.	Part No.	Description	Markets
* ZF535200	P. C. B.	OPERATION	U
* ZF535300	P. C. B.	OPERATION	C
* ZF535400	P. C. B.	OPERATION	RS
* ZF535500	P. C. B.	OPERATION	T
* ZF535600	P. C. B.	OPERATION	A
* ZF535700	P. C. B.	OPERATION	BGF
* ZF535800	P. C. B.	OPERATION	LH
CB301	VK026900	CN	10P
CB303	VQ045400	CN. BS. PIN	25P
CB306	VQ044200	CN. BS. PIN	6P
CB307	WQ680200	CN. USB	4P TE AAPVA004C0
CB308	VB858300	CN. BS. PIN	4P
CB342	VQ046900	CN. BS. PIN	5P
CB343	VQ047000	CN. BS. PIN	6P
CB344	VP573800	CN. BS. PIN	18P
CB345	VQ961800	CN. BS. PIN	15P
CB346	VQ047200	CN. BS. PIN	9P
CB347	LB918020	CN. BS. PIN	2P
CB361	VQ044100	CN. BS. PIN	5P
CB371	VG879900	CN. BS. PIN	2P
CB372-373	WN103000	CLIP. FUSE	TP00351-31
CB374	VG879900	CN. BS. PIN	2P
CB381	VQ963600	CN. BS. PIN	15P
CB382	VQ961400	CN. BS. PIN	11P
CB383	VQ963600	CN. BS. PIN	15P
CB384	VB389800	CN. BS. PIN	2P
CB391	VL844800	CN. BS. PIN	4P
C3001	US065100	C. CE. CHP	0. 1uF 50V B
C3002	US063100	C. CE. CHP	1000pF 50V B
C3003	UM397100	C. EL	10uF 16V
C3004	US064100	C. CE. CHP	0. 01uF 50V B
C3005	US163100	C. CE. CHP	1000pF 50V
C3006	WV360900	C. EL	22uF 16V
C3007	US062100	C. CE. CHP	100pF 50V B
C3008	UM397470	C. EL	47uF 16V
C3009	US061330	C. CE. CHP	33pF 50V B
C3012-3013	WV360900	C. EL	22uF 16V
C3014	UM397100	C. EL	10uF 16V
C3015-3016	US035100	C. CE. CHP	0. 1uF 16V B
C3017	US163100	C. CE. CHP	1000pF 50V
C3019	UR268220	C. EL	220uF 50V
C3020	UM388330	C. EL	330uF 6. 3V
C3021	US035100	C. CE. CHP	0. 1uF 16V B
C3022	US061680	C. CE. CHP	68pF 50V B
C3023	US065100	C. CE. CHP	0. 1uF 50V B
C3024	US064100	C. CE. CHP	0. 01uF 50V B
C3025	US065100	C. CE. CHP	0. 1uF 50V B
C3027	UM417100	C. EL	10uF 50V
C3028	US064100	C. CE. CHP	0. 01uF 50V B
C3029	US035100	C. CE. CHP	0. 1uF 16V B
C3030	US062220	C. CE. CHP	220pF 50V B
C3031-3032	US063100	C. CE. CHP	1000pF 50V B
C3034	WH773700	C. EL	470uF 16V
C3035	WY034800	C. CE. CHP	0. 022uF 50V
C3036	US063100	C. CE. CHP	1000pF 50V B
C3037	US046100	C. CE. CHP	1uF 25V
C3038	US063100	C. CE. CHP	1000pF 50V B

* New Parts

Ref No.	Part No.	Description	Markets
C3039	US062100	C. CE. CHP	100pF 50V B
C3040	US035100	C. CE. CHP	0. 1uF 16V B
C3043	US062100	C. CE. CHP	100pF 50V B
C3044	WM490200	C. CE. M. CHP	0. 47uF 50V
C3045	WG251600	C. CE. CHP	4. 7uF 6. 3V
C3046-3047	US035100	C. CE. CHP	0. 1uF 16V B
C3048	UM416100	C. EL	1uF 50V
C3049	UM416220	C. EL	2. 2uF 50V
C3050	US035100	C. CE. CHP	0. 1uF 16V B
C3051-3052	US163100	C. CE. CHP	1000pF 50V
C3053-3054	WJ609500	C. MYLAR	3300pF 100V
C3055	US064100	C. CE. CHP	0. 01uF 50V B
C3056	US063100	C. CE. CHP	1000pF 50V B
C3057	US035100	C. CE. CHP	0. 1uF 16V B
C3058	WD758300	C. CE. CHP	10uF 10V
C3059	US062100	C. CE. CHP	100pF 50V B
C3060	US063100	C. CE. CHP	1000pF 50V B
C3061-3062	US061470	C. CE. CHP	47pF 50V B
C3401-3402	US062100	C. CE. CHP	100pF 50V B
C3403-3405	US060800	C. CE. CHP	8pF 50V B
C3406-3411	WD758300	C. CE. CHP	10uF 10V
C3412-3413	UR237100	C. EL	10uF 16V
C3414	UR837220	C. EL	22uF 16V
C3415	UR237100	C. EL	10uF 16V
C3416-3420	US135100	C. CE. CHP	0. 1uF 16V
C3421-3422	WG251600	C. CE. CHP	4. 7uF 6. 3V
C3424-3438	US135100	C. CE. CHP	0. 1uF 16V
C3439-3440	UR238100	C. EL	100uF 16V
C3441-3443	US135100	C. CE. CHP	0. 1uF 16V
C3444-3445	WH773500	C. EL	330uF 16V
C3446	WH771300	C. EL	100uF 10V
C3448	US062100	C. CE. CHP	100pF 50V B
C3450	US062100	C. CE. CHP	100pF 50V B
C3451-3452	US064100	C. CE. CHP	0. 01uF 50V B
C3454-3455	WH773300	C. EL	120uF 16V
C3456	WH773500	C. EL	330uF 16V
C3457	WH773300	C. EL	120uF 16V
C3458	US135100	C. CE. CHP	0. 1uF 16V
C3459-3460	UR238100	C. EL	100uF 16V
C3461-3466	WD758300	C. CE. CHP	10uF 10V
C3467	UR237470	C. EL	47uF 16V
C3601-3602	UR237100	C. EL	10uF 16V
△ C3701	WJ361200	C. POL. MTL	0. 047uF 400V UC
△ C3701	WJ361800	C. POL. MTL	0. 022uF 630V RTABGFLSH
△ C3702-3703	WQ902300	C. CE. SAFTY	1000pF 250V UCRABGFLSH
△ C3704	V5877700	C. MYLAR	0. 22uF 250V
△ C3705	US163100	C. CE. CHP	1000pF 50V
C3706	ZE600100	C. EL	270uF 220V UC
C3706	ZE600200	C. EL	220uF 400V RS
C3706	WW751700	C. EL	100uF 400V TABGFLH
△ C3707	WQ939400	C. CE. SAFTY	0. 01uF 250V
△ C3708	UR867470	C. EL	47uF 50V
△ C3709	WJ322400	C. CE. M. CHP	0. 01uF 250V
△ C3710	US063100	C. CE. CHP	1000pF 50V B
△ C3711	WY685500	C. CE. SAFTY	3300pF 250V UC
△ C3711	WQ902200	C. CE. SAFTY	2200pF 250V RABGFLSH
△ C3711	WY896500	C. CE. SAFTY	1500pF 250V T

* New Parts

RX-V675/HTR-6066/TSR-6750

OPERATION

	Ref No.	Part No.	Description	Markets		Ref No.	Part No.	Description	Markets
△	C3712	WJ361200	C. POL. MTL	0. 047uF 400V	UC	IC342	YF016A00	IC	RP170H331B-T1-FE
△	C3712	WJ361800	C. POL. MTL	0. 022uF 630V	RTABGFLSH	IC343-344	YF077A00	IC	BD00GA3WEFJ-E2
	C3713	WJ322300	C. CE. M. CHP	1000pF 630V		IC345	YE018A00	IC	NJM41033V
	C3714-3715	ZF616900	C. EL	3300uF 16V		IC346	YF013A00	IC	BD7541G-TR OPAMP
	C3716	US034470	C. CE. CHP	0. 047uF 16V B		△ IC372	WP388200	PHOT. CPL	TLP781 (D4-GR, F)
	C3718	WH771600	C. EL	220uF 10V		△ IC373	YA276A00	IC	TL431AC 2. 5-36V
	C3719	US064100	C. CE. CHP	0. 01uF 50V B		△ IC374	WP388200	PHOT. CPL	TLP781 (D4-GR, F)
	C3720	V7887800	C. EL	1uF 50V		△ IC375	YE895A00	IC	STR-Y6753
	C3721	WJ335500	C. EL	2. 2uF 50V		IC381	XZ509A00	IC	TC74VHC04FT INVER
	C3722	ZE673300	C. CE. CHP	470pF 1000V		IC382	YF016A00	IC	RP170H331B-T1-FE
	C3723	US064100	C. CE. CHP	0. 01uF 50V B		JK301	WJ117300	JACK. MNI	MSJ-2200C AG
△	C3724	WJ322300	C. CE. M. CHP	1000pF 630V		JK302	WZ975700	JACK. PHONE	MSJ-064-05B-B-RF
△	C3727	ZG415000	C. CE. M. CHP	4. 7uF 10V		JK381-383	V9435700	JACK. MINI	MSJ-035-12APC
	C3802	US064100	C. CE. CHP	0. 01uF 50V B		PJ301	WZ631700	JACK. PIN	1P MTJ-032-21B-NI
	C3803	US035100	C. CE. CHP	0. 1uF 16V B		PJ341	WG583200	JACK. PIN	6P RJ-1146+08-0H00
	C3804-3805	US061220	C. CE. CHP	22pF 50V B		PJ342	WH381400	JACK. PIN	3P JACK G, B, R
	C3806	US035100	C. CE. CHP	0. 1uF 16V B		PJ343-344	V7190000	JACK. PIN	2P
	C3807-3808	US063100	C. CE. CHP	1000pF 50V B		PJ361	V7190000	JACK. PIN	2P
	C3809-3811	US035100	C. CE. CHP	0. 1uF 16V B		PJ381	V9420700	JACK. PIN	2P MSP-252V1-30NI
	C3812	UR238100	C. EL	100uF 16V		Q3001-3004	WC529400	TR	KTC3875S Y GR RTK
	C3814	US035100	C. CE. CHP	0. 1uF 16V B		Q3005	WW782100	TR. DGT	DTC014EUBTL
	C3817	UU238470	C. EL	470uF 16V		Q3010	WW782100	TR. DGT	DTC014EUBTL
	C3818-3819	WD758300	C. CE. CHP	10uF 10V		Q3011	WQ381000	FET	MCH6336-TL-E
	C3820	UR367470	C. EL	47uF 50V		△ Q3012-3013	WW223000	TR	2SC5964-TD-E
	C3901-3904	WJ610200	C. MYLAR	0. 01uF 100V		Q3014	WW782100	TR. DGT	DTC014EUBTL
	D3001-3002	WW783900	DIODE	1SS355VM		△ Q3015	WC397700	TR	2N5401C-AT
	D3003	WY163200	DIODE. ZENR	UDZV5. 1B		Q3401-3402	WW782100	TR. DGT	DTC014EUBTL
	D3004	WR095700	LED	8224-10SDRD/S530A3		Q3404-3405	WQ381000	FET	MCH6336-TL-E
	D3005	V2598200	LED	SIR-505ST		△ Q3407-3410	WW223000	TR	2SC5964-TD-E
	D3008-3009	WW783900	DIODE	1SS355VM		Q3413	WC397700	TR	2N5401C-AT
	D3010-3011	WY163000	DIODE. ZENR	UDZV4. 3B		Q3420	WE834500	FET	UPA672T-T1-A
	D3012	WW783900	DIODE	1SS355VM		Q3701-3702	VQ986700	TR	2SC4081 T106
	D3013	WP080300	LED. BLUE	Blue SLR343BC4T3F		Q3703	WW782300	TR. DGT	DTC044EUBTL
	D3014-3017	WW783900	DIODE	1SS355VM		Q3801	WC398400	TR	2N5551C-AT
	D3018	WY165200	DIODE. ZENR	UDZV36B		Q3802	ZA348800	TR	KTA1046-Y-U/PFY
	D3019-3020	WW783900	DIODE	1SS355VM		Q3803	WC398400	TR	2N5551C-AT
	D3022	WW783900	DIODE	1SS355VM		Q3804	WC397700	TR	2N5401C-AT
	D3024	WW783900	DIODE	1SS355VM		R3057-3058	WW969500	R. MTL. OXD	120Ω 1/4W
	D3403-3404	WW783900	DIODE	1SS355VM		R3077-3078	V8071400	R. MTL. FLM	560Ω 1W
	D3406-3409	ZF305000	DIODE. CHP	RB162L-40 TE25 TP		R3416	WW965300	R. MTL. OXD	2. 2Ω 1/4W
	D3412-3417	ZF305000	DIODE. CHP	RB162L-40 TE25 TP		R3444-3445	WW968500	R. MTL. OXD	47Ω 1/4W
	D3420-3421	ZF305000	DIODE. CHP	RB162L-40 TE25 TP		△ R3701-3702	WR033300	R. CHP	4. 7KΩ 1/4W
△	D3701	WW872000	DIODE. BRG	DBL155G 1. 5A 600		△ R3703	WU547900	R. ANTI. SURGE	3MΩ 1/2W
△	D3702	ZE932800	DIODE	US1002FL		△ R3704	ZE673100	R. CAR. CHP	0. 47Ω 1W
△	D3703	ZE932600	DIODE	UF1K		△ R3732-3734	ZE673900	R. CAR. CHP	12KΩ 1W
	D3704	ZF519800	D. SCHOTTKY	RBQ30T65A 30A 65V		△ R3736	ZE673900	R. CAR. CHP	12KΩ 1W
	D3705	ZA385400	DIODE. ZENR	TFZGTR24B 24V		△ R3737	VE995200	R. CAR. CHP	15Ω 1W
△	D3706-3715	WW783900	DIODE	1SS355VM		△ R3737	WH158700	R. CHP	10Ω 1W J
	D3716	WY727900	DIODE. ZENR	P6KE200A 200V		△ R3738	VE995200	R. CAR. CHP	15Ω 1W
	D3801-3802	WW783900	DIODE	1SS355VM		△ R3738	WH158700	R. CHP	10Ω 1W J
△	F3701	WR944000	FUSE	2A 250V		△ R3739	VE995200	R. CAR. CHP	15Ω 1W
△	F3702	WQ211100	FUSE	8A 125V	UCRS	△ R3739	WH158700	R. CHP	10Ω 1W J
	F3702	VV071800	FUSE	4A 250V	TABGFLH	R3816	WW966300	R. MTL. OXD	5. 6Ω 1/4W
△	IC301	X6386A00	IC	M66003-0131FP		R3819	WC860100	R. MTL. FLM	2. 2Ω 1W
△	IC302	YC288A00	IC	RP130Q331D-TR-F		R3820	V8070100	R. MTL. FLM	2. 2Ω 1W
	IC303	X7378A00	IC	NJM4565M (TE1)		R3901-3902	WW974100	R. MTL. OXD	10KΩ 1/4W
	IC341	YD948A00	IC	NJW1329FH2		△ RY371	WQ804100	RELAY	DC DLS5D1-0 (M) 0. 25

* New Parts

* New Parts

OPERATION

Ref No.	Part No.	Description	Markets
SW301-322	WD483100	SW. TACT	SKRGAAD010
SW323	V9597100	SW. RT. ENC	EC12E2460802
△ T3701	YE896A00	TRANS. PWR	
TE391	WB213900	TERM. SP	MSP-113V2-03 PUSH
△ TH371	WF544600	PTC. THERMISTOR	NTPAD5R1LDNBO 5. 1
U3001	WR153900	L. DTCT	RPM7238-H9R
U3801-3802	WH169900	CN. PHOTO. R	1P GP1FAV51RK0F
* V3001	ZG266300	FL. DSPLY	18-MT-11GNAK
	ZA889400	SPACER	4. 3x8x30
	WE774200	SCR. BND. HD	3x10 MFZN2W3

* New Parts

Ref No.	Part No.	Description	Markets
*	ZF543100	P. C. B.	OPERATION
*	ZF543200	P. C. B.	OPERATION
*	ZF543300	P. C. B.	OPERATION
*	ZF543400	P. C. B.	OPERATION
*	ZF543500	P. C. B.	OPERATION
CB302	VB858300	CN. BS. PIN	4P
CB304	VQ045400	CN. BS. PIN	25P
CB305	VQ044200	CN. BS. PIN	6P
CB310	WQ680200	CN. USB	4P TE AAPVA004C0
CB342	VQ046900	CN. BS. PIN	5P
CB343	VQ047000	CN. BS. PIN	6P
CB344	VP573800	CN. BS. PIN	18P
CB345	VQ961800	CN. BS. PIN	15P
CB346	VQ047200	CN. BS. PIN	9P
CB347	LB918020	CN. BS. PIN	2P
CB361	VQ044100	CN. BS. PIN	5P
CB372-373	WN103000	CLIP. FUSE	TP00351-31
CB374	VG879900	CN. BS. PIN	2P
CB381	VQ963600	CN. BS. PIN	15P
CB382	VQ961400	CN. BS. PIN	11P
CB383	VQ963600	CN. BS. PIN	15P
CB384	VB389800	CN. BS. PIN	2P
CB391	VL844800	CN. BS. PIN	4P
C3001	US065100	C. CE. CHP	0. 1uF 50V B
C3002-3003	US063100	C. CE. CHP	1000pF 50V B
C3004	WJ609500	C. MYLAR	3300pF 100V
C3005	UR267100	C. EL	10uF 50V
C3006	US064100	C. CE. CHP	0. 01uF 50V B
C3007	WJ609500	C. MYLAR	3300pF 100V
C3008	WV360900	C. EL	22uF 16V
C3009	US064100	C. CE. CHP	0. 01uF 50V B
C3010	US063100	C. CE. CHP	1000pF 50V B
C3012	US062100	C. CE. CHP	100pF 50V B
C3013	UM387470	C. EL	47uF 16V
C3014	WV360900	C. EL	22uF 16V
C3015	US061330	C. CE. CHP	33pF 50V B
C3017	WV360900	C. EL	22uF 16V
C3018	UM397100	C. EL	10uF 16V
C3019-3020	US035100	C. CE. CHP	0. 1uF 16V B
C3021-3022	US063100	C. CE. CHP	1000pF 50V B
C3024	UR268220	C. EL	220uF 50V
C3025	UM388330	C. EL	330uF 6. 3V
C3026	US035100	C. CE. CHP	0. 1uF 16V B
C3027	US061680	C. CE. CHP	68pF 50V B
C3028	US065100	C. CE. CHP	0. 1uF 50V B
C3029	US064100	C. CE. CHP	0. 01uF 50V B
C3030-3031	US163100	C. CE. CHP	1000pF 50V
C3032	US065100	C. CE. CHP	0. 1uF 50V B
C3033-3036	US035100	C. CE. CHP	0. 1uF 16V B
C3038	US046100	C. CE. CHP	1uF 25V
C3039	US035100	C. CE. CHP	0. 1uF 16V B
C3040	US062100	C. CE. CHP	100pF 50V B
C3042	US062100	C. CE. CHP	100pF 50V B
C3043	WG251600	C. CE. CHP	4. 7uF 6. 3V
C3044-3045	US035100	C. CE. CHP	0. 1uF 16V B
C3046	UM388100	C. EL	100uF 6. 3V
C3047-3048	US163100	C. CE. CHP	1000pF 50V

* New Parts

RX-A730

OPERATION

Ref No.	Part No.	Description	Markets	Ref No.	Part No.	Description	Markets
C3049-3050	US035100	C. CE. CHP	0. 1uF 16V B	C3713	WJ322300	C. CE. M. CHP	1000pF 630V
C3051	US063100	C. CE. CHP	1000pF 50V B	C3714-3715	ZF616900	C. EL	3300uF 16V
C3052	US062220	C. CE. CHP	220pF 50V B	C3716	US034470	C. CE. CHP	0. 047uF 16V B
C3053	US063100	C. CE. CHP	1000pF 50V B	C3718	WH771600	C. EL	220uF 10V
C3054	WH773700	C. EL	470uF 16V	C3719	US064100	C. CE. CHP	0. 01uF 50V B
C3055	US063100	C. CE. CHP	1000pF 50V B	C3720	V7887800	C. EL	1uF 50V
C3056	US061470	C. CE. CHP	47pF 50V B	C3721	WJ335500	C. EL	2. 2uF 50V
C3057	US063100	C. CE. CHP	1000pF 50V B	C3722	ZE673300	C. CE. CHP	470pF 1000V
C3058	WY034800	C. CE. CHP	0. 022uF 50V	C3723	US064100	C. CE. CHP	0. 01uF 50V B
C3059	US061470	C. CE. CHP	47pF 50V B	△ C3724	WJ322300	C. CE. M. CHP	1000pF 630V
C3060	WD758300	C. CE. CHP	10uF 10V	△ C3727	ZG415000	C. CE. M. CHP	4. 7uF 10V
C3061	US035100	C. CE. CHP	0. 1uF 16V B	C3802	US064100	C. CE. CHP	0. 01uF 50V B
C3062	US062100	C. CE. CHP	100pF 50V B	C3803	US035100	C. CE. CHP	0. 1uF 16V B
C3063	US063100	C. CE. CHP	1000pF 50V B	C3804-3805	US061220	C. CE. CHP	22pF 50V B
C3064	WM490200	C. CE. M. CHP	0. 47uF 50V	C3806	US035100	C. CE. CHP	0. 1uF 16V B
C3065	US135100	C. CE. CHP	0. 1uF 16V	C3807-3808	US063100	C. CE. CHP	1000pF 50V B
C3066	UM416100	C. EL	1uF 50V	C3809-3811	US035100	C. CE. CHP	0. 1uF 16V B
C3067	UM416220	C. EL	2. 2uF 50V	C3812	UR238100	C. EL	100uF 16V
C3401-3402	US062100	C. CE. CHP	100pF 50V B	C3814	US035100	C. CE. CHP	0. 1uF 16V B
C3403-3405	US060800	C. CE. CHP	8pF 50V B	C3817	UU238470	C. EL	470uF 16V
C3406-3411	WD758300	C. CE. CHP	10uF 10V	C3818-3819	WD758300	C. CE. CHP	10uF 10V
C3412-3413	UR237100	C. EL	10uF 16V	C3820	UR367470	C. EL	47uF 50V
C3414	UR837220	C. EL	22uF 16V	C3901-3904	WJ610200	C. MYLAR	0. 01uF 100V
C3415	UR237100	C. EL	10uF 16V	D3001-3004	WW783900	DIODE	1SS355VM
C3416-3420	US135100	C. CE. CHP	0. 1uF 16V	D3006	WY163200	DIODE. ZENR	UDZV5. 1B
C3421-3422	WG251600	C. CE. CHP	4. 7uF 6. 3V	D3009-3010	WY163000	DIODE. ZENR	UDZV4. 3B
C3424-3438	US135100	C. CE. CHP	0. 1uF 16V	D3011	V2598200	LED	SIR-505ST
C3439-3440	UR238100	C. EL	100uF 16V	D3012	WP080300	LED. BLUE	Blue SLR343BC4T3F
C3441-3443	US135100	C. CE. CHP	0. 1uF 16V	D3015	WW783900	DIODE	1SS355VM
C3444-3445	WH773500	C. EL	330uF 16V	D3016	WR095700	LED	8224-10SDRD/S530A3
C3446	WH771300	C. EL	100uF 10V	D3019-3024	WW783900	DIODE	1SS355VM
C3448	US062100	C. CE. CHP	100pF 50V B	D3025	WY165200	DIODE. ZENR	UDZV36B
C3450	US062100	C. CE. CHP	100pF 50V B	D3403-3404	WW783900	DIODE	1SS355VM
C3451-3452	US064100	C. CE. CHP	0. 01uF 50V B	D3406-3409	ZF305000	DIODE. CHP	RB162L-40 TE25 TP
C3454-3455	WH773300	C. EL	120uF 16V	D3412-3417	ZF305000	DIODE. CHP	RB162L-40 TE25 TP
C3456	WH773500	C. EL	330uF 16V	D3420-3421	ZF305000	DIODE. CHP	RB162L-40 TE25 TP
C3457	WH773300	C. EL	120uF 16V	△ D3701	WW872000	DIODE. BRG	DBL155G 1. 5A 600
C3458	US135100	C. CE. CHP	0. 1uF 16V	△ D3702	ZE932800	DIODE	US1002FL
C3459-3460	UR238100	C. EL	100uF 16V	△ D3703	ZE932600	DIODE	UF1K
C3461-3466	WD758300	C. CE. CHP	10uF 10V	D3704	ZF519800	D. SCHOTTKY	RBQ30T65A 30A 65V
C3467	UR237470	C. EL	47uF 16V	△ D3705	ZA385400	DIODE. ZENR	TFZGTR24B 24V
C3601-3602	UR237100	C. EL	10uF 16V	△ D3706-3715	WW783900	DIODE	1SS355VM
△ C3701	WJ361200	C. POL. MTL	0. 047uF 400V	△ D3716	WY727900	DIODE. ZENR	P6KE200A 200V
△ C3701	WJ361800	C. POL. MTL	0. 022uF 630V	D3801-3802	WW783900	DIODE	1SS355VM
△ C3702-3703	WQ902300	C. CE. SAFTY	1000pF 250V	△ F3701	WR944000	FUSE	2A 250V
△ C3704	V5877700	C. MYLAR	0. 22uF 250V	△ F3702	WQ211100	FUSE	8A 125V
△ C3705	US163100	C. CE. CHP	1000pF 50V	F3702	VV071800	FUSE	4A 250V
C3706	ZE600100	C. EL	270uF 220V	△ IC301	X6386A00	IC	M66003-0131FP
C3706	WW751700	C. EL	100uF 400V	△ IC302	YC288A00	IC	RP130Q331D-TR-F
△ C3707	WQ939400	C. CE. SAFTY	0. 01uF 250V	IC303	X7378A00	IC	NJM4565M (TE1)
△ C3708	UR867470	C. EL	47uF 50V	IC341	YD948A00	IC	NJW1329FH2
△ C3709	WJ322400	C. CE. M. CHP	0. 01uF 250V	IC342	YF016A00	IC	RP170H331B-T1-FE
△ C3710	US063100	C. CE. CHP	1000pF 50V B	IC343-344	YF077A00	IC	BD00GA3WEFJ-E2
△ C3711	WY685500	C. CE. SAFTY	3300pF 250V	IC345	YE018A00	IC	NJM41033V
△ C3711	WQ902200	C. CE. SAFTY	2200pF 250V	IC346	YF013A00	IC	BD7541G-TR OPAMP
△ C3712	WJ361200	C. POL. MTL	0. 047uF 400V	△ IC372	WP388200	PHOT. CPL	TLP781 (D4-GR, F)
△ C3712	WJ361800	C. POL. MTL	0. 022uF 630V	△ IC373	YA276A00	IC	TL431AC 2. 5-36V

* New Parts

* New Parts

OPERATION

	Ref No.	Part No.	Description	Markets
△	IC374	WP388200	PHOT. CPL	TLP781 (D4-GR, F)
△	IC375	YE895A00	IC	STR-Y6753
	IC381	XZ509A00	IC	TC74VHC04FT INVER
	IC382	YF016A00	IC	RP170H331B-T1-FE
	JK301	WC814400	JACK. MNI	JY-3554-01-130
	JK302	WZ975700	JACK. PHONE	MSJ-064-05B-B-RF
	JK381-383	V9435700	JACK. MINI	MSJ-035-12APC
	PJ301	WZ631700	JACK. PIN	1P MTJ-032-21B-NI
	PJ341	WG583200	JACK. PIN	6P RJ-1146+08-0H00
	PJ342	WH381400	JACK. PIN	3P JACK G, B, R
	PJ343-344	V7190000	JACK. PIN	2P
	PJ361	V7190000	JACK. PIN	2P
	PJ381	V9420700	JACK. PIN	2P MSP-252V1-30NI
	Q3001-3004	WC529400	TR	KTC3875S Y GR RTK
	Q3009-3010	WW782100	TR. DGT	DTC014EUBTL
	Q3011	WQ381000	FET	MCH6336-TL-E
△	Q3012-3013	WW223000	TR	2SC5964-TD-E
	Q3014	WW782100	TR. DGT	DTC014EUBTL
△	Q3015	WC397700	TR	2N5401C-AT
	Q3401-3402	WW782100	TR. DGT	DTC014EUBTL
	Q3404-3405	WQ381000	FET	MCH6336-TL-E
△	Q3407-3410	WW223000	TR	2SC5964-TD-E
	Q3413	WC397700	TR	2N5401C-AT
	Q3420	WE834500	FET	UPA672T-T1-A
	Q3701-3702	VQ986700	TR	2SC4081 T106
	Q3703	WW782300	TR. DGT	DTC044EUBTL
	Q3801	WC398400	TR	2N5551C-AT
	Q3802	ZA348800	TR	KTA1046-Y-U/PFY
	Q3803	WC398400	TR	2N5551C-AT
	Q3804	WC397700	TR	2N5401C-AT
	R3013-3014	V8071400	R. MTL. FLM	560 Ω 1W
	R3416	WW965300	R. MTL. OXD	2. 2 Ω 1/4W
	R3444-3445	WW968500	R. MTL. OXD	47 Ω 1/4W
△	R3701-3702	WR033300	R. CHP	4. 7K Ω 1/4W
△	R3703	WU547900	R. ANTI. SURGE	3M Ω 1/2W
△	R3704	ZE673100	R. CAR. CHP	0. 47 Ω 1W
△	R3732-3734	ZE673900	R. CAR. CHP	12K Ω 1W
△	R3736	ZE673900	R. CAR. CHP	12K Ω 1W
△	R3737-3739	VE995200	R. CAR. CHP	15 Ω 1W
	R3816	WW966300	R. MTL. OXD	5. 6 Ω 1/4W
	R3819	WC860100	R. MTL. FLM	2. 2 Ω 1W
	R3820	V8070100	R. MTL. FLM	2. 2 Ω 1W
	R3901-3902	WW974100	R. MTL. OXD	10K Ω 1/4W
△	RY371	WQ804100	RELAY	DC DLS5D1-O (M) 0. 25
	SW301	WD483100	SW. TACT	SKRGAAD010
	SW303	WD483100	SW. TACT	SKRGAAD010
	SW305	WD483100	SW. TACT	SKRGAAD010
	SW307	WD483100	SW. TACT	SKRGAAD010
	SW309	WD483100	SW. TACT	SKRGAAD010
	SW312-313	WD483100	SW. TACT	SKRGAAD010
	SW316-317	WD483100	SW. TACT	SKRGAAD010
	SW319	WD483100	SW. TACT	SKRGAAD010
	SW321	WD483100	SW. TACT	SKRGAAD010
	SW324-325	WD483100	SW. TACT	SKRGAAD010
	SW328-329	WD483100	SW. TACT	SKRGAAD010
	SW332-333	WD483100	SW. TACT	SKRGAAD010
	SW336-337	WD483100	SW. TACT	SKRGAAD010

* New Parts

	Ref No.	Part No.	Description	Markets
	SW339	V9597100	SW. RT. ENC	EC12E2460802
	SW340	WD483100	SW. TACT	SKRGAAD010
	SW342	WQ291600	SW. RT. ENC	XREB12105PVB25FINA
△	T3701	YE896A00	TRANS. PWR	
	TE371	ZD538700	INLET. AC	2P R-30190 (26) CCC
	TE391	WW726500	TERM. SP	4P
	TE391	WW728900	TERM. SP	4P UCA
	TE391	WW726500	TERM. SP	4P BGL
△	TH371	WF544600	PTC. THERMISTOR	NTPAD5R1LDNB0 5. 1
	U3001	WR153900	L. DTCT	RPM7238-H9R
	U3801-3802	WH169900	CN. PHOTO. R	1P GP1FAV51RK0F
*	V3001	ZG266300	FL. DSPLY	18-MT-11GNAK
		ZA889400	SPACER	4. 3x8x30
		WE774200	SCR. BND. HD	3x10 MFZN2W3

* New Parts

RX-V675/HTR-6066/TSR-6750

RX-A730

MAIN

Ref No.	Part No.	Description	Markets
* ZF534700	P. C. B.	MAIN	UC
* ZF534800	P. C. B.	MAIN	RS
* ZF534900	P. C. B.	MAIN	TA
* ZF535000	P. C. B.	MAIN	B
* ZF535100	P. C. B.	MAIN	GFLH
CB101	LB932060	CN. BS. PIN	6P
CB102	LB918020	CN. BS. PIN	2P
CB103	LB918030	CN. BS. PIN	3P
CB111	V9377900	CN. BS. PIN	4P
CB112-113	WN077700	CLIP. FUSE	CLIP PFC5000-0202F
CB153	VQ963200	CN. BS. PIN	11P
C1001	UR257100	C. EL	10uF 35V UCRTAS
C1001	UR067100	C. EL	10uF 50V B
C1001	ZD241900	C. EL	10uF 50V GFLH
C1002	UR257100	C. EL	10uF 35V UCRTAS
C1002	UR067100	C. EL	10uF 50V B
C1002	ZD241900	C. EL	10uF 50V GFLH
C1003	UR257100	C. EL	10uF 35V UCRTAS
C1003	UR067100	C. EL	10uF 50V B
C1003	ZD241900	C. EL	10uF 50V GFLH
C1004	UR257100	C. EL	10uF 35V UCRTAS
C1004	UR267100	C. EL	10uF 50V BGFLH
C1005	UR257100	C. EL	10uF 35V UCRTAS
C1005	UR267100	C. EL	10uF 50V BGFLH
C1006	UR257100	C. EL	10uF 35V UCRTAS
C1006	UR267100	C. EL	10uF 50V BGFLH
C1007	UR257100	C. EL	10uF 35V UCRTAS
C1007	UR267100	C. EL	10uF 50V BGFLH
C1008	WN164200	C. PP	220pF 100V UCRTAS
C1008	WE100900	C. PP	220pF 630V K BGFLH
C1009	WN164200	C. PP	220pF 100V UCRTAS
C1009	WE100900	C. PP	220pF 630V K BGFLH
C1010	WN164200	C. PP	220pF 100V UCRTAS
C1010	WE100900	C. PP	220pF 630V K BGFLH
C1011	WN164200	C. PP	220pF 100V UCRTAS
C1011	WJ608300	C. MYLAR	220pF 100V BGFLH
C1012	WN164200	C. PP	220pF 100V UCRTAS
C1012	WJ608300	C. MYLAR	220pF 100V BGFLH
C1013	WN164200	C. PP	220pF 100V UCRTAS
C1013	WJ608300	C. MYLAR	220pF 100V BGFLH
C1014	WN164200	C. PP	220pF 100V UCRTAS
C1014	WJ608300	C. MYLAR	220pF 100V BGFLH
C1015	WQ107500	C. PP	120pF 100V UCRTAS
C1015	WE100600	C. PP	120pF 630V K BGFLH
C1016	WQ107500	C. PP	120pF 100V UCRTAS
C1016	WE100600	C. PP	120pF 630V K BGFLH
C1017	WQ107500	C. PP	120pF 100V UCRTAS
C1017	WE100600	C. PP	120pF 630V K BGFLH
C1018	WQ107500	C. PP	120pF 100V UCRTAS
C1018	WW179700	C. MYLAR	120pF 100V BGFLH
C1019	WQ107500	C. PP	120pF 100V UCRTAS
C1019	WW179700	C. MYLAR	120pF 100V BGFLH
C1020	WQ107500	C. PP	120pF 100V UCRTAS
C1020	WW179700	C. MYLAR	120pF 100V BGFLH
C1021	WQ107500	C. PP	120pF 100V UCRTAS
C1021	WW179700	C. MYLAR	120pF 100V BGFLH
C1022	WN164900	C. PP	3300pF 100V UCRTAS
C1022	WJ609500	C. MYLAR	3300pF 100V BGFLH
C1023	WN164900	C. PP	3300pF 100V UCRTAS
C1023	WJ609500	C. MYLAR	3300pF 100V BGFLH
C1024	WN164900	C. PP	3300pF 100V UCRTAS
C1024	WJ609500	C. MYLAR	3300pF 100V BGFLH
C1025	WN164900	C. PP	3300pF 100V UCRTAS
C1025	WJ609500	C. MYLAR	3300pF 100V BGFLH
C1026	WN164900	C. PP	3300pF 100V UCRTAS
C1026	WJ609500	C. MYLAR	3300pF 100V BGFLH
C1027	WN164900	C. PP	3300pF 100V UCRTAS
C1027	WJ609500	C. MYLAR	3300pF 100V BGFLH
C1028	WN164900	C. PP	3300pF 100V UCRTAS
C1028	WJ609500	C. MYLAR	3300pF 100V BGFLH
C1029	UR067470	C. EL	47uF 50V UCRTABS
C1029	UR267470	C. EL	47uF 50V GFLH
C1030	UR068100	C. EL	100uF 50V UCRTABS
C1030	UR268100	C. EL	100uF 50V GFLH
C1031	UR068100	C. EL	100uF 50V UCRTABS
C1031	UR268100	C. EL	100uF 50V GFLH
C1032-1035	UR067470	C. EL	47uF 50V
C1036	WQ627600	C. CE	22pF 500V UCRTAS
C1036	WE100200	C. PP	22pF 630V K BGFLH
C1037	WQ627600	C. CE	22pF 500V UCRTAS
C1037	WE100200	C. PP	22pF 630V K BGFLH
C1038	WQ627600	C. CE	22pF 500V UCRTAS
C1038	WE100200	C. PP	22pF 630V K BGFLH
C1039-1042	WQ627600	C. CE	22pF 500V
C1043-1049	WJ608400	C. MYLAR	330pF 100V
C1050	UR067100	C. EL	10uF 50V
C1050	UR067100	C. EL	10uF 50V UCRTAS
C1050	ZD241900	C. EL	10uF 50V B
C1050	UR397100	C. EL	10uF 100V GFLH
C1051	UR067100	C. EL	10uF 50V UCRTAS
C1051	ZD241900	C. EL	10uF 50V B
C1051	UR397100	C. EL	10uF 100V GFLH
C1052	UR067100	C. EL	10uF 50V UCRTAS
C1052	ZD241900	C. EL	10uF 50V B
C1052	UR397100	C. EL	10uF 100V GFLH
C1053	UR067100	C. EL	10uF 50V UCRTAS
C1053	ZD241900	C. EL	10uF 50V B
C1053	UU267100	C. EL	10uF 50V GFLH
C1054	UR067100	C. EL	10uF 50V UCRTAS
C1054	ZD241900	C. EL	10uF 50V B
C1054	UU267100	C. EL	10uF 50V GFLH
C1055	UR067100	C. EL	10uF 50V UCRTAS
C1055	ZD241900	C. EL	10uF 50V B
C1055	UU267100	C. EL	10uF 50V GFLH
C1056	UR067100	C. EL	10uF 50V UCRTAS
C1056	ZD241900	C. EL	10uF 50V B
C1056	UU267100	C. EL	10uF 50V GFLH
C1057-1063	WJ610600	C. MYLAR	0.022uF 100V
C1066-1067	WN156000	C. PP	1000pF 250V
C1068	UR866470	C. EL	4.7uF 50V
C1069	UR818330	C. EL	330uF 6.3V
C1070-1073	UR297100	C. EL	10uF 100V
C1074	UR267330	C. EL	33uF 50V
C1075	ZD295900	C. EL	10uF 16V UCRTAS

* New Parts

* New Parts

MAIN

Ref No.	Part No.	Description	Markets
* C1075	ZD242000	C. EL	47uF 50V B
C1075	UR367470	C. EL	47uF 50V GFLH
C1078-1079	WJ611400	C. MYLAR	0. 1uF 100V J
△ C1084-1085	WN331300	C. EL	6800uF 71V
C1101-1102	WJ610400	C. MYLAR	0. 015uF 100V
C1103-1104	WJ610200	C. MYLAR	0. 01uF 100V
C1105-1107	WJ610400	C. MYLAR	0. 015uF 100V
C1108-1110	WJ610200	C. MYLAR	0. 01uF 100V
C1111-1112	WJ610400	C. MYLAR	0. 015uF 100V
C1113-1114	WJ610200	C. MYLAR	0. 01uF 100V
C1116	WN165500	C. PP	0. 022uF 100V UCRTAS
C1116	WJ610600	C. MYLAR	0. 022uF 100V BGFLH
C1117	WN165500	C. PP	0. 022uF 100V UCRTAS
C1117	WJ610600	C. MYLAR	0. 022uF 100V BGFLH
C1117	WN165500	C. PP	0. 022uF 100V
C1118	URO49220	C. EL	2200uF 25V
C1119	URO49100	C. EL	1000uF 25V
C1120	US135100	C. CE. CHP	0. 1uF 16V
C1121	URO67470	C. EL	47uF 50V
C1122	UR247100	C. EL	10uF 25V UCRTAS
C1122	UR267100	C. EL	10uF 50V BGFLH
C1123	UR247100	C. EL	10uF 25V UCRTAS
C1123	UR267100	C. EL	10uF 50V BGFLH
C1517-1520	US062220	C. CE. CHP	220pF 50V B
C1523	UR238100	C. EL	100uF 16V UCRTAGFLSH
C1523	URO38100	C. EL	100uF 16V B
C1526	UR238100	C. EL	100uF 16V UCRTAGFLSH
C1526	URO38100	C. EL	100uF 16V B
C1527	UR238100	C. EL	100uF 16V UCRTAGFLSH
C1527	URO38100	C. EL	100uF 16V B
C1528-1529	US062220	C. CE. CHP	220pF 50V B
C1530	UR238100	C. EL	100uF 16V UCRTAGFLSH
C1530	URO38100	C. EL	100uF 16V B
C1531	UR267330	C. EL	33uF 50V
C1532	UR238100	C. EL	100uF 16V UCRTAGFLSH
C1532	URO38100	C. EL	100uF 16V B
C1533	UR238100	C. EL	100uF 16V UCRTAGFLSH
C1533	URO38100	C. EL	100uF 16V B
C1534-1535	US062220	C. CE. CHP	220pF 50V B
C1536	UR238100	C. EL	100uF 16V UCRTAGFLSH
C1536	URO38100	C. EL	100uF 16V B
C1542	US035100	C. CE. CHP	0. 1uF 16V B
C1545	US035100	C. CE. CHP	0. 1uF 16V B
C1547	UR267100	C. EL	10uF 50V
C1549	UR267100	C. EL	10uF 50V
C1553-1554	UR267220	C. EL	22uF 50V
C1556	UR267100	C. EL	10uF 50V
C1571	UR267100	C. EL	10uF 50V
C1572	US062100	C. CE. CHP	100pF 50V B
C1574	UM397100	C. EL	10uF 16V
C1575	US061470	C. CE. CHP	47pF 50V B
C1576	UR267100	C. EL	10uF 50V
C1578	US061470	C. CE. CHP	47pF 50V B
C1579	UM397100	C. EL	10uF 16V
C1580	UR837100	C. EL	10uF 16V
C1581-1582	US061470	C. CE. CHP	47pF 50V B
C1583-1584	UR267470	C. EL	47uF 50V

* New Parts

Ref No.	Part No.	Description	Markets
C1585	UR837100	C. EL	10uF 16V
C1589-1590	UR267100	C. EL	10uF 50V
C1600-1601	UR267100	C. EL	10uF 50V
C1605	US064100	C. CE. CHP	0. 01uF 50V B
C1608	US044220	C. CE. CHP	0. 022uF 25V B
C1612	US064100	C. CE. CHP	0. 01uF 50V B
C1614	UR267470	C. EL	47uF 50V UCRTAS
C1614	UR067470	C. EL	47uF 50V B
* C1614	ZD242000	C. EL	47uF 50V GFLH
C1615	UR267470	C. EL	47uF 50V UCRTAS
C1615	UR067470	C. EL	47uF 50V B
* C1615	ZD242000	C. EL	47uF 50V GFLH
△ D1001-1016	WW783900	DIODE	1SS355VM
△ D1017-1023	WY163200	DIODE. ZENR	UDZV5. 1B
△ D1024-1039	WW783900	DIODE	1SS355VM
△ D1040	WB212700	DIODE. BRG	RS603M 6A 200V
△ D1042	ZA384800	DIODE. ZENR	TFZGTR13B
D1043	WY164800	DIODE. ZENR	UDZV24B RS
D1044-1050	WW783900	DIODE	1SS355VM
D1051	WB121700	DIODE. BRG	RS103 1.0A 200V
△ D1501-1502	ZA384200	DIODE. ZENR	TFZGTR6. 8B 6. 8V TP
△ F101	VV071800	FUSE	4A 250V RS
G101	V5995800	PLATE. GND	
IC101	YA381A00	IC	LM19C1Z/LF THERMAL
IC102	YA381A00	IC	LM19C1Z/LF THERMAL UC
△ IC103	XJ608A00	IC	NJM7812FA
△ IC104	X4154A00	IC	KIA7912PI
IC153	YA361B00	IC	R2A15220FP
IC154	X7378A00	IC	NJM4565M (TE1)
PJ151-152	V7046800	JACK. PIN	6P MSP-246V1-01NI
PJ155	V9392100	JACK. PIN	MSP-242V1-02N1FELF
Q1001-1014	WF549900	TR	2SC3906K T146 R, S
Q1015-1021	V3966800	TR	2SA949 O, Y
△ Q1022-1028	ZD495300	TR	2SC4115S S
△ Q1029-1035	VR325600	TR	2SC2229 O, Y
△ Q1036-1042	V4096100	TR	2SC4614 S, T
△ Q1043-1049	V4096000	TR	2SA1770 S, T
△ Q1050-1056	VR355900	TR. PAIR	A1695/C4468 OPY (1X630850, 1X630860)
Q1057-1063	ZF457100	TR	INC6002AC1-T112-1W
Q1064	ZF457000	TR	INA6002AC1-TH12-1W
Q1065	WF549900	TR	2SC3906K T146 R, S
△ Q1067-1068	WC292600	TR	KTA1837-U
△ Q1069-1070	WC398400	TR	2N5551C-AT
△ Q1071	WC397700	TR	2N5401C-AT
△ Q1072	VP872600	TR	2SA1708 S, T
Q1073	WC883400	TR	2SD2704 K
Q1074	WW782200	TR. DGT	DTC023JUBTL
Q1075	WC883400	TR	2SD2704 K
Q1076-1077	WW782200	TR. DGT	DTC023JUBTL
Q1078-1079	WC883400	TR	2SD2704 K
Q1501-1502	WC883400	TR	2SD2704 K
Q1504	WC883400	TR	2SD2704 K
Q1507	WC883400	TR	2SD2704 K
Q1509	WC883400	TR	2SD2704 K
Q1511-1514	WC883400	TR	2SD2704 K
Q1520-1521	WC883400	TR	2SD2704 K
Q1524-1525	WC883400	TR	2SD2704 K

* New Parts

RX-V675/HTR-6066/TSR-6750

RX-A730


MAIN

Carbon Resistors

Ref No.	Part No.	Description	Markets
Q1527	WC883400	TR	2SD2704 K
R1001-1007	HF356100	R. CAR	1KΩ 1/2W
R1008-1014	HF356180	R. CAR	1.8KΩ 1/2W
R1022-1028	HF355330	R. CAR	330Ω 1/2W
R1029-1035	HL006120	R. MTL. OXD	1.2KΩ 1/2W
R1036-1042	V8070900	R. MTL. FLM	100Ω 1W
R1043-1045	V8072600	R. MTL. OXD	33KΩ 1W
R1046-1049	HL007330	R. MTL. OXD	33KΩ 1/2W
R1071-1077	WW975700	R. MTL. OXD	47KΩ 1/4W
R1079-1085	HL005120	R. MTL. OXD	120Ω 1/2W
R1100-1106	WW972100	R. MTL. OXD	1.5KΩ 1/4W
△ R1113-1118	WC862200	R. MTL. FLM	120Ω 1W
△ R1119-1126	HL005120	R. MTL. OXD	120Ω 1/2W
R1127-1133	HF355470	R. CAR	470Ω 1/2W
△ R1134-1147	HL004100	R. MTL. OXD	10Ω 1/2W
△ R1148-1154	WP839400	R. CEMENT	0.22+0.22 3W
R1155-1161	WW973500	R. MTL. OXD	5.6KΩ 1/4W
△ R1176-1182	V8070300	R. MTL. FLM	10Ω 1W
△ R1197-1198	V8070200	R. MTL. FLM	4.7Ω 1W
△ R1211	WW966900	R. MTL. OXD	10Ω 1/4W
R1213	V8072100	R. MTL. OXD	5.6KΩ 1W
R1214	WW971100	R. MTL. OXD	560Ω 1/4W
R1219	V8072000	R. MTL. OXD	4.7KΩ 1W
△ R1222	V8071600	R. MTL. FLM	1KΩ 1W
R1223	WW975100	R. MTL. OXD	27KΩ 1/4W
R1225	WW976100	R. MTL. OXD	68KΩ 1/4W
R1251-1252	WW974100	R. MTL. OXD	10KΩ 1/4W
R1258	VP939500	R. MTL. FLM	1Ω 1W
R1262	V8070100	R. MTL. FLM	2.2Ω 1W
R1664-1665	WA621400	R. MTL. OXD	82Ω 1W J
R1701-1702	WW976100	R. MTL. OXD	68KΩ 1/4W
R1703	WA621400	R. MTL. OXD	82Ω 1W J
R1703	WQ835700	R. MTL. OXD	82Ω 1W
R1704	WA621400	R. MTL. OXD	82Ω 1W J
R1704	WQ835700	R. MTL. OXD	82Ω 1W
△ RY101	ZE429100	RELAY	DC DH5D2-0 5V
△ RY102-107	ZE399200	RELAY	981-2A-5DS-SP7 5V
△ SW1	WV382900	SW. SLIDE	SL14
TE101	WW728900	TERM. SP	4P
TE101	WW726500	TERM. SP	4P
TE102	WW726600	TERM. SP	6P
TE102	WW728800	TERM. SP	6P
TE103	WW728900	TERM. SP	4P
TE103	WW726500	TERM. SP	4P
	WE774200	SCR. BND. HD	3x10 MFZN2W3

Ref No.	Part No.	Description	Markets

Value	1/4W Type Part No.	1/6W Type Part No.	Value	1/4W Type Part No.	1/6W Type Part No.
1.0 Ω	HJ35 3100	HF85 3100	11 kΩ	HF45 7110	HF45 7110
1.8 Ω	HJ35 3180	※	12 kΩ	HJ35 7120	HF85 7120
2.2 Ω	HJ35 3220	HF85 3220	13 kΩ	HF45 7130	HF45 7130
3.3 Ω	HJ35 3330	HF85 3330	15 kΩ	HF45 7150	HF45 7150
4.7 Ω	HJ35 3470	HF85 3470	18 kΩ	HF45 7180	HF45 7180
5.6 Ω	HJ35 3560	HF85 3560	22 kΩ	HF45 7220	HF45 7220
10 Ω	HF45 4100	HF45 4100	24 kΩ	HF45 7240	HF45 7240
15 Ω	HJ35 4150	HF85 4150	27 kΩ	HJ35 7270	HF85 7270
22 Ω	HF45 4220	HF45 4220	30 kΩ	HF45 7300	HF45 7300
27 Ω	HJ35 4270	HF85 4270	33 kΩ	HF45 7330	HF45 7330
33 Ω	HF45 4330	HF45 4330	36 kΩ	HF45 7360	HF45 7360
39 Ω	HJ35 4470	HF85 4390	39 kΩ	HF45 7390	HF45 7390
47 Ω	HF45 4470	HF45 4470	47 kΩ	HF45 7470	HF45 7470
56 Ω	HF45 4560	HF45 4560	51 kΩ	HF45 7510	HF45 7510
68 Ω	HF45 4680	HF45 4680	56 kΩ	HF45 7560	HF45 7560
75 Ω	HF45 4750	HF45 4750	62 kΩ	HF45 7620	HF45 7620
82 Ω	HF45 4820	HF45 4820	68 kΩ	HF45 7680	HF45 7680
91 Ω	HF45 4910	HF45 4910	82 kΩ	HF45 7820	HF45 7820
100 Ω	HF45 5100	HF45 5100	91 kΩ	HF45 7910	HF45 7910
110 Ω	HJ35 5110	HF85 5110	100 kΩ	HF45 8100	HF45 8100
120 Ω	HF45 5120	HF45 5120	110 kΩ	HF45 8110	HF45 8110
150 Ω	HF45 5150	HF45 5150	120 kΩ	HF45 8120	HF45 8120
160 Ω	HJ35 5160	※	130 kΩ	HF45 8130	※
180 Ω	HF45 5180	HF45 5180	150 kΩ	HF45 8150	HF45 8150
200 Ω	HF45 5200	HF45 5200	180 kΩ	HF45 8180	HF45 8180
220 Ω	HF45 5220	HF45 5220	220 kΩ	HJ35 8220	HF85 8220
270 Ω	HF45 5270	HF45 5270	270 kΩ	HF45 8270	HF45 8270
330 Ω	HF45 5330	HF45 5330	300 kΩ	HF45 8300	HF45 8300
390 Ω	HF45 5390	HF45 5390	330 kΩ	HF45 8330	HF45 8330
430 Ω	HF45 5430	HF45 5430	390 kΩ	HJ35 8390	HF85 8390
470 Ω	HF45 5470	HF45 5470	470 kΩ	HF45 8470	HF45 8470
510 Ω	HF45 5510	HF45 5510	560 kΩ	HJ35 8560	HF85 8560
560 Ω	HF45 5560	HF45 5560	680 kΩ	HJ35 8680	HF85 8680
680 Ω	HF45 5680	HF45 5680	820 kΩ	HJ35 8820	HF85 8820
820 Ω	HF45 5820	HF45 5820	1.0 MΩ	HF45 9100	HF45 9100
910 Ω	HF45 5910	HF45 5910	1.2 MΩ	HJ35 9120	※
1.0 kΩ	HF45 6100	HF45 6100	1.5 MΩ	HJ35 9150	HF85 9150
1.2 kΩ	HF45 6120	HF45 6120	1.8 MΩ	HJ35 9180	HF85 9180
1.5 kΩ	HF45 6150	HF45 6150	2.2 MΩ	HJ35 9220	HF85 9220
1.8 kΩ	HF45 6180	HF45 6180	3.3 MΩ	HJ35 9330	HF85 9330
2.0 kΩ	HJ35 6200	HF85 6200	3.9 MΩ	HJ35 9390	※
2.2 kΩ	HF45 6220	HF45 6220	4.7 MΩ	HJ35 9470	HF85 9470
2.4 kΩ	HJ35 6240	HF85 6240			
2.7 kΩ	HF45 6270	HF45 6270			
3.0 kΩ	HF45 6300	HF45 6300			
3.3 kΩ	HF45 6330	HF45 6330			
3.6 kΩ	HJ35 6360	HF85 6360			
3.9 kΩ	HF45 6390	HF45 6390			
4.7 kΩ	HF45 6470	HF45 6470			
5.1 kΩ	HF45 6510	HF45 6510			
5.6 kΩ	HF45 6560	HF45 6560			
6.8 kΩ	HF45 6680	HF45 6680			
8.2 kΩ	HF45 6820	HF45 6820			
9.1 kΩ	HF45 6910	HF45 6910			
10 kΩ	HF45 7100	HF45 7100			



* New Parts


* New Parts

※ : Not available

• OVERALL ASSEMBLY

L, H models

R, S models



RX-V675/HTR-6066/TSR-6750

	Ref No.	Part No.	Description	Remarks	Markets
*	1	ZF534400	P. C. B. ASSEMBLY	DIGITAL	
*	3-1	ZF534700	P. C. B. ASSEMBLY	MAIN	UC
*	3-1	ZF534800	P. C. B. ASSEMBLY	MAIN	RS
*	3-1	ZF534900	P. C. B. ASSEMBLY	MAIN	TA
*	3-1	ZF535000	P. C. B. ASSEMBLY	MAIN	B
*	3-1	ZF535100	P. C. B. ASSEMBLY	MAIN	GFLH
*	6-2	ZF535200	P. C. B. ASSEMBLY	OPERATION	U
*	6-2	ZF535300	P. C. B. ASSEMBLY	OPERATION	C
*	6-2	ZF535400	P. C. B. ASSEMBLY	OPERATION	RS
*	6-2	ZF535500	P. C. B. ASSEMBLY	OPERATION	T
*	6-2	ZF535600	P. C. B. ASSEMBLY	OPERATION	A
*	6-2	ZF535700	P. C. B. ASSEMBLY	OPERATION	BGF
*	6-2	ZF535800	P. C. B. ASSEMBLY	OPERATION	LH
	6-17	ZA116600	FLEXIBLE FLAT CABLE	22P 210mm P=1.0	
	12	WW891000	AM/FM TUNER	FAEH08-W02	UCRTLSH
	12	WW891100	AM/FM TUNER	FAEH08-E02	ABGF
△ *	15	YF260A00	POWER TRANSFORMER		UC
△ *	15	YF261A00	POWER TRANSFORMER		RS
△ *	15	YF262A00	POWER TRANSFORMER		T
△ *	15	YF263A00	POWER TRANSFORMER		ALH
△ *	15	YF264A00	POWER TRANSFORMER		BGF
△	16	WR336800	POWER CABLE	2m	UC
△	16	WY042500	POWER CABLE	1. 8m	R
△	16	WY042600	POWER CABLE	1. 8m	T
△	16	WY042100	POWER CABLE	1. 8m	A
△	16	WY041100	POWER CABLE	1. 8m	B
△	16	WR336900	POWER CABLE	2m	GFL
△	16	ZC898500	POWER CABLE	1. 8m	S
△	16	WY094600	POWER CABLE	1. 8m	H
	17	V2438700	CORD STOPPER	10P1	
*	25	ZF457300	FLEXIBLE FLAT CABLE	18P 200mm P=1. 25	
*	26	ZF457600	FLEXIBLE FLAT CABLE	5P 100mm P=1. 25	
	31	WY194600	FLEXIBLE FLAT CABLE	9P 100mm P=1. 25	
	101	ZA554700	TOP COVER		GD
	101	ZA554500	TOP COVER		BL
	101	ZA554600	TOP COVER		TI
*	103	ZF096600	REAR PANEL	RX-V675	UC
*	103	ZG305600	REAR PANEL	TSR-6750	U
*	103	ZF096700	REAR PANEL	RX-V675	RS
*	103	ZF097000	REAR PANEL	RX-V675, HTR-6066	TABGFLH
*	107	ZF611400	FFC BARRIER		
	109	WQ664500	SUPPORT	H8	
*	112	ZG891700	CABLE CLAMP	RBWS-0409E-V0	
	120	ZE253400	LEG	D60 H21 Black	

* New Parts

Finish GD: Gold color, BL: Black color, TI: Titanium color

	Ref No.	Part No.	Description	Remarks	Markets
	121	ZA168900	KNOB	D52	GD
	121	ZA168700	KNOB	D52	BL
	121	ZA168800	KNOB	D52	TI
	130	WR306100	SHEET	TOP PANEL	LH
	131	WJ053800	RIVET	TOP PANEL	LH
	151	V5881100	CUSHION	5x8x25	
	152	WC879000	DAMPER	SCREW MASK	
*	153	ZF102700	SUPPORT	TRANSISTOR	
*	154	ZF101600	DAMPER	6x6x3	
	160	WE774100	BIND HEAD BONDING B-T. SCREW	3x8 MFZN2B3	
	163	WE774300	BIND HEAD B-TIGHT SCREW	3x8 MFZN2W3	
	164	WE877900	BIND HEAD S-TIGHT SCREW	3x6 MFZN2W3	
	167	WF002600	PW HEAD B-TIGHT SCREW	3x8 MFZN2W3	
	168	WE774600	HEXAGONAL HEAD B-TIGHT SCREW	3x18 MFZN2W3	
	170	WU048900	BIND HEAD S-TIGHT SCREW	4x10 MFZN2W3	
	171	VDO69600	PW HEAD S-TIGHT SCREW	4x8-10 MFN133	GD, TI
	171	VH313200	PW HEAD S-TIGHT SCREW	4x8-10 MFN13BL	BL
			ACCESSORIES		
*	200	ZF269900	REMOTE CONTROL	RAV501	000-224700100
	200-1	AAX82380	BATTERY COVER	Black	CG-2209
	202	V6267000	FM ANTENNA	1. 4m 1pc	UCRTLSH
	202	VQ147100	FM ANTENNA	1. 4m 1pc	ABGF
	203	VR248500	AM ANTENNA	1. 0m 1pc	
	204	WN649600	YPAO MICROPHONE	6m 1pc	EM6022L-HN1700
	205	ZC175500	REMOTE CONTROL SHEET	1pc	T
	206	ZG306200	ANTENNA ISOLATOR	11D05Z42 1pc	T
	207	ZG306400	CONVERSION PLUG	EP-6004-02-01 1pc	T
			BATTERY	R03, AAA, UM-4 2pcs	
			SERVICE TOOL		
*		ZF454800	PCB CHECKING JIG	for RX-V675/V775/A830	with CABLE

* New Parts

Finish GD: Gold color, BL: Black color, TI: Titanium color

RX-V675/HTR-6066/TSR-6750


AMP UNIT

Ref No.	Part No.	Description	Remarks	Markets
* 3-1	ZF534700	P. C. B. ASSEMBLY	MAIN	UC
* 3-1	ZF534800	P. C. B. ASSEMBLY	MAIN	RS
* 3-1	ZF534900	P. C. B. ASSEMBLY	MAIN	TA
* 3-1	ZF535000	P. C. B. ASSEMBLY	MAIN	B
* 3-1	ZF535100	P. C. B. ASSEMBLY	MAIN	GFLH
3-11	WQ753200	RADIATION SHEET	40x23x0.06 MICA	
3-16	ZF101700	FFC BARRIER		
3-20	ZE764000	LOCK SUPPORT	LSB-28 YASUTOMI	
3-103	WM220800	HEXAGONAL HEAD B-TIGHT SCREW	3x15 SP MFZN2W3	
3-105	WE774300	BIND HEAD B-TIGHT SCREW	3x8 MFZN2W3	
3-106	VQ368600	PUSH RIVET	P3555-B	
* 6-2	ZF535200	P. C. B. ASSEMBLY	OPERATION	U
* 6-2	ZF535300	P. C. B. ASSEMBLY	OPERATION	C
* 6-2	ZF535400	P. C. B. ASSEMBLY	OPERATION	RS
* 6-2	ZF535500	P. C. B. ASSEMBLY	OPERATION	T
* 6-2	ZF535600	P. C. B. ASSEMBLY	OPERATION	A
* 6-2	ZF535700	P. C. B. ASSEMBLY	OPERATION	BGF
* 6-2	ZF535800	P. C. B. ASSEMBLY	OPERATION	LH

* New Parts

RX-A730

• OVERALL ASSEMBLY



RX-A730

	Ref No.	Part No.	Description	Remarks	Markets
*	1	ZF534400	P. C. B. ASSEMBLY	DIGITAL	
*	5-1	ZF543100	P. C. B. ASSEMBLY	OPERATION	U
*	5-1	ZF543200	P. C. B. ASSEMBLY	OPERATION	C
*	5-1	ZF543300	P. C. B. ASSEMBLY	OPERATION	A
*	5-1	ZF543400	P. C. B. ASSEMBLY	OPERATION	BG
*	5-1	ZF543500	P. C. B. ASSEMBLY	OPERATION	L
	12	WW891000	AM/FM TUNER	FAEH08-W02	UCL
	12	WW891100	AM/FM TUNER	FAEH08-E02	ABG
△ *	15	YF260A00	POWER TRANSFORMER		UC
△ *	15	YF263A00	POWER TRANSFORMER		AL
△ *	15	YF264A00	POWER TRANSFORMER		BG
*	25	ZF457300	FLEXIBLE FLAT CABLE	18P 200mm P=1.25	
*	26	ZF457600	FLEXIBLE FLAT CABLE	5P 100mm P=1.25	
	31	WY194600	FLEXIBLE FLAT CABLE	9P 100mm P=1.25	
	101	WQ665500	TOP COVER		BL
	101	WQ665700	TOP COVER		TI
*	103	ZF098300	REAR PANEL		UC
*	103	ZF098500	REAR PANEL		ABGL
	105	WW982200	SIDE PLATE	1pair	BL
	105	WW982300	SIDE PLATE	1pair	TI
*	107	ZF611400	FFC BARRIER		
	109	WQ664500	SUPPORT	H8	
*	112	ZG891700	CABLE CLAMP	RBWS-0409E-V0	
	120	ZE253400	LEG	D60 H21 Black	
	121	WW981000	KNOB	D48 VOLUME	BL
	121	WW981100	KNOB	D48 VOLUME	TI
	122	WW981300	KNOB	D38 INPUT	BL
	122	WW981400	KNOB	D38 INPUT	TI
	123	WV139700	CENTER LEG	D48	
	130	WK667900	SHEET	TOP PANEL	L
	131	WJ053800	RIVET	TOP PANEL	L
	151	V5881100	CUSHION	5x8x25	
	152	WC879000	DAMPER	SCREW MASK	
*	153	ZF102700	SUPPORT	TRANSISTOR	
*	154	ZF101600	DAMPER	6x6x3	
	155	VQ368600	PUSH RIVET	P3555-B	
	160	WE774100	BIND HEAD BONDING B-T. SCREW	3x8 MFZN2B3	
	163	WE774300	BIND HEAD B-TIGHT SCREW	3x8 MFZN2W3	
	164	WE877900	BIND HEAD S-TIGHT SCREW	3x6 MFZN2W3	
	167	WF002600	PW HEAD B-TIGHT SCREW	3x8 MFZN2W3	
	168	WE774600	HEXAGONAL HEAD B-TIGHT SCREW	3x18 MFZN2W3	
*	170	WU048900	BIND HEAD S-TIGHT SCREW	4x10 MFZN2W3	
	171	VH313200	PW HEAD S-TIGHT SCREW	4x8-10 MFN13BL	BL
	171	VDO69600	PW HEAD S-TIGHT SCREW	4x8-10 MFN133	TI

* New Parts


Finish BL: Black color, TI: Titanium color

	Ref No.	Part No.	Description	Remarks	Markets
	172	WE200500	DISH HEAD B-TIGHT SCREW	3x6 MFN13BL	BL
	172	WE200400	DISH HEAD B-TIGHT SCREW	3x6 MFN133	TI
			ACCESSORIES		
*	200	ZF269900	REMOTE CONTROL	RAV501	000-224700100
	200-1	AAX82380	BATTERY COVER	Black	CG-2209
	202	V6267000	FM ANTENNA	1.4m 1pc	UCL
	202	VQ147100	FM ANTENNA	1.4m 1pc	ABG
	203	VR248500	AM ANTENNA	1.0m 1pc	
	204	WN649600	YPAO MICROPHONE	6m 1pc	EM6022L-HN1700
△	205	WU900300	POWER CABLE	2m 1pc	UC
△	205	WB750900	POWER CABLE	2m 1pc	A
△	205	WU900200	POWER CABLE	2m 1pc	B
△	205	WU900100	POWER CABLE	2m 1pc	G
△	205	WQ577000	POWER CABLE	2m 1pc	L
			BATTERY	R03, AAA, UM-4 2pcs	

* New Parts

Finish BL: Black color, TI: Titanium color

• FRONT PANEL UNIT and SUB-CHASSIS UNIT



Ref No.	Part No.	Description	Remarks	Markets
* 1	ZF534400	P. C. B. ASSEMBLY	DIGITAL	
* 4-1	ZF096300	FRONT PANEL	BL	
* 4-1	ZF096400	FRONT PANEL	TI	
* 4-2	ZF097600	SHEET WINDOW	RX-A730	
4-3	WW980100	BUTTON	POWER	
4-4	WW980500	BUTTON	PURE DIRECT	
4-5	WU155600	BUTTON LENS	PURE DIRECT	
4-6	WW961500	ESCUTCHEON	SCENE	BL
4-6	WW961600	ESCUTCHEON	SCENE	TI
* 5-1	ZF543100	P. C. B. ASSEMBLY	OPERATION	U
* 5-1	ZF543200	P. C. B. ASSEMBLY	OPERATION	C
* 5-1	ZF543300	P. C. B. ASSEMBLY	OPERATION	A
* 5-1	ZF543400	P. C. B. ASSEMBLY	OPERATION	BG
* 5-1	ZF543500	P. C. B. ASSEMBLY	OPERATION	L
5-5	WW983400	BUTTON	TUNER	
5-6	ZA567100	BUTTON CASE		BL
5-6	ZA567200	BUTTON CASE		TI
5-7	WW981600	ESCUTCHEON	VOLUME	BL
5-7	WW981700	ESCUTCHEON	VOLUME	TI
5-8	WW981900	ESCUTCHEON	INPUT	BL
5-8	WW982000	ESCUTCHEON	INPUT	TI
5-9	WW983100	BUTTON	SCENE	BL
5-9	WW983200	BUTTON	SCENE	TI
5-10	VQ368600	PUSH RIVET	P3555-B	
5-15	WR482100	FLEXIBLE FLAT CABLE	25P 250mm P=1.25	
* 5-16	ZF457400	FLEXIBLE FLAT CABLE	6P 250mm P=1.25	
5-17	ZA116600	FLEXIBLE FLAT CABLE	22P 210mm P=1.0	
5-101	WE774300	BIND HEAD B-TIGHT SCREW	3x8 MFZN2W3	
5-102	WF266600	BIND HEAD P-TIGHT SCREW	3x8 MFZN2B3	

* New Parts

Finish BL: Black color, TI: Titanium color


RX-A730

AMP UNIT

Ref No.	Part No.	Description	Remarks	Markets
* 3-1	ZF534700	P. C. B. ASSEMBLY	MAIN	UC
* 3-1	ZF534900	P. C. B. ASSEMBLY	MAIN	A
* 3-1	ZF535000	P. C. B. ASSEMBLY	MAIN	B
* 3-1	ZF535100	P. C. B. ASSEMBLY	MAIN	GL
3-11	WQ753200	RADIATION SHEET	40x23x0.06 MICA	
3-16	ZF101700	FFC BARRIER		
3-20	ZE764000	LOCK SUPPORT	LSB-28 YASUTOMI	
3-103	WM220800	HEXAGONAL HEAD B-TIGHT SCREW	3x15 SP MFZN2W3	
3-105	WE774300	BIND HEAD B-TIGHT SCREW	3x8 MFZN2W3	
3-106	VQ368600	PUSH RIVET	P3555-B	
* 5-1	ZF543100	P. C. B. ASSEMBLY	OPERATION	U
* 5-1	ZF543200	P. C. B. ASSEMBLY	OPERATION	C
* 5-1	ZF543300	P. C. B. ASSEMBLY	OPERATION	A
* 5-1	ZF543400	P. C. B. ASSEMBLY	OPERATION	BG
* 5-1	ZF543500	P. C. B. ASSEMBLY	OPERATION	L

* New Parts

KEY NO. LAYOUT




KEY CODE
RECEIVER MODE

Key No.	FUNCTION		ID-1 (5019)		ID-2 (5020)	
	(U, C, R, T, A, B, G, F, L, S, H models)	Remote control sheet (T model)	MAIN	ZONE2	MAIN	ZONE2
SW1	MAIN/ZONE2		[MAIN]	[ZONE2]	[MAIN]	[ZONE2]
SW2	CODE SET		[CODE SET]	[CODE SET]	[CODE SET]	[CODE SET]
K2	SOURCE		select RCU "mode: SOURCE"			
K3	RECEIVER		select RCU "mode: RECEIVER"			
"RECEIVER" (mode fixed)	K4	RECEIVER	7E-2A	7A-453A	7E-2AD4	7A-453B
	K5	HDMI-1	7A-4738	7A-4837	7A-4739	7A-4836
	K6	HDMI-2	7A-4A35	7A-4B34	7A-4A34	7A-4B35
	K7	HDMI-3	7A-4D32	7A-4E31	7A-4D33	7A-4E30
	K8	HDMI-4	7A-502F	7A-512E	7A-502E	7A-512F
	K9	HDMI-5	7A-700F	7A-710E	7A-700E	7A-710F
	K12	V-AUX	7A-55	7A-D8	7A-55AB	7A-D826
	K13	AV-1	7A-532C	7A-542B	7A-532D	7A-542A
	K14	AV-2	7A-5629	7A-5728	7A-5628	7A-5729
	K15	AV-3	7A-5926	7A-5A25	7A-5927	7A-5A24
	K16	AV-4	7A-5C23	7A-5D22	7A-5C22	7A-5D23
	K17	AV-5	7A-5F20	7A-601F	7A-5F21	7A-601E
	K18	AV-6	7A-621D	7A-631C	7A-621C	7A-631D
	K19	AUDIO-1	7A-651A	7A-6619	7A-651B	7A-6618
	K20	AUDIO-2	7A-6817	7A-6916	7A-6816	7A-6917
	K21	TUNER	7A-16	7A-D2	7A-16E8	7A-D22C
	K22	USB	7F01-720D	7F01-730C	7F01-720C	7F01-730D
	K23	NET	7F01-3F	7F01-40	7F01-3FC1	7F01-40BE
	K24	★	7A-14	7A-D0	7A-14EA	7A-D02E
	K27	BD/DVD (SCENE)	7A-007F	7A-017E	7A-007E	7A-017F
	K28	TV (SCENE)	7A-037C	7A-047B	7A-037D	7A-047A
	K29	NET (SCENE)	7A-0679	7A-0778	7A-0678	7A-0779
	K30	RADIO (SCENE)	7A-0976	7A-0A75	7A-0977	7A-0A74
	K31	PROGRAM	7A-58	–	7A-58A6	–
	K32	VOLUME (+)	7A-1A	7A-DA	7A-1AE4	7A-DA24
	K33	MUTE	7A-1C	7A-DC	7A-1CE2	7A-DC22
	K34	PROGRAM	7A-59	–	7A-59A7	–
	K35	VOLUME (-)	7A-1B	7A-DB	7A-1BE5	7A-DB25
	K38	ON SCREEN	7A-84	7A-3B44	7A-847A	7A-3B45
	K40	OPTION	7A-6B14	7A-6C13	7A-6B15	7A-6C12
	K55	MOVIE	7A-88	–	7A-8876	–
	K56	MUSIC	7A-89	–	7A-8977	–
	K57	SUR. DECODE	7A-8D	–	7A-8D73	–
	K58	STRAIGHT	7A-56	–	7A-56A8	–
	K59	INFO	7A-2758	7A-2857	7A-2759	7A-2856
	K60	SLEEP	7A-30	7A-31	7A-30CE	7A-31CF
	K61	ENHANCER	7A-94	–	7A-946A	–
	K62	PURE DIRECT	7A-DD	–	7A-DD23	–

K41 [cursor -LEFT] + K27 [SCENE -BD/DVD]	ID-1			
K41 [cursor -LEFT] + K28 [SCENE -TV]			ID-2	

K43 [cursor -RIGHT] + K27 [SCENE -BD/DVD]	MAIN		MAIN	
K43 [cursor -RIGHT] + K28 [SCENE -TV]		ZONE2		ZONE2
K43 [cursor -RIGHT] + K29 [SCENE -NET]				

KEY NO. LAYOUT




KEY CODE
SOURCE MODE

	Key No.	FUNCTION		IR code in "RECEIVER" mode				IR code in "SOURCE" mode																K24	K23	K22	K21	K20	K19	K18	K17	K16	K15	K14	K13	K12	K9	K8	K7	K6	K5
		(U, C, R, A, B, G, F, L, S, H models)	Remote control sheet (T model)	ID-1		ID-2		ID-1 / ID-2	[☆]	[NET]	[USB]	[TUNER]	[AU-DIO-2]	[AU-DIO-1]	[AV-6]	[AV-5]	[AV-4]	[AV-3]	[AV-2]	[AV-1]	[V-AUX]	[HDMI-5]	[HDMI-4]	[HDMI-3]	[HDMI-2]	[HDMI-1]															
				MAIN	ZONE2	MAIN	ZONE2	MAIN / ZONE2 / ZONE3																																	
"SOURCE/RECEIVER"	K1	SOURCE 		7F01-50	7F01-70	7F01-50AE	7F01-708E	* SOURCE *																																	
	K36	TOP MENU	主菜单	7A-A0DF	7A-A1DE	7A-A0DE	7A-A1DF		* RECEIVER *																																
	K37	POP-UP MENU		7A-A4DB	7A-A5DA	7A-A4DA	7A-A5DB		transmit "RECEIVER" code then switch RCU to "SOURCE" mode																																
	K39	 (UP)		7A-9D	7A-2B54	7A-9D63	7A-2B55	* SOURCE *																																	
	K41	 (LEFT)		7A-9F	7A-2D52	7A-9F61	7A-2D53																																		
	K42	ENTER		7A-DE	7A-2F50	7A-DE20	7A-2F51																																		
	K43	 (RIGHT)		7A-9E	7A-2E51	7A-9E60	7A-2E50																																		
	K44	RETURN		7A-AA	7A-3C43	7A-AA54	7A-3C42																																		
	K45	 (DOWN)		7A-9C	7A-2C53	7A-9C62	7A-2C52																																		
	K46	DISPLAY		7F01-60	7F01-80	7F01-609E	7F01-807E		* SOURCE *																																
	K47	MODE	模式	7F01-66	7F01-86	7F01-6698	7F01-8678																																		
	K48	 (STOP)		7F01-69	7F01-89	7F01-6997	7F01-8977																																		
	K49	 (PAUSE)		7F01-67	7F01-87	7F01-6799	7F01-8779																																		
	K50	BAND  (PLAY)	波段	7F01-68	7F01-88	7F01-6896	7F01-8876	* SOURCE *																																	
	K51	 (REW) / TUNING (-)	调频	7F01-6A	7F01-8A	7F01-6A94	7F01-8A74																																		
	K52	 (FF) / TUNING (+)		7F01-6B	7F01-8B	7F01-6B95	7F01-8B75																																		
	K53	 (SKIP) / PRESET (-)	预设	7F01-6C	7F01-8C	7F01-6C92	7F01-8C72			* SOURCE *																															
	K54	 (SKIP) / PRESET (+)		7F01-6D	7F01-8D	7F01-6D93	7F01-8D73																																		
	K63	1		7F01-51	7F01-71	7F01-51AF	7F01-718F																																		
	K64	2		7F01-52	7F01-72	7F01-52AC	7F01-728C																																		
	K65	3		7F01-53	7F01-73	7F01-53AD	7F01-738D																																		
	K66	4		7F01-54	7F01-74	7F01-54AA	7F01-748A																																		
	K67	5		7F01-55	7F01-75	7F01-55AB	7F01-758B																																		
	K68	6		7F01-56	7F01-76	7F01-56A8	7F01-7688																																		
K69	7		7F01-57	7F01-77	7F01-57A9	7F01-7789																																			
K70	8		7F01-58	7F01-78	7F01-58A6	7F01-7886																																			
K71	9		7F01-59	7F01-79	7F01-59A7	7F01-7987																																			
K72	0		7F01-5A	7F01-7A	7F01-5AA4	7F01-7A84																																			
K73	+10 / MEMORY		7F01-5B	7F01-7B	7F01-5BA5	7F01-7B85																																			
K74	ENT		7F01-5C	7F01-7C	7F01-5CA2	7F01-7C82																																			
"SOURCE" (mode fixed)	K75	TV -INPUT		* SOURCE (TV) *					* TV -INPUT																																
	K76	TV -VOL (+)							* TV -VOL (+)																																
	K77	TV -CH (+)							* TV -CH (+)																																
	K78	TV - 							* TV - 																																
	K79	TV -MUTE							* TV -MUTE																																
	K80	TV -VOL (-)							* TV -VOL (-)																																
	K81	TV -CH (-)							* TV -CH (-)																																

■ ADVANCED SETUP

Configure the system settings of the unit while viewing the front display.

- 1 Set the unit to standby mode.
- 2 While holding down STRAIGHT on the front panel, press MAIN ZONE ⏻.



- 3 Press PROGRAM to select an item.
- 4 Press STRAIGHT to select a setting.
- 5 Press MAIN ZONE ⏻ to set the unit to standby mode and turn it on again.
The new settings take effect.

ADVANCED SETUP menu items

Item	Function
SP IMP.	Changes the speaker impedance setting.
REMOTE ID	Selects the unit's remote control ID.
TU	(R, T, L, H models) Changes the FM/AM tuning frequency setting.
TV FORMAT	Switches the video signal type.
MON.CHK	Removes the limitation on HDMI video output.
INIT	Restores the default settings.
UPDATE	Updates the firmware.
VERSION	Checks the version of firmware currently installed on the unit.

Changing the speaker impedance setting (SP IMP.)

SP IMP. . . 8Ω MIN

Change the unit's speaker impedance settings depending on the impedance of the speakers connected.

Settings	
6 Ω MIN	Select this option when you connect 6-ohm speakers to the unit. You can also use 4-ohm speakers as the front speakers.
8 Ω MIN (default)	Select this option when you connect 8-ohm or higher speakers to the unit.

Selecting the remote control ID (REMOTE ID)

REMOTE ID . . ID1

Change the unit's remote control ID so that it matches the remote control's ID (default: ID1). When using multiple Yamaha AV receivers, you can set each remote control with a unique remote control ID for its corresponding receiver.

Settings	
ID1 (default), ID2	

■ Changing the remote control ID of the remote control

Perform each of the following steps within 1 minute. Otherwise, the setting will be automatically canceled.

- 1 Press CODE SET on the remote control.
 - 2 Press RECEIVER.
 - 3 Use the numeric keys to enter "5019" (ID1) or "5020" (ID2).
- Once the remote control ID is registered successfully, SOURCE blinks twice. If it blinks six times, registration failed. Repeat from Step 1.



• The registered remote control codes are not cleared even if you change the remote control ID.

Changing the FM/AM tuning frequency setting (TU)

(R, T, L, H models)

TU . . . FM50/AM9

Change the FM/AM tuning frequency setting of the unit depending on your country or region.

Settings	
FM100/AM10	Select this when you want to adjust the FM frequency by 100-kHz steps and AM by 10-kHz steps.
FM50/AM9 (default)	Select this when you want to adjust the FM frequency by 50-kHz steps and AM by 9-kHz steps.

Switching the video signal type (TV FORMAT)

TV FORMAT . NTSC

Switch the video signal type of the unit so that it matches to the format of your TV.

Settings	
NTSC, PAL	
Default	
U, C, R models: NTSC	
T, A, B, G, L, F, S, H models: PAL	

Removing the limitation on HDMI video output (MON.CHK)

MON.CHK . . . YES

The unit automatically detects resolutions supported by a TV connected to the HDMI OUT jack.

Disable the monitor check function if you want to specify a resolution in "Resolution" when the unit cannot detect the TV's resolution or when you want to specify a different resolution than the detected resolution.

Settings	
YES (default)	Enables the monitor check function. (Outputs video signals with a resolution supported by the TV only.)
SKIP	Disables the monitor check function. (Outputs video signals with a specified resolution regardless of compatibility with the TV.)



• Reset to "YES" if the unit becomes inoperable because video from the unit cannot be displayed on the TV after "MON.CHK" has been set to "SKIP".

Restoring the default settings (INIT)

INIT . . . CANCEL

Restores the default settings for the unit.

Choices	
VIDEO	Restores the default settings for video configurations.
ALL	Restores the default settings for the unit.
CANCEL	Does not perform an initialization.

Updating the firmware (UPDATE)



New firmware that provides additional features or product improvements will be released as needed. Updates can be downloaded from our website. If the unit is connected to the Internet, you can download the firmware via the network. For details, refer to the information supplied with updates.

■ Firmware update procedure

Do not perform this procedure unless firmware update is necessary. Also, make sure you read the information supplied with updates before updating the firmware.

1 Press STRAIGHT repeatedly to select “USB” or “NETWORK” and press INFO to start firmware update.

Choices	
USB	Update the firmware using a USB memory device.
NETWORK	Update the firmware via the network.



• If the unit detects newer firmware over the network, the corresponding message will be displayed after ON SCREEN is pressed. In this case, you can also update the unit's firmware by following the procedure in "Updating the unit's firmware via the network".

Checking the firmware version (VERSION)



Check the version of firmware currently installed on the unit.



- You can also check the firmware version in "System" in the "Information" menu.
- It may take a while until the firmware version is displayed.

FIRMWARE UPDATING PROCEDURE

IMPORTANT NOTICE

Do not attempt to update your Yamaha receiver using any other data file except those provided directly from the Yamaha website or through your network connection.

Follow the instructions carefully and do not attempt any other procedures not specified in the instructions provided by Yamaha.

Improperly updated products may cause improper operation, and any parts or service required to restore proper operation will not be covered under the Yamaha Limited Warranty.

Choose from the following 2 methods to update to the latest firmware.

Click here for [Firmware Update Through the Internet](#)

(Connection to the Internet is required)

Click here for [Firmware Update by USB](#)

(A USB thumb drive is required)

In case of error, see the [Troubleshooting](#) section

Firmware Update Through the Internet

Requirement: Internet connection

Your receiver is connected to the Internet if you can receive Internet radio stations.
(See owner's manual for details)

1 Power off the receiver (Standby mode)

2 Enter the ADVANCED SETUP mode

While pressing the **STRAIGHT** key, press the **MAIN ZONE**  key and keep **STRAIGHT** key pressed until "ADVANCED SETUP" appears on the front panel display.

* "ADVANCED SETUP" is displayed only for a few seconds.



3 Select "FIRM UPDATE" from the menu

- Press the **PROGRAM** key until "UPDATE: USB" is displayed.
- Then, press **STRAIGHT** key until "UPDATE: NETWORK" is displayed.





4 Start firmware update

- Press **INFO** key to start the update.
(Update process may take up to 15 minutes)

* If "UPDATE SUCCESS" appears, this means your receiver is already up-to-date. In this case, power off to exit from Advanced Setup. Your AV receiver is ready for normal use.

Firmware update in progress








Caution


DO NOT interrupt power during the update.

In case the power is accidentally cut off resulting in a condition where you can't recover normal operation, refer to the troubleshooting method (**Troubleshooting CASE 2**) on the last page.

- When completed, "UPDATE SUCCESS" appears on the display.



- Turn off the power of the receiver by pressing the **MAIN ZONE**  key.



5 Check the updated firmware version

- Power on the AV receiver and press the **ON SCREEN** key on the remote control.
- Select "Information" > "System".
- Confirm that the firmware version is updated to the latest version.

ON SCREEN key



Congratulations!

You have completed the firmware update. Your AV receiver is ready for normal use.


Firmware Update by USB

Requirement: USB thumb drive, with enough free space to store over 25MB.
(File system with FAT16 or FAT32 format)

Firmware file provided by YAMAHA, "R0331-xxxx.bin".

1 Prepare USB thumb drive for the update

Download the firmware, unzip and copy "R0331-xxxx.bin" into the root directory of the USB thumb drive.



2 Power off the receiver (Standby mode)

3 Insert the USB thumb drive

USB port is located at the lower left corner of the front panel.

4 Enter the ADVANCED SETUP mode


While pressing the **STRAIGHT** key, press the **MAIN ZONE**  key and keep **STRAIGHT** key pressed until "ADVANCED SETUP" appears on the front panel display.

ADVANCED SETUP

5 Select firmware update from the menu

Press the **PROGRAM** key until "UPDATE: * * * * USB" is displayed.

UPDATE: * * * * USB



RX-V675/HTR-6066/TSR-6750

6 Start firmware update

- a. Press **INFO** key to start the update.

(Update process may take up to 10 minutes)

- * If "UPDATE SUCCESS" appears, this means your receiver is already up-to-date. In this case, power off to exit from Advanced Setup. Your AV receiver is ready for normal use.



! Caution


DO NOT interrupt power during the update.

In case the power is accidentally cut off resulting in a condition where you can't recover normal operation, refer to the troubleshooting method (**Troubleshooting CASE 2**) on the last page.

- b. When completed, "UPDATE SUCCESS" appears on the display.

UPDATE SUCCESS


- c. Turn off the power of the receiver by pressing the **MAIN ZONE** key.



7 Check the updated firmware version

- a. Power on the AV receiver and press the **ON SCREEN** key on the remote control.
- b. Select "Information" > "System".
- c. Confirm that the firmware version is updated to the latest version.

ON SCREEN key



Congratulations!

You have completed the firmware update. Your AV receiver is ready for normal use.

Troubleshooting

CASE 1 Error message appeared during the update

Cause: For some reason, the receiver can't read the firmware data.

Method: For your solution, check the following

[Update through Internet]

- ☐ Check Internet connection.
Your Internet connection is working by playing an Internet radio station.
(See owner's manual for details)

[Update by USB thumb drive]


- ☐ USB thumb drive is connected properly to the receiver.
- ☐ USB thumb drive is not password protected.
(AV receiver cannot read data from a security protected USB thumb drive)
- ☐ Make sure the USB thumb drive is inserted before the receiver is powered on for the update.
- ☐ The firmware data, R0331-xxxx.bin is stored in the root directory of the USB thumb drive.
- ☐ There is no other data except the firmware data in the USB thumb drive.
- ☐ No folders are created in the USB thumb drive.
Else, retry the update by USB using another USB thumb drive.

CASE 2 Firmware update doesn't start for other reasons

- Receiver doesn't power up after the update.
- Or, error message appeared when confirming the firmware version.

Recovery method using USB method:

1. Unplug the AC power cable from wall outlet.
2. Insert the USB thumb drive which has the firmware data stored inside, into the USB port located on the front panel.
3. Press and hold the **PURE DIRECT** key and keep it pressed while you plug the AC power cable back into the wall outlet again.
"USB UPDATE" will appear on the front display. Then, release the **PURE DIRECT** key.
4. The update will start automatically.
5. When "UPDATE SUCCESS" appears on the display, firmware update is completed.
Power off the receiver and remove the USB thumb drive.
6. Confirm updated firmware version.



FIRMWARE UPDATING PROCEDURE

IMPORTANT NOTICE

Do not attempt to update your Yamaha receiver using any other data file except those provided directly from the Yamaha website or through your network connection.

Follow the instructions carefully and do not attempt any other procedures not specified in the instructions provided by Yamaha.

Improperly updated products may cause improper operation, and any parts or service required to restore proper operation will not be covered under the Yamaha Limited Warranty.

Choose from the following 2 methods to update to the latest firmware.

Click here for [Firmware Update Through the Internet](#)

(Connection to the Internet is required)

Click here for [Firmware Update by USB](#)

(A USB thumb drive is required)

In case of error, see the [Troubleshooting](#) section

Firmware Update Through the Internet

Requirement: Internet connection

Your receiver is connected to the Internet if you can receive Internet radio stations.
(See owner's manual for details)

1 Power off the receiver (Standby mode)

2 Enter the ADVANCED SETUP mode

While pressing the **STRAIGHT** key, press the **MAIN ZONE**  key and keep **STRAIGHT** key pressed until "ADVANCED SETUP" appears on the front panel display.

* "ADVANCED SETUP" is displayed only for a few seconds.



3 Select "FIRM UPDATE" from the menu

- Press the **PROGRAM** key until "UPDATE: USB" is displayed.
- Then, press **STRAIGHT** key until "UPDATE: NETWORK" is displayed.





4 Start firmware update

- Press **INFO** key to start the update.
(Update process may take up to 15 minutes)

* If "UPDATE SUCCESS" appears, this means your receiver is already up-to-date. In this case, power off to exit from Advanced Setup. Your AV receiver is ready for normal use.

Firmware update in progress







Caution


DO NOT interrupt power during the update.

In case the power is accidentally cut off resulting in a condition where you can't recover normal operation, refer to the troubleshooting method (**Troubleshooting CASE 2**) on the last page.

- When completed, "UPDATE SUCCESS" appears on the display.



- Turn off the power of the receiver by pressing the **MAIN ZONE**  key.




RX-A730

5 Check the updated firmware version

- Power on the AV receiver and press the **ON SCREEN** key on the remote control.
- Select "Information" > "System".
- Confirm that the firmware version is updated to the latest version.

ON SCREEN key



Congratulations!

You have completed the firmware update. Your AV receiver is ready for normal use.


Firmware Update by USB

Requirement: USB thumb drive, with enough free space to store over 25MB.
(File system with FAT16 or FAT32 format)

Firmware file provided by YAMAHA, "R0331-xxxx.bin".

1 Prepare USB thumb drive for the update

Download the firmware, unzip and copy "R0331-xxxx.bin" into the root directory of the USB thumb drive.



2 Power off the receiver (Standby mode)

3 Insert the USB thumb drive

USB port is located at the lower left corner of the front panel.

4 Enter the ADVANCED SETUP mode


While pressing the **STRAIGHT** key, press the **MAIN ZONE**  key and keep **STRAIGHT** key pressed until "ADVANCED SETUP" appears on the front panel display.

ADVANCED SETUP

5 Select firmware update from the menu

Press the **PROGRAM** key until "UPDATE: * * * * USB" is displayed.

UPDATE: * * * * USB




RX-A730

6 Start firmware update

- a. Press **INFO** key to start the update.

(Update process may take up to 10 minutes)

- * If "UPDATE SUCCESS" appears, this means your receiver is already up-to-date. In this case, power off to exit from Advanced Setup. Your AV receiver is ready for normal use.



! Caution


DO NOT interrupt power during the update.

In case the power is accidentally cut off resulting in a condition where you can't recover normal operation, refer to the troubleshooting method (**Troubleshooting CASE 2**) on the last page.

- b. When completed, "UPDATE SUCCESS" appears on the display.

UPDATE SUCCESS

- c. Turn off the power of the receiver by pressing the **MAIN ZONE** key.



7 Check the updated firmware version

- a. Power on the AV receiver and press the **ON SCREEN** key on the remote control.
- b. Select "Information" > "System".
- c. Confirm that the firmware version is updated to the latest version.

ON SCREEN key



Congratulations!

You have completed the firmware update. Your AV receiver is ready for normal use.

Troubleshooting

CASE 1 Error message appeared during the update

Cause: For some reason, the receiver can't read the firmware data.

Method: For your solution, check the following

[Update through Internet]

- ☐ Check Internet connection.
Your Internet connection is working by playing an Internet radio station.
(See owner's manual for details)

[Update by USB thumb drive]


- ☐ USB thumb drive is connected properly to the receiver.
- ☐ USB thumb drive is not password protected.
(AV receiver cannot read data from a security protected USB thumb drive)
- ☐ Make sure the USB thumb drive is inserted before the receiver is powered on for the update.
- ☐ The firmware data, R0331-xxxx.bin is stored in the root directory of the USB thumb drive.
- ☐ There is no other data except the firmware data in the USB thumb drive.
- ☐ No folders are created in the USB thumb drive.
Else, retry the update by USB using another USB thumb drive.

CASE 2 Firmware update doesn't start for other reasons

- Receiver doesn't power up after the update.
- Or, error message appeared when confirming the firmware version.

Recovery method using USB method:

1. Unplug the AC power cable from wall outlet.
2. Insert the USB thumb drive which has the firmware data stored inside, into the USB port located on the front panel.
3. Press and hold the **PURE DIRECT** key and keep it pressed while you plug the AC power cable back into the wall outlet again.
"USB UPDATE" will appear on the front display. Then, release the **PURE DIRECT** key.
4. The update will start automatically.
5. When "UPDATE SUCCESS" appears on the display, firmware update is completed.
Power off the receiver and remove the USB thumb drive.
6. Confirm updated firmware version.



MEMO

RX-V675/HTR-6066/
RX-A730/TSR-6750

**RX-V675/HTR-6066/
RX-A730/TSR-6750**



YAMAHA
