


The Harman Kardon Model Citation 25 STEREO PREAMPLIFIER

Manual 129A

Technical Manual

Citation25



The following marks found in the parts list of this manual identify the models as follows.

- **UA** : North America area model
- **G** : General model
- **N** : Japan model

harman/kardon

240 Crossways Park West, Woodbury, N.Y. 11797
1112-3152129A3 P-078801 1500 Printed in Japan

SPECIFICATIONS

	Nominal	Limit		Nominal	Limit
Input Sensitivity/Impedance			Frequency Response (-3dB Down)	0.25Hz ~ 245kHz	
Phono (MM)	2.2mV/47k Ω		Subsonic Filter at 20Hz	-3dB $\pm$ 1dB	
(MC)	125 μ V/10 Ω , 30 Ω ,		Tone Control Characteristics		
	125 μ V $\pm$ 10 μ V/56 Ω , 100 Ω		Bass (400Hz/200Hz)		
Tone amp	130mV/23k Ω		Boost	10.5dB/9.5dB $\pm$ 1dB	
Ham and Noise Ratio			Cut	-11dB/-9dB $\pm$ 1dB	
Phono (MM)	78dB $\geq$ 74dB		Treble (2kHz/6kHz)		
(MC)	73dB $\geq$ 69dB		Boost	9dB/4.5dB $\pm$ 1dB	
Tone amp	84dB $\geq$ 80dB		Cut	-9dB/-4.5dB $\pm$ 1dB	
Signal to Noise Ratio (IHF-A)			Dimensions (W x H x D)	17-3/8" x 3-3/8" x 14-5/8"	
Phono (MM)	84dB $\geq$ 80dB			(443 x 85 x 371 mm)	
(MC)	78dB $\geq$ 74dB		Weight	20 lbs. / 9.09kg	
Tone amp	94dB $\geq$ 90dB				
Channel Separation			Power Supply		
Phono (MM)	54dB $\geq$ 50dB		North America area model	AC120V, 60Hz	
(MC)	55dB $\geq$ 50dB		General model	AC220/240V, 50/60Hz	
Tone amp	54dB $\geq$ 50dB		Japan model	AC100V, 50/60Hz	
Overload (20 ~ 20kHz)			Power Consumption	27W	
Phono (MM)	165mV $\geq$ 150mV		Japan model	24W	
(MC)	9.2mV $\geq$ 5mV				
THD at 1V Output					
Tone amp (20Hz)	0.0052% $\leq$ 0.01%				
(1kHz)	0.0050% $\leq$ 0.01%				
(20kHz)	0.0045% $\leq$ 0.01%				

These specifications are Service target specs.

Specifications and components subject to change without notice.
Overall performance will be maintained or improved.



LEAKAGE TEST (FOR SERVICE ENGINEERS IN THE U.S.A.)

Before returning the unit to the user, perform the following safety checks:

1. Inspect all lead dress to make certain that leads are not pinched or that hardware is not lodged between the chassis and other metal parts in the unit.
2. Replace all protective devices such as nonmetallic control knobs, insulating fishpapers, cabinet backs, adjustment and compartment covers or shields, isolation resistor-capacitor networks, mechanical insulators, etc.
3. Be sure that no shock hazard exists; check for leakage current using Simpson Model 229 Leakage Tester, standard equipment item No. 21641, RCA Model WT540A or use alternate method as follows:

Plug the AC line cord directly into a 120-volt AC receptacle (do not use an Isolation Transformer for this test). Using two clip leads, connect a 1500 ohm, 10-watt resistor paralleled by a 0.15 μ F capacitor, in series with all exposed metal cabinet parts and a known earth ground, such as a water pipe or conduit. Use a VTVM or VOM with 1000 ohms per volt, or higher sensitivity to measure the AC voltage drop across the resistor. (See Diagram.) Move the resistor connection to each exposed metal part having a return path to the chassis (antenna, metal, cabinet, screw heads, knobs and control shafts, escutcheon, etc.) and measure the AC voltage drop across the resistor. (This test should be performed with the power switch in both the On and Off positions.) A reading of 0.35 volt RMS or more is excessive and indicates a potential shock hazard which must be corrected before returning the unit to the owner.

SIMPSON MODEL 229 ETC. FOR LEAKAGE TEST



DISASSEMBLY PROCEDURES (REFER TO PAGES 5 THROUGH 8)**1 CABINET TOP REMOVAL**

Remove 6 screws (A) and then remove the Cabinet Top (131).

2 FRONT PANEL ASS'Y (AA) REMOVAL

1. Remove the Cabinet Top (131), referring to the previous step 1.
2. Remove 5 screws (B) and then remove the Front Panel Ass'y (AA).

3 FRONT CHASSIS REMOVAL

1. Remove the Front Panel Ass'y (AA), referring to the previous step 2.
2. Open the lid of connector (CN713) on the Equalizer P.C. Board (PCB-1) and then disconnect the lead wire.
3. Remove 2 screws (C) and then remove the Record Output (Sub) P.C. Board (PCB-8).
4. Open the lid of connectors (CN701, CN702, CN708, CN709 and CN712) on the Equalizer P.C. Board (PCB-1) and connector (CN706) on the Volume P.C. Board (PCB-3) and then disconnect the lead wires.
5. Unsolder the lead wires and jumper lead from the Equalizer P.C. Board (PCB-1).
6. Pull off Volume, Balance, Treble, Bass and Turnover knobs (142, 147 and 149).
7. Remove 3 nuts (D) and 11 screws (E) and then remove the Volume Control P.C. Board (PCB-3) and the Front Chassis (161) with the Headphone Jack P.C. Board (PCB-2), Function Switch P.C. Board (PCB-4), Mute Indicator P.C. Board (PCB-5), Record Output (Main) P.C. Board (PCB-9) and Power Indicator P.C. Board (PCB-11).

4 TONE CONTROL P.C. BOARD (PCB-6) REMOVAL

1. Remove the Front Chassis (161), referring to the previous step 3.
2. Open the lid of connectors (CN703, CN704, CN706, CN710, CN714 and CN716) on the Tone P.C. Board (PCB-6), Equalizer P.C. Board (PCB-1) and Volume P.C. Board (PCB-3) and then disconnect the lead wires.
3. Unsolder the lead wires from the Tone Control P.C. Board (PCB-6).
4. Remove 5 screws (F) and 2 nuts (G) and then remove the Tone Control P.C. Board (PCB-6).

5 EQUALIZER P.C. BOARD (PCB-1) REMOVAL


1. Remove the Front Chassis (161), referring to the previous step 3.
2. Open the lid of connectors (CN703, CN704, CN710, CN714 and CN716) on the Tone Control P.C. Board (PCB-6) and connectors (CN701, CN702, CN707, CN708, CN709, CN711, CN712, CN713 and CN715) on the Equalizer P.C. Board (PCB-1) and then disconnect the lead wires.
3. Unsolder the lead wires from the Equalizer P.C. Board (PCB-1).
4. Remove 11 screws (H) and then remove the Equalizer P.C. Board (PCB-1).

6 VIDEO P.C. BOARD (PCB-7) REMOVAL


1. Remove the Cabinet Top (131), referring to the previous step 1.
2. Open the lid of connectors (CN707 and CN711) on the Equalizer P.C. Board (PCB-1) and then disconnect the jumper leads.
3. Remove 4 screws (I) and then remove the Video P.C. Board (PCB-7).

POWER CORD REPLACEMENT (FOR SERVICE ENGINEERS OTHER THAN NORTH AMERICA)

In order to prevent fire or shock hazard when replacing the power cord, follow the Procedure below to replace the part with the standard supply parts.




BLOCK DIAGRAM



GENERAL UNIT EXPLODED VIEW

General model





PARTS LIST

Ref. No.	Part No.	Description
AA	A443-H203A	FRONT PANEL ASS'Y (G)
025A	2132-7116	SPACER (G)
026A	2327-R0130124	SCREW (G)
027A	2440-7017	SPECIAL NUT (G)
028A	1756-01402	LABEL (G)
041A	4411-102729	SWITCH ROTARY (G)
114	1117-78	SERIAL LABEL, REAR
116	1756-CSA	LABEL (UA)
131	1414-09401	CABINET TOP
134	1424-24701	CABI BACK, REAR (UA)
134A	1424-24703	CABI BACK, REAR (G)
134B	1424-24702	CABI BACK, REAR (N)
147	1632-15801	ROTARY KNOB
148	1632-17301	ROTARY KNOB
149	1642-14001	KNOB
163	2218-7001	BRACKET, FIX
169	2219-8151	METAL FITTG, HEAD PHONE
174	2222-7218	HEAT SINK
175	2222-7218	HEAT SINK
177	2240-364	HOLDER, AC CORD
178	2240-385	HOLDER, WIRING
195	2132-7136	SPACER
196	2360-7014	SPECIAL BOSS
198	2310-7036	SPECIAL SCREW
199	2410-7018	SPECIAL WASHER
200	2440-7027	SPECIAL NUT
201	2440-7016	SPECIAL NUT
216	2320-34	SPECIAL SCREW
217	2320-34	SPECIAL SCREW
219	2327-R0130124	SCREW
221	2327-R0130064	SCREW
225	2340-7003	SPECIAL SCREW
227	2340-7008	SPECIAL SCREW, TOP COVER
230	2347-R0130064	SCREW
232	2347-R0130084	SCREW, BOTTOM
238	2327-R0130084	SCREW
239	2401-0320	WASHER, METAL
241	4211-5006	LUG, GND
242	2414-402	WASHER

GENERAL UNIT EXPLODED VIEW

General model






Description

AA	A443-H203A	FRONT PANEL ASSY	G
025A	2132-7116	SPACER	G
026A	2327-R0130124	SCREW	G
027A	2440-7017	SPECIAL NUT	G
028A	1756-01402	LABEL	G
041A	4411-102729	SWITCH ROTALY	G
114	1117-78	SERIAL LABEL, REAR	
116	1756-CSA	LABEL	UA
131	1414-09401	CABINET TOP	
134	1424-24701	CABI BACK, REAR	UA
134A	1424-24703	CABI BACK, REAR	G
134B	1424-24702	CABI BACK, REAR	N
147	1632-15801	ROTARY KNOB	
148	1632-17301	ROTARY KNOB	
149	1642-14001	KNOB	
163	2218-7001	BRACKET, FIX	
169	2219-8151	METAL FITTG, HEAD PHONE	
174	2222-7218	HEAT SINK	
175	2222-7218	HEAT SINK	
177	2240-364	HOLDER, AC CORD	
178	2240-385	HOLDER, WIRING	
195	2132-7136	SPACER	
196	2360-7014	SPECIAL BOSS	
198	2310-7036	SPECIAL SCREW	
199	2410-7018	SPECIAL WASHER	
200	2440-7027	SPECIAL NUT	
201	2440-7016	SPECIAL NUT	
216	2320-34	SPECIAL SCREW	
217	2320-34	SPECIAL SCREW	
219	2327-R0130124	SCREW	
221	2327-R0130064	SCREW	
225	2340-7003	SPECIAL SCREW	
227	2340-7008	SPECIAL SCREW, TOP COVER	
230	2347-R0130064	SCREW	
232	2347-R0130084	SCREW, BOTTOM	
238	2327-R0130084	SCREW	
239	2401-0320	WASHER, METAL	
241	4211-5006	LUG, GND	
242	2414-402	WASHER	

GENERAL UNIT
EXPLODED VIEW (FRONT PANEL ASS'Y)

1
2
3
4
5
6
7



PARTS LIST

Ref. No.	Part No.	Description
AA	A443-H203A	FRONT PANEL ASS'Y
137	1443-12201	PANEL
138	1453-00901	LID
139	1562-06501	FRAME
140	1721-08501	INDICATOR PLATE
141	1721-08601	INDICATOR PLATE
150	1662-30401	PUSH BUTTON, POWER
151	1662-30701	PUSH BUTTON
152	1662-30801	PUSH BUTTON
153	1662-30901	PUSH BUTTON
154	1662-30501	PUSH BUTTON
157	1532-14501	WINDOW
158	1732-03601	INDICATOR
159	1511-06304	PLATE
171	2221-102	HINGE
172	2221-103	HINGE
180	2240-7290	HOLDER, POWER
181	2240-7291	HOLDER, POWER
182	2240-7300	HOLDER, FUNCTION
183	2240-7301	HOLDER, FUNCTION
184	2240-7302	HOLDER
185	2240-7303	HOLDER
186	2240-7306	HOLDER
187	2240-7334	HOLDER
191	2430-7008	SPECIAL FASTENER
192	2692-13	DAMPER
205	2459-3005511	PLASTIC RIVET
209	2651-006	SPRING
210	2651-2101727	SPRING
211	2651-2101710	SPRING
213	2651-2101728	SPRING

**GENERAL UNIT
EXPLODED VIEW (FRONT PANEL ASS'Y)**

1

2


3

4

5

6

7




F

G

H

I


J



PARTS LIST

Ref. No.	Part No.	Description
AA	A443-H203A	FRONT PANEL ASS'Y
137	1443-12201	PANEL
138	1453-00901	LID
139	1562-06501	FRAME
140	1721-08501	INDICATOR PLATE
141	1721-08601	INDICATOR PLATE
150	1662-30401	PUSH BUTTON, POWER
151	1662-30701	PUSH BUTTON
152	1662-30801	PUSH BUTTON
153	1662-30901	PUSH BUTTON
154	1662-30501	PUSH BUTTON
157	1532-14501	WINDOW
158	1732-03601	INDICATOR
159	1511-06304	PLATE
171	2221-102	HINGE
172	2221-103	HINGE
180	2240-7290	HOLDER, POWER
181	2240-7291	HOLDER, POWER
182	2240-7300	HOLDER, FUNCTION
183	2240-7301	HOLDER, FUNCTION
184	2240-7302	HOLDER
185	2240-7303	HOLDER
186	2240-7306	HOLDER
187	2240-7334	HOLDER
191	2430-7008	SPECIAL FASTENER
192	2692-13	DAMPER
205	2459-3005511	PLASTIC RIVET
209	2651-006	SPRING
210	2651-2101727	SPRING
211	2651-2101710	SPRING
213	2651-2101728	SPRING


GENERAL UNIT EXPLODED VIEW (FRONT CHASSIS)



PARTS LIST


Ref. No.	Part No.	Description
142	1630-03501	ROTARY KNOB, VOLUME
161	2211-7299	CHASSIS
188	2240-7336	HOLDER
189	2240-7338	HOLDER
193	2132-7119	SPACER
194	2132-7119	SPACER
221	2327-R0130064	SCREW

GENERAL UNIT EXPLODED VIEW (CABINET BOTTOM)




PARTS LIST

Ref. No.	Part No.	Description
029A	2224-7121	INSULATOR (G)
222A	2327-R0140104	SCREW (G)
222B	2327-R0140104	SCREW (N)
133	1424-21701	CABI BACK, BOTTOM
156	1319-7181	LEG
166	2219-7093	METAL FITTG, TRANS
167	2219-8149	METAL FITTG, TRANS
168	2219-8150	METAL FITTG
196	2360-7014	SPECIAL BOSS
203	2440-7019	SPECIAL NUT
221	2327-R0130064	SCREW
222	2327-R0140104	SCREW
230	2347-R0130064	SCREW
232	2347-R0130084	SCREW
234	2347-R0140124	SCREW
237	2362-10101	BOSS, THREAD
△T1	5584-701554	XFORMER, POWER (UA)
△T1A	5584-702453	XFORMER, POWER (G)
△T1B	5584-703453	XFORMER, POWER (N)




**GENERAL UNIT
EXPLODED VIEW (FRONT CHASSIS)**



PARTS LIST

Ref. No.	Part No.	Description
142	1630-03501	ROTARY KNOB, VOLUME
161	2211-7299	CHASSIS
188	2240-7336	HOLDER
189	2240-7338	HOLDER
193	2132-7119	SPACER
194	2132-7119	SPACER
221	2327-R0130064	SCREW


GENERAL UNIT EXPLODED VIEW (CABINET BOTTOM)




PARTS LIST

Ref. No.	Part No.	Description
029A	2224-7121	INSULATOR G
222A	2327-R0140104	SCREW G
222B	2327-R0140104	SCREW N
133	1424-21701	CABI BACK, BOTTOM
156	1319-7181	LEG
166	2219-7093	METAL FITTG, TRANS
167	2219-8149	METAL FITTG, TRANS
168	2219-8150	METAL FITTG
196	2360-7014	SPECIAL BOSS
203	2440-7019	SPECIAL NUT
221	2327-R0130064	SCREW
222	2327-R0140104	SCREW
230	2347-R0130064	SCREW
232	2347-R0130084	SCREW
234	2347-R0140124	SCREW
237	2362-10101	BOSS, THREAD
△T1	5584-701554	XFORMER, POWER UA
△T1A	5584-702453	XFORMER, POWER G
△T1B	5584-703453	XFORMER, POWER N

General model




Japan model




WIRE COLOR ABBREVIATIONS

RED: Red	YEL: Yellow
ORG: Orange	PUP: Purple
BLU: Blue	PIK: Pink
WHT: White	GRY: Gray
GRN: Green	BRN: Brown
BLK: Black	




WIRING DIAGRAM

General model





Japan model




WIRE COLOR ABBREVIATIONS

RED: Red
OR: Orange
BLU: Blue
WHT: White
GRN: Green
BLK: Black

YEL: Yellow
PUR: Purple
PIK: Pink
GRY: Gray
BRN: Brown







P.C. BOARDS (1)

PCB-1 Equalizer P. C. Board


MM/MC




PCB-9 Record Output P. C. Board (MAIN)




PCB-2 Headphone Jack P. C. Board



PCB-3 Volume Control P. C. Board




PCB-8 Record Output P. C. Board (SUB)



(): General model only
 []: General model only
 Others Jumper


E

PCB-1


MM/MC

P.C. BOARDS (2)

PCB-5 Mute Indicator P. C. Board




PCB-6 Tone Control P. C. Board



PCB-4 Function Switch P. C. Board




PCB-7 Video P. C. Board



PCB-10 Mini Jack P. C. Board




PCB-11 Power Indicator P. C. Board


Mono
Hi Cut
Subsonic
Phase-
Correct Loudness
TREBLE
TURNOVER
BASS

P.C. BOARDS (2)


PCB-5 Mute Indicator P. C. Board




PCB-6 Tone Control P. C. Board




PCB-4 Function Switch P. C. Board




PCB-7 Video P. C. Board




SCHEMATIC DIAGRAM (1)







SCHEMATIC DIAGRAM (2)




[illegible]




SCHEMATIC DIAGRAM (3)






SCHEMATIC DIAGRAM (4)



(G): General model


Page 11, E-1
Page 12, D-7
Page 13, I-1

NOTE:
1. ALL RESISTANCE VALUES ARE IN Ω .
K Ω =1000 Ω , M Ω =1000K Ω .
2. ALL CAPACITANCE VALUES ARE IN μ F UNLESS OTHERWISE NOTED. P=PPH.




IC BLOCK DIAGRAM


IC1 : TC4069BP
Tone Amp.




IC401 : μ PC4556C
Headphone Amp.




IC801, 802 : BA7001
Rec. Out Selector




IC755, 756, 757, 758 : LC7818
Function Selector




IC803, 804 : LC4966
Rec. Out Selector




IC851, 852 : BA612
Amp.




IC853 : TC4514BP
Selector




IC854 : TC4013BP
Selector




IC855 : TC4011BP
Nand Gate



IC856 : LB1641
Motor Driver



IC857 : M50117P
Remote Control Micro Processor



ELECTRICAL PARTS LIST

Ser. No.	Ref. No.	Part No.	Description
----------	----------	----------	-------------

PCB-1 EQUALIZER P.C. BOARD

CAPACITORS

699	C9	5345-107C041	CAP, MINI ELE 100 μ /16V
699	C10	5345-107C041	CAP, MINI ELE 100 μ /16V
699	C13	5345-107C041	CAP, MINI ELE 100 μ /16V
699	C14	5345-107C041	CAP, MINI ELE 100 μ /16V
750	C91	5345-337D041	CAP, MINI ELE 330 μ /25V
750	C92	5345-337D041	CAP, MINI ELE 330 μ /25V
750	C93	5345-337D041	CAP, MINI ELE 330 μ /25V
750	C94	5345-337D041	CAP, MINI ELE 330 μ /25V
749	C95	5345-228D041	CAP, MINI ELE 2200 μ /25V
749	C96	5345-228D041	CAP, MINI ELE 2200 μ /25V
750	C97	5345-337D041	CAP, MINI ELE 330 μ /25V
750	C98	5345-337D041	CAP, MINI ELE 330 μ /25V
683	C401	5345-475F0951	CAP, MINI ELE 4.7 μ /50V
683	C402	5345-475F0951	CAP, MINI ELE 4.7 μ /50V
685	C403	5359-1515851	CAP, PPP 150p
685	C404	5359-1515851	CAP, PPP 150p
543	C601	5345-106D0951	CAP, MINI ELE 10 μ /25V
543	C602	5345-106D0951	CAP, MINI ELE 10 μ /25V
546	C603	5345-107B041	CAP, MINI ELE 100 μ /10V
546	C604	5345-107B041	CAP, MINI ELE 100 μ /10V
545	C605	5345-477B0952	CAP, MINI ELE 470 μ /10V
545	C606	5345-477B0952	CAP, MINI ELE 470 μ /10V
547	C607	5345-226C041	CAP, MINI ELE 22 μ /16V
547	C608	5345-226C041	CAP, MINI ELE 22 μ /16V
550	C609	5353-100934	CAP, MCA 10p
550	C610	5353-100934	CAP, MCA 10p
550	C611	5353-100934	CAP, MCA 10p
550	C612	5353-100934	CAP, MCA 10p
554	C613	5359-4725851	CAP, PPP 4700p
554	C614	5359-4725851	CAP, PPP 4700p
556	C615	5359-1025851	CAP, PPP 1000p
556	C616	5359-1025851	CAP, PPP 1000p
553	C617	5359-1825851	CAP, PPP 1800p
553	C618	5359-1825851	CAP, PPP 1800p
552	C619	5359-1815851	CAP, PPP 180p
552	C620	5359-1815851	CAP, PPP 180p
544	C621	5345-336D0951	CAP, MINI ELE 33 μ /25V
544	C622	5345-336D0951	CAP, MINI ELE 33 μ /25V
549	C623	5353-121534	CAP, MCA 120p UA N
549A	C623	5359-3315851	CAP, PPP 330p G
549	C624	5353-121534	CAP, MCA 120p UA N
549A	C624	5359-3315851	CAP, PPP 330p G
555	C625	5359-2225851	CAP, PPP 2200p
555	C626	5359-2225851	CAP, PPP 2200p
551	C629	5353-010934	CAP, MCA 1p
551	C630	5353-010934	CAP, MCA 1p
558	C631	5354-104593	CAP, MYL .1 μ
504	C701	5345-106F0951	CAP, MINI ELE 10 μ /50V
504	C702	5345-106F0951	CAP, MINI ELE 10 μ /50V
504	C703	5345-106F0951	CAP, MINI ELE 10 μ /50V
504	C704	5345-106F0951	CAP, MINI ELE 10 μ /50V
522	C705	5345-337C041	CAP, MINI ELE 330 μ /16V
522	C706	5345-337C041	CAP, MINI ELE 330 μ /16V
522	C707	5345-337C041	CAP, MINI ELE 330 μ /16V
522	C708	5345-337C041	CAP, MINI ELE 330 μ /16V
557	C709	5359-3315851	CAP, PPP 330p
557	C710	5359-3315851	CAP, PPP 330p
559	C711	5359-2215851	CAP, PPP 220p
559	C712	5359-2215851	CAP, PPP 220p
560	C713	5359-1015851	CAP, PPP 100p
560	C714	5359-1015851	CAP, PPP 100p
042A	C715	5359-3315851	CAP, PPP 330p G
042A	C716	5359-3315851	CAP, PPP 330p G
043A	C717	5359-1025851	CAP, PPP 1000p G
043A	C718	5359-1025851	CAP, PPP 1000p G
044A	C719	5359-S010J103	CAP, PPP .01 μ G
044A	C720	5359-S010J103	CAP, PPP .01 μ G
461	C751	5359-S010J102	CAP, PPP 1000p
461	C752	5359-S010J102	CAP, PPP 1000p
461	C753	5359-S010J102	CAP, PPP 1000p
461	C754	5359-S010J102	CAP, PPP 1000p

Ser. No.	Ref. No.	Part No.	Description
----------	----------	----------	-------------

448	C756	5345-106D0951	CAP, MINI ELE 10 μ /25V
449	C757	5345-104F0951	CAP, MINI ELE .1 μ /50V
448	C758	5345-106D0951	CAP, MINI ELE 10 μ /25V
448	C759	5345-106D0951	CAP, MINI ELE 10 μ /25V
449	C760	5345-104F0951	CAP, MINI ELE .1 μ /50V
448	C761	5345-106D0951	CAP, MINI ELE 10 μ /25V
460	C762	5359-S010J222	CAP, PPP 2200p
448	C763	5345-106D0951	CAP, MINI ELE 10 μ /25V
449	C764	5345-104F0951	CAP, MINI ELE .1 μ /50V
448	C765	5345-106D0951	CAP, MINI ELE 10 μ /25V
448	C766	5345-106D0951	CAP, MINI ELE 10 μ /25V
449	C767	5345-104F0951	CAP, MINI ELE .1 μ /50V
448	C768	5345-106D0951	CAP, MINI ELE 10 μ /25V
415	C771	5354-104593	CAP, MYL .1 μ
415	C772	5354-104593	CAP, MYL .1 μ
462	C781	5345-336D0951	CAP, MINI ELE 33 μ /25V
462	C782	5345-336D0951	CAP, MINI ELE 33 μ /25V
409	C851	5359-1015851	CAP, PPP 100p
409	C852	5359-1015851	CAP, PPP 100p
407	C854	5359-S010J103	CAP, PPP .01 μ
406	C855	5345-105F041	CAP, MINI ELE 1 μ /50V
388	C856	5345-227A041	CAP, MINI ELE 220 μ /6.3V
388	C857	5345-227A041	CAP, MINI ELE 220 μ /6.3V
407	C858	5359-S010J103	CAP, PPP .01 μ
777	C859	5345-477C041	CAP, MINI ELE 470 μ /16V
777	C860	5345-477C041	CAP, MINI ELE 470 μ /16V
777	C861	5345-477C041	CAP, MINI ELE 470 μ /16V
777	C862	5345-477C041	CAP, MINI ELE 470 μ /16V
408	C868	5359-S010J102	CAP, PPP 1000p
407	C891	5359-S010J103	CAP, PPP .01 μ
415	C892	5354-104593	CAP, MYL .1 μ

RESISTORS

701	R7	5135-182522	RES, CBN 1/2P 1.8K
701	R8	5135-182522	RES, CBN 1/2P 1.8K
703	R9	5135-101522	RES, CBN 1/2P 100
703	R10	5135-101522	RES, CBN 1/2P 100
702	R31	5135-221522	RES, CBN 1/2P 220
702	R32	5135-221522	RES, CBN 1/2P 220
756	R91	5135-220522	RES, CBN 1/2P 22
756	R92	5135-220522	RES, CBN 1/2P 22
756	R93	5135-220522	RES, CBN 1/2P 22
756	R94	5135-220522	RES, CBN 1/2P 22
754	R95	5135-331522	RES, CBN 1/2P 330
754	R96	5135-331522	RES, CBN 1/2P 330
753	R97	5135-101522	RES, CBN 1/2P 100
753	R98	5135-101522	RES, CBN 1/2P 100
752	R101	5135-4R7522	RES, CBN 1/2P 4.7
752	R102	5135-4R7522	RES, CBN 1/2P 4.7
576	R103	5135-104522	RES, CBN 1/2P 100K
692	R401	5135-563522	RES, CBN 1/2P 56K
692	R402	5135-563522	RES, CBN 1/2P 56K
691	R403	5135-273522	RES, CBN 1/2P 27K
691	R404	5135-273522	RES, CBN 1/2P 27K
687	R405	5135-683522	RES, CBN 1/2P 68K
687	R406	5135-683522	RES, CBN 1/2P 68K
688	R407	5135-154522	RES, CBN 1/2P 150K
688	R408	5135-154522	RES, CBN 1/2P 150K
689	R409	5135-331522	RES, CBN 1/2P 330
689	R410	5135-331522	RES, CBN 1/2P 330
690	R411	5135-8R2522	RES, CBN 1/2P 8.2
690	R412	5135-8R2522	RES, CBN 1/2P 8.2
690	R413	5135-8R2522	RES, CBN 1/2P 8.2
690	R414	5135-8R2522	RES, CBN 1/2P 8.2
581	R601	5135-470522	RES, CBN 1/2P 47
581A	R601	5135-102522	RES, CBN 1/2P 1K G
581	R602	5135-470522	RES, CBN 1/2P 47
581A	R602	5135-102522	RES, CBN 1/2P 1K G
563	R603	5135-823522	RES, CBN 1/2P 82K
563	R604	5135-823522	RES, CBN 1/2P 82K
564	R605	5135-124522	RES, CBN 1/2P 120K
564	R606	5135-124522	RES, CBN 1/2P 120K
561	R607	5135-272522	RES, CBN 1/2P 2.7K
561	R608	5135-272522	RES, CBN 1/2P 2.7K
561	R609	5135-272522	RES, CBN 1/2P 2.7K

Ser. No.	Ref. No.	Part No.	Description	Ser. No.	Ref. No.	Part No.	Description
561	R610	5135-272522	RES, CBN 1/2P 2.7K	510	R720	5135-220522	RES, CBN 1/2P 22
566	R611	5135-331522	RES, CBN 1/2P 330	511	R721	5135-392522	RES, CBN 1/2P 3.9K
566	R612	5135-331522	RES, CBN 1/2P 330	511	R722	5135-392522	RES, CBN 1/2P 3.9K
566	R613	5135-331522	RES, CBN 1/2P 330	507	R723	5135-101522	RES, CBN 1/2P 100
566	R614	5135-331522	RES, CBN 1/2P 330	507	R724	5135-101522	RES, CBN 1/2P 100
567	R615	5135-123522	RES, CBN 1/2P 12K	508	R727	5135-121522	RES, CBN 1/2P 120
567	R616	5135-123522	RES, CBN 1/2P 12K	508	R728	5135-121522	RES, CBN 1/2P 120
567	R617	5135-123522	RES, CBN 1/2P 12K	515	R729	5135-470522	RES, CBN 1/2P 47
567	R618	5135-123522	RES, CBN 1/2P 12K	515	R730	5135-470522	RES, CBN 1/2P 47
561	R619	5135-272522	RES, CBN 1/2P 2.7K	505	R731	5135-120522	RES, CBN 1/2P 12
561	R620	5135-272522	RES, CBN 1/2P 2.7K	505	R732	5135-120522	RES, CBN 1/2P 12
561	R621	5135-272522	RES, CBN 1/2P 2.7K	513	R733	5135-331522	RES, CBN 1/2P 330
561	R622	5135-272522	RES, CBN 1/2P 2.7K	513	R734	5135-331522	RES, CBN 1/2P 330
566	R623	5135-331522	RES, CBN 1/2P 330	466	R737	5135-105522	RES, CBN 1/2P 1M
566	R624	5135-331522	RES, CBN 1/2P 330	466	R738	5135-105522	RES, CBN 1/2P 1M
566	R625	5135-331522	RES, CBN 1/2P 330	451	R739	5135-103522	RES, CBN 1/2P 10K
566	R626	5135-331522	RES, CBN 1/2P 330	451	R740	5135-103522	RES, CBN 1/2P 10K
568	R627	5135-821522	RES, CBN 1/2P 820	452	R743	5135-102522	RES, CBN 1/2P 1K
568	R628	5135-821522	RES, CBN 1/2P 820	452	R744	5135-102522	RES, CBN 1/2P 1K
570	R629	5135-682522	RES, CBN 1/2P 6.8K	451	R745	5135-103522	RES, CBN 1/2P 10K
570	R630	5135-682522	RES, CBN 1/2P 6.8K	453	R751	5135-102522	RES, CBN 1/2P 1K
562	R633	5135-471522	RES, CBN 1/2P 470	453	R752	5135-102522	RES, CBN 1/2P 1K
562	R634	5135-471522	RES, CBN 1/2P 470	453	R753	5135-102522	RES, CBN 1/2P 1K
562	R635	5135-471522	RES, CBN 1/2P 470	453	R754	5135-102522	RES, CBN 1/2P 1K
562	R636	5135-471522	RES, CBN 1/2P 470	453	R755	5135-102522	RES, CBN 1/2P 1K
571	R637	5135-125522	RES, CBN 1/2P 1.2M	453	R756	5135-102522	RES, CBN 1/2P 1K
571	R638	5135-125522	RES, CBN 1/2P 1.2M	453	R757	5135-102522	RES, CBN 1/2P 1K
572	R639	5135-563522	RES, CBN 1/2P 56K	453	R758	5135-102522	RES, CBN 1/2P 1K
572	R640	5135-563522	RES, CBN 1/2P 56K	453	R759	5135-102522	RES, CBN 1/2P 1K
573	R641	5135-393522	RES, CBN 1/2P 39K	453	R760	5135-102522	RES, CBN 1/2P 1K
573	R642	5135-393522	RES, CBN 1/2P 39K	452	R761	5135-102522	RES, CBN 1/2P 1K
574	R643	5135-222522	RES, CBN 1/2P 2.2K	452	R762	5135-102522	RES, CBN 1/2P 1K
574	R644	5135-222522	RES, CBN 1/2P 2.2K	453	R763	5135-102522	RES, CBN 1/2P 1K
579	R645	5135-330522	RES, CBN 1/2P 33	453	R764	5135-102522	RES, CBN 1/2P 1K
579	R646	5135-330522	RES, CBN 1/2P 33	452	R765	5135-102522	RES, CBN 1/2P 1K
579	R647	5135-330522	RES, CBN 1/2P 33	452	R766	5135-102522	RES, CBN 1/2P 1K
579	R648	5135-330522	RES, CBN 1/2P 33	453	R767	5135-102522	RES, CBN 1/2P 1K
569	R649	5135-102522	RES, CBN 1/2P 1K	453	R768	5135-102522	RES, CBN 1/2P 1K
569	R650	5135-102522	RES, CBN 1/2P 1K	452	R769	5135-102522	RES, CBN 1/2P 1K
569	R651	5135-102522	RES, CBN 1/2P 1K	452	R770	5135-102522	RES, CBN 1/2P 1K
569	R652	5135-102522	RES, CBN 1/2P 1K	453	R771	5135-102522	RES, CBN 1/2P 1K
578	R653	5135-474522	RES, CBN 1/2P 470K	453	R772	5135-102522	RES, CBN 1/2P 1K
578	R654	5135-474522	RES, CBN 1/2P 470K	452	R773	5135-102522	RES, CBN 1/2P 1K
576	R655	5135-104522	RES, CBN 1/2P 100K	452	R774	5135-102522	RES, CBN 1/2P 1K
576	R656	5135-104522	RES, CBN 1/2P 100K	458	R775	5232-473J16P	RES, CBN 1/6P 47K
577	R657	5135-105522	RES, CBN 1/2P 1M	458	R776	5232-473J16P	RES, CBN 1/6P 47K
571	R661	5135-125522	RES, CBN 1/2P 1.2M	458	R777	5232-473J16P	RES, CBN 1/6P 47K
571	R662	5135-125522	RES, CBN 1/2P 1.2M	458	R778	5232-473J16P	RES, CBN 1/6P 47K
575	R663	5135-121522	RES, CBN 1/2P 120	455	R779	5232-224J16P	RES, CBN 1/6P 220K
575	R664	5135-121522	RES, CBN 1/2P 120	455	R780	5232-224J16P	RES, CBN 1/6P 220K
575	R665	5135-121522	RES, CBN 1/2P 120	455	R781	5232-224J16P	RES, CBN 1/6P 220K
575	R666	5135-121522	RES, CBN 1/2P 120	450	R782	5212-223J0501	R COMPOSITE 22K
433	R698	5135-223522	RES, CBN 1/2P 22K	455	R783	5232-224J16P	RES, CBN 1/6P 220K
432	R699	5135-270522	RES, CBN 1/2P 27	455	R784	5232-224J16P	RES, CBN 1/6P 220K
514	R701	5135-1R0522	RES, CBN 1/2P 1 UA N	459	R785	5232-124J16P	RES, CBN 1/6P 120K
514A	R701	5135-100522	RES, CBN 1/2P 10 G	455	R786	5232-224J16P	RES, CBN 1/6P 220K
514	R702	5135-1R0522	RES, CBN 1/2P 1 UA N	455	R787	5232-224J16P	RES, CBN 1/6P 220K
514A	R702	5135-100522	RES, CBN 1/2P 10 G	450	R788	5212-223J0501	R COMPOSITE 22K
507	R703	5135-101522	RES, CBN 1/2P 100	451	R789	5135-103522	RES, CBN 1/2P 10K
507	R704	5135-101522	RES, CBN 1/2P 100	455	R790	5232-224J16P	RES, CBN 1/6P 220K
512	R705	5135-472522	RES, CBN 1/2P 4.7K	459	R791	5232-124J16P	RES, CBN 1/6P 120K
512	R706	5135-472522	RES, CBN 1/2P 4.7K	455	R792	5232-224J16P	RES, CBN 1/6P 220K
512	R707	5135-472522	RES, CBN 1/2P 4.7K	455	R794	5232-224J16P	RES, CBN 1/6P 220K
512	R708	5135-472522	RES, CBN 1/2P 4.7K	455	R795	5232-224J16P	RES, CBN 1/6P 220K
509	R709	5135-100522	RES, CBN 1/2P 10	455	R796	5232-224J16P	RES, CBN 1/6P 220K
509	R710	5135-100522	RES, CBN 1/2P 10	455	R797	5232-224J16P	RES, CBN 1/6P 220K
509	R711	5135-100522	RES, CBN 1/2P 10	455	R798	5232-224J16P	RES, CBN 1/6P 220K
509	R712	5135-100522	RES, CBN 1/2P 10	412	R861	5232-102J16P	RES, CBN 1/6P 1K
506	R713	5135-561522	RES, CBN 1/2P 560	412	R862	5232-102J16P	RES, CBN 1/6P 1K
506	R714	5135-561522	RES, CBN 1/2P 560	412	R863	5232-102J16P	RES, CBN 1/6P 1K
506	R715	5135-561522	RES, CBN 1/2P 560	411	R864	5232-103J16P	RES, CBN 1/6P 10K
506	R716	5135-561522	RES, CBN 1/2P 560	413	R865	5232-105J16P	RES, CBN 1/6P 1M
510	R717	5135-220522	RES, CBN 1/2P 22	411	R866	5232-103J16P	RES, CBN 1/6P 10K
510	R718	5135-220522	RES, CBN 1/2P 22	390	R868	5135-472522	RES, CBN 1/2P 4.7K
510	R719	5135-220522	RES, CBN 1/2P 22	426	R869	5135-473522	RES, CBN 1/2P 47K

Ser. No.	Ref. No.	Part No.	Description	Ser. No.	Ref. No.	Part No.	Description
425	R870	5135-221522	RES, CBN 1/2P 220	502	Q702	5611-1190 (E)	XISTOR, PNP R
426	R871	5135-473522	RES, CBN 1/2P 47K	501	Q703	5613-2855 (D)	XISTOR, NPN R
427	R872	5135-331522	RES, CBN 1/2P 330	501	Q704	5613-2855 (D)	XISTOR, NPN R
428	R873	5135-100522	RES, CBN 1/2P 10	501	Q705	5613-2855 (D)	XISTOR, NPN R
783	R874	5135-331522	RES, CBN 1/2P 330	501	Q706	5613-2855 (D)	XISTOR, NPN R
785	R875	5135-2R2522	RES, CBN 1/2P 2.2	502	Q707	5611-1190 (E)	XISTOR, PNP R
784	R876	5135-101522	RES, CBN 1/2P 100	502	Q708	5611-1190 (E)	XISTOR, PNP R
782	R877	5135-472522	RES, CBN 1/2P 4.7K	517	Q709	5614-667A (C)	XISTOR, NPN A
783	R878	5135-331522	RES, CBN 1/2P 330	518	Q710	5612-647A (C)	XISTOR, PNP A
784	R879	5135-101522	RES, CBN 1/2P 100	503	Q711	5616-2SK246 (GR)	FET, N-CH
786	R880	5135-4R7522	RES, CBN 1/2P 4.7	503	Q712	5616-2SK246 (GR)	FET, N-CH
782	R881	5135-472522	RES, CBN 1/2P 4.7K	447	Q751	5613-RN1203	XISTOR, NPN R
413	R882	5232-105J16P	RES, CBN 1/6P 1M	447	Q752	5613-RN1203	XISTOR, NPN R
413	R883	5232-105J16P	RES, CBN 1/6P 1M	447	Q753	5613-RN1203	XISTOR, NPN R
413	R884	5232-105J16P	RES, CBN 1/6P 1M	447	Q754	5613-RN1203	XISTOR, NPN R
413	R885	5232-105J16P	RES, CBN 1/6P 1M	445	Q756	5611-1115 (E) or (F)	XISTOR, PNP R
413	R891	5232-105J16P	RES, CBN 1/6P 1M	444	Q761	5616-2SK364 (BL) or (V)	FET, N-CH
424	R892	5135-122522	RES, CBN 1/2P 1.2K	444	Q762	5616-2SK364 (BL) or (V)	FET, N-CH
411	R893	5232-103J16P	RES, CBN 1/6P 10K	444	Q763	5616-2SK364 (BL) or (V)	FET, N-CH
430	R894	5135-105522	RES, CBN 1/2P 1M	444	Q764	5616-2SK364 (BL) or (V)	FET, N-CH
429	R895	5135-334522	RES, CBN 1/2P 330K	444	Q765	5616-2SK364 (BL) or (V)	FET, N-CH
429	R896	5135-334522	RES, CBN 1/2P 330K	444	Q766	5616-2SK364 (BL) or (V)	FET, N-CH
431	R897	5135-104522	RES, CBN 1/2P 100K	444	Q767	5616-2SK364 (BL) or (V)	FET, N-CH
389	R898	5135-101522	RES, CBN 1/2P 100	444	Q768	5616-2SK364 (BL) or (V)	FET, N-CH
411	R899	5232-103J16P	RES, CBN 1/6P 10K	443	Q851	5611-RN2203	XISTOR, PNP R
INTEGRATED CIRCUITS				443	Q852	5611-RN2203	XISTOR, PNP R
681	IC401	5653-UPC4556C	IC, LINEAR	443	Q853	5611-RN2203	XISTOR, PNP R
441	IC755	5654-LC7818	IC, DIGITAL	443	Q854	5611-RN2203	XISTOR, PNP R
441	IC756	5654-LC7818	IC, DIGITAL	443	Q855	5611-RN2203	XISTOR, PNP R
441	IC757	5654-LC7818	IC, DIGITAL	443	Q856	5611-RN2203	XISTOR, PNP R
441	IC758	5654-LC7818	IC, DIGITAL	443	Q857	5611-RN2203	XISTOR, PNP R
442	IC851	5654-BA612	IC, DIGITAL	443	Q858	5611-RN2203	XISTOR, PNP R
442	IC852	5654-BA612	IC, DIGITAL	443	Q859	5611-RN2203	XISTOR, PNP R
393	IC853	5654-TC4514BP	IC, DIGITAL	443	Q860	5611-RN2203	XISTOR, PNP R
396	IC854	5654-TC4013BP	IC, DIGITAL	443	Q861	5611-RN2203	XISTOR, PNP R
395	IC855	5654-TC4011BP	IC, DIGITAL	386	Q862	5614-667A (C)	XISTOR, NPN A
397	IC856	5653-LB1641BP	IC, LINEAR	404	Q863	5613-2603 (E) or (F)	XISTOR, NPN R
394	IC857	5654-MS0117P	IC, DIGITAL	404	Q864	5613-2603 (E) or (F)	XISTOR, NPN R
TRANSISTORS				771	Q865	5612-1015 (O) or (Y)	XISTOR, PNP A
694	Q7	5614-667A (C)	XISTOR, NPN A	772	Q866	5613-2603 (E) or (F)	XISTOR, NPN R
695	Q8	5612-647A (C)	XISTOR, PNP A	772	Q867	5613-2603 (E) or (F)	XISTOR, NPN R
742	Q91	5612-1015 (O) or (Y)	XISTOR, PNP A	772	Q868	5613-2603 (E) or (F)	XISTOR, NPN R
741	Q92	5614-1406 (O) or (Y)	XISTOR, NPN A	771	Q869	5612-1015 (O) or (Y)	XISTOR, PNP A
743	Q93	5613-2603 (F) or (E)	XISTOR, NPN R	772	Q870	5613-2603 (E) or (F)	XISTOR, NPN R
744	Q94	5611-1115 (F) or (E)	XISTOR, PNP R	403	Q871	5611-1115 (E) or (F)	XISTOR, PNP R
745	Q95	5616-2SK246 (GR)	FET, N-CH	421	Q891	5613-RN1203	XISTOR, NPN R
745	Q96	5616-2SK246 (GR)	FET, N-CH	419	Q892	5611-1115 (E) or (F)	XISTOR, PNP R
743	Q97	5613-2603 (F) or (E)	XISTOR, NPN R	421	Q893	5613-RN1203	XISTOR, NPN R
744	Q98	5611-1115 (F) or (E)	XISTOR, PNP R	418	Q895	5616-2SK364 (BL) or (V)	FET, N-CH
531	Q601	5613-2240 (BL)	XISTOR, NPN R	418	Q896	5616-2SK364 (BL) or (V)	FET, N-CH
531	Q602	5613-2240 (BL)	XISTOR, NPN R	DIODES			
532	Q603	5611-970 (BL)	XISTOR, PNP R	697	D9	5635-HZ15-1L	DIODE, ZENER
532	Q604	5611-970 (BL)	XISTOR, PNP R	697	D10	5635-HZ15-1L	DIODE, ZENER
531	Q605	5613-2240 (BL)	XISTOR, NPN R	747	D91	5635-HZ20-1L	DIODE, ZENER
531	Q606	5613-2240 (BL)	XISTOR, NPN R	747	D92	5635-HZ20-1L	DIODE, ZENER
532	Q607	5611-970 (BL)	XISTOR, PNP R	541	D601	5641-MV103	VARISTOR
532	Q608	5611-970 (BL)	XISTOR, PNP R	541	D602	5641-MV103	VARISTOR
533	Q609	5613-2320L (F)	XISTOR, NPN R	520	D701	5635-HZ15-1L	DIODE, ZENER
533	Q610	5613-2320L (F)	XISTOR, NPN R	520	D702	5635-HZ15-1L	DIODE, ZENER
534	Q611	5611-999L (F)	XISTOR, PNP R	446	D751	5631-ISS133	DIODE, DET
534	Q612	5611-999L (F)	XISTOR, PNP R	446	D752	5631-ISS133	DIODE, DET
535	Q613	5612-646 (C)	XISTOR, PNP A	446	D753	5631-ISS133	DIODE, DET
535	Q614	5612-646 (C)	XISTOR, PNP A	446	D754	5631-ISS133	DIODE, DET
536	Q615	5614-666 (C)	XISTOR, NPN A	446	D755	5631-ISS133	DIODE, DET
536	Q616	5614-666 (C)	XISTOR, NPN A	446	D756	5631-ISS133	DIODE, DET
537	Q617	5614-667 (C)	XISTOR, NPN A	446	D757	5631-ISS133	DIODE, DET
537	Q618	5614-667 (C)	XISTOR, NPN A	446	D758	5631-ISS133	DIODE, DET
538	Q619	5612-647 (C)	XISTOR, PNP A	446	D759	5631-ISS133	DIODE, DET
538	Q620	5612-647 (C)	XISTOR, PNP A	446	D760	5631-ISS133	DIODE, DET
539	Q621	5616-2SK364 (BL) or (V)	FET, N-CH	446	D781	5631-ISS133	DIODE, DET
539	Q622	5616-2SK364 (BL) or (V)	FET, N-CH	446	D782	5631-ISS133	DIODE, DET
386	Q698	5614-667A (C)	XISTOR, NPN A	446	D783	5631-ISS133	DIODE, DET
386	Q699	5614-667A (C)	XISTOR, NPN A	446	D784	5631-ISS133	DIODE, DET
502	Q701	5611-1190 (E)	XISTOR, PNP R	446	D785	5631-ISS133	DIODE, DET

Ser. No.	Ref. No.	Part No.	Description
446	D786	5631-1SS133	DIODE, DET
446	D787	5631-1SS133	DIODE, DET
446	D788	5631-1SS133	DIODE, DET
401	D851	5635-RD2R7EB2	DIODE, ZENER
387	D852	5635-RD5R6EB2	DIODE, ZENER
402	D853	5635-RD5R6EB2	DIODE, ZENER
775	D854	5635-RD13EB2	DIODE, ZENER
775	D855	5635-RD13EB2	DIODE, ZENER
422	D892	5631-1SS133	DIODE, DET
422	D893	5631-1SS133	DIODE, DET
422	D895	5631-1SS133	DIODE, DET
422	D896	5631-1SS133	DIODE, DET

CONTROLS

812	VR507	5113-50343122	RES, V CBN 16 50K
812	VR508	5113-50343122	RES, V CBN 16 50K

MISCELLANEOUS

831	J11	4484-49	PIN JACK, 4P
831	J12	4484-49	PIN JACK, 4P
831	J13	4484-49	PIN JACK, 4P
831	J14	4484-49	PIN JACK, 4P
831	J15	4484-49	PIN JACK, 4P
831	J16	4484-49	PIN JACK, 4P
831	J17	4484-49	PIN JACK, 4P
920	JL701	4242-R0104600	JUMPER LEAD
872	JL702	4242-R0103101	JUMPER LEAD
870	JL703	4242-R0406161	JUMPER LEAD
883	JL704	4242-R0403301	JUMPER LEAD
869	JL710	4242-R0405161	JUMPER LEAD
885	JL714	4242-R0403601	JUMPER LEAD
045A	L701	5597-45502	CORE, BEADS G
045A	L702	5597-45502	CORE, BEADS G
045A	L703	5597-45502	CORE, BEADS G
045A	L704	5597-45502	CORE, BEADS G
889	CN701	4443-0701140	CONNECTOR
889	CN702	4443-0701140	CONNECTOR
916	CN705	4443-030185	CONNECTOR
861	CN707	4443-040185	CONNECTOR
887	CN708	4443-0501140	CONNECTOR
886	CN709	4443-0401140	CONNECTOR
863	CN711	4443-060185	CONNECTOR
888	CN712	4443-0601140	CONNECTOR
888	CN713	4443-0601140	CONNECTOR
916	CN715	4443-030185	CONNECTOR
878	LCN720	4163-0116020	CONNECTOR W/W
878	LCN721	4163-0116020	CONNECTOR W/W
877	LCN722	4163-0125020	CONNECTOR W/W
400	CS851	5693-CSB455E	OSC, CER
801	SW701	4411-204724	ROTARY SWITCH
801	SW702	4411-204724	ROTARY SWITCH
808	SW703	4422-70214	REMOTE SWITCH
874	LCN1	4132-R0100251	CORD, 2C
874	LCN2	4132-R0100251	CORD, 2C
865		2240-Z051	HOLDER
867		2240-Z031	HOLDER
876		2240-Z061	HOLDER

PCB-2 HEADPHONE JACK P.C. BOARD**MISCELLANEOUS**

820	J1	4451-00161	JACK, 1P
-----	----	------------	----------

PCB-3 VOLUME CONTROL P.C. BOARD**CONTROLS**

810	VR505	6161-00301	VR BLOCK
810	VR506	6161-00301	VR BLOCK

MISCELLANEOUS

915	CN706	4443-030185	CONNECTOR
-----	-------	-------------	-----------

Ser. No.	Ref. No.	Part No.	Description
----------	----------	----------	-------------

PCB-4 FUNCTION SWITCH P.C. BOARD**CAPACITORS**

827	C773	5345-106C0951	CAP, MINI ELE 10 μ /16V
827	C774	5345-106C0951	CAP, MINI ELE 10 μ /16V
827	C775	5345-106C0951	CAP, MINI ELE 10 μ /16V
827	C776	5345-106C0951	CAP, MINI ELE 10 μ /16V

RESISTORS

464	R851	5135-102522	RES, CBN 1/2P 1K
464	R852	5135-102522	RES, CBN 1/2P 1K
464	R853	5135-102522	RES, CBN 1/2P 1K
464	R854	5135-102522	RES, CBN 1/2P 1K
464	R855	5135-102522	RES, CBN 1/2P 1K
465	R856	5135-182522	RES, CBN 1/2P 1.8K
465	R857	5135-182522	RES, CBN 1/2P 1.8K
465	R858	5135-182522	RES, CBN 1/2P 1.8K
465	R859	5135-182522	RES, CBN 1/2P 1.8K
465	R860	5135-182522	RES, CBN 1/2P 1.8K

DIODES

822	D761	5637-GL5EG41	LED
822	D762	5637-GL5EG41	LED
822	D763	5637-GL5EG41	LED
822	D764	5637-GL5EG41	LED
822	D765	5637-GL5EG41	LED
822	D766	5637-GL5EG41	LED
822	D767	5637-GL5EG41	LED
822	D768	5637-GL5EG41	LED
822	D769	5637-GL5EG41	LED
822	D770	5637-GL5EG41	LED
823	D771	5631-1SS133	DIODE, DET
823	D772	5631-1SS133	DIODE, DET
823	D773	5631-1SS133	DIODE, DET

MISCELLANEOUS

807	SW760	4431-A017163	SWITCH, PUSH
807	SW761	4431-A017163	SWITCH, PUSH
807	SW762	4431-A017163	SWITCH, PUSH
807	SW763	4431-A017163	SWITCH, PUSH
807	SW764	4431-A017163	SWITCH, PUSH
807	SW765	4431-A017163	SWITCH, PUSH
807	SW766	4431-A017163	SWITCH, PUSH
807	SW767	4431-A017163	SWITCH, PUSH
807	SW768	4431-A017163	SWITCH, PUSH
807	SW769	4431-A017163	SWITCH, PUSH
884	LCN701	4163-01407007	CONNECTOR W/W
884	LCN702	4163-01407007	CONNECTOR W/W

PCB-5 MUTE INDICATOR P.C. BOARD**DIODE**

417	D894	5637-GL5HD10	LED
-----	------	--------------	-----

PCB-6 TONE CONTROL P.C. BOARD**CAPACITORS**

794	Δ C1	5352-1030961	CAP, MTL .01 μ UA N
794A	Δ C1	5352-1030958	CAP, MTL .01 μ G
791	C2	5345-477F041	CAP, MINI ELE 470 μ /50V
795	C3	5352-1041957	CAP, MTL .1 μ
795	C4	5352-1041957	CAP, MTL .1 μ
793	C5	5341-S09FM688	CAP, ELE 6800 μ /50V
792	C6	5341-478F0955	CAP, ELE 4700 μ /50V
765	C7	5345-337D041	CAP, MINI ELE 330 μ /25V
765	C8	5345-337D041	CAP, MINI ELE 330 μ /25V
766	C12	5345-228D041	CAP, MINI ELE 2200 μ /25V
721	C15	5345-476C0951	CAP, MINI ELE 47 μ /16V
766	C16	5345-228D041	CAP, MINI ELE 2200 μ /25V
383	C17	5345-477D041	CAP, MINI ELE 470 μ /25V
720	C18	5345-106C0951	CAP, MINI ELE 10 μ /16V
720	C19	5345-106C0951	CAP, MINI ELE 10 μ /16V
722	C20	5354-104593	CAP, MYL .1 μ
601	C51	5345-337C041	CAP, MINI ELE 330 μ /16V

Ser. No.	Ref. No.	Part No.	Description	Ser. No.	Ref. No.	Part No.	Description
601	C52	5345-337C041	CAP, MINI ELE 330 μ /16V	767	R28	5135-4R7522	RES, CBN 1/2P 4.7
601	C53	5345-337C041	CAP, MINI ELE 330 μ /16V	727	R33	5135-472522	RES, CBN 1/2P 4.7K
601	C54	5345-337C041	CAP, MINI ELE 330 μ /16V	615	R51	5135-182522	RES, CBN 1/2P 1.8K
764	C55	5345-228D041	CAP, MINI ELE 2200 μ /25V	615	R52	5135-182522	RES, CBN 1/2P 1.8K
764	C56	5345-228D041	CAP, MINI ELE 2200 μ /25V	617	R53	5135-101522	RES, CBN 1/2P 100
764	C57	5345-228D041	CAP, MINI ELE 2200 μ /25V	617	R54	5135-101522	RES, CBN 1/2P 100
764	C58	5345-228D041	CAP, MINI ELE 2200 μ /25V	770	R55	5135-220522	RES, CBN 1/2P 22
629	C501	5345-106C0951	CAP, MINI ELE 10 μ /16V	770	R56	5135-220522	RES, CBN 1/2P 22
629	C502	5345-106C0951	CAP, MINI ELE 10 μ /16V	770	R57	5135-220522	RES, CBN 1/2P 22
632	C503	5345-107B0951	CAP, MINI ELE 100 μ /10V	770	R58	5135-220522	RES, CBN 1/2P 22
632	C504	5345-107B0951	CAP, MINI ELE 100 μ /10V	668	R501	5135-331522	RES, CBN 1/2P 330
637	C507	5353-010934	CAP, MCA 1p	668	R502	5135-331522	RES, CBN 1/2P 330
637	C508	5353-010934	CAP, MCA 1p	654	R505	5135-394522	RES, CBN 1/2P 390K
631	C509	5345-107B0951	CAP, MINI ELE 100 μ /10V	654	R506	5135-394522	RES, CBN 1/2P 390K
631	C510	5345-107B0951	CAP, MINI ELE 100 μ /10V	652	R507	5135-182522	RES, CBN 1/2P 1.8K
640	C511	5354-183J1HM	CAP, MYL .018 μ	652	R508	5135-182522	RES, CBN 1/2P 1.8K
640	C512	5354-183J1HM	CAP, MYL .018 μ	652	R509	5135-182522	RES, CBN 1/2P 1.8K
639	C513	5354-104593	CAP, MYL .1 μ	652	R510	5135-182522	RES, CBN 1/2P 1.8K
639	C514	5354-104593	CAP, MYL .1 μ	652	R511	5135-182522	RES, CBN 1/2P 1.8K
640	C515	5354-183J1HM	CAP, MYL .018 μ	652	R512	5135-182522	RES, CBN 1/2P 1.8K
640	C516	5354-183J1HM	CAP, MYL .018 μ	652	R513	5135-182522	RES, CBN 1/2P 1.8K
643	C517	5354-182J1HM	CAP, MYL 1800p	652	R514	5135-182522	RES, CBN 1/2P 1.8K
642	C518	5354-682J1HM	CAP, MYL 6800p	656	R515	5135-103522	RES, CBN 1/2P 10K
642	C519	5354-682J1HM	CAP, MYL 6800p	656	R516	5135-103522	RES, CBN 1/2P 10K
643	C520	5354-182J1HM	CAP, MYL 1800p	656	R517	5135-103522	RES, CBN 1/2P 10K
639	C521	5354-104593	CAP, MYL .1 μ	656	R518	5135-103522	RES, CBN 1/2P 10K
639	C522	5354-104593	CAP, MYL .1 μ	655	R519	5135-271522	RES, CBN 1/2P 270
644	C523	5354-123J1HM	CAP, MYL .012 μ	655	R520	5135-271522	RES, CBN 1/2P 270
644	C524	5354-123J1HM	CAP, MYL .012 μ	655	R521	5135-271522	RES, CBN 1/2P 270
641	C525	5354-393J1HM	CAP, MYL .039 μ	655	R522	5135-271522	RES, CBN 1/2P 270
641	C526	5354-393J1HM	CAP, MYL .039 μ	655	R523	5135-271522	RES, CBN 1/2P 270
630	C527	5345-226D0951	CAP, MINI ELE 22 μ /25V	655	R524	5135-271522	RES, CBN 1/2P 270
630	C528	5345-226D0951	CAP, MINI ELE 22 μ /25V	655	R525	5135-271522	RES, CBN 1/2P 270
631	C529	5345-107B0951	CAP, MINI ELE 100 μ /10V	655	R526	5135-271522	RES, CBN 1/2P 270
631	C530	5345-107B0951	CAP, MINI ELE 100 μ /10V	657	R527	5135-153522	RES, CBN 1/2P 15K
635	C551	5353-101534	CAP, MCA 100p UA N	657	R528	5135-153522	RES, CBN 1/2P 15K
635A	C551	5359-4715851	CAP, PPP 470p G	658	R529	5135-473522	RES, CBN 1/2P 47K
635	C552	5353-101534	CAP, MCA 100p UA N	658	R530	5135-473522	RES, CBN 1/2P 47K
635A	C552	5359-4715851	CAP, PPP 470p G	659	R531	5135-274522	RES, CBN 1/2P 270K
645	C553	5354-394593	CAP, MYL .39 μ	659	R532	5135-274522	RES, CBN 1/2P 270K
645	C554	5354-394593	CAP, MYL .39 μ	664	R533	5135-181522	RES, CBN 1/2P 180
647	C555	5354-103J1HM	CAP, MYL .01 μ	664	R534	5135-181522	RES, CBN 1/2P 180
647	C556	5354-103J1HM	CAP, MYL .01 μ	664	R535	5135-181522	RES, CBN 1/2P 180
603	C903	5354-154593	CAP, MYL .15 μ	664	R536	5135-181522	RES, CBN 1/2P 180
603	C904	5354-154593	CAP, MYL .15 μ	668	R537	5135-331522	RES, CBN 1/2P 330
600	C905	5345-476D041	CAP, MINI ELE 47 μ /25V	668	R538	5135-331522	RES, CBN 1/2P 330
600	C906	5345-476D041	CAP, MINI ELE 47 μ /25V	657	R539	5135-153522	RES, CBN 1/2P 15K
604	C907	5354-334593	CAP, MYL .33 μ	657	R540	5135-153522	RES, CBN 1/2P 15K
604	C908	5354-334593	CAP, MYL .33 μ	661	R543	5135-122522	RES, CBN 1/2P 1.2K
599	C909	5345-226D0951	CAP, MINI ELE 22 μ /25V	661	R544	5135-122522	RES, CBN 1/2P 1.2K
599	C910	5345-226D0951	CAP, MINI ELE 22 μ /25V	662	R545	5135-121522	RES, CBN 1/2P 120
598	C919	5345-474F0951	CAP, MINI ELE .47 μ /50V	662	R546	5135-121522	RES, CBN 1/2P 120
598	C920	5345-474F0951	CAP, MINI ELE .47 μ /50V	651	R547	5135-331522	RES, CBN 1/2P 330
RESISTORS				651	R548	5135-331522	RES, CBN 1/2P 330
769	R3	5135-331522	RES, CBN 1/2P 330	672	R549	5135-335522	RES, CBN 1/2P 3.3M
769	R4	5135-331522	RES, CBN 1/2P 330	672	R550	5135-335522	RES, CBN 1/2P 3.3M
768	R5	5135-101522	RES, CBN 1/2P 100	663	R551	5135-122522	RES, CBN 1/2P 1.2K
768	R6	5135-101522	RES, CBN 1/2P 100	663	R552	5135-122522	RES, CBN 1/2P 1.2K
731	R11	5135-222522	RES, CBN 1/2P 2.2K	672	R553	5135-335522	RES, CBN 1/2P 3.3M
723	R12	5135-102522	RES, CBN 1/2P 1K	672	R554	5135-335522	RES, CBN 1/2P 3.3M
725	R13	5135-474522	RES, CBN 1/2P 470K	648	R555	5135-331522	RES, CBN 1/2P 330 UA N
731	R14	5135-222522	RES, CBN 1/2P 2.2K	648A	R555	5135-102522	RES, CBN 1/2P 1K G
729	R15	5135-104522	RES, CBN 1/2P 100K	648	R556	5135-331522	RES, CBN 1/2P 330 UA N
724	R16	5135-103522	RES, CBN 1/2P 10K	648A	R556	5135-102522	RES, CBN 1/2P 1K G
724	R18	5135-103522	RES, CBN 1/2P 10K	649	R557	5135-105522	RES, CBN 1/2P 1M
730	R19	5135-684522	RES, CBN 1/2P 680K	649	R558	5135-105522	RES, CBN 1/2P 1M
391	R20	5135-102522	RES, CBN 1/2P 1K	669	R559	5135-683522	RES, CBN 1/2P 68K
726	R21	5135-271522	RES, CBN 1/2P 270	669	R560	5135-683522	RES, CBN 1/2P 68K
726	R22	5135-271522	RES, CBN 1/2P 270	666	R561	5135-392522	RES, CBN 1/2P 3.9K
052A	R23	5135-222522	RES, CBN 1/2P 2.2K G	666	R562	5135-392522	RES, CBN 1/2P 3.9K
052A	R24	5135-222522	RES, CBN 1/2P 2.2K G	671	R563	5135-105522	RES, CBN 1/2P 1M
762	R25	5135-472522	RES, CBN 1/2P 4.7K	671	R564	5135-105522	RES, CBN 1/2P 1M
762	R26	5135-472522	RES, CBN 1/2P 4.7K	671	R565	5135-105522	RES, CBN 1/2P 1M
767	R27	5135-4R7522	RES, CBN 1/2P 4.7	671	R566	5135-105522	RES, CBN 1/2P 1M
				671	R567	5135-105522	RES, CBN 1/2P 1M

Ser. No.	Ref. No.	Part No.	Description
671	R568	5135-105522	RES, CBN 1/2P 1M
660	R569	5135-272522	RES, CBN 1/2P 2.7K
660	R570	5135-272522	RES, CBN 1/2P 2.7K
672	R571	5135-335522	RES, CBN 1/2P 3.3M
672	R572	5135-335522	RES, CBN 1/2P 3.3M
668	R573	5135-331522	RES, CBN 1/2P 330
668	R574	5135-331522	RES, CBN 1/2P 330
618	R901	5135-473522	RES, CBN 1/2P 47K
618	R902	5135-473522	RES, CBN 1/2P 47K
607	R903	5135-102522	RES, CBN 1/2P 1K
607	R904	5135-102522	RES, CBN 1/2P 1K
608	R905	5135-154522	RES, CBN 1/2P 150K
608	R906	5135-154522	RES, CBN 1/2P 150K
618	R907	5135-473522	RES, CBN 1/2P 47K
618	R908	5135-473522	RES, CBN 1/2P 47K
607	R909	5135-102522	RES, CBN 1/2P 1K
607	R910	5135-102522	RES, CBN 1/2P 1K
609	R911	5135-332522	RES, CBN 1/2P 3.3K
609	R912	5135-332522	RES, CBN 1/2P 3.3K
609	R913	5135-332522	RES, CBN 1/2P 3.3K
609	R914	5135-332522	RES, CBN 1/2P 3.3K
610	R915	5135-183522	RES, CBN 1/2P 18K
610	R916	5135-183522	RES, CBN 1/2P 18K
616	R917	5135-472522	RES, CBN 1/2P 4.7K
616	R918	5135-472522	RES, CBN 1/2P 4.7K
611	R919	5135-562522	RES, CBN 1/2P 5.6K
611	R920	5135-562522	RES, CBN 1/2P 5.6K
609	R921	5135-332522	RES, CBN 1/2P 3.3K
609	R922	5135-332522	RES, CBN 1/2P 3.3K
610	R923	5135-183522	RES, CBN 1/2P 18K
610	R924	5135-183522	RES, CBN 1/2P 18K
612	R925	5135-331522	RES, CBN 1/2P 330
612	R926	5135-331522	RES, CBN 1/2P 330
609	R927	5135-332522	RES, CBN 1/2P 3.3K
609	R928	5135-332522	RES, CBN 1/2P 3.3K
613	R929	5135-221522	RES, CBN 1/2P 220
613	R930	5135-221522	RES, CBN 1/2P 220
612	R931	5135-331522	RES, CBN 1/2P 330
612	R932	5135-331522	RES, CBN 1/2P 330
614	R933	5135-104522	RES, CBN 1/2P 100K
614	R934	5135-104522	RES, CBN 1/2P 100K

INTEGRATED CIRCUIT

714	IC1	5654-TC4069BP	IC, DIGITAL
-----	-----	---------------	-------------

TRANSISTORS

758	Q1	5612-1015 (Q) or (Y)	XISTOR, PNP A
757	Q2	5614-1406 (Q) or (Y)	XISTOR, NPN A
759	Q3	5613-2603 (F) or (E)	XISTOR, NPN R
760	Q4	5611-1115 (F) or (E)	XISTOR, PNP R
719	Q10	5613-RN1203	XISTOR, NPN R
711	Q11	5614-667A (C)	XISTOR, NPN A
385	Q12	5613-3246 (H)	XISTOR, NPN R
713	Q13	5611-RN2203	XISTOR, PNP R
712	Q14	5611-1115 (F) or (E)	XISTOR, PNP R
759	Q15	5613-2603 (F) or (E)	XISTOR, NPN R
760	Q16	5611-1115 (F) or (E)	XISTOR, PNP R
593	Q51	5614-667A (C)	XISTOR, NPN A
594	Q52	5612-647A (C)	XISTOR, PNP A
621	Q501	5613-2240 (BL)	XISTOR, NPN R
621	Q502	5613-2240 (BL)	XISTOR, NPN R
622	Q503	5611-970 (BL)	XISTOR, PNP R
622	Q504	5611-970 (BL)	XISTOR, PNP R
621	Q505	5613-2240 (BL)	XISTOR, NPN R
621	Q506	5613-2240 (BL)	XISTOR, NPN R
622	Q507	5611-970 (BL)	XISTOR, PNP R
622	Q508	5611-970 (BL)	XISTOR, PNP R
623	Q509	5613-2320L (F)	XISTOR, NPN R
623	Q510	5613-2320L (F)	XISTOR, NPN R
624	Q511	5611-999L (F)	XISTOR, PNP R
624	Q512	5611-999L (F)	XISTOR, PNP R
625	Q513	5612-646A (C)	XISTOR, PNP A
625	Q514	5612-646A (C)	XISTOR, PNP A
626	Q515	5614-666A (C)	XISTOR, NPN A
626	Q516	5614-666A (C)	XISTOR, NPN A
591	Q901	5613-2603 (F) or (E)	XISTOR, NPN R

Ser. No.	Ref. No.	Part No.	Description
591	Q902	5613-2603 (F) or (E)	XISTOR, NPN R
592	Q903	5611-1115 (F) or (E)	XISTOR, PNP R
592	Q904	5611-1115 (F) or (E)	XISTOR, PNP R
592	Q905	5611-1115 (F) or (E)	XISTOR, PNP R
592	Q906	5611-1115 (F) or (E)	XISTOR, PNP R
591	Q907	5613-2603 (F) or (E)	XISTOR, NPN R
591	Q908	5613-2603 (F) or (E)	XISTOR, NPN R

DIODES

790	△D1	5632-10DF2	DIODE, RECT
790	△D2	5632-10DF2	DIODE, RECT
790	△D3	5632-10DF2	DIODE, RECT
790	△D4	5632-10DF2	DIODE, RECT
773	D5	5632-10DF2	DIODE, RECT
773	D6	5632-10DF2	DIODE, RECT
763	D7	5635-HZ20-1L	DIODE, ZENER
763	D8	5635-HZ20-1L	DIODE, ZENER
384	D11	5632-10DF2	DIODE, RECT
717	D12	5631-1S2473	DIODE, DET
715	D13	5635-RD5R6EB2	DIODE, ZENER
384	D14	5632-10DF2	DIODE, RECT
716	D15	5636-1S2471	DIODE, SWITCH
716	D16	5636-1S2471	DIODE, SWITCH
717	D17	5631-1S2473	DIODE, DET
384	D18	5632-10DF2	DIODE, RECT
596	D51	5635-HZ15-1L	DIODE, ZENER
596	D52	5635-HZ15-1L	DIODE, ZENER
717	D891	5631-1S2473	DIODE, DET

TRANSFORMER

381	△T2	5584-702550	XFORMER, POWER UA
381A	△T2	5584-701550	XFORMER, POWER G
381B	△T2	5584-703550	XFORMER, POWER N

CONTROLS

814	VR501	5113-10449122	RES, V CBN 16 100K
814	VR502	5113-10449122	RES, V CBN 16 100K
816	VR503	5113-50350122	RES, V CBN 16 50K
816	VR504	5113-50350122	RES, V CBN 16 50K

MISCELLANEOUS

797	△F1	5732-122031	FUSE UA
797A	△F1	5732-122030	FUSE G
797B	△F1	5732-122036	FUSE N
797	△F2	5732-122031	FUSE UA
797A	△F2	5732-122030	FUSE G
797B	△F2	5732-122036	FUSE N
798	△HL1	4472-0131	HOLDER, FUSE
798	△HL2	4472-0131	HOLDER, FUSE
798	△HL3	4472-0131	HOLDER, FUSE
798	△HL4	4472-0131	HOLDER, FUSE
832	J3	4482-7136	PIN JACK, 2P
718	RL1	4331-2024736	RELAY, DC
800	TM101	4214-11023	TERMINAL
800	TM102	4214-11023	TERMINAL
799	TM103	4214-11033	TERMINAL
804	SW501	4431-S0603416	PUSH SWITCH
804	SW502	4431-S0603416	PUSH SWITCH
804	SW503	4431-S0603416	PUSH SWITCH
804	SW504	4431-S0603416	PUSH SWITCH
805	SW505	4462-00301043	LEVER SWITCH
805	SW506	4462-00301043	LEVER SWITCH
879	LCN718	4163-0160020	CONNECTOR W/W
879	LCN719	4163-0160020	CONNECTOR W/W
890	CN703	4443-060185	CONNECTOR
917	CN704	4443-030185	CONNECTOR
862	CN710	4443-050185	CONNECTOR
917	CN714	4443-030185	CONNECTOR
382	△S1	4331-10120237	RELAY, DC
875	LCN4	4132-R0100161	CORD, 2C
919		2240-2031	HOLDER

PCB-7 VIDEO P.C. BOARD**CAPACITORS**

477	C801	5345-107C041	CAP, MINI ELE 100µ/16V
477	C802	5345-107C041	CAP, MINI ELE 100µ/16V

Ser. No.	Ref. No.	Part No.	Description
477	C803	5345-107C041	CAP, MINI ELE 100 μ /16V
477	C804	5345-107C041	CAP, MINI ELE 100 μ /16V
477	C805	5345-107C041	CAP, MINI ELE 100 μ /16V
477	C806	5345-107C041	CAP, MINI ELE 100 μ /16V
477	C807	5345-107C041	CAP, MINI ELE 100 μ /16V
477	C808	5345-107C041	CAP, MINI ELE 100 μ /16V
477	C809	5345-107C041	CAP, MINI ELE 100 μ /16V
476	C810	5345-477C041	CAP, MINI ELE 470 μ /16V
476	C811	5345-477C041	CAP, MINI ELE 470 μ /16V
476	C812	5345-477C041	CAP, MINI ELE 470 μ /16V
477	C813	5345-107C041	CAP, MINI ELE 100 μ /16V
477	C814	5345-107C041	CAP, MINI ELE 100 μ /16V
047A	C864	5359-1015851	CAP, PPP 100p G
047A	C865	5359-1015851	CAP, PPP 100p G
047A	C866	5359-1015851	CAP, PPP 100p G
047A	C867	5359-1015851	CAP, PPP 100p G

RESISTORS

479	R801	5135-221522	RES, CBN 1/2P 220
479A	R801	5135-102522	RES, CBN 1/2P 1K G
479	R802	5135-221522	RES, CBN 1/2P 220
479A	R802	5135-102522	RES, CBN 1/2P 1K G
478	R803	5135-750522	RES, CBN 1/2P 75
481	R804	5135-393522	RES, CBN 1/2P 39K
482	R805	5135-683522	RES, CBN 1/2P 68K
478	R806	5135-750522	RES, CBN 1/2P 75
479	R807	5135-221522	RES, CBN 1/2P 220
479A	R807	5135-102522	RES, CBN 1/2P 1K G
479	R808	5135-221522	RES, CBN 1/2P 220
479A	R808	5135-102522	RES, CBN 1/2P 1K G
481	R809	5135-393522	RES, CBN 1/2P 39K
482	R810	5135-683522	RES, CBN 1/2P 68K
482	R811	5135-683522	RES, CBN 1/2P 68K
481	R812	5135-393522	RES, CBN 1/2P 39K
481	R813	5135-393522	RES, CBN 1/2P 39K
482	R814	5135-683522	RES, CBN 1/2P 68K
482	R815	5135-683522	RES, CBN 1/2P 68K
482	R816	5135-683522	RES, CBN 1/2P 68K
482	R817	5135-683522	RES, CBN 1/2P 68K
482	R818	5135-683522	RES, CBN 1/2P 68K
481	R819	5135-393522	RES, CBN 1/2P 39K
481	R820	5135-393522	RES, CBN 1/2P 39K
479	R821	5135-221522	RES, CBN 1/2P 220
479A	R821	5135-102522	RES, CBN 1/2P 1K G
481	R822	5135-393522	RES, CBN 1/2P 39K
481	R823	5135-393522	RES, CBN 1/2P 39K
483	R824	5135-103522	RES, CBN 1/2P 10K
488	R826	5135-181522	RES, CBN 1/2P 180
486	R827	5135-221522	RES, CBN 1/2P 220
487	R828	5135-271522	RES, CBN 1/2P 270
480	R829	5135-680522	RES, CBN 1/2P 68
483	R831	5135-103522	RES, CBN 1/2P 10K
488	R832	5135-181522	RES, CBN 1/2P 180
486	R833	5135-221522	RES, CBN 1/2P 220
487	R834	5135-271522	RES, CBN 1/2P 270
478	R835	5135-750522	RES, CBN 1/2P 75
479	R836	5135-221522	RES, CBN 1/2P 220
479A	R836	5135-102522	RES, CBN 1/2P 1K G
480	R837	5135-680522	RES, CBN 1/2P 68
483	R839	5135-103522	RES, CBN 1/2P 10K
488	R840	5135-181522	RES, CBN 1/2P 180
486	R841	5135-221522	RES, CBN 1/2P 220
487	R842	5135-271522	RES, CBN 1/2P 270
480	R843	5135-680522	RES, CBN 1/2P 68
484	R846	5135-332522	RES, CBN 1/2P 3.3K
485	R847	5135-182522	RES, CBN 1/2P 1.8K
478	R848	5135-750522	RES, CBN 1/2P 75

INTEGRATED CIRCUITS

472	IC801	5652-BA7001	IC, MONO
472	IC802	5652-BA7001	IC, MONO
471	IC803	5654-LC4966	IC, DIGITAL
471	IC804	5654-LC4966	IC, DIGITAL

TRANSISTORS

474	Q801	5613-2603 (E) or (F)	XISTOR, NPN R
475	Q802	5611-1115 (E) or (F)	XISTOR, PNP R

Ser. No.	Ref. No.	Part No.	Description
474	Q803	5613-2603 (E) or (F)	XISTOR, NPN R
475	Q804	5611-1115 (E) or (F)	XISTOR, PNP R
474	Q805	5613-2603 (E) or (F)	XISTOR, NPN R
475	Q806	5611-1115 (E) or (F)	XISTOR, PNP R

DIODES

473	D801	5631-1SS133	DIODE, DET
473	D802	5631-1SS133	DIODE, DET

MISCELLANEOUS

842	J20	4489-00601003	PIN JACK, MLT
843	J21	4489-00701002	PIN JACK, MLT
843	J22	4489-00701002	PIN JACK, MLT
868	JL707	4242-R0404101	JUMPER LEAD
871	JL711	4242-R0406161	JUMPER LEAD
873	LCN723	4163-0125020	CONNECTOR W/W
053A	LCN3	4132-R0100161	CORD, 2C G
867		2240-Z031	HOLDER
866		2240-Z061	HOLDER

PCB-8 RECORD OUTPUT P.C. BOARD (SUB)**MISCELLANEOUS**

802	SW755	4431-S0605510	PUSH SWITCH
802	SW756	4431-S0605510	PUSH SWITCH
802	SW757	4431-S0605510	PUSH SWITCH
802	SW758	4431-S0605510	PUSH SWITCH
802	SW759	4431-S0605510	PUSH SWITCH
882	LCN713	4163-01404006	CONNECTOR W/W

PCB-9 RECORD OUTPUT P.C. BOARD (MAIN)**MISCELLANEOUS**

803	SW750	4431-S0604510	PUSH SWITCH
803	SW751	4431-S0604510	PUSH SWITCH
803	SW752	4431-S0604510	PUSH SWITCH
803	SW753	4431-S0604510	PUSH SWITCH
803	SW754	4431-S0604510	PUSH SWITCH
914	LCN712	4161-01404006	CORD W/PLUG

PCB-10 MINI JACK P.C. BOARD**RESISTORS**

705	R29	5135-102522	RES, CBN 1/2P 1K
705	R30	5135-102522	RES, CBN 1/2P 1K

MISCELLANEOUS

824	J2	4451-00177	JACK, 1P
-----	----	------------	----------

PCB-11 POWER INDICATOR P.C. BOARD**CAPACITOR**

410	C863	5345-106C0951	CAP, MINI ELE 10 μ /16V
-----	------	---------------	-----------------------------

DIODE

399	D856	5637-GL5HY10	LED
392	D857	5637-GL5EG21	LED

MISCELLANEOUS

398	RU801	6143-00101	RECEIVER UNIT
806	SW801	4431-A027192	PUSH SWITCH
881	LCN708	4163-01408005	CONNECTOR, W/W
880	LCN709	4163-01405004	CONNECTOR, W/W

Ser. No.	Ref. No.	Part No.	Description
----------	----------	----------	-------------

ABBREVIATIONS IN PARTS LIST**CAPACITORS**

CAP, MINI ELE : Electrolytic
 CAP, CER : Ceramic
 CAP, PPP : Polypropylene
 CAP, MYL : Mylar
 CAP, MCA : Mica
 CAP, MINI BP : Bipolar
 CAP, ELE BP : Electrolytic Bipolar
 CAP, STY : Polystyrene Film
 CAP, SPE : Special
 CAP, TAN : Tantalum
 470 μ : 470 μ F
 6800p : 6800pF
 .047 μ : 0.047 μ F

RESISTORS

RES, CBN 1/6P : Carbon 1/6W
 RES, FUSE : Fuse
 RES, CEM 5P : Cement 5W
 RES, MTL 1P : Metal 1W
 2.2K : 2.2k Ω
 220 : 220 Ω

TRANSISTORS

XISTOR : Transistor
 FET : Field Effect Transistor

CONTROLS

RES, V CBN : Variable Carbon Resistor
 RES, SEMI FIX : Semi-fixed Resistor

CHASSIS MISCELLANEOUS

788 Δ T1	5584-701554	XFORMER, POWER UA
788A Δ T1	5584-702453	XFORMER, POWER G
788B Δ T1	5584-703453	XFORMER, POWER N
837 Δ P1	4161-71151	CORD W/PLUG, POWER CORD UA
837A Δ P1	4161-7256	CORD W/PLUG, POWER CORD G
837B Δ P1	4161-00401192	CORD W/PLUG, POWER CORD N
834 Δ S01	4474-221	SOCKET, AC OUTLET UA N
835 Δ S02	4474-222	SOCKET, AC OUTLET UA N
041A Δ SW101	4411-102729	ROTARY SWITCH, VOLTAGE SELECTOR G

PACKAGE PARTS LIST

021A	1756-06303	LABEL, 220V/50Hz G
021B	1756-03113	LABEL N
022A	1756-03108	LABEL, INT G
022B	1241-PB	POLYETHY BAG, WARRANTY N
024A	1119-026	ATTACH SHEET, FTZ SHEET G
105	1111-J90195	OWNER GUIDE, UL UA N
106	1111-J30277	OWNER GUIDE, OG
106A	1111-J30278	OWNER GUIDE, OG G
106B	1111-J2037	OWNER GUIDE, OG N
107	1113-717005	OWNER CARD, REPLY CARD UA
107B	1113-OC	OWNER CARD, REPLY CARD N
108	1119-057	ATTACH SHEET, WARRANTY
108B	1116-GC	GUARANT CARD, WARRANTY
109	1119-0137	ATTACH SHEET, SERVICE GUIDE
111	1241-C12732	POLYETHY BAG, OG
116	1756-CSA	LABEL, CSA
120	1221-727199	CARTON BOX
121	1222-7309	CUSHION, R
122	1222-7310	CUSHION, L
123	1223-11748	SOFT SHEET, SET
125	1241-C1491	POLYETHY BAG, SET
127	1241-C1216	POLYETHY BAG, ACCESSORY
128	1223-11751	SOFT SHEET
839	4442-14	PIN PLUG, SHORT PIN
846	6142-02601	CONT BLOCK, COMANDER
848	4191-0355	BATTER, DRY
905	4161-71174	CORD W/PLUG

NOTE

SAFETY RELATED COMPONENT. USE ONLY EXACT REPLACEMENT PART AS SPECIFIED.