

Service Manual

ORDER NO.
RRV3474

DJ MIXER

DJM-800

THIS MANUAL IS APPLICABLE TO THE FOLLOWING MODEL(S) AND TYPE(S).

Model	Type	Power Requirement	Remarks
DJM-800	WAXJ5	AC 220 to 240 V	

- This service manual should be used together with the following manual(s):

Model No.	Order No.	Remarks
DJM-800/KUCXJ	RRV3340	

- For SPECIFICATIONS and PANEL FACILITIES, refer to the operating instructions.

PIONEER CORPORATION 4-1, Meguro 1-chome, Meguro-ku, Tokyo 153-8654, Japan

PIONEER ELECTRONICS (USA) INC. P.O. Box 1760, Long Beach, CA 90801-1760, U.S.A.

PIONEER EUROPE NV Haven 1087, Keetberglaan 1, 9120 Melsele, Belgium

PIONEER ELECTRONICS ASIACENTRE PTE. LTD. 253 Alexandra Road, #04-01, Singapore 159936

©PIONEER CORPORATION 2006

1. CONTRAST OF MISCELLANEOUS PARTS

A NOTES: • Parts marked by "NSP" are generally unavailable because they are not in our Master Spare Parts List.

• The Δ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.

• Screws adjacent to ∇ mark on product are used for disassembly.

• Reference Nos. indicate the pages and Nos. in the service manual for the base model.

• For the applying amount of lubricants or glue, follow the instructions in this manual.
(In the case of no amount instructions, apply as you think it appropriate.)

• When ordering resistors, first convert resistance values into code form as shown in the following examples.

Ex.1 When there are 2 effective digits (any digit apart from 0), such as 560 ohm and 47k ohm (tolerance is shown by J=5%, and K=10%).

560 Ω \rightarrow 56×10^3 \rightarrow 561 RD1/4PU 5 6 1 J

47k Ω \rightarrow 47×10^3 \rightarrow 473 RD1/4PU 4 7 3 J

0.5 Ω \rightarrow R50 RN2H R 5 0 K

1 Ω \rightarrow 1R0 RS1P 1 R 0 K

Ex.2 When there are 3 effective digits (such as in high precision metal film resistors).

5.62k Ω \rightarrow 562×10^3 \rightarrow 5621 RNI/4PC 5 6 2 1 F

■ CONTRAST TABLE

DJM-800/WAXJ5 and DJM-800/KUCXJ are constructed the same except for the following :

Ref. No.	Mark	Symbol and Description	Part No.		Remarks
			DJM-800 /KUCXJ	DJM-800 /WAXJ5	
C	Δ NSP	PACKING SECTION Instruction Manual (English) Instruction Manual (English, Chinese) Packing Case	DRB1393 Not used DHG2559	Not used DRB1395 DHG2603	
		Power Cord Warranty Card	DDG1028 ARY7043	ADG7105 Not used	
		EXTERIOR SECTION			
		AC Inlet Assy Rear Panel	DKP3761 DNC1800	DKP3762 DNC1793	
		Label Caution Label	DRW2294 DRW1975	DRW2297 Not used	
		CCC S&E Label	Not used	DRW2310	
D	NSP NSP	Earth Label Serial Label	DRW2276 DRW2311	Not used VRW1629	