

SERVICE TECHNICAL INFORMATION

ONE POINT REPAIR



UTSUNOMIYA, DECEMBER 31, 1995

REF. NO. : SI-95-047

CUSTOMER RELATIONS & SERVICE DIV.

- MODEL : XG-990 (SX-N990)
 SUBJECT : Prevention of tweeter short recurrence
 CONTENTS : When there is a short in the speaker tweeter, perform the remedy described below.
 When the tweeter shorts, the protection circuit of the unit operates to turn the power off.
 REMEDY : Along with replacing the tweeter, also add the condenser listed below when repairing the relevant products.

- Method**
- 1) Remove the speaker panel and replace the tweeter.
 - 2) As shown in the figure below, add a BP condenser (2.7 μ F/100V) in series to the (+) terminal of the replaced tweeter.
 - 3) Glue the added condenser to the tweeter.



Part No.	Part Name	Ref. No.
83-135-627-010	BP 2.7 μ F / 100V	---
82-NS6-601-010	Speaker tweeter	---